



## Pin Information for the Cyclone® V 5CEBA4 Device

Version 1.1

Note (1)

Bank Number	VREF	Pin Name/Function	Optional Function(s)	Configuration Function	Dedicated Tx/Rx Channel	Emulated LVDS Output Channel	U324	DQS for X8
2A	VREFB2AN0	IO			DIFFIO_RX_L9n	DIFFOUT_L9n	E2	
2A	VREFB2AN0	IO			DIFFIO_RX_L10n	DIFFOUT_L10n	J4	DQ1L
2A	VREFB2AN0	IO			DIFFIO_RX_L9p	DIFFOUT_L9p	D1	DQ1L
2A	VREFB2AN0	IO			DIFFIO_RX_L10p	DIFFOUT_L10p	J3	DQ1L
2A	VREFB2AN0	IO			DIFFIO_RX_L11n	DIFFOUT_L11n	K2	DQSn1L
2A	VREFB2AN0	IO			DIFFIO_RX_L12n	DIFFOUT_L12n	E3	DQ1L
2A	VREFB2AN0	IO			DIFFIO_RX_L11p	DIFFOUT_L11p	K3	DQSn1L
2A	VREFB2AN0	IO			DIFFIO_RX_L12p	DIFFOUT_L12p	F2	
2A	VREFB2AN0	IO			DIFFIO_RX_L13n	DIFFOUT_L13n	E1	DQ1L
2A	VREFB2AN0	IO			DIFFIO_RX_L14n	DIFFOUT_L14n	F4	DQ1L
2A	VREFB2AN0	IO			DIFFIO_RX_L13p	DIFFOUT_L13p	F1	DQ1L
2A	VREFB2AN0	IO			DIFFIO_RX_L14p	DIFFOUT_L14p	G3	DQ1L
2A	VREFB2AN0	IO			DIFFIO_RX_L15n	DIFFOUT_L15n	K1	
2A	VREFB2AN0	IO			DIFFIO_RX_L16n	DIFFOUT_L16n	H2	DQ1L
2A	VREFB2AN0	IO			DIFFIO_RX_L15p	DIFFOUT_L15p	L1	
2A	VREFB2AN0	IO			DIFFIO_RX_L16p	DIFFOUT_L16p	G2	DQ1L
2A	VREFB2AN0	IO			DIFFIO_RX_L17n	DIFFOUT_L17n	J1	
2A	VREFB2AN0	IO			DIFFIO_RX_L18n	DIFFOUT_L18n	L2	DQ2L
2A	VREFB2AN0	IO			DIFFIO_RX_L17p	DIFFOUT_L17p	H1	DQ2L
2A	VREFB2AN0	IO			DIFFIO_RX_L18p	DIFFOUT_L18p	M2	DQ2L
2A	VREFB2AN0	IO			DIFFIO_RX_L19n	DIFFOUT_L19n	L5	DQSn2L
2A	VREFB2AN0	IO			DIFFIO_RX_L20n	DIFFOUT_L20n	R1	DQ2L
2A	VREFB2AN0	IO			DIFFIO_RX_L19p	DIFFOUT_L19p	M4	DQSn2L
2A	VREFB2AN0	IO			DIFFIO_RX_L20p	DIFFOUT_L20p	P1	
2A	VREFB2AN0	IO			DIFFIO_RX_L21n	DIFFOUT_L21n	R2	DQ2L
2A	VREFB2AN0	IO			DIFFIO_RX_L22n	DIFFOUT_L22n	N2	DQ2L
2A	VREFB2AN0	IO			DIFFIO_RX_L21p	DIFFOUT_L21p	T1	DQ2L
2A	VREFB2AN0	IO			DIFFIO_RX_L22p	DIFFOUT_L22p	N3	DQ2L
2A	VREFB2AN0	IO			DIFFIO_RX_L23n	DIFFOUT_L23n	L4	
2A	VREFB2AN0	IO			DIFFIO_RX_L24n	DIFFOUT_L24n	T2	DQ2L
2A	VREFB2AN0	IO			DIFFIO_RX_L23p	DIFFOUT_L23p	M3	
2A	VREFB2AN0	IO			DIFFIO_RX_L24p	DIFFOUT_L24p	R3	DQ2L
3A		TDO		TDO			P5	
3A		nCSO		DATA4			P3	
3A		TMS		TMS			P6	
3A		AS_DATA3		DATA3			M5	
3A		TCK		TCK			L6	
3A		AS_DATA2		DATA2			U3	
3A		TDI		TDI			N6	
3A		AS_DATA1		DATA1			U2	
3A		DCLK		DCLK			K6	
3A		AS_DATA0,ASDO		DATA0			V1	
3A	VREFB3AN0	IO		DATA6	DIFFIO_RX_B1n	DIFFOUT_B1n	M7	DQ1B
3A	VREFB3AN0	IO		DATA5	DIFFIO_RX_B2n	DIFFOUT_B2n	V2	
3A	VREFB3AN0	IO		DATA8	DIFFIO_RX_B1p	DIFFOUT_B1p	N7	DQ1B
3A	VREFB3AN0	IO		DATA7	DIFFIO_RX_B2p	DIFFOUT_B2p	V3	DQ1B
3A	VREFB3AN0	IO		DATA10	DIFFIO_RX_B3n	DIFFOUT_B3n	M10	DQSn1B
3A	VREFB3AN0	IO		DATA9	DIFFIO_RX_B4n	DIFFOUT_B4n	U7	DQ1B
3A	VREFB3AN0	IO		DATA12	DIFFIO_RX_B3p	DIFFOUT_B3p	N10	DQSn1B
3A	VREFB3AN0	IO		DATA11	DIFFIO_RX_B4p	DIFFOUT_B4p	T7	
3A	VREFB3AN0	IO		DATA14	DIFFIO_RX_B5n	DIFFOUT_B5n	M8	DQ1B
3A	VREFB3AN0	IO		DATA13	DIFFIO_RX_B6n	DIFFOUT_B6n	P4	DQ1B
3A	VREFB3AN0	IO		CLKUSR	DIFFIO_RX_B5p	DIFFOUT_B5p	M9	DQ1B
3A	VREFB3AN0	IO		DATA15	DIFFIO_RX_B6p	DIFFOUT_B6p	R4	DQ1B
3A	VREFB3AN0	IO		PR_DONE	DIFFIO_RX_B7n	DIFFOUT_B7n	N11	
3A	VREFB3AN0	IO		PR_READY	DIFFIO_RX_B8n	DIFFOUT_B8n	P8	DQ1B



## Pin Information for the Cyclone® V 5CEBA4 Device

Version 1.1

Note (1)

Bank Number	VREF	Pin Name/Function	Optional Function(s)	Configuration Function	Dedicated Tx/Rx Channel	Emulated LVDS Output Channel	U324	DQS for X8
3A	VREFB3AN0	IO		PR_ERROR	DIFFIO_RX_B7p	DIFFOUT_B7p	P11	
3A	VREFB3AN0	IO			DIFFIO_TX_B8p	DIFFOUT_B8p	N8	DQ1B
3B	VREFB3BN0	IO			DIFFIO_RX_B17n	DIFFOUT_B17n	V6	
3B	VREFB3BN0	IO			DIFFIO_RX_B18n	DIFFOUT_B18n	U5	DQ2B
3B	VREFB3BN0	IO			DIFFIO_TX_B17p	DIFFOUT_B17p	V7	DQ2B
3B	VREFB3BN0	IO			DIFFIO_RX_B18p	DIFFOUT_B18p	U4	DQ2B
3B	VREFB3BN0	IO			DIFFIO_RX_B19n	DIFFOUT_B19n	P9	DQS2B
3B	VREFB3BN0	IO			DIFFIO_TX_B20n	DIFFOUT_B20n	T4	DQ2B
3B	VREFB3BN0	IO			DIFFIO_RX_B19p	DIFFOUT_B19p	P10	DQS2B
3B	VREFB3BN0	IO			DIFFIO_RX_B20p	DIFFOUT_B20p	T5	
3B	VREFB3BN0	IO	FPLL_BL_CLKOUT1,FPLL_BL_CLKOUTn		DIFFIO_RX_B21n	DIFFOUT_B21n	V8	DQ2B
3B	VREFB3BN0	IO			DIFFIO_RX_B22n	DIFFOUT_B22n	T9	DQ2B
3B	VREFB3BN0	IO	FPLL_BL_CLKOUT0,FPLL_BL_CLKOUTp,FPLL_BL_FB		DIFFIO_RX_B21p	DIFFOUT_B21p	U8	DQ2B
3B	VREFB3BN0	IO			DIFFIO_RX_B22p	DIFFOUT_B22p	R9	DQ2B
3B	VREFB3BN0	IO	CLK1n		DIFFIO_RX_B23n	DIFFOUT_B23n	T11	
3B	VREFB3BN0	IO			DIFFIO_RX_B24n	DIFFOUT_B24n	U9	DQ2B
3B	VREFB3BN0	IO	CLK1p		DIFFIO_RX_B23p	DIFFOUT_B23p	R11	
3B	VREFB3BN0	IO			DIFFIO_RX_B24p	DIFFOUT_B24p	V10	DQ2B
4A	VREFB4AN0	IO	RZQ_0		DIFFIO_RX_B25n	DIFFOUT_B25n	U13	
4A	VREFB4AN0	IO			DIFFIO_RX_B26n	DIFFOUT_B26n	V13	DQ3B
4A	VREFB4AN0	IO			DIFFIO_RX_B25p	DIFFOUT_B25p	U14	DQ3B
4A	VREFB4AN0	IO			DIFFIO_RX_B26p	DIFFOUT_B26p	V12	DQ3B
4A	VREFB4AN0	IO			DIFFIO_RX_B27n	DIFFOUT_B27n	M14	DQS3B
4A	VREFB4AN0	IO			DIFFIO_RX_B27n	DIFFOUT_B27n	U18	DQ3B
4A	VREFB4AN0	IO			DIFFIO_RX_B27p	DIFFOUT_B27p	L13	DQS3B
4A	VREFB4AN0	IO			DIFFIO_RX_B28p	DIFFOUT_B28p	V17	
4A	VREFB4AN0	IO			DIFFIO_RX_B29n	DIFFOUT_B29n	U17	DQ3B
4A	VREFB4AN0	IO			DIFFIO_RX_B30n	DIFFOUT_B30n	V16	DQ3B
4A	VREFB4AN0	IO			DIFFIO_RX_B29p	DIFFOUT_B29p	T17	DQ3B
4A	VREFB4AN0	IO			DIFFIO_RX_B30p	DIFFOUT_B30p	V15	DQ3B
4A	VREFB4AN0	IO	CLK2n		DIFFIO_RX_B31n	DIFFOUT_B31n	U12	
4A	VREFB4AN0	IO			DIFFIO_RX_B32n	DIFFOUT_B32n	R18	DQ3B
4A	VREFB4AN0	IO	CLK2p		DIFFIO_RX_B31p	DIFFOUT_B31p	T12	
4A	VREFB4AN0	IO			DIFFIO_RX_B32p	DIFFOUT_B32p	P18	DQ3B
4A	VREFB4AN0	IO			DIFFIO_RX_B33n	DIFFOUT_B33n	T16	
4A	VREFB4AN0	IO			DIFFIO_RX_B34n	DIFFOUT_B34n	P14	DQ4B
4A	VREFB4AN0	IO			DIFFIO_RX_B33p	DIFFOUT_B33p	R17	DQ4B
4A	VREFB4AN0	IO			DIFFIO_RX_B34p	DIFFOUT_B34p	P15	DQ4B
4A	VREFB4AN0	IO			DIFFIO_RX_B35n	DIFFOUT_B35n	M13	DQS4B
4A	VREFB4AN0	IO			DIFFIO_RX_B36n	DIFFOUT_B36n	R16	DQ4B
4A	VREFB4AN0	IO			DIFFIO_RX_B35p	DIFFOUT_B35p	N12	DQS4B
4A	VREFB4AN0	IO			DIFFIO_RX_B36p	DIFFOUT_B36p	P16	
4A	VREFB4AN0	IO			DIFFIO_RX_B37n	DIFFOUT_B37n	N17	DQ4B
4A	VREFB4AN0	IO			DIFFIO_RX_B38n	DIFFOUT_B38n	R13	DQ4B
4A	VREFB4AN0	IO			DIFFIO_RX_B37p	DIFFOUT_B37p	N16	DQ4B
4A	VREFB4AN0	IO			DIFFIO_RX_B38p	DIFFOUT_B38p	T14	DQ4B
4A	VREFB4AN0	IO	CLK3n		DIFFIO_RX_B39n	DIFFOUT_B39n	N13	
4A	VREFB4AN0	IO			DIFFIO_RX_B40n	DIFFOUT_B40n	U15	DQ4B
4A	VREFB4AN0	IO	CLK3p		DIFFIO_RX_B39p	DIFFOUT_B39p	P13	
4A	VREFB4AN0	IO			DIFFIO_RX_B40p	DIFFOUT_B40p	T15	DQ4B
5A	VREFB5AN0	IO	RZQ_1		DIFFIO_RX_R1p	DIFFOUT_R1p	L16	DQ1R
5A	VREFB5AN0	IO		INIT_DONE	DIFFIO_RX_R2p	DIFFOUT_R2p	L14	
5A	VREFB5AN0	IO		PR_REQUEST	DIFFIO_RX_R1n	DIFFOUT_R1n	L15	DQ1R
5A	VREFB5AN0	IO		CRC_ERROR	DIFFIO_RX_R2n	DIFFOUT_R2n	K13	
5A	VREFB5AN0	IO		nCEO	DIFFIO_RX_R3p	DIFFOUT_R3p	M18	DQ1R
5A	VREFB5AN0	IO			DIFFIO_RX_R4p	DIFFOUT_R4p	J13	DQ1R



## Pin Information for the Cyclone® V 5CCEBA4 Device

Version 1.1

Note (1)

Bank Number	VREF	Pin Name/Function	Optional Function(s)	Configuration Function	Dedicated Tx/Rx Channel	Emulated LVDS Output Channel	U324	DQS for X8
5A	VREFB5A0	IO		CvP_CONF DONE	DIFFIO_TX_R3n	DIFFOUT_R3n	N18	DQ1R
5A	VREFB5A0	IO			DIFFIO_RX_R4n	DIFFOUT_R4n	J14	DQ1R
5A	VREFB5A0	IO		DEV_OE	DIFFIO_TX_R5p	DIFFOUT_R5p	K17	
5A	VREFB5A0	IO			DIFFIO_RX_R6p	DIFFOUT_R6p	G13	DQS1R
5A	VREFB5A0	IO		DEV_CLRn	DIFFIO_TX_R5n	DIFFOUT_R5n	K16	DQ1R
5A	VREFB5A0	IO			DIFFIO_RX_R6n	DIFFOUT_R6n	H13	DQS1R
5A	VREFB5A0	IO			DIFFIO_TX_R7p	DIFFOUT_R7p	L17	DQ1R
5A	VREFB5A0	IO			DIFFIO_RX_R8p	DIFFOUT_R8p	J16	DQ1R
5A	VREFB5A0	IO			DIFFIO_TX_R7n	DIFFOUT_R7n	K18	
5A	VREFB5A0	IO			DIFFIO_RX_R8n	DIFFOUT_R8n	J15	DQ1R
5B	VREFB5BN0	IO	CLK6p		DIFFIO_RX_R9p	DIFFOUT_R9p	F14	
5B	VREFB5BN0	IO			DIFFIO_TX_R10p	DIFFOUT_R10p	H17	DQ2R
5B	VREFB5BN0	IO	CLK6n		DIFFIO_RX_R9n	DIFFOUT_R9n	G14	
5B	VREFB5BN0	IO			DIFFIO_TX_R10n	DIFFOUT_R10n	G17	DQ2R
5B	VREFB5BN0	IO			DIFFIO_RX_R11p	DIFFOUT_R11p	G15	DQ2R
5B	VREFB5BN0	IO	FPLL_BR_CLKOUT0,FPLL_BR_CLKOUTp,FPLL_BR_FB		DIFFIO_TX_R12p	DIFFOUT_R12p	J18	DQ2R
5B	VREFB5BN0	IO			DIFFIO_RX_R11n	DIFFOUT_R11n	H16	DQ2R
5B	VREFB5BN0	IO	FPLL_BR_CLKOUT1,FPLL_BR_CLKOUTn		DIFFIO_TX_R12n	DIFFOUT_R12n	H18	DQ2R
5B	VREFB5BN0	IO			DIFFIO_RX_R13p	DIFFOUT_R13p	E16	DQS2R
5B	VREFB5BN0	IO			DIFFIO_TX_R14p	DIFFOUT_R14p	E18	
5B	VREFB5BN0	IO			DIFFIO_RX_R13n	DIFFOUT_R13n	F16	DQS2R
5B	VREFB5BN0	IO			DIFFIO_TX_R14n	DIFFOUT_R14n	D18	DQ2R
5B	VREFB5BN0	IO			DIFFIO_RX_R15p	DIFFOUT_R15p	G18	DQ2R
5B	VREFB5BN0	IO			DIFFIO_TX_R16p	DIFFOUT_R16p	C18	DQ2R
5B	VREFB5BN0	IO			DIFFIO_RX_R15n	DIFFOUT_R15n	F17	DQ2R
5B	VREFB5BN0	IO			DIFFIO_TX_R16n	DIFFOUT_R16n	C17	
7A		GND					D15	
7A	VREFB7A0	IO	CLK11p		DIFFIO_RX_T9p	DIFFOUT_T9p	F12	
7A	VREFB7A0	IO			DIFFIO_TX_T10p	DIFFOUT_T10p	D16	DQ1T
7A	VREFB7A0	IO	CLK11n		DIFFIO_RX_T9n	DIFFOUT_T9n	F11	
7A	VREFB7A0	IO			DIFFIO_TX_T10n	DIFFOUT_T10n	C16	DQ1T
7A	VREFB7A0	IO			DIFFIO_RX_T11p	DIFFOUT_T11p	C13	DQ1T
7A	VREFB7A0	IO			DIFFIO_TX_T12p	DIFFOUT_T12p	B14	DQ1T
7A	VREFB7A0	IO			DIFFIO_RX_T11n	DIFFOUT_T11n	C12	DQ1T
7A	VREFB7A0	IO			DIFFIO_TX_T12n	DIFFOUT_T12n	B15	DQ1T
7A	VREFB7A0	IO			DIFFIO_RX_T13p	DIFFOUT_T13p	E12	DQS1T
7A	VREFB7A0	IO			DIFFIO_TX_T14p	DIFFOUT_T14p	B17	
7A	VREFB7A0	IO			DIFFIO_RX_T13n	DIFFOUT_T13n	E11	DQS1T
7A	VREFB7A0	IO			DIFFIO_TX_T14n	DIFFOUT_T14n	B18	DQ1T
7A	VREFB7A0	IO			DIFFIO_RX_T15p	DIFFOUT_T15p	D13	DQ1T
7A	VREFB7A0	IO			DIFFIO_TX_T16p	DIFFOUT_T16p	A16	DQ1T
7A	VREFB7A0	IO			DIFFIO_RX_T15n	DIFFOUT_T15n	E14	DQ1T
7A	VREFB7A0	IO			DIFFIO_TX_T16n	DIFFOUT_T16n	A17	
7A	VREFB7A0	IO	CLK10p		DIFFIO_RX_T17p	DIFFOUT_T17p	F9	
7A	VREFB7A0	IO			DIFFIO_TX_T18p	DIFFOUT_T18p	A14	DQ2T
7A	VREFB7A0	IO	CLK10n		DIFFIO_RX_T17n	DIFFOUT_T17n	F10	
7A	VREFB7A0	IO			DIFFIO_TX_T18n	DIFFOUT_T18n	A15	DQ2T
7A	VREFB7A0	IO			DIFFIO_RX_T19p	DIFFOUT_T19p	C11	DQ2T
7A	VREFB7A0	IO			DIFFIO_TX_T20p	DIFFOUT_T20p	A12	DQ2T
7A	VREFB7A0	IO			DIFFIO_RX_T19n	DIFFOUT_T19n	B10	DQ2T
7A	VREFB7A0	IO			DIFFIO_TX_T20n	DIFFOUT_T20n	B12	DQ2T
7A	VREFB7A0	IO			DIFFIO_RX_T21p	DIFFOUT_T21p	D9	DQS2T
7A	VREFB7A0	IO			DIFFIO_TX_T22p	DIFFOUT_T22p	A11	
7A	VREFB7A0	IO			DIFFIO_RX_T21n	DIFFOUT_T21n	E9	DQS2T
7A	VREFB7A0	IO			DIFFIO_TX_T22n	DIFFOUT_T22n	A10	DQ2T
7A	VREFB7A0	IO			DIFFIO_RX_T23p	DIFFOUT_T23p	D11	DQ2T



## Pin Information for the Cyclone® V 5CEBA4 Device

Version 1.1

Note (1)

Bank Number	VREF	Pin Name/Function	Optional Function(s)	Configuration Function	Dedicated Tx/Rx Channel	Emulated LVDS Output Channel	U324	DQS for X8
7A	VREFB7A0	IO			DIFFIO_TX_T24p	DIFFOUT_T24p	A9	DQ2T
7A	VREFB7A0	IO			DIFFIO_RX_T23n	DIFFOUT_T23n	D10	DQ2T
7A	VREFB7A0	IO	RZQ_2		DIFFIO_TX_T24n	DIFFOUT_T24n	B9	
8A	VREFB8A0	IO	CLK9p		DIFFIO_RX_T25p	DIFFOUT_T25p	G6	
8A	VREFB8A0	IO			DIFFIO_TX_T26p	DIFFOUT_T26p	A7	DQ3T
8A	VREFB8A0	IO	CLK9n		DIFFIO_RX_T25n	DIFFOUT_T25n	F6	
8A	VREFB8A0	IO			DIFFIO_TX_T26n	DIFFOUT_T26n	A6	DQ3T
8A	VREFB8A0	IO			DIFFIO_RX_T27p	DIFFOUT_T27p	B7	DQ3T
8A	VREFB8A0	IO	FPLL_TL_CLKOUT0,FPLL_TL_CLKOUTp,FPLL_TL_FB		DIFFIO_TX_T28p	DIFFOUT_T28p	A4	DQ3T
8A	VREFB8A0	IO			DIFFIO_RX_T27n	DIFFOUT_T27n	B8	DQ3T
8A	VREFB8A0	IO	FPLL_TL_CLKOUT1,FPLL_TL_CLKOUTn		DIFFIO_TX_T28n	DIFFOUT_T28n	A5	DQ3T
8A	VREFB8A0	IO			DIFFIO_RX_T29p	DIFFOUT_T29p	E8	DQS3T
8A	VREFB8A0	IO			DIFFIO_TX_T30p	DIFFOUT_T30p	C1	
8A	VREFB8A0	IO			DIFFIO_RX_T29n	DIFFOUT_T29n	F7	DQS3T
8A	VREFB8A0	IO			DIFFIO_TX_T30n	DIFFOUT_T30n	C2	DQ3T
8A	VREFB8A0	IO			DIFFIO_RX_T31p	DIFFOUT_T31p	B4	DQ3T
8A	VREFB8A0	IO			DIFFIO_TX_T32p	DIFFOUT_T32p	B3	DQ3T
8A	VREFB8A0	IO			DIFFIO_RX_T31n	DIFFOUT_T31n	B5	DQ3T
8A	VREFB8A0	IO			DIFFIO_TX_T32n	DIFFOUT_T32n	C3	
9A		MSEL0		MSEL0			J6	
9A		CONF_DONE		CONF_DONE			C6	
9A		MSEL1		MSEL1			H5	
9A		nSTATUS		nSTATUS			D6	
9A		nCE		nCE			E4	
9A		MSEL2		MSEL2			D3	
9A		MSEL3		MSEL3			G5	
9A		nCONFIG		nCONFIG			D4	
9A		MSEL4		MSEL4			G4	
9A		GND					D5	
		GND					D12	
		GND					V18	
		GND					V14	
		GND					V4	
		GND					U1	
		GND					T13	
		GND					T3	
		GND					R10	
		GND					P17	
		GND					P12	
		GND					P7	
		GND					N14	
		GND					N9	
		GND					N4	
		GND					M12	
		GND					M6	
		GND					M1	
		GND					L18	
		GND					L11	
		GND					L9	
		GND					L7	
		GND					K12	
		GND					K10	
		GND					K8	
		GND					K5	
		GND					J17	
		GND					J11	



## Pin Information for the Cyclone® V 5CEBA4 Device

Version 1.1

Note (1)

Bank Number	VREF	Pin Name/Function	Optional Function(s)	Configuration Function	Dedicated Tx/Rx Channel	Emulated LVDS Output Channel	U324	DQS for X8
		GND					J9	
		GND					J7	
		GND					H14	
		GND					H12	
		GND					H10	
		GND					H8	
		GND					H6	
		GND					G11	
		GND					G9	
		GND					G7	
		GND					G1	
		GND					F13	
		GND					F8	
		GND					F3	
		GND					E10	
		GND					E5	
		GND					D17	
		GND					D7	
		GND					D2	
		GND					C4	
		GND					B11	
		GND					B1	
		GND					A18	
		GND					A8	
		GND					A3	
		VCC					M11	
		VCC					L12	
		VCC					L10	
		VCC					L8	
		VCC					K11	
		VCC					K9	
		VCC					K7	
		VCC					J12	
		VCC					J10	
		VCC					J8	
		VCC					H11	
		VCC					H9	
		VCC					H7	
		VCC					G12	
		VCC					G10	
		VCC					G8	
		DNU					A2	
		DNU					B2	
		DNU					C15	
		DNU					C8	
		VCCPGM					T6	
		VCCPGM					M15	
		VCCPGM					E7	
		VCCBAT					C5	
		VCCIO2A					H4	
		VCCIO2A					P2	
		VCCIO2A					L3	
		VCCIO2A					J2	
		VCCIO3A					R5	
		VCCIO3A					U6	
		VCCIO3B					T8	



## Pin Information for the Cyclone® V 5CEBA4 Device

Version 1.1

Note (1)

Bank Number	VREF	Pin Name/Function	Optional Function(s)	Configuration Function	Dedicated Tx/Rx Channel	Emulated LVDS Output Channel	U324	DQS for X8
		VCCIO3B					V9	
		VCCIO4A					T18	
		VCCIO4A					U16	
		VCCIO4A					U11	
		VCCIO4A					R15	
		VCCIO5A					K15	
		VCCIO5A					M16	
		VCCIO5B					F18	
		VCCIO5B					G16	
		VCCIO7A					B16	
		VCCIO7A					E15	
		VCCIO7A					C14	
		VCCIO7A					A13	
		VCCIO8A					C9	
		VCCIO8A					B6	
		VCCPD1A2A					K4	
		VCCPD1A2A					J5	
		VCCPD3A					R7	
		VCCPD3B4A					R12	
		VCCPD3B4A					R8	
		VCCPD5A					K14	
		VCCPD5B					H15	
		VCCPD7A8A					D8	
		VCCPD7A8A					E13	
2A	VREFB2AN0	VREFB2AN0					N1	
3A	VREFB3AN0	VREFB3AN0					V5	
3B	VREFB3BN0	VREFB3BN0					U10	
4A	VREFB4AN0	VREFB4AN0					V11	
5A	VREFB5AN0	VREFB5AN0					M17	
5B	VREFB5BN0	VREFB5BN0					E17	
7A	VREFB7AN0	VREFB7AN0					B13	
8A	VREFB8AN0	VREFB8AN0					C7	
		RREF_TL					A1	
		VCCA_FPLL					H3	
		VCCA_FPLL					N5	
		VCCA_FPLL					F5	
		VCCA_FPLL					N15	
		VCCA_FPLL					F15	
		VCC_AUX					E6	
		VCC_AUX					C10	
		VCC_AUX					D14	
		VCC_AUX					R14	
		VCC_AUX					T10	
		VCC_AUX					R6	

Note:

(1) For more information about pin definition and pin connection guidelines, refer to the

[Cyclone V Device Family Pin Connection Guidelines.](#)



Pin Information for the Cyclone® V 5CBEA4 Device  
Version 1.1  
Note (1)

Bank Number	VREF	Pin Name/Function	Optional Function(s)	Configuration Function	Dedicated Tx/Rx Channel	Emulated LVDS Output Channel	U484	DQS for X8	DQS for X16
2A	VREFB2AN0	IO			DIFFIO_TX_L9n	DIFFOUT_L9n	C1		
2A	VREFB2AN0	IO			DIFFIO_RX_L10n	DIFFOUT_L10n	L1	DQ1L	
2A	VREFB2AN0	IO			DIFFIO_TX_L9p	DIFFOUT_L9p	C2	DQ1L	
2A	VREFB2AN0	IO			DIFFIO_RX_L10p	DIFFOUT_L10p	L2	DQ1L	
2A	VREFB2AN0	IO			DIFFIO_RX_L11n	DIFFOUT_L11n	N1	DQS1L	
2A	VREFB2AN0	IO			DIFFIO_TX_L12n	DIFFOUT_L12n	E2	DQ1L	
2A	VREFB2AN0	IO			DIFFIO_RX_L11p	DIFFOUT_L11p	N2	DQS1L	
2A	VREFB2AN0	IO			DIFFIO_TX_L12p	DIFFOUT_L12p	D3		
2A	VREFB2AN0	IO			DIFFIO_RX_L13n	DIFFOUT_L13n	G1	DQ1L	
2A	VREFB2AN0	IO			DIFFIO_RX_L14n	DIFFOUT_L14n	U1	DQ1L	
2A	VREFB2AN0	IO			DIFFIO_TX_L13p	DIFFOUT_L13p	G2	DQ1L	
2A	VREFB2AN0	IO			DIFFIO_RX_L14p	DIFFOUT_L14p	U2	DQ1L	
2A	VREFB2AN0	IO			DIFFIO_RX_L15n	DIFFOUT_L15n	W2		
2A	VREFB2AN0	IO			DIFFIO_TX_L16n	DIFFOUT_L16n	AA1	DQ1L	
2A	VREFB2AN0	IO			DIFFIO_RX_L15p	DIFFOUT_L15p	Y3		
2A	VREFB2AN0	IO			DIFFIO_TX_L16p	DIFFOUT_L16p	AA2	DQ1L	
3A		TDO		TDO			V3		
3A		nCSO		DATA4			AB6		
3A		TMS		TMS			R4		
3A		AS_DATA3		DATA3			AA5		
3A		TCK		TCK			V5		
3A		AS_DATA2		DATA2			T5		
3A		TDI		TDI			P5		
3A		AS_DATA1		DATA1			W5		
3A		DCLK		DCLK			M5		
3A		AS_DATA0,ASDO		DATA0			AB4		
3A	VREFB3AN0	IO		DATA6	DIFFIO_RX_B1n	DIFFOUT_B1n	P6	DQ1B	
3A	VREFB3AN0	IO		DATA5	DIFFIO_RX_B2n	DIFFOUT_B2n	U7		
3A	VREFB3AN0	IO		DATA8	DIFFIO_RX_B1p	DIFFOUT_B1p	N6	DQ1B	
3A	VREFB3AN0	IO		DATA7	DIFFIO_RX_B2p	DIFFOUT_B2p	U6	DQ1B	
3A	VREFB3AN0	IO		DATA10	DIFFIO_RX_B3n	DIFFOUT_B3n	M6	DQS1B	
3A	VREFB3AN0	IO		DATA9	DIFFIO_RX_B4n	DIFFOUT_B4n	R5	DQ1B	
3A	VREFB3AN0	IO		DATA12	DIFFIO_RX_B3p	DIFFOUT_B3p	M7	DQS1B	
3A	VREFB3AN0	IO		DATA11	DIFFIO_RX_B4p	DIFFOUT_B4p	R6		
3A	VREFB3AN0	IO		DATA14	DIFFIO_RX_B5n	DIFFOUT_B5n	R7	DQ1B	
3A	VREFB3AN0	IO		DATA13	DIFFIO_RX_B6n	DIFFOUT_B6n	L7	DQ1B	
3A	VREFB3AN0	IO		CLKUSR	DIFFIO_RX_B5p	DIFFOUT_B5p	T7	DQ1B	
3A	VREFB3AN0	IO		DATA15	DIFFIO_RX_B6p	DIFFOUT_B6p	L8	DQ1B	
3A	VREFB3AN0	IO		PR_DONE	DIFFIO_RX_B7n	DIFFOUT_B7n	T8		
3A	VREFB3AN0	IO		PR_READY	DIFFIO_RX_B8n	DIFFOUT_B8n	P7	DQ1B	
3A	VREFB3AN0	IO		PR_ERROR	DIFFIO_RX_B7p	DIFFOUT_B7p	T9		
3A	VREFB3AN0	IO			DIFFIO_RX_B8p	DIFFOUT_B8p	P8	DQ1B	
3B	VREFB3BN0	IO			DIFFIO_RX_B9n	DIFFOUT_B9n	V8		
3B	VREFB3BN0	IO			DIFFIO_RX_B10n	DIFFOUT_B10n	N8	DQ2B	
3B	VREFB3BN0	IO			DIFFIO_RX_B9p	DIFFOUT_B9p	W8	DQ2B	
3B	VREFB3BN0	IO			DIFFIO_RX_B10p	DIFFOUT_B10p	M8	DQ2B	
3B	VREFB3BN0	IO			DIFFIO_RX_B11n	DIFFOUT_B11n	N9	DQS1B	
3B	VREFB3BN0	IO			DIFFIO_RX_B12n	DIFFOUT_B12n	AA7	DQ2B	
3B	VREFB3BN0	IO			DIFFIO_RX_B11p	DIFFOUT_B11p	N10	DQS2B	
3B	VREFB3BN0	IO			DIFFIO_RX_B12p	DIFFOUT_B12p	AB7		
3B	VREFB3BN0	IO			DIFFIO_RX_B13n	DIFFOUT_B13n	Y7	DQ2B	
3B	VREFB3BN0	IO			DIFFIO_RX_B14n	DIFFOUT_B14n	U8	DQ2B	
3B	VREFB3BN0	IO			DIFFIO_RX_B13p	DIFFOUT_B13p	W7	DQ2B	
3B	VREFB3BN0	IO			DIFFIO_RX_B14p	DIFFOUT_B14p	V9	DQ2B	
3B	VREFB3BN0	IO	CLK0n,FPLL_BL_FBn		DIFFIO_RX_B15n	DIFFOUT_B15n	R9		
3B	VREFB3BN0	IO			DIFFIO_RX_B16n	DIFFOUT_B16n	AB8	DQ2B	
3B	VREFB3BN0	IO	CLK0p,FPLL_BL_FBp		DIFFIO_RX_B15p	DIFFOUT_B15p	P9		
3B	VREFB3BN0	IO			DIFFIO_RX_B16p	DIFFOUT_B16p	AA8	DQ2B	
3B	VREFB3BN0	IO			DIFFIO_RX_B17n	DIFFOUT_B17n	Y10		
3B	VREFB3BN0	IO			DIFFIO_RX_B18n	DIFFOUT_B18n	AA9	DQ3B	
3B	VREFB3BN0	IO			DIFFIO_RX_B17p	DIFFOUT_B17p	AA10	DQ3B	
3B	VREFB3BN0	IO			DIFFIO_RX_B18p	DIFFOUT_B18p	Y9	DQ3B	
3B	VREFB3BN0	IO			DIFFIO_RX_B19n	DIFFOUT_B19n	L9	DQS3B	
3B	VREFB3BN0	IO			DIFFIO_RX_B20n	DIFFOUT_B20n	W11	DQ3B	
3B	VREFB3BN0	IO			DIFFIO_RX_B19p	DIFFOUT_B19p	M10	DQS3B	
3B	VREFB3BN0	IO			DIFFIO_RX_B20p	DIFFOUT_B20p	Y11		
3B	VREFB3BN0	IO	FPLL_BL_CLKOUT1,FPLL_BL_CLKOUTn		DIFFIO_RX_B21n	DIFFOUT_B21n	AB10	DQ3B	
3B	VREFB3BN0	IO			DIFFIO_RX_B22n	DIFFOUT_B22n	U10	DQ3B	
3B	VREFB3BN0	IO	FPLL_BL_CLKOUT0,FPLL_BL_CLKOUTp,FPLL_BL_FB		DIFFIO_RX_B21p	DIFFOUT_B21p	AB11	DQ3B	
3B	VREFB3BN0	IO			DIFFIO_RX_B22p	DIFFOUT_B22p	U11	DQ3B	
3B	VREFB3BN0	IO	CLK1n		DIFFIO_RX_B23n	DIFFOUT_B23n	T10		



Pin Information for the Cyclone® V 5CBEA4 Device  
Version 1.1  
Note (1)

Bank Number	VREF	Pin Name/Function	Optional Function(s)	Configuration Function	Dedicated Tx/Rx Channel	Emulated LVDS Output Channel	U484	DQS for X8	DQS for X16
3B	VREFB3BN0	IO			DIFFIO_TX_B24n	DIFFOUT_B24n	R11	DQ3B	
3B	VREFB3BN0	IO	CLK1p		DIFFIO_RX_B23p	DIFFOUT_B23p	R10		
3B	VREFB3BN0	IO			DIFFIO_TX_B24p	DIFFOUT_B24p	P12	DQ3B	
4A	VREFB4AN0	IO	RZQ_0		DIFFIO_TX_B25n	DIFFOUT_B25n	AA13		
4A	VREFB4AN0	IO			DIFFIO_RX_B26n	DIFFOUT_B26n	W12	DQ4B	
4A	VREFB4AN0	IO			DIFFIO_TX_B25p	DIFFOUT_B25p	AB13	DQ4B	
4A	VREFB4AN0	IO			DIFFIO_RX_B26p	DIFFOUT_B26p	Y12	DQ4B	
4A	VREFB4AN0	IO			DIFFIO_RX_B27n	DIFFOUT_B27n	U12	DQS4B	
4A	VREFB4AN0	IO			DIFFIO_TX_B28n	DIFFOUT_B28n	R12	DQ4B	
4A	VREFB4AN0	IO			DIFFIO_RX_B27p	DIFFOUT_B27p	T12	DQS4B	
4A	VREFB4AN0	IO			DIFFIO_TX_B28p	DIFFOUT_B28p	T13		
4A	VREFB4AN0	IO			DIFFIO_TX_B29n	DIFFOUT_B29n	AB15	DQ4B	
4A	VREFB4AN0	IO			DIFFIO_RX_B30n	DIFFOUT_B30n	W13	DQ4B	
4A	VREFB4AN0	IO			DIFFIO_TX_B29p	DIFFOUT_B29p	AB16	DQ4B	
4A	VREFB4AN0	IO			DIFFIO_RX_B30p	DIFFOUT_B30p	V13	DQ4B	
4A	VREFB4AN0	IO	CLK2n		DIFFIO_RX_B31n	DIFFOUT_B31n	T14		
4A	VREFB4AN0	IO			DIFFIO_TX_B32n	DIFFOUT_B32n	AB18	DQ4B	
4A	VREFB4AN0	IO	CLK2p		DIFFIO_RX_B31p	DIFFOUT_B31p	U13		
4A	VREFB4AN0	IO			DIFFIO_TX_B32p	DIFFOUT_B32p	AA18	DQ4B	
4A	VREFB4AN0	IO			DIFFIO_RX_B33n	DIFFOUT_B33n	AA19		
4A	VREFB4AN0	IO			DIFFIO_RX_B34n	DIFFOUT_B34n	Y14	DQ5B	DQ1B
4A	VREFB4AN0	IO			DIFFIO_TX_B33p	DIFFOUT_B33p	Y19	DQ5B	DQ1B
4A	VREFB4AN0	IO			DIFFIO_RX_B34p	DIFFOUT_B34p	W14	DQ5B	DQ1B
4A	VREFB4AN0	IO			DIFFIO_RX_B35n	DIFFOUT_B35n	P14	DQS5B	DQ1B
4A	VREFB4AN0	IO			DIFFIO_TX_B36n	DIFFOUT_B36n	AA20	DQ5B	DQ1B
4A	VREFB4AN0	IO			DIFFIO_RX_B35p	DIFFOUT_B35p	R14	DQS5B	DQ1B
4A	VREFB4AN0	IO			DIFFIO_TX_B36p	DIFFOUT_B36p	Y20		
4A	VREFB4AN0	IO			DIFFIO_TX_B37n	DIFFOUT_B37n	AA15	DQ5B	DQ1B
4A	VREFB4AN0	IO			DIFFIO_RX_B38n	DIFFOUT_B38n	U15	DQ5B	DQ1B
4A	VREFB4AN0	IO			DIFFIO_TX_B37p	DIFFOUT_B37p	Y15	DQ5B	DQ1B
4A	VREFB4AN0	IO			DIFFIO_RX_B38p	DIFFOUT_B38p	V15	DQ5B	DQ1B
4A	VREFB4AN0	IO	CLK3n		DIFFIO_RX_B39n	DIFFOUT_B39n	R15		
4A	VREFB4AN0	IO			DIFFIO_TX_B40n	DIFFOUT_B40n	AB20	DQ5B	DQ1B
4A	VREFB4AN0	IO	CLK3p		DIFFIO_RX_B39p	DIFFOUT_B39p	T15		
4A	VREFB4AN0	IO			DIFFIO_TX_B40p	DIFFOUT_B40p	AB21	DQ5B	DQ1B
4A	VREFB4AN0	IO			DIFFIO_TX_B41n	DIFFOUT_B41n	AB22		
4A	VREFB4AN0	IO			DIFFIO_RX_B42n	DIFFOUT_B42n	Y16	DQ6B	DQ1B
4A	VREFB4AN0	IO			DIFFIO_TX_B41p	DIFFOUT_B41p	AA22	DQ6B	DQ1B
4A	VREFB4AN0	IO			DIFFIO_RX_B42p	DIFFOUT_B42p	Y17	DQ6B	DQ1B
4A	VREFB4AN0	IO			DIFFIO_RX_B43n	DIFFOUT_B43n	U16	DQS6B	DQS1B
4A	VREFB4AN0	IO			DIFFIO_TX_B44n	DIFFOUT_B44n	AA17	DQ6B	DQ1B
4A	VREFB4AN0	IO			DIFFIO_RX_B43p	DIFFOUT_B43p	U17	DQS6B	DQS1B
4A	VREFB4AN0	IO			DIFFIO_TX_B44p	DIFFOUT_B44p	AB17		
4A	VREFB4AN0	IO			DIFFIO_RX_B45n	DIFFOUT_B45n	Y22	DQ6B	DQ1B
4A	VREFB4AN0	IO			DIFFIO_RX_B46n	DIFFOUT_B46n	V18	DQ6B	DQ1B
4A	VREFB4AN0	IO			DIFFIO_TX_B45p	DIFFOUT_B45p	Y21	DQ6B	DQ1B
4A	VREFB4AN0	IO			DIFFIO_RX_B46p	DIFFOUT_B46p	W18	DQ6B	DQ1B
4A	VREFB4AN0	IO			DIFFIO_RX_B47n	DIFFOUT_B47n	W16		
4A	VREFB4AN0	IO			DIFFIO_TX_B48n	DIFFOUT_B48n	W21	DQ6B	DQ1B
4A	VREFB4AN0	IO			DIFFIO_RX_B47p	DIFFOUT_B47p	W17		
4A	VREFB4AN0	IO			DIFFIO_TX_B48p	DIFFOUT_B48p	W22	DQ6B	DQ1B
5A	VREFB5AN0	IO	RZQ_1		DIFFIO_RX_R1p	DIFFOUT_R1p	U22	DQ1R	
5A	VREFB5AN0	IO		INIT_DONE	DIFFIO_RX_R2p	DIFFOUT_R2p	V20		
5A	VREFB5AN0	IO		PR_REQUEST	DIFFIO_TX_R1n	DIFFOUT_R1n	U21	DQ1R	
5A	VREFB5AN0	IO		CRC_ERROR	DIFFIO_RX_R2n	DIFFOUT_R2n	V19		
5A	VREFB5AN0	IO		rCEO	DIFFIO_RX_R3p	DIFFOUT_R3p	T19	DQ1R	
5A	VREFB5AN0	IO			DIFFIO_RX_R4p	DIFFOUT_R4p	T17	DQ1R	
5A	VREFB5AN0	IO		CvP_CONF DONE	DIFFIO_TX_R3n	DIFFOUT_R3n	T20	DQ1R	
5A	VREFB5AN0	IO			DIFFIO_RX_R4n	DIFFOUT_R4n	T18	DQ1R	
5A	VREFB5AN0	IO		DEV_OE	DIFFIO_TX_R5p	DIFFOUT_R5p	T22		
5A	VREFB5AN0	IO			DIFFIO_RX_R6p	DIFFOUT_R6p	R16	DQS1R	
5A	VREFB5AN0	IO		DEV_CLRn	DIFFIO_TX_R5n	DIFFOUT_R5n	R22	DQ1R	
5A	VREFB5AN0	IO			DIFFIO_RX_R6n	DIFFOUT_R6n	R17	DQS1R	
5A	VREFB5AN0	IO			DIFFIO_RX_R7p	DIFFOUT_R7p	R20	DQ1R	
5A	VREFB5AN0	IO			DIFFIO_RX_R8p	DIFFOUT_R8p	R19	DQ1R	
5A	VREFB5AN0	IO			DIFFIO_TX_R7n	DIFFOUT_R7n	R21		
5A	VREFB5AN0	IO			DIFFIO_RX_R8n	DIFFOUT_R8n	P19	DQ1R	
5B	VREFB5BN0	IO	CLK6p		DIFFIO_RX_R9p	DIFFOUT_R9p	L17		
5B	VREFB5BN0	IO	CLK6n		DIFFIO_TX_R10p	DIFFOUT_R10p	E20	DQ2R	
5B	VREFB5BN0	IO			DIFFIO_RX_R9n	DIFFOUT_R9n	K17		
5B	VREFB5BN0	IO			DIFFIO_TX_R10n	DIFFOUT_R10n	F20	DQ2R	



Pin Information for the Cyclone® V 5CBEA4 Device  
Version 1.1  
Note (1)

Bank Number	VREF	Pin Name/Function	Optional Function(s)	Configuration Function	Dedicated Tx/Rx Channel	Emulated LVDS Output Channel	U484	DQS for X8	DQS for X16
5B	VREFB5BN0	IO			DIFFIO_RX_R11p	DIFFOUT_R11p	H20	DQ2R	
5B	VREFB5BN0	IO	FPPLL_BR_CLKOUT0,FPPLL_BR_CLKOUTp,FPPLL_BR_FB		DIFFIO_TX_R12p	DIFFOUT_R12p	G18	DQ2R	
5B	VREFB5BN0	IO			DIFFIO_RX_R11n	DIFFOUT_R11n	H19	DQ2R	
5B	VREFB5BN0	IO	FPPLL_BR_CLKOUT1,FPPLL_BR_CLKOUTn		DIFFIO_TX_R12n	DIFFOUT_R12n	G17	DQ2R	
5B	VREFB5BN0	IO			DIFFIO_RX_R13p	DIFFOUT_R13p	K16	DQS2R	
5B	VREFB5BN0	IO			DIFFIO_TX_R14p	DIFFOUT_R14p	F19		
5B	VREFB5BN0	IO			DIFFIO_RX_R13n	DIFFOUT_R13n	J16	DQS2R	
5B	VREFB5BN0	IO			DIFFIO_TX_R14n	DIFFOUT_R14n	F18	DQ2R	
5B	VREFB5BN0	IO			DIFFIO_RX_R15p	DIFFOUT_R15p	J17	DQ2R	
5B	VREFB5BN0	IO			DIFFIO_TX_R16p	DIFFOUT_R16p	J19	DQ2R	
5B	VREFB5BN0	IO			DIFFIO_RX_R15n	DIFFOUT_R15n	J18	DQ2R	
5B	VREFB5BN0	IO			DIFFIO_TX_R16n	DIFFOUT_R16n	H18		
7A		GND					F17		
7A	VREFB7AN0	IO			DIFFIO_RX_T1p	DIFFOUT_T1p	H16		
7A	VREFB7AN0	IO			DIFFIO_TX_T2p	DIFFOUT_T2p	C21	DQ1T	DQ1T
7A	VREFB7AN0	IO			DIFFIO_RX_T1n	DIFFOUT_T1n	G16		
7A	VREFB7AN0	IO			DIFFIO_TX_T2n	DIFFOUT_T2n	C20	DQ1T	DQ1T
7A	VREFB7AN0	IO			DIFFIO_RX_T3p	DIFFOUT_T3p	D18	DQ1T	DQ1T
7A	VREFB7AN0	IO			DIFFIO_TX_T4p	DIFFOUT_T4p	B20	DQ1T	DQ1T
7A	VREFB7AN0	IO			DIFFIO_RX_T3n	DIFFOUT_T3n	E17	DQ1T	DQ1T
7A	VREFB7AN0	IO			DIFFIO_TX_T4n	DIFFOUT_T4n	B21	DQ1T	DQ1T
7A	VREFB7AN0	IO			DIFFIO_RX_T5p	DIFFOUT_T5p	G15	DQS1T	DQS1T
7A	VREFB7AN0	IO			DIFFIO_TX_T6p	DIFFOUT_T6p	B22		
7A	VREFB7AN0	IO			DIFFIO_RX_T5n	DIFFOUT_T5n	G14	DQS1T	DQS1T
7A	VREFB7AN0	IO			DIFFIO_TX_T6n	DIFFOUT_T6n	A22	DQ1T	DQ1T
7A	VREFB7AN0	IO			DIFFIO_RX_T7p	DIFFOUT_T7p	E16	DQ1T	DQ1T
7A	VREFB7AN0	IO			DIFFIO_TX_T8p	DIFFOUT_T8p	A20	DQ1T	DQ1T
7A	VREFB7AN0	IO			DIFFIO_RX_T7n	DIFFOUT_T7n	D17	DQ1T	DQ1T
7A	VREFB7AN0	IO			DIFFIO_TX_T8n	DIFFOUT_T8n	A19		
7A	VREFB7AN0	IO	CLK11p		DIFFIO_RX_T9p	DIFFOUT_T9p	G13		
7A	VREFB7AN0	IO			DIFFIO_TX_T10p	DIFFOUT_T10p	C19	DQ2T	DQ1T
7A	VREFB7AN0	IO	CLK11n		DIFFIO_RX_T9n	DIFFOUT_T9n	F14		
7A	VREFB7AN0	IO			DIFFIO_TX_T10n	DIFFOUT_T10n	C18	DQ2T	DQ1T
7A	VREFB7AN0	IO			DIFFIO_RX_T11p	DIFFOUT_T11p	C16	DQ2T	DQ1T
7A	VREFB7AN0	IO			DIFFIO_TX_T12p	DIFFOUT_T12p	B16	DQ2T	DQ1T
7A	VREFB7AN0	IO			DIFFIO_RX_T11n	DIFFOUT_T11n	C15	DQ2T	DQ1T
7A	VREFB7AN0	IO			DIFFIO_TX_T12n	DIFFOUT_T12n	B15	DQ2T	DQ1T
7A	VREFB7AN0	IO			DIFFIO_RX_T13p	DIFFOUT_T13p	G12	DQS2T	DQ1T
7A	VREFB7AN0	IO			DIFFIO_TX_T14p	DIFFOUT_T14p	A18		
7A	VREFB7AN0	IO			DIFFIO_RX_T13n	DIFFOUT_T13n	H12	DQS2T	DQ1T
7A	VREFB7AN0	IO			DIFFIO_TX_T14n	DIFFOUT_T14n	A17	DQ2T	DQ1T
7A	VREFB7AN0	IO			DIFFIO_RX_T15p	DIFFOUT_T15p	F15	DQ2T	DQ1T
7A	VREFB7AN0	IO			DIFFIO_TX_T16p	DIFFOUT_T16p	B18	DQ2T	DQ1T
7A	VREFB7AN0	IO			DIFFIO_RX_T15n	DIFFOUT_T15n	E14	DQ2T	DQ1T
7A	VREFB7AN0	IO			DIFFIO_TX_T16n	DIFFOUT_T16n	B17		
7A	VREFB7AN0	IO	CLK10p		DIFFIO_RX_T17p	DIFFOUT_T17p	H10		
7A	VREFB7AN0	IO			DIFFIO_TX_T18p	DIFFOUT_T18p	A15	DQ3T	
7A	VREFB7AN0	IO	CLK10n		DIFFIO_RX_T17n	DIFFOUT_T17n	G11		
7A	VREFB7AN0	IO			DIFFIO_TX_T18n	DIFFOUT_T18n	A14	DQ3T	
7A	VREFB7AN0	IO			DIFFIO_RX_T19p	DIFFOUT_T19p	D13	DQ3T	
7A	VREFB7AN0	IO			DIFFIO_TX_T20p	DIFFOUT_T20p	C14	DQ3T	
7A	VREFB7AN0	IO			DIFFIO_RX_T19n	DIFFOUT_T19n	C13	DQ3T	
7A	VREFB7AN0	IO			DIFFIO_TX_T20n	DIFFOUT_T20n	D14	DQ3T	
7A	VREFB7AN0	IO			DIFFIO_RX_T21p	DIFFOUT_T21p	H9	DQS3T	
7A	VREFB7AN0	IO			DIFFIO_TX_T22p	DIFFOUT_T22p	A13		
7A	VREFB7AN0	IO			DIFFIO_RX_T21n	DIFFOUT_T21n	G8	DQS3T	
7A	VREFB7AN0	IO			DIFFIO_TX_T22n	DIFFOUT_T22n	B13	DQ3T	
7A	VREFB7AN0	IO			DIFFIO_RX_T23p	DIFFOUT_T23p	E12	DQ3T	
7A	VREFB7AN0	IO			DIFFIO_TX_T24p	DIFFOUT_T24p	B12	DQ3T	
7A	VREFB7AN0	IO			DIFFIO_RX_T23n	DIFFOUT_T23n	F12	DQ3T	
7A	VREFB7AN0	IO	RZQ_2		DIFFIO_TX_T24n	DIFFOUT_T24n	A12		
8A	VREFB8AN0	IO	CLK9p		DIFFIO_RX_T25p	DIFFOUT_T25p	G10		
8A	VREFB8AN0	IO			DIFFIO_TX_T26p	DIFFOUT_T26p	C11	DQ4T	
8A	VREFB8AN0	IO	CLK9n		DIFFIO_RX_T25n	DIFFOUT_T25n	F10		
8A	VREFB8AN0	IO			DIFFIO_TX_T26n	DIFFOUT_T26n	B11	DQ4T	
8A	VREFB8AN0	IO			DIFFIO_RX_T27p	DIFFOUT_T27p	D11	DQ4T	
8A	VREFB8AN0	IO	FPPLL_TL_CLKOUT0,FPPLL_TL_CLKOUTp,FPPLL_TL_FB		DIFFIO_TX_T28p	DIFFOUT_T28p	A8	DQ4T	
8A	VREFB8AN0	IO			DIFFIO_RX_T27n	DIFFOUT_T27n	E11	DQ4T	
8A	VREFB8AN0	IO	FPPLL_TL_CLKOUT1,FPPLL_TL_CLKOUTn		DIFFIO_TX_T28n	DIFFOUT_T28n	A7	DQ4T	
8A	VREFB8AN0	IO			DIFFIO_RX_T29p	DIFFOUT_T29p	J9	DQS4T	
8A	VREFB8AN0	IO			DIFFIO_TX_T30p	DIFFOUT_T30p	F8		



Pin Information for the Cyclone® V 5CBEA4 Device  
Version 1.1  
Note (1)

Bank Number	VREF	Pin Name/Function	Optional Function(s)	Configuration Function	Dedicated Tx/Rx Channel	Emulated LVDS Output Channel	U484	DQS for X8	DQS for X16
8A	VREFB8AN0	IO			DIFFIO_RX_T29n	DIFFOUT_T29n	J8	DQSn4T	
8A	VREFB8AN0	IO			DIFFIO_RX_T30n	DIFFOUT_T30n	E7	DQ4T	
8A	VREFB8AN0	IO			DIFFIO_RX_T31p	DIFFOUT_T31p	C10	DQ4T	
8A	VREFB8AN0	IO			DIFFIO_RX_T32p	DIFFOUT_T32p	C6	DQ4T	
8A	VREFB8AN0	IO			DIFFIO_RX_T31n	DIFFOUT_T31n	C9	DQ4T	
8A	VREFB8AN0	IO			DIFFIO_RX_T32n	DIFFOUT_T32n	D7		
8A	VREFB8AN0	IO	CLK8p,FPLL_TL_FBp		DIFFIO_RX_T33p	DIFFOUT_T33p	K7		
8A	VREFB8AN0	IO			DIFFIO_RX_T34p	DIFFOUT_T34p	A10	DQ5T	
8A	VREFB8AN0	IO	CLK8n,FPLL_TL_FBn		DIFFIO_RX_T33n	DIFFOUT_T33n	J7		
8A	VREFB8AN0	IO			DIFFIO_RX_T34n	DIFFOUT_T34n	A9	DQ5T	
8A	VREFB8AN0	IO			DIFFIO_RX_T35p	DIFFOUT_T35p	D9	DQ5T	
8A	VREFB8AN0	IO			DIFFIO_RX_T36p	DIFFOUT_T36p	B6	DQ5T	
8A	VREFB8AN0	IO			DIFFIO_RX_T35n	DIFFOUT_T35n	D8	DQ5T	
8A	VREFB8AN0	IO			DIFFIO_RX_T36n	DIFFOUT_T36n	B5	DQ5T	
8A	VREFB8AN0	IO			DIFFIO_RX_T37p	DIFFOUT_T37p	H8	DQ5T	
8A	VREFB8AN0	IO			DIFFIO_RX_T38p	DIFFOUT_T38p	C8		
8A	VREFB8AN0	IO			DIFFIO_RX_T37n	DIFFOUT_T37n	G7	DQSn6T	
8A	VREFB8AN0	IO			DIFFIO_RX_T38n	DIFFOUT_T38n	B8	DQ5T	
8A	VREFB8AN0	IO			DIFFIO_RX_T39p	DIFFOUT_T39p	H6	DQ5T	
8A	VREFB8AN0	IO			DIFFIO_RX_T40p	DIFFOUT_T40p	E6	DQ5T	
8A	VREFB8AN0	IO			DIFFIO_RX_T39n	DIFFOUT_T39n	G6	DQ5T	
8A	VREFB8AN0	IO			DIFFIO_RX_T40n	DIFFOUT_T40n	F7		
9A	MSEL0			MSEL0		L6			
9A	CONF_DONE			CONF_DONE		J6			
9A	MSEL1			MSEL1		K6			
9A	nSTATUS			nSTATUS		G5			
9A	nCE			nCE		H5			
9A	MSEL2			MSEL2		A2			
9A	MSEL3			MSEL3		E5			
9A	nCONFIG			nCONFIG		A4			
9A	MSEL4			MSEL4		C5			
9A	GND					F3			
	GND					A21			
	GND					AB19			
	GND					AB2			
	GND					AB1			
	GND					AA16			
	GND					AA11			
	GND					AA4			
	GND					AA3			
	GND					Y13			
	GND					Y8			
	GND					Y5			
	GND					Y2			
	GND					Y1			
	GND					W20			
	GND					W4			
	GND					W3			
	GND					V22			
	GND					V17			
	GND					V4			
	GND					V2			
	GND					V1			
	GND					U19			
	GND					U14			
	GND					U9			
	GND					U5			
	GND					U4			
	GND					U3			
	GND					T11			
	GND					T2			
	GND					T1			
	GND					R13			
	GND					R3			
	GND					P10			
	GND					P4			
	GND					P2			
	GND					P1			
	GND					N22			
	GND					N15			
	GND					N13			



Pin Information for the Cyclone® V 5CBEA4 Device  
Version 1.1  
Note (1)

Bank Number	VREF	Pin Name/Function	Optional Function(s)	Configuration Function	Dedicated Tx/Rx Channel	Emulated LVDS Output Channel	U484	DQS for X8	DQS for X16
		GND					N11		
		GND					N7		
		GND					N5		
		GND					N3		
		GND					M19		
		GND					M14		
		GND					M12		
		GND					M9		
		GND					M4		
		GND					M2		
		GND					M1		
		GND					L16		
		GND					L13		
		GND					L11		
		GND					L5		
		GND					L3		
		GND					K14		
		GND					K12		
		GND					K10		
		GND					K8		
		GND					K4		
		GND					K2		
		GND					K1		
		GND					J20		
		GND					J15		
		GND					J13		
		GND					J11		
		GND					J5		
		GND					J3		
		GND					H14		
		GND					H4		
		GND					H3		
		GND					H2		
		GND					H1		
		GND					G9		
		GND					G4		
		GND					G3		
		GND					F21		
		GND					F16		
		GND					F11		
		GND					F6		
		GND					F5		
		GND					F2		
		GND					F1		
		GND					E13		
		GND					E4		
		GND					E3		
		GND					D20		
		GND					D10		
		GND					D5		
		GND					D2		
		GND					D1		
		GND					C22		
		GND					C17		
		GND					C7		
		GND					C4		
		GND					C3		
		GND					B14		
		GND					B2		
		GND					B1		
		GND					A11		
		GND					A5		
		VCC					L4		
		VCC					P15		
		VCC					P13		
		VCC					P11		
		VCC					P3		
		VCC					N14		
		VCC					N12		
		VCC					N4		
		VCC					M15		



Pin Information for the Cyclone® V 5CBEA4 Device  
Version 1.1  
Note (1)

Bank Number	VREF	Pin Name/Function	Optional Function(s)	Configuration Function	Dedicated Tx/Rx Channel	Emulated LVDS Output Channel	U484	DQS for X8	DQS for X16
		VCC					M13		
		VCC					M11		
		VCC					L14		
		VCC					L12		
		VCC					L10		
		VCC					K13		
		VCC					K11		
		VCC					K9		
		VCC					K5		
		VCC					K3		
		VCC					J14		
		VCC					J12		
		VCC					J10		
		VCC					J4		
		VCC					H15		
		VCC					H13		
		VCC					H11		
		DNU					B3		
		DNU					B4		
		DNU					D21		
		DNU					E10		
		VCCPGM					Y6		
		VCCPGM					U20		
		VCCPGM					B7		
		VCCBAT					A3		
		VCCI02A					D4		
		VCCI02A					Y4		
		VCCI02A					R1		
		VCCI02A					J1		
		VCCI03A					T6		
		VCCI03A					AA6		
		VCCI03B					R8		
		VCCI03B					AB9		
		VCCI03B					W10		
		VCCI03B					V7		
		VCCI04A					T16		
		VCCI04A					AB14		
		VCCI04A					AA21		
		VCCI04A					Y18		
		VCCI04A					W15		
		VCCI04A					V12		
		VCCI05A					T21		
		VCCI05A					R18		
		VCCI05B					G19		
		VCCI05B					P20		
		VCCI05B					N17		
		VCCI05B					L21		
		VCCI05B					K18		
		VCCI05B					H22		
		VCCI07A					B19		
		VCCI07A					H17		
		VCCI07A					E18		
		VCCI07A					D15		
		VCCI07A					C12		
		VCCI07A					A16		
		VCCI08A					B9		
		VCCI08A					H7		
		VCCI08A					E8		
		VCCI08A					A6		
		VCCPD1A2A					R2		
		VCCPD1A2A					J2		
		VCCPD1A2A					E1		
		VCCPD3A					V6		
		VCCPD3B4A					W9		
		VCCPD3B4A					V16		
		VCCPD3B4A					V14		
		VCCPD3B4A					V10		
		VCCPD5A					P17		
		VCCPD5B					M18		
		VCCPD5B					N19		
		VCCPD7A8A					E15		



Pin Information for the Cyclone® V 5CBEA4 Device  
Version 1.1  
Note (1)

Bank Number	VREF	Pin Name/Function	Optional Function(s)	Configuration Function	Dedicated Tx/Rx Channel	Emulated LVDS Output Channel	U484	DQS for X8	DQS for X16
		VCCPD7A8A					F13		
		VCCPD7A8A					F9		
		VCCPD7A8A					E9		
2A	VREFB2A0	VREFB2A0					W1		
3A	VREFB3A0	VREFB3A0					W6		
3B	VREFB3BN0	VREFB3BN0					AB12		
4A	VREFB4A0	VREFB4A0					AA14		
5A	VREFB5A0	VREFB5A0					V21		
5B	VREFB5BN0	VREFB5BN0					K20		
7A	VREFB7A0	VREFB7A0					D16		
8A	VREFB8A0	VREFB8A0					B10		
		NC					AB3		
		NC					V11		
		NC					P22		
		NC					P21		
		NC					P18		
		NC					P16		
		NC					N21		
		NC					N20		
		NC					N18		
		NC					N16		
		NC					M22		
		NC					M21		
		NC					M20		
		NC					M17		
		NC					M16		
		NC					L22		
		NC					L20		
		NC					L19		
		NC					L18		
		NC					L15		
		NC					K22		
		NC					K21		
		NC					K19		
		NC					K15		
		NC					J22		
		NC					J21		
		NC					H21		
		NC					G22		
		NC					G21		
		NC					G20		
		NC					F22		
		NC					E22		
		NC					E21		
		NC					D22		
		RREF_TL					A1		
		VCCA_FPLL					M3		
		VCCA_FPLL					T3		
		VCCA_FPLL					T4		
		VCCA_FPLL					F4		
		VCCA_FPLL					U18		
		VCCA_FPLL					E19		
		VCC_AUX					D6		
		VCC_AUX					D12		
		VCC_AUX					D19		
		VCC_AUX					W19		
		VCC_AUX					AA12		
		VCC_AUX					AB5		

Note:

(1) For more information about pin definition and pin connection guidelines, refer to the [Cyclone V Device Family Pin Connection Guidelines](#).



## Pin Information for the Cyclone® V 5CBEA4 Device

Version 1.1

Note (1)

Bank Number	VREF	Pin Name/Function	Optional Function(s)	Configuration Function	Dedicated Tx/Rx Channel	Emulated LVDS Output Channel	F256	DQS for X8
2A	VREFB2AN0	IO			DIFFIO_RX_L9n	DIFFOUT_L9n	F3	
2A	VREFB2AN0	IO			DIFFIO_RX_L10n	DIFFOUT_L10n	G3	DQ1L
2A	VREFB2AN0	IO			DIFFIO_RX_L9p	DIFFOUT_L9p	F4	DQ1L
2A	VREFB2AN0	IO			DIFFIO_RX_L10p	DIFFOUT_L10p	H3	DQ1L
2A	VREFB2AN0	IO			DIFFIO_RX_L11n	DIFFOUT_L11n	H4	DQS1L
2A	VREFB2AN0	IO			DIFFIO_RX_L12n	DIFFOUT_L12n	E2	DQ1L
2A	VREFB2AN0	IO			DIFFIO_RX_L11p	DIFFOUT_L11p	H5	DQS1L
2A	VREFB2AN0	IO			DIFFIO_RX_L12p	DIFFOUT_L12p	F2	
2A	VREFB2AN0	IO			DIFFIO_RX_L13n	DIFFOUT_L13n	G1	DQ1L
2A	VREFB2AN0	IO			DIFFIO_RX_L14n	DIFFOUT_L14n	J2	DQ1L
2A	VREFB2AN0	IO			DIFFIO_RX_L13p	DIFFOUT_L13p	G2	DQ1L
2A	VREFB2AN0	IO			DIFFIO_RX_L14p	DIFFOUT_L14p	J3	DQ1L
2A	VREFB2AN0	IO			DIFFIO_RX_L15n	DIFFOUT_L15n	K4	
2A	VREFB2AN0	IO			DIFFIO_RX_L16n	DIFFOUT_L16n	H1	DQ1L
2A	VREFB2AN0	IO			DIFFIO_RX_L15p	DIFFOUT_L15p	K5	
2A	VREFB2AN0	IO			DIFFIO_RX_L16p	DIFFOUT_L16p	J1	DQ1L
3A		TDO		TDO			M6	
3A		nCSO		DATA4			L3	
3A		TMS		TMS			L6	
3A		AS_DATA3		DATA3			M2	
3A		TCK		TCK			M3	
3A		AS_DATA2		DATA2			L2	
3A		TDI		TDI			L4	
3A		AS_DATA1		DATA1			K1	
3A		DCLK		DCLK			M5	
3A		AS_DATA0,ASDO		DATA0			M1	
3A	VREFB3AN0	IO		DATA6	DIFFIO_RX_B1n	DIFFOUT_B1n	N4	DQ1B
3A	VREFB3AN0	IO		DATA5	DIFFIO_RX_B2n	DIFFOUT_B2n	N1	
3A	VREFB3AN0	IO		DATA8	DIFFIO_RX_B1p	DIFFOUT_B1p	P4	DQ1B
3A	VREFB3AN0	IO		DATA7	DIFFIO_RX_B2p	DIFFOUT_B2p	P1	DQ1B
3A	VREFB3AN0	IO		DATA10	DIFFIO_RX_B3n	DIFFOUT_B3n	M7	DQS1B
3A	VREFB3AN0	IO		DATA9	DIFFIO_RX_B4n	DIFFOUT_B4n	R1	DQ1B
3A	VREFB3AN0	IO		DATA12	DIFFIO_RX_B3p	DIFFOUT_B3p	L7	DQS1B
3A	VREFB3AN0	IO		DATA11	DIFFIO_RX_B4p	DIFFOUT_B4p	P2	
3A	VREFB3AN0	IO		DATA14	DIFFIO_RX_B5n	DIFFOUT_B5n	P3	DQ1B
3A	VREFB3AN0	IO		DATA13	DIFFIO_RX_B6n	DIFFOUT_B6n	T2	DQ1B
3A	VREFB3AN0	IO		CLKUSR	DIFFIO_RX_B5p	DIFFOUT_B5p	N3	DQ1B
3A	VREFB3AN0	IO		DATA15	DIFFIO_RX_B6p	DIFFOUT_B6p	R2	DQ1B
3A	VREFB3AN0	IO	PR_DONE		DIFFIO_RX_B7n	DIFFOUT_B7n	R6	
3A	VREFB3AN0	IO	PR_READY		DIFFIO_RX_B8n	DIFFOUT_B8n	T3	DQ1B
3A	VREFB3AN0	IO	PR_ERROR		DIFFIO_RX_B7p	DIFFOUT_B7p	P7	
3A	VREFB3AN0	IO			DIFFIO_RX_B8p	DIFFOUT_B8p	R4	DQ1B
3B	VREFB3BN0	IO			DIFFIO_RX_B17n	DIFFOUT_B17n	T5	
3B	VREFB3BN0	IO			DIFFIO_RX_B18n	DIFFOUT_B18n	R7	DQ2B
3B	VREFB3BN0	IO			DIFFIO_RX_B17p	DIFFOUT_B17p	T4	DQ2B
3B	VREFB3BN0	IO			DIFFIO_RX_B18p	DIFFOUT_B18p	P8	DQ2B
3B	VREFB3BN0	IO			DIFFIO_RX_B19n	DIFFOUT_B19n	M8	DQS2B
3B	VREFB3BN0	IO			DIFFIO_RX_B20n	DIFFOUT_B20n	T7	DQ2B
3B	VREFB3BN0	IO			DIFFIO_RX_B19p	DIFFOUT_B19p	L9	DQS2B
3B	VREFB3BN0	IO			DIFFIO_RX_B20p	DIFFOUT_B20p	T8	
3B	VREFB3BN0	IO	FPLL_BL_CLKOUT1,FPLL_BL_CLKOUTn		DIFFIO_RX_B21n	DIFFOUT_B21n	R11	DQ2B
3B	VREFB3BN0	IO			DIFFIO_RX_B22n	DIFFOUT_B22n	T12	DQ2B
3B	VREFB3BN0	IO	FPLL_BL_CLKOUT0,FPLL_BL_CLKOUTp,FPLL_BL_FB		DIFFIO_RX_B21p	DIFFOUT_B21p	R12	DQ2B
3B	VREFB3BN0	IO			DIFFIO_RX_B22p	DIFFOUT_B22p	T13	DQ2B



## Pin Information for the Cyclone® V 5CBEA4 Device

Version 1.1

Note (1)

Bank Number	VREF	Pin Name/Function	Optional Function(s)	Configuration Function	Dedicated Tx/Rx Channel	Emulated LVDS Output Channel	F256	DQS for X8
3B	VREFB3BN0	IO	CLK1n		DIFFIO_RX_B23n	DIFFOUT_B23n	R9	
3B	VREFB3BN0	IO			DIFFIO_RX_B24n	DIFFOUT_B24n	T10	DQ2B
3B	VREFB3BN0	IO	CLK1p		DIFFIO_RX_B23p	DIFFOUT_B23p	P9	
3B	VREFB3BN0	IO			DIFFIO_TX_B24p	DIFFOUT_B24p	R10	DQ2B
4A	VREFB4AN0	IO	RZQ_0		DIFFIO_TX_B25n	DIFFOUT_B25n	R15	
4A	VREFB4AN0	IO			DIFFIO_RX_B26n	DIFFOUT_B26n	T15	DQ3B
4A	VREFB4AN0	IO			DIFFIO_TX_B25p	DIFFOUT_B25p	P16	DQ3B
4A	VREFB4AN0	IO			DIFFIO_RX_B26p	DIFFOUT_B26p	R16	DQ3B
4A	VREFB4AN0	IO			DIFFIO_RX_B27n	DIFFOUT_B27n	M10	DQS3B
4A	VREFB4AN0	IO			DIFFIO_TX_B28n	DIFFOUT_B28n	M13	DQ3B
4A	VREFB4AN0	IO			DIFFIO_RX_B27p	DIFFOUT_B27p	L10	DQS3B
4A	VREFB4AN0	IO			DIFFIO_TX_B28p	DIFFOUT_B28p	N14	
4A	VREFB4AN0	IO			DIFFIO_RX_B29n	DIFFOUT_B29n	P14	DQ3B
4A	VREFB4AN0	IO			DIFFIO_RX_B30n	DIFFOUT_B30n	M12	DQ3B
4A	VREFB4AN0	IO			DIFFIO_TX_B29p	DIFFOUT_B29p	P13	DQ3B
4A	VREFB4AN0	IO			DIFFIO_RX_B30p	DIFFOUT_B30p	M11	DQ3B
4A	VREFB4AN0	IO	CLK2n		DIFFIO_RX_B31n	DIFFOUT_B31n	P11	
4A	VREFB4AN0	IO			DIFFIO_TX_B32n	DIFFOUT_B32n	T14	DQ3B
4A	VREFB4AN0	IO	CLK2p		DIFFIO_RX_B31p	DIFFOUT_B31p	N11	
4A	VREFB4AN0	IO			DIFFIO_TX_B32p	DIFFOUT_B32p	R14	DQ3B
5A	VREFB5AN0	IO	RZQ_1		DIFFIO_RX_R1p	DIFFOUT_R1p	N15	DQ1R
5A	VREFB5AN0	IO		INIT_DONE	DIFFIO_RX_R2p	DIFFOUT_R2p	L13	
5A	VREFB5AN0	IO		PR_REQUEST	DIFFIO_RX_R1n	DIFFOUT_R1n	N16	DQ1R
5A	VREFB5AN0	IO		CRC_ERROR	DIFFIO_RX_R2n	DIFFOUT_R2n	K14	
5A	VREFB5AN0	IO		nCEO	DIFFIO_RX_R3p	DIFFOUT_R3p	H16	DQ1R
5A	VREFB5AN0	IO			DIFFIO_RX_R4p	DIFFOUT_R4p	L14	DQ1R
5A	VREFB5AN0	IO		CvP_CONF DONE	DIFFIO_RX_R3n	DIFFOUT_R3n	J16	DQ1R
5A	VREFB5AN0	IO			DIFFIO_RX_R4n	DIFFOUT_R4n	L15	DQ1R
5A	VREFB5AN0	IO		DEV_OE	DIFFIO_RX_R5p	DIFFOUT_R5p	G15	
5A	VREFB5AN0	IO			DIFFIO_RX_R6p	DIFFOUT_R6p	K12	DQS1R
5A	VREFB5AN0	IO		DEV_CLRn	DIFFIO_RX_R5n	DIFFOUT_R5n	G16	DQ1R
5A	VREFB5AN0	IO			DIFFIO_RX_R6n	DIFFOUT_R6n	J12	DQS1R
5A	VREFB5AN0	IO			DIFFIO_RX_R7p	DIFFOUT_R7p	J14	DQ1R
5A	VREFB5AN0	IO			DIFFIO_RX_R8p	DIFFOUT_R8p	K15	DQ1R
5A	VREFB5AN0	IO			DIFFIO_RX_R7n	DIFFOUT_R7n	H15	
5A	VREFB5AN0	IO			DIFFIO_RX_R8n	DIFFOUT_R8n	K16	DQ1R
5B	VREFB5BN0	IO	CLK6p		DIFFIO_RX_R9p	DIFFOUT_R9p	F12	
5B	VREFB5BN0	IO			DIFFIO_RX_R10p	DIFFOUT_R10p	E16	DQ2R
5B	VREFB5BN0	IO	CLK6n		DIFFIO_RX_R9n	DIFFOUT_R9n	G12	
5B	VREFB5BN0	IO			DIFFIO_RX_R10n	DIFFOUT_R10n	D16	DQ2R
5B	VREFB5BN0	IO			DIFFIO_RX_R11p	DIFFOUT_R11p	E12	DQ2R
5B	VREFB5BN0	IO	FPLL_BR_CLKOUT0,FPLL_BR_CLKOUTp,FPLL_BR_FB		DIFFIO_RX_R12p	DIFFOUT_R12p	B16	DQ2R
5B	VREFB5BN0	IO			DIFFIO_RX_R11n	DIFFOUT_R11n	D13	DQ2R
5B	VREFB5BN0	IO	FPLL_BR_CLKOUT1,FPLL_BR_CLKOUTn		DIFFIO_RX_R12n	DIFFOUT_R12n	C16	DQ2R
5B	VREFB5BN0	IO			DIFFIO_RX_R13p	DIFFOUT_R13p	H13	DQS2R
5B	VREFB5BN0	IO			DIFFIO_RX_R14p	DIFFOUT_R14p	B15	
5B	VREFB5BN0	IO			DIFFIO_RX_R13n	DIFFOUT_R13n	G13	DQS2R
5B	VREFB5BN0	IO			DIFFIO_RX_R14n	DIFFOUT_R14n	C15	DQ2R
5B	VREFB5BN0	IO			DIFFIO_RX_R15p	DIFFOUT_R15p	F14	DQ2R
5B	VREFB5BN0	IO			DIFFIO_RX_R16p	DIFFOUT_R16p	D14	DQ2R
5B	VREFB5BN0	IO			DIFFIO_RX_R15n	DIFFOUT_R15n	F15	DQ2R
5B	VREFB5BN0	IO			DIFFIO_RX_R16n	DIFFOUT_R16n	E15	
7A	VREFB7AN0	GND			DIFFIO_RX_T17p	DIFFOUT_T17p	C14	
7A	VREFB7AN0	IO	CLK10p		DIFFIO_RX_T17p	DIFFOUT_T17p	F11	



## Pin Information for the Cyclone® V 5CCEBA4 Device

Version 1.1

Note (1)

Bank Number	VREF	Pin Name/Function	Optional Function(s)	Configuration Function	Dedicated Tx/Rx Channel	Emulated LVDS Output Channel	F256	DQS for X8
7A	VREFB7AN0	IO			DIFFIO_RX_T18p	DIFFOUT_T18p	A15	DQ1T
7A	VREFB7AN0	IO	CLK10n		DIFFIO_RX_T17n	DIFFOUT_T17n	F10	
7A	VREFB7AN0	IO			DIFFIO_RX_T18n	DIFFOUT_T18n	A14	DQ1T
7A	VREFB7AN0	IO			DIFFIO_RX_T19p	DIFFOUT_T19p	D11	DQ1T
7A	VREFB7AN0	IO			DIFFIO_RX_T20p	DIFFOUT_T20p	A13	DQ1T
7A	VREFB7AN0	IO			DIFFIO_RX_T19n	DIFFOUT_T19n	C11	DQ1T
7A	VREFB7AN0	IO			DIFFIO_RX_T20n	DIFFOUT_T20n	A12	DQ1T
7A	VREFB7AN0	IO			DIFFIO_RX_T21p	DIFFOUT_T21p	E10	DQS1T
7A	VREFB7AN0	IO			DIFFIO_RX_T22p	DIFFOUT_T22p	B12	
7A	VREFB7AN0	IO			DIFFIO_RX_T21n	DIFFOUT_T21n	E9	DQS1nT
7A	VREFB7AN0	IO			DIFFIO_RX_T22n	DIFFOUT_T22n	B11	DQ1T
7A	VREFB7AN0	IO			DIFFIO_RX_T23p	DIFFOUT_T23p	C10	DQ1T
7A	VREFB7AN0	IO			DIFFIO_RX_T24p	DIFFOUT_T24p	B10	DQ1T
7A	VREFB7AN0	IO			DIFFIO_RX_T23n	DIFFOUT_T23n	C9	DQ1T
7A	VREFB7AN0	IO	RZQ_2		DIFFIO_RX_T24n	DIFFOUT_T24n	A10	
8A	VREFB8AN0	IO	CLK9p		DIFFIO_RX_T25p	DIFFOUT_T25p	F8	
8A	VREFB8AN0	IO			DIFFIO_RX_T26p	DIFFOUT_T26p	A8	DQ2T
8A	VREFB8AN0	IO	CLK9n		DIFFIO_RX_T25n	DIFFOUT_T25n	F7	
8A	VREFB8AN0	IO			DIFFIO_RX_T26n	DIFFOUT_T26n	A9	DQ2T
8A	VREFB8AN0	IO			DIFFIO_RX_T27p	DIFFOUT_T27p	B8	DQ2T
8A	VREFB8AN0	IO	FPLL_TL_CLKOUT0,FPLL_TL_CLKOUTp,FPLL_TL_FB		DIFFIO_RX_T28p	DIFFOUT_T28p	A5	DQ2T
8A	VREFB8AN0	IO			DIFFIO_RX_T27n	DIFFOUT_T27n	A7	DQ2T
8A	VREFB8AN0	IO	FPLL_TL_CLKOUT1,FPLL_TL_CLKOUTn		DIFFIO_RX_T28n	DIFFOUT_T28n	A4	DQ2T
8A	VREFB8AN0	IO			DIFFIO_RX_T29p	DIFFOUT_T29p	D8	DQS2T
8A	VREFB8AN0	IO			DIFFIO_RX_T30p	DIFFOUT_T30p	B3	
8A	VREFB8AN0	IO			DIFFIO_RX_T29n	DIFFOUT_T29n	D7	DQS2nT
8A	VREFB8AN0	IO			DIFFIO_RX_T30n	DIFFOUT_T30n	A3	DQ2T
8A	VREFB8AN0	IO			DIFFIO_RX_T31p	DIFFOUT_T31p	B7	DQ2T
8A	VREFB8AN0	IO			DIFFIO_RX_T32p	DIFFOUT_T32p	C3	DQ2T
8A	VREFB8AN0	IO			DIFFIO_RX_T31n	DIFFOUT_T31n	B6	DQ2T
8A	VREFB8AN0	IO			DIFFIO_RX_T32n	DIFFOUT_T32n	C4	
9A		MSEL0		MSEL0			E5	
9A		CONF_DONE		CONF_DONE			C1	
9A		MSEL1		MSEL1			E4	
9A		nSTATUS		nSTATUS			D1	
9A		nCE		nCE			E1	
9A		MSEL2		MSEL2			D2	
9A		MSEL3		MSEL3			E6	
9A		nCONFIG		nCONFIG			D3	
9A		MSEL4		MSEL4			F6	
9A		GND					D4	
		GND					H12	
		GND					T16	
		GND					T6	
		GND					T1	
		GND					R13	
		GND					P10	
		GND					P5	
		GND					N2	
		GND					M14	
		GND					M9	
		GND					M4	
		GND					L11	
		GND					L1	



## Pin Information for the Cyclone® V 5CCEBA4 Device

Version 1.1

Note (1)

Bank Number	VREF	Pin Name/Function	Optional Function(s)	Configuration Function	Dedicated Tx/Rx Channel	Emulated LVDS Output Channel	F256	DQS for X8
		GND					K13	
		GND					K10	
		GND					K8	
		GND					K6	
		GND					J11	
		GND					J9	
		GND					J7	
		GND					J5	
		GND					H10	
		GND					H8	
		GND					H6	
		GND					G11	
		GND					G9	
		GND					G7	
		GND					G4	
		GND					F16	
		GND					F1	
		GND					E13	
		GND					E8	
		GND					E3	
		GND					D10	
		GND					D5	
		GND					C2	
		GND					B9	
		GND					B1	
		GND					A16	
		GND					A11	
		GND					A6	
		VCC					F9	
		VCC					L8	
		VCC					K11	
		VCC					K9	
		VCC					K7	
		VCC					J10	
		VCC					J8	
		VCC					J6	
		VCC					H11	
		VCC					H9	
		VCC					H7	
		VCC					G10	
		VCC					G8	
		VCC					G6	
		DNU					B2	
		DNU					A2	
		DNU					C13	
		DNU					C8	
		VCCPGM					P6	
		VCCPGM					M15	
		VCCPGM					C6	
		VCCBAT					C5	
		VCCIO2A					H2	
		VCCIO2A					K3	
		VCCIO3A					N7	
		VCCIO3A					R3	



## Pin Information for the Cyclone® V 5CEBA4 Device

Version 1.1

Note (1)

Bank Number	VREF	Pin Name/Function	Optional Function(s)	Configuration Function	Dedicated Tx/Rx Channel	Emulated LVDS Output Channel	F256	DQS for X8
		VCCIO3B					R8	
		VCCIO3B					T11	
		VCCIO4A					N12	
		VCCIO4A					P15	
		VCCIO5A					J15	
		VCCIO5A					L16	
		VCCIO5B					D15	
		VCCIO5B					G14	
		VCCIO7A					B14	
		VCCIO7A					C12	
		VCCIO8A					C7	
		VCCIO8A					B4	
		VCCPD1A2A					J4	
		VCCPD3A					N6	
		VCCPD3B4A					N10	
		VCCPD3B4A					N8	
		VCCPD5A					J13	
		VCCPD5B					H14	
		VCCPD7A8A					E7	
		VCCPD7A8A					E11	
2A	VREFB2AN0	VREFB2AN0					K2	
3A	VREFB3AN0	VREFB3AN0					R5	
3B	VREFB3BN0	VREFB3BN0					T9	
4A	VREFB4AN0	VREFB4AN0					P12	
5A	VREFB5AN0	VREFB5AN0					M16	
5B	VREFB5BN0	VREFB5BN0					E14	
7A	VREFB7AN0	VREFB7AN0					B13	
8A	VREFB8AN0	VREFB8AN0					B5	
		RREF_TL					A1	
		VCCA_FPLL					G5	
		VCCA_FPLL					L5	
		VCCA_FPLL					F5	
		VCCA_FPLL					L12	
		VCCA_FPLL					F13	
		VCC_AUX					D6	
		VCC_AUX					D9	
		VCC_AUX					D12	
		VCC_AUX					N13	
		VCC_AUX					N9	
		VCC_AUX					N5	

Note:

(1) For more information about pin definition and pin connection guidelines, refer to the [Cyclone V Device Family Pin Connection Guidelines](#).



Pin Information for the Cyclone® V 5CBEA4 Device  
Version 1.1  
Note (1)

Bank Number	VREF	Pin Name/Function	Optional Function(s)	Configuration Function	Dedicated Tx/Rx Channel	Emulated LVDS Output Channel	F484	DQS for X8	DQS for X16
2A	VREFB2AN0	IO			DIFFIO_TX_L9n	DIFFOUT_L9n	C1		
2A	VREFB2AN0	IO			DIFFIO_RX_L10n	DIFFOUT_L10n	G1	DQ1L	
2A	VREFB2AN0	IO			DIFFIO_TX_L9p	DIFFOUT_L9p	C2	DQ1L	
2A	VREFB2AN0	IO			DIFFIO_RX_L10p	DIFFOUT_L10p	G2	DQ1L	
2A	VREFB2AN0	IO			DIFFIO_RX_L11n	DIFFOUT_L11n	E2	DQS1L	
2A	VREFB2AN0	IO			DIFFIO_TX_L12n	DIFFOUT_L12n	L1	DQ1L	
2A	VREFB2AN0	IO			DIFFIO_RX_L11p	DIFFOUT_L11p	D3	DQS1L	
2A	VREFB2AN0	IO			DIFFIO_TX_L12p	DIFFOUT_L12p	L2		
2A	VREFB2AN0	IO			DIFFIO_TX_L13n	DIFFOUT_L13n	N1	DQ1L	
2A	VREFB2AN0	IO			DIFFIO_RX_L14n	DIFFOUT_L14n	U1	DQ1L	
2A	VREFB2AN0	IO			DIFFIO_TX_L13p	DIFFOUT_L13p	N2	DQ1L	
2A	VREFB2AN0	IO			DIFFIO_RX_L14p	DIFFOUT_L14p	U2	DQ1L	
2A	VREFB2AN0	IO			DIFFIO_RX_L15n	DIFFOUT_L15n	W2		
2A	VREFB2AN0	IO			DIFFIO_TX_L16n	DIFFOUT_L16n	AA1	DQ1L	
2A	VREFB2AN0	IO			DIFFIO_RX_L15p	DIFFOUT_L15p	Y3		
2A	VREFB2AN0	IO			DIFFIO_TX_L16p	DIFFOUT_L16p	AA2	DQ1L	
3A		TDO		TDO			M5		
3A		nCSO		DATA4			R4		
3A		TMS		TMS			P5		
3A		AS_DATA3		DATA3			T4		
3A		TCK		TCK			V5		
3A		AS_DATA2		DATA2			AA5		
3A		TDI		TDI			W5		
3A		AS_DATA1		DATA1			AB3		
3A		DCLK		DCLK			V3		
3A		AS_DATA0,ASDO		DATA0			AB4		
3A	VREFB3AN0	IO		DATA6	DIFFIO_RX_B1n	DIFFOUT_B1n	R6	DQ1B	
3A	VREFB3AN0	IO		DATA5	DIFFIO_TX_B2n	DIFFOUT_B2n	U7		
3A	VREFB3AN0	IO		DATA8	DIFFIO_RX_B1p	DIFFOUT_B1p	R5	DQ1B	
3A	VREFB3AN0	IO		DATA7	DIFFIO_TX_B2p	DIFFOUT_B2p	U8	DQ1B	
3A	VREFB3AN0	IO		DATA10	DIFFIO_RX_B3n	DIFFOUT_B3n	P6	DQS1B	
3A	VREFB3AN0	IO		DATA9	DIFFIO_TX_B4n	DIFFOUT_B4n	W8	DQ1B	
3A	VREFB3AN0	IO		DATA12	DIFFIO_RX_B3p	DIFFOUT_B3p	N6	DQS1B	
3A	VREFB3AN0	IO		DATA11	DIFFIO_TX_B4p	DIFFOUT_B4p	W9		
3A	VREFB3AN0	IO		DATA14	DIFFIO_RX_B5n	DIFFOUT_B5n	T7	DQ1B	
3A	VREFB3AN0	IO		DATA13	DIFFIO_TX_B6n	DIFFOUT_B6n	U6	DQ1B	
3A	VREFB3AN0	IO		CLKUSR	DIFFIO_RX_B5p	DIFFOUT_B5p	T8	DQ1B	
3A	VREFB3AN0	IO		DATA15	DIFFIO_TX_B6p	DIFFOUT_B6p	V6	DQ1B	
3A	VREFB3AN0	IO		PR_DONE	DIFFIO_RX_B7n	DIFFOUT_B7n	M6		
3A	VREFB3AN0	IO		PR_READY	DIFFIO_TX_B8n	DIFFOUT_B8n	R7	DQ1B	
3A	VREFB3AN0	IO		PR_ERROR	DIFFIO_RX_B7p	DIFFOUT_B7p	M7		
3A	VREFB3AN0	IO			DIFFIO_TX_B8p	DIFFOUT_B8p	P7	DQ1B	
3B	VREFB3BN0	IO			DIFFIO_RX_B9n	DIFFOUT_B9n	AB6		
3B	VREFB3BN0	IO			DIFFIO_RX_B10n	DIFFOUT_B10n	V9	DQ2B	
3B	VREFB3BN0	IO			DIFFIO_RX_B9p	DIFFOUT_B9p	AB5	DQ2B	
3B	VREFB3BN0	IO			DIFFIO_RX_B10p	DIFFOUT_B10p	V10	DQ2B	
3B	VREFB3BN0	IO			DIFFIO_RX_B11n	DIFFOUT_B11n	P8	DQS1B	
3B	VREFB3BN0	IO			DIFFIO_TX_B12n	DIFFOUT_B12n	AA7	DQ2B	
3B	VREFB3BN0	IO			DIFFIO_RX_B11p	DIFFOUT_B11p	N8	DQS2B	
3B	VREFB3BN0	IO			DIFFIO_TX_B12p	DIFFOUT_B12p	AB7		
3B	VREFB3BN0	IO			DIFFIO_RX_B13n	DIFFOUT_B13n	AA8	DQ2B	
3B	VREFB3BN0	IO			DIFFIO_RX_B14n	DIFFOUT_B14n	T9	DQ2B	
3B	VREFB3BN0	IO			DIFFIO_TX_B13p	DIFFOUT_B13p	AB8	DQ2B	
3B	VREFB3BN0	IO			DIFFIO_RX_B14p	DIFFOUT_B14p	U10	DQ2B	
3B	VREFB3BN0	IO	CLK0n,FPLL_BL_FBn		DIFFIO_RX_B15n	DIFFOUT_B15n	M8		
3B	VREFB3BN0	IO			DIFFIO_TX_B16n	DIFFOUT_B16n	AA10	DQ2B	
3B	VREFB3BN0	IO	CLK0p,FPLL_BL_FBp		DIFFIO_RX_B15p	DIFFOUT_B15p	M9		
3B	VREFB3BN0	IO			DIFFIO_RX_B16p	DIFFOUT_B16p	AA9	DQ2B	
3B	VREFB3BN0	IO			DIFFIO_TX_B17n	DIFFOUT_B17n	Y10		
3B	VREFB3BN0	IO			DIFFIO_RX_B18n	DIFFOUT_B18n	T10	DQ3B	
3B	VREFB3BN0	IO			DIFFIO_TX_B17p	DIFFOUT_B17p	Y9	DQ3B	
3B	VREFB3BN0	IO			DIFFIO_RX_B18p	DIFFOUT_B18p	R9	DQ3B	
3B	VREFB3BN0	IO			DIFFIO_RX_B19n	DIFFOUT_B19n	U11	DQS3B	
3B	VREFB3BN0	IO			DIFFIO_TX_B20n	DIFFOUT_B20n	R12	DQ3B	
3B	VREFB3BN0	IO			DIFFIO_RX_B19p	DIFFOUT_B19p	U12	DQS3B	
3B	VREFB3BN0	IO			DIFFIO_TX_B20p	DIFFOUT_B20p	P12		
3B	VREFB3BN0	IO	FPLL_BL_CLKOUT1,FPLL_BL_CLKOUTn		DIFFIO_RX_B21n	DIFFOUT_B21n	AB10	DQ3B	
3B	VREFB3BN0	IO			DIFFIO_RX_B22n	DIFFOUT_B22n	R10	DQ3B	
3B	VREFB3BN0	IO	FPLL_BL_CLKOUT0,FPLL_BL_CLKOUTp,FPLL_BL_FB		DIFFIO_RX_B21p	DIFFOUT_B21p	AB11	DQ3B	
3B	VREFB3BN0	IO			DIFFIO_RX_B22p	DIFFOUT_B22p	R11	DQ3B	
3B	VREFB3BN0	IO	CLK1n		DIFFIO_RX_B23n	DIFFOUT_B23n	P9		



Pin Information for the Cyclone® V 5CBEA4 Device  
Version 1.1  
Note (1)

Bank Number	VREF	Pin Name/Function	Optional Function(s)	Configuration Function	Dedicated Tx/Rx Channel	Emulated LVDS Output Channel	F484	DQS for X8	DQS for X16
3B	VREFB3BN0	IO			DIFFIO_TX_B24n	DIFFOUT_B24n	Y11	DQ3B	
3B	VREFB3BN0	IO	CLK1p		DIFFIO_RX_B23p	DIFFOUT_B23p	N9		
3B	VREFB3BN0	IO			DIFFIO_TX_B24p	DIFFOUT_B24p	AA12	DQ3B	
4A	VREFB4AN0	IO	RZQ_0		DIFFIO_TX_B25n	DIFFOUT_B25n	AB13		
4A	VREFB4AN0	IO			DIFFIO_RX_B26n	DIFFOUT_B26n	V13	DQ4B	
4A	VREFB4AN0	IO			DIFFIO_TX_B25p	DIFFOUT_B25p	AB12	DQ4B	
4A	VREFB4AN0	IO			DIFFIO_RX_B26p	DIFFOUT_B26p	U13	DQ4B	
4A	VREFB4AN0	IO			DIFFIO_RX_B27n	DIFFOUT_B27n	T12	DQS4B	
4A	VREFB4AN0	IO			DIFFIO_TX_B28n	DIFFOUT_B28n	AA14	DQ4B	
4A	VREFB4AN0	IO			DIFFIO_RX_B27p	DIFFOUT_B27p	T13	DQS4B	
4A	VREFB4AN0	IO			DIFFIO_TX_B28p	DIFFOUT_B28p	AA13		
4A	VREFB4AN0	IO			DIFFIO_TX_B29n	DIFFOUT_B29n	AB15	DQ4B	
4A	VREFB4AN0	IO			DIFFIO_RX_B30n	DIFFOUT_B30n	Y14	DQ4B	
4A	VREFB4AN0	IO			DIFFIO_TX_B29p	DIFFOUT_B29p	AA15	DQ4B	
4A	VREFB4AN0	IO			DIFFIO_RX_B30p	DIFFOUT_B30p	Y15	DQ4B	
4A	VREFB4AN0	IO	CLK2n		DIFFIO_RX_B31n	DIFFOUT_B31n	V14		
4A	VREFB4AN0	IO			DIFFIO_TX_B32n	DIFFOUT_B32n	AB17	DQ4B	
4A	VREFB4AN0	IO	CLK2p		DIFFIO_RX_B31p	DIFFOUT_B31p	V15		
4A	VREFB4AN0	IO			DIFFIO_TX_B32p	DIFFOUT_B32p	AB18	DQ4B	
4A	VREFB4AN0	IO			DIFFIO_TX_B33n	DIFFOUT_B33n	AB20		
4A	VREFB4AN0	IO			DIFFIO_RX_B34n	DIFFOUT_B34n	Y16	DQ5B	DQ1B
4A	VREFB4AN0	IO			DIFFIO_TX_B33p	DIFFOUT_B33p	AB21	DQ5B	DQ1B
4A	VREFB4AN0	IO			DIFFIO_RX_B34p	DIFFOUT_B34p	Y17	DQ5B	DQ1B
4A	VREFB4AN0	IO			DIFFIO_RX_B35n	DIFFOUT_B35n	T14	DQS5B	DQ1B
4A	VREFB4AN0	IO			DIFFIO_TX_B36n	DIFFOUT_B36n	AA17	DQ5B	DQ1B
4A	VREFB4AN0	IO			DIFFIO_RX_B35p	DIFFOUT_B35p	U15	DQS5B	DQ1B
4A	VREFB4AN0	IO			DIFFIO_TX_B36p	DIFFOUT_B36p	AA18		
4A	VREFB4AN0	IO			DIFFIO_TX_B37n	DIFFOUT_B37n	AA19	DQ5B	DQ1B
4A	VREFB4AN0	IO			DIFFIO_RX_B38n	DIFFOUT_B38n	V20	DQ5B	DQ1B
4A	VREFB4AN0	IO			DIFFIO_TX_B37p	DIFFOUT_B37p	AA20	DQ5B	DQ1B
4A	VREFB4AN0	IO			DIFFIO_RX_B38p	DIFFOUT_B38p	W19	DQ5B	DQ1B
4A	VREFB4AN0	IO	CLK3n		DIFFIO_RX_B39n	DIFFOUT_B39n	V16		
4A	VREFB4AN0	IO			DIFFIO_TX_B40n	DIFFOUT_B40n	AB22	DQ5B	DQ1B
4A	VREFB4AN0	IO	CLK3p		DIFFIO_RX_B39p	DIFFOUT_B39p	W16		
4A	VREFB4AN0	IO			DIFFIO_TX_B40p	DIFFOUT_B40p	AA22	DQ5B	DQ1B
4A	VREFB4AN0	IO			DIFFIO_TX_B41n	DIFFOUT_B41n	Y22		
4A	VREFB4AN0	IO			DIFFIO_RX_B42n	DIFFOUT_B42n	Y20	DQ6B	DQ1B
4A	VREFB4AN0	IO			DIFFIO_TX_B41p	DIFFOUT_B41p	W22	DQ6B	DQ1B
4A	VREFB4AN0	IO			DIFFIO_RX_B42p	DIFFOUT_B42p	Y19	DQ6B	DQ1B
4A	VREFB4AN0	IO			DIFFIO_RX_B43n	DIFFOUT_B43n	P14	DQS6B	DQS1B
4A	VREFB4AN0	IO			DIFFIO_TX_B44n	DIFFOUT_B44n	Y21	DQ6B	DQ1B
4A	VREFB4AN0	IO			DIFFIO_RX_B43p	DIFFOUT_B43p	R14	DQS6B	DQS1B
4A	VREFB4AN0	IO			DIFFIO_TX_B44p	DIFFOUT_B44p	W21		
4A	VREFB4AN0	IO			DIFFIO_RX_B45n	DIFFOUT_B45n	U22	DQ6B	DQ1B
4A	VREFB4AN0	IO			DIFFIO_RX_B46n	DIFFOUT_B46n	V19	DQ6B	DQ1B
4A	VREFB4AN0	IO			DIFFIO_TX_B45p	DIFFOUT_B45p	V21	DQ6B	DQ1B
4A	VREFB4AN0	IO			DIFFIO_RX_B46p	DIFFOUT_B46p	V18	DQ6B	DQ1B
4A	VREFB4AN0	IO			DIFFIO_RX_B47n	DIFFOUT_B47n	U16		
4A	VREFB4AN0	IO			DIFFIO_TX_B48n	DIFFOUT_B48n	U21	DQ6B	DQ1B
4A	VREFB4AN0	IO			DIFFIO_RX_B47p	DIFFOUT_B47p	U17		
4A	VREFB4AN0	IO			DIFFIO_TX_B48p	DIFFOUT_B48p	U20	DQ6B	DQ1B
5A	VREFB5AN0	IO	RZQ_1		DIFFIO_RX_R1p	DIFFOUT_R1p	T19	DQ1R	
5A	VREFB5AN0	IO		INIT_DONE	DIFFIO_RX_R2p	DIFFOUT_R2p	T18		
5A	VREFB5AN0	IO		PR_REQUEST	DIFFIO_TX_R1n	DIFFOUT_R1n	T20	DQ1R	
5A	VREFB5AN0	IO		CRC_ERROR	DIFFIO_RX_R2n	DIFFOUT_R2n	T17		
5A	VREFB5AN0	IO		rCEO	DIFFIO_TX_R3p	DIFFOUT_R3p	T22	DQ1R	
5A	VREFB5AN0	IO			DIFFIO_RX_R4p	DIFFOUT_R4p	T15	DQ1R	
5A	VREFB5AN0	IO		CvP_CONF DONE	DIFFIO_TX_R3n	DIFFOUT_R3n	R22	DQ1R	
5A	VREFB5AN0	IO			DIFFIO_RX_R4n	DIFFOUT_R4n	R15	DQ1R	
5A	VREFB5AN0	IO		DEV_OE	DIFFIO_TX_R5p	DIFFOUT_R5p	R21		
5A	VREFB5AN0	IO			DIFFIO_RX_R6p	DIFFOUT_R6p	R16	DQS1R	
5A	VREFB5AN0	IO		DEV_CLRn	DIFFIO_TX_R5n	DIFFOUT_R5n	P22	DQ1R	
5A	VREFB5AN0	IO			DIFFIO_RX_R6n	DIFFOUT_R6n	R17	DQS1R	
5A	VREFB5AN0	IO			DIFFIO_TX_R7p	DIFFOUT_R7p	P19	DQ1R	
5A	VREFB5AN0	IO			DIFFIO_RX_R8p	DIFFOUT_R8p	P16	DQ1R	
5A	VREFB5AN0	IO			DIFFIO_TX_R7n	DIFFOUT_R7n	P18		
5A	VREFB5AN0	IO			DIFFIO_RX_R8n	DIFFOUT_R8n	P17	DQ1R	
5B	VREFB5BN0	IO	CLK6p		DIFFIO_RX_R9p	DIFFOUT_R9p	N16		
5B	VREFB5BN0	IO	CLK6n		DIFFIO_TX_R10p	DIFFOUT_R10p	N20	DQ2R	
5B	VREFB5BN0	IO			DIFFIO_RX_R9n	DIFFOUT_R9n	M16		
5B	VREFB5BN0	IO			DIFFIO_TX_R10n	DIFFOUT_R10n	N21	DQ2R	



Pin Information for the Cyclone® V 5CBEA4 Device  
Version 1.1  
Note (1)

Bank Number	VREF	Pin Name/Function	Optional Function(s)	Configuration Function	Dedicated Tx/Rx Channel	Emulated LVDS Output Channel	F484	DQS for X8	DQS for X16
5B	VREFB5BN0	IO			DIFFIO_RX_R11p	DIFFOUT_R11p	N19	DQ2R	
5B	VREFB5BN0	IO	FPPLL_BR_CLKOUT0,FPPLL_BR_CLKOUTp,FPPLL_BR_FB		DIFFIO_TX_R12p	DIFFOUT_R12p	M22	DQ2R	
5B	VREFB5BN0	IO			DIFFIO_RX_R11n	DIFFOUT_R11n	M18	DQ2R	
5B	VREFB5BN0	IO	FPPLL_BR_CLKOUT1,FPPLL_BR_CLKOUTn		DIFFIO_TX_R12n	DIFFOUT_R12n	L22	DQ2R	
5B	VREFB5BN0	IO			DIFFIO_RX_R13p	DIFFOUT_R13p	K17	DQS2R	
5B	VREFB5BN0	IO			DIFFIO_TX_R14p	DIFFOUT_R14p	M20		
5B	VREFB5BN0	IO			DIFFIO_RX_R13n	DIFFOUT_R13n	L17	DQS2R	
5B	VREFB5BN0	IO			DIFFIO_TX_R14n	DIFFOUT_R14n	M21	DQ2R	
5B	VREFB5BN0	IO			DIFFIO_RX_R15p	DIFFOUT_R15p	L19	DQ2R	
5B	VREFB5BN0	IO			DIFFIO_TX_R16p	DIFFOUT_R16p	K21	DQ2R	
5B	VREFB5BN0	IO			DIFFIO_RX_R15n	DIFFOUT_R15n	L18	DQ2R	
5B	VREFB5BN0	IO			DIFFIO_TX_R16n	DIFFOUT_R16n	K22		
7A		GND					F17		
7A	VREFB7AN0	IO			DIFFIO_RX_T1p	DIFFOUT_T1p	K20		
7A	VREFB7AN0	IO			DIFFIO_TX_T2p	DIFFOUT_T2p	B16	DQ1T	DQ1T
7A	VREFB7AN0	IO			DIFFIO_RX_T1n	DIFFOUT_T1n	K19		
7A	VREFB7AN0	IO			DIFFIO_TX_T2n	DIFFOUT_T2n	C16	DQ1T	DQ1T
7A	VREFB7AN0	IO			DIFFIO_RX_T3p	DIFFOUT_T3p	D17	DQ1T	DQ1T
7A	VREFB7AN0	IO			DIFFIO_TX_T4p	DIFFOUT_T4p	G17	DQ1T	DQ1T
7A	VREFB7AN0	IO			DIFFIO_RX_T3n	DIFFOUT_T3n	E16	DQ1T	DQ1T
7A	VREFB7AN0	IO			DIFFIO_TX_T4n	DIFFOUT_T4n	G16	DQ1T	DQ1T
7A	VREFB7AN0	IO			DIFFIO_RX_T5p	DIFFOUT_T5p	G18	DQS1T	DQS1T
7A	VREFB7AN0	IO			DIFFIO_TX_T6p	DIFFOUT_T6p	J19		
7A	VREFB7AN0	IO			DIFFIO_RX_T5n	DIFFOUT_T5n	H18	DQS1T	DQS1T
7A	VREFB7AN0	IO			DIFFIO_TX_T6n	DIFFOUT_T6n	J18	DQ1T	DQ1T
7A	VREFB7AN0	IO			DIFFIO_RX_T7p	DIFFOUT_T7p	E15	DQ1T	DQ1T
7A	VREFB7AN0	IO			DIFFIO_TX_T8p	DIFFOUT_T8p	A15	DQ1T	DQ1T
7A	VREFB7AN0	IO			DIFFIO_RX_T7n	DIFFOUT_T7n	F15	DQ1T	DQ1T
7A	VREFB7AN0	IO			DIFFIO_TX_T8n	DIFFOUT_T8n	A14		
7A	VREFB7AN0	IO	CLK11p		DIFFIO_RX_T9p	DIFFOUT_T9p	H16		
7A	VREFB7AN0	IO			DIFFIO_TX_T10p	DIFFOUT_T10p	J17	DQ2T	DQ1T
7A	VREFB7AN0	IO	CLK11n		DIFFIO_RX_T9n	DIFFOUT_T9n	H15		
7A	VREFB7AN0	IO			DIFFIO_TX_T10n	DIFFOUT_T10n	K16	DQ2T	DQ1T
7A	VREFB7AN0	IO			DIFFIO_RX_T11p	DIFFOUT_T11p	C15	DQ2T	DQ1T
7A	VREFB7AN0	IO			DIFFIO_TX_T12p	DIFFOUT_T12p	G15	DO2T	DQ1T
7A	VREFB7AN0	IO			DIFFIO_RX_T11n	DIFFOUT_T11n	B15	DQ2T	DQ1T
7A	VREFB7AN0	IO			DIFFIO_TX_T12n	DIFFOUT_T12n	F14	DQ2T	DQ1T
7A	VREFB7AN0	IO			DIFFIO_RX_T13p	DIFFOUT_T13p	H14	DQS2T	DQ1T
7A	VREFB7AN0	IO			DIFFIO_TX_T14p	DIFFOUT_T14p	B13		
7A	VREFB7AN0	IO			DIFFIO_RX_T13n	DIFFOUT_T13n	J13	DQS2T	DQ1T
7A	VREFB7AN0	IO			DIFFIO_TX_T14n	DIFFOUT_T14n	A13	DQ2T	DQ1T
7A	VREFB7AN0	IO			DIFFIO_RX_T15p	DIFFOUT_T15p	E14	DQ2T	DQ1T
7A	VREFB7AN0	IO			DIFFIO_TX_T16p	DIFFOUT_T16p	J11	DQ2T	DQ1T
7A	VREFB7AN0	IO			DIFFIO_RX_T15n	DIFFOUT_T15n	F13	DQ2T	DQ1T
7A	VREFB7AN0	IO			DIFFIO_TX_T16n	DIFFOUT_T16n	H10		
7A	VREFB7AN0	IO	CLK10p		DIFFIO_RX_T17p	DIFFOUT_T17p	H13		
7A	VREFB7AN0	IO			DIFFIO_TX_T18p	DIFFOUT_T18p	G11	DQ3T	
7A	VREFB7AN0	IO	CLK10n		DIFFIO_RX_T17n	DIFFOUT_T17n	G13		
7A	VREFB7AN0	IO			DIFFIO_TX_T18n	DIFFOUT_T18n	F12	DQ3T	
7A	VREFB7AN0	IO			DIFFIO_RX_T19p	DIFFOUT_T19p	D13	DQ3T	
7A	VREFB7AN0	IO			DIFFIO_TX_T20p	DIFFOUT_T20p	B12	DQ3T	
7A	VREFB7AN0	IO			DIFFIO_RX_T19n	DIFFOUT_T19n	C13	DQ3T	
7A	VREFB7AN0	IO			DIFFIO_TX_T20n	DIFFOUT_T20n	A12	DQ3T	
7A	VREFB7AN0	IO			DIFFIO_RX_T21p	DIFFOUT_T21p	H11	DQS3T	
7A	VREFB7AN0	IO			DIFFIO_TX_T22p	DIFFOUT_T22p	L8		
7A	VREFB7AN0	IO			DIFFIO_RX_T21n	DIFFOUT_T21n	G12	DQS3T	
7A	VREFB7AN0	IO			DIFFIO_TX_T22n	DIFFOUT_T22n	K9	DQ3T	
7A	VREFB7AN0	IO			DIFFIO_RX_T23p	DIFFOUT_T23p	D12	DQ3T	
7A	VREFB7AN0	IO			DIFFIO_TX_T24p	DIFFOUT_T24p	C11	DQ3T	
7A	VREFB7AN0	IO			DIFFIO_RX_T23n	DIFFOUT_T23n	E12	DQ3T	
7A	VREFB7AN0	IO	RZQ_2		DIFFIO_TX_T24n	DIFFOUT_T24n	B11		
8A	VREFB8AN0	IO	CLK9p		DIFFIO_RX_T25p	DIFFOUT_T25p	G10		
8A	VREFB8AN0	IO			DIFFIO_TX_T26p	DIFFOUT_T26p	L7	DQ4T	
8A	VREFB8AN0	IO	CLK9n		DIFFIO_RX_T25n	DIFFOUT_T25n	F10		
8A	VREFB8AN0	IO			DIFFIO_TX_T26n	DIFFOUT_T26n	K7	DQ4T	
8A	VREFB8AN0	IO			DIFFIO_RX_T27p	DIFFOUT_T27p	J7	DQ4T	
8A	VREFB8AN0	IO	FPPLL_TL_CLKOUT0,FPPLL_TL_CLKOUTp,FPPLL_TL_FB		DIFFIO_TX_T28p	DIFFOUT_T28p	H8	DQ4T	
8A	VREFB8AN0	IO			DIFFIO_RX_T27n	DIFFOUT_T27n	J8	DQ4T	
8A	VREFB8AN0	IO	FPPLL_TL_CLKOUT1,FPPLL_TL_CLKOUTn		DIFFIO_TX_T28n	DIFFOUT_T28n	G8	DQ4T	
8A	VREFB8AN0	IO			DIFFIO_RX_T29p	DIFFOUT_T29p	J9	DQS4T	
8A	VREFB8AN0	IO			DIFFIO_TX_T30p	DIFFOUT_T30p	A10		



Pin Information for the Cyclone® V 5CBEA4 Device  
Version 1.1  
Note (1)

Bank Number	VREF	Pin Name/Function	Optional Function(s)	Configuration Function	Dedicated Tx/Rx Channel	Emulated LVDS Output Channel	F484	DQS for X8	DQS for X16
8A	VREFB8AN0	IO			DIFFIO_RX_T29n	DIFFOUT_T29n	H9	DQSn4T	
8A	VREFB8AN0	IO			DIFFIO_RX_T30n	DIFFOUT_T30n	A9	DQ4T	
8A	VREFB8AN0	IO			DIFFIO_RX_T31p	DIFFOUT_T31p	B10	DQ4T	
8A	VREFB8AN0	IO			DIFFIO_RX_T32p	DIFFOUT_T32p	A5	DQ4T	
8A	VREFB8AN0	IO			DIFFIO_RX_T31n	DIFFOUT_T31n	C9	DQ4T	
8A	VREFB8AN0	IO			DIFFIO_RX_T32n	DIFFOUT_T32n	B5		
8A	VREFB8AN0	IO	CLK8p,FPLL_TL_FBp		DIFFIO_RX_T33p	DIFFOUT_T33p	E10		
8A	VREFB8AN0	IO			DIFFIO_RX_T34p	DIFFOUT_T34p	B6	DQ5T	
8A	VREFB8AN0	IO	CLK8n,FPLL_TL_FBn		DIFFIO_RX_T33n	DIFFOUT_T33n	F9		
8A	VREFB8AN0	IO			DIFFIO_RX_T34n	DIFFOUT_T34n	B7	DQ5T	
8A	VREFB8AN0	IO			DIFFIO_RX_T35p	DIFFOUT_T35p	A8	DQ5T	
8A	VREFB8AN0	IO			DIFFIO_RX_T36p	DIFFOUT_T36p	C6	DQ5T	
8A	VREFB8AN0	IO			DIFFIO_RX_T35n	DIFFOUT_T35n	A7	DQ5T	
8A	VREFB8AN0	IO			DIFFIO_RX_T36n	DIFFOUT_T36n	D6	DQ5T	
8A	VREFB8AN0	IO			DIFFIO_RX_T37p	DIFFOUT_T37p	E9	DQ5T	
8A	VREFB8AN0	IO			DIFFIO_RX_T38p	DIFFOUT_T38p	D7		
8A	VREFB8AN0	IO			DIFFIO_RX_T37n	DIFFOUT_T37n	D9	DQSn6T	
8A	VREFB8AN0	IO			DIFFIO_RX_T38n	DIFFOUT_T38n	C8	DQ5T	
8A	VREFB8AN0	IO			DIFFIO_RX_T39p	DIFFOUT_T39p	G6	DQ5T	
8A	VREFB8AN0	IO			DIFFIO_RX_T40p	DIFFOUT_T40p	F7	DQ5T	
8A	VREFB8AN0	IO			DIFFIO_RX_T39n	DIFFOUT_T39n	H6	DQ5T	
8A	VREFB8AN0	IO			DIFFIO_RX_T40n	DIFFOUT_T40n	E7		
9A	MSEL0			MSEL0		I6			
9A	CONF_DONE			CONF_DONE		K6			
9A	MSEL1			MSEL1		J6			
9A	nSTATUS			nSTATUS		H5			
9A	nCE			nCE		G5			
9A	MSEL2			MSEL2		A2			
9A	MSEL3			MSEL3		E5			
9A	nCONFIG			nCONFIG		A4			
9A	MSEL4			MSEL4		F3			
9A	GND					C5			
	GND					P2			
	GND					AB19			
	GND					AB14			
	GND					AB9			
	GND					AB2			
	GND					AB1			
	GND					AA11			
	GND					AA6			
	GND					AA4			
	GND					AA3			
	GND					Y18			
	GND					Y5			
	GND					Y2			
	GND					Y1			
	GND					W4			
	GND					W3			
	GND					V22			
	GND					V17			
	GND					V12			
	GND					V7			
	GND					V4			
	GND					V2			
	GND					V1			
	GND					U9			
	GND					U5			
	GND					U4			
	GND					U3			
	GND					T21			
	GND					T16			
	GND					T2			
	GND					T1			
	GND					R13			
	GND					R3			
	GND					P10			
	GND					P4			
	GND					P1			
	GND					N22			
	GND					N17			
	GND					N15			



Pin Information for the Cyclone® V 5CBEA4 Device  
Version 1.1  
Note (1)

Bank Number	VREF	Pin Name/Function	Optional Function(s)	Configuration Function	Dedicated Tx/Rx Channel	Emulated LVDS Output Channel	F484	DQS for X8	DQS for X16
		GND					N13		
		GND					N11		
		GND					N7		
		GND					N5		
		GND					N3		
		GND					M14		
		GND					M12		
		GND					M10		
		GND					M4		
		GND					M2		
		GND					M1		
		GND					L21		
		GND					L15		
		GND					L13		
		GND					L11		
		GND					L5		
		GND					L3		
		GND					K14		
		GND					K12		
		GND					K10		
		GND					K8		
		GND					K4		
		GND					K2		
		GND					K1		
		GND					J20		
		GND					J15		
		GND					J5		
		GND					J3		
		GND					H22		
		GND					H12		
		GND					H7		
		GND					H4		
		GND					H3		
		GND					H2		
		GND					H1		
		GND					G19		
		GND					G9		
		GND					G4		
		GND					G3		
		GND					F16		
		GND					F6		
		GND					F5		
		GND					F2		
		GND					F1		
		GND					E13		
		GND					E4		
		GND					E3		
		GND					D20		
		GND					D10		
		GND					D5		
		GND					D2		
		GND					D1		
		GND					C17		
		GND					C4		
		GND					C3		
		GND					B14		
		GND					B9		
		GND					B2		
		GND					B1		
		GND					A21		
		GND					A11		
		VCC					N4		
		VCC					P15		
		VCC					P13		
		VCC					P11		
		VCC					P3		
		VCC					N14		
		VCC					N12		
		VCC					N10		
		VCC					M15		
		VCC					M13		



Pin Information for the Cyclone® V 5CBEA4 Device  
Version 1.1  
Note (1)

Bank Number	VREF	Pin Name/Function	Optional Function(s)	Configuration Function	Dedicated Tx/Rx Channel	Emulated LVDS Output Channel	F484	DQS for X8	DQS for X16
		VCC					M11		
		VCC					L16		
		VCC					L14		
		VCC					L12		
		VCC					L10		
		VCC					L4		
		VCC					K15		
		VCC					K13		
		VCC					K11		
		VCC					K5		
		VCC					K3		
		VCC					J16		
		VCC					J14		
		VCC					J12		
		VCC					J10		
		VCC					J4		
		DNU					B3		
		DNU					B4		
		DNU					E17		
		DNU					L9		
		VCCPGM					V8		
		VCCPGM					R19		
		VCCPGM					F8		
		VCCBAT					A3		
		VCCI02A					D4		
		VCCI02A					Y4		
		VCCI02A					R1		
		VCCI02A					J1		
		VCCI03A					T6		
		VCCI03A					Y8		
		VCCI03B					T11		
		VCCI03B					Y13		
		VCCI03B					W10		
		VCCI03B					R8		
		VCCI04A					U19		
		VCCI04A					AA21		
		VCCI04A					AA16		
		VCCI04A					W20		
		VCCI04A					W15		
		VCCI04A					U14		
		VCCI05A					P20		
		VCCI05A					R18		
		VCCI05B					M19		
		VCCI05B					K18		
		VCCI07A					A16		
		VCCI07A					H17		
		VCCI07A					G14		
		VCCI07A					F21		
		VCCI07A					F11		
		VCCI07A					E18		
		VCCI07A					D15		
		VCCI07A					C22		
		VCCI07A					C12		
		VCCI07A					B19		
		VCCI08A					A6		
		VCCI08A					G7		
		VCCI08A					E8		
		VCCI08A					C7		
		VCCPD1A2A					E1		
		VCCPD1A2A					R2		
		VCCPD1A2A					J2		
		VCCPD3A					W6		
		VCCPD3B4A					W17		
		VCCPD3B4A					W14		
		VCCPD3B4A					W12		
		VCCPD3B4A					W11		
		VCCPD5A					P21		
		VCCPD5B					N18		
		VCCPD5B					M17		
		VCCPD7A8A					D16		
		VCCPD7A8A					E11		



Pin Information for the Cyclone® V 5CBEA4 Device  
Version 1.1  
Note (1)

Bank Number	VREF	Pin Name/Function	Optional Function(s)	Configuration Function	Dedicated Tx/Rx Channel	Emulated LVDS Output Channel	F484	DQS for X8	DQS for X16
		VCCPD7A8A					D14		
		VCCPD7A8A					D8		
		VCCPD7A8A					C10		
2A	VREFB2A0	VREFB2A0					W1		
3A	VREFB3A0	VREFB3A0					Y7		
3B	VREFB3B0	VREFB3B0					Y12		
4A	VREFB4A0	VREFB4A0					AB16		
5A	VREFB5A0	VREFB5A0					R20		
5B	VREFB5B0	VREFB5B0					L20		
7A	VREFB7A0	VREFB7A0					C14		
8A	VREFB8A0	VREFB8A0					B8		
		NC					Y6		
		NC					V11		
		NC					J22		
		NC					J21		
		NC					H21		
		NC					H20		
		NC					G22		
		NC					G21		
		NC					G20		
		NC					F22		
		NC					F20		
		NC					F19		
		NC					F18		
		NC					E22		
		NC					E21		
		NC					E20		
		NC					E19		
		NC					D22		
		NC					D21		
		NC					D19		
		NC					C21		
		NC					C20		
		NC					C19		
		NC					C18		
		NC					B22		
		NC					B21		
		NC					B20		
		NC					B18		
		NC					B17		
		NC					A22		
		NC					A20		
		NC					A19		
		NC					A18		
		NC					A17		
		RREF_TL					A1		
		VCCA_FPLL					M3		
		VCCA_FPLL					T3		
		VCCA_FPLL					T5		
		VCCA_FPLL					F4		
		VCCA_FPLL					U18		
		VCCA_FPLL					H19		
		VCC_AUX					E6		
		VCC_AUX					D11		
		VCC_AUX					D18		
		VCC_AUX					W18		
		VCC_AUX					W13		
		VCC_AUX					W7		

Note:

(1) For more information about pin definition and pin connection guidelines, refer to the [Cyclone V Device Family Pin Connection Guidelines](#).



**Pin Information for the Cyclone® V 5CEBA4 Device  
Version 1.1**

Version Number	Date	Changes Made
1.0	9/20/2012	Initial release.
1.1	10/5/2012	Removed nPERST* pins because Cyclone V E devices do not support PCIe interface.