



Pin Information for the Cyclone® V 5CGXBC9 Device  
Version 1.2  
Note (1)

Bank Number	VREF	Pin Name/Function	Optional Function(s)	Configuration Function	Dedicated Tx/Rx Channel	Emulated LVDS Output Channel	U484	DQS for X8	DQS for X16
GXB_L1		REFCLK1Ln					G4		
GXB_L1		REFCLK1Lp					F5		
GXB_L1		GXB_TX_L4n					E1		
GXB_L1		GXB_TX_L4p					E2		
GXB_L1		GXB_RX_L4p,GXB_REFCLK_L4p					G2		
GXB_L1		GXB_RX_L4n,GXB_REFCLK_L4n					G1		
GXB_L1		GXB_TX_L3n					J1		
GXB_L1		GXB_TX_L3p					J2		
GXB_L1		GXB_RX_L3p,GXB_REFCLK_L3p					L2		
GXB_L1		GXB_RX_L3n,GXB_REFCLK_L3n					L1		
GXB_L0		GXB_TX_L2n					N1		
GXB_L0		GXB_TX_L2p					N2		
GXB_L0		GXB_RX_L2p,GXB_REFCLK_L2p					R2		
GXB_L0		GXB_RX_L2n,GXB_REFCLK_L2n					R1		
GXB_L0		GXB_TX_L1n					U1		
GXB_L0		GXB_TX_L1p					U2		
GXB_L0		GXB_RX_L1p,GXB_REFCLK_L1p					W2		
GXB_L0		GXB_RX_L1n,GXB_REFCLK_L1n					W1		
GXB_L0		GXB_TX_L0n					Y3		
GXB_L0		GXB_TX_L0p					Y4		
GXB_L0		GXB_RX_L0p,GXB_REFCLK_L0p					AA2		
GXB_L0		GXB_RX_L0n,GXB_REFCLK_L0n					AA1		
GXB_L0		REFCLK0Lp					V4		
GXB_L0		REFCLK0Ln					U4		
3A		TDO		TDO			V3		
3A		hCSO		DATA4			AB6		
3A		TMS		TMS			R4		
3A		AS_DATA3		DATA3			AA5		
3A		TCK		TCK			V5		
3A		AS_DATA2		DATA2			T5		
3A		TDI		TDI			P5		
3A		AS_DATA1		DATA1			W5		
3A		DCLK		DCLK			M5		
3A		AS_DATA0,ASDO		DATA0			AB4		
3A	VREFB3AN0	IO		DATA6	DIFFIO_RX_B1n	DIFFOUT_B1n	P6	DQ1B	
3A	VREFB3AN0	IO		DATA5	DIFFIO_TX_B2n	DIFFOUT_B2n	U7		
3A	VREFB3AN0	IO		DATA8	DIFFIO_RX_B1p	DIFFOUT_B1p	N6	DQ1B	
3A	VREFB3AN0	IO		DATA7	DIFFIO_TX_B2p	DIFFOUT_B2p	U6	DQ1B	
3A	VREFB3AN0	IO		DATA10	DIFFIO_RX_B3n	DIFFOUT_B3n	M6	DQSn1B	
3A	VREFB3AN0	IO		DATA9	DIFFIO_TX_B4n	DIFFOUT_B4n	R5	DQ1B	
3A	VREFB3AN0	IO		DATA12	DIFFIO_RX_B3p	DIFFOUT_B3p	M7	DQS1B	
3A	VREFB3AN0	IO		DATA11	DIFFIO_TX_B4p	DIFFOUT_B4p	R6		
3A	VREFB3AN0	IO		DATA14	DIFFIO_RX_B5n	DIFFOUT_B5n	R7	DQ1B	
3A	VREFB3AN0	IO		DATA13	DIFFIO_TX_B6n	DIFFOUT_B6n	L7	DQ1B	
3A	VREFB3AN0	IO		CLKUSR	DIFFIO_RX_B5p	DIFFOUT_B5p	T7	DQ1B	
3A	VREFB3AN0	IO		DATA15	DIFFIO_TX_B6p	DIFFOUT_B6p	L8	DQ1B	
3A	VREFB3AN0	IO		PR_DONE	DIFFIO_RX_B7n	DIFFOUT_B7n	T8		
3A	VREFB3AN0	IO		PR_READY	DIFFIO_TX_B8n	DIFFOUT_B8n	P7	DQ1B	
3A	VREFB3AN0	IO		PR_ERROR	DIFFIO_RX_B7p	DIFFOUT_B7p	T9		
3A	VREFB3AN0	IO			DIFFIO_TX_B8p	DIFFOUT_B8p	P8	DQ1B	
3B	VREFB3BN0	IO			DIFFIO_TX_B33n	DIFFOUT_B33n	V8		
3B	VREFB3BN0	IO			DIFFIO_RX_B34n	DIFFOUT_B34n	N8	DQ5B	
3B	VREFB3BN0	IO			DIFFIO_TX_B33p	DIFFOUT_B33p	W8	DQ5B	
3B	VREFB3BN0	IO			DIFFIO_RX_B34p	DIFFOUT_B34p	M8	DQ5B	
3B	VREFB3BN0	IO			DIFFIO_RX_B35n	DIFFOUT_B35n	N9	DQSn5B	
3B	VREFB3BN0	IO			DIFFIO_TX_B36n	DIFFOUT_B36n	AA7	DQ5B	
3B	VREFB3BN0	IO			DIFFIO_RX_B35p	DIFFOUT_B35p	N10	DQS5B	
3B	VREFB3BN0	IO			DIFFIO_TX_B36p	DIFFOUT_B36p	AB7		
3B	VREFB3BN0	IO			DIFFIO_TX_B37n	DIFFOUT_B37n	Y7	DQ5B	
3B	VREFB3BN0	IO			DIFFIO_RX_B38n	DIFFOUT_B38n	U8	DQ5B	
3B	VREFB3BN0	IO			DIFFIO_TX_B37p	DIFFOUT_B37p	W7	DQ5B	
3B	VREFB3BN0	IO			DIFFIO_RX_B38p	DIFFOUT_B38p	V9	DQ5B	
3B	VREFB3BN0	IO	CLK0n,FPLL_BL_FBn		DIFFIO_RX_B39n	DIFFOUT_B39n	R9		
3B	VREFB3BN0	IO			DIFFIO_TX_B40n	DIFFOUT_B40n	AB8	DQ5B	
3B	VREFB3BN0	IO	CLK0p,FPLL_BL_FBp		DIFFIO_RX_B39p	DIFFOUT_B39p	P9		
3B	VREFB3BN0	IO			DIFFIO_TX_B40p	DIFFOUT_B40p	AA8	DQ5B	
3B	VREFB3BN0	IO			DIFFIO_TX_B41n	DIFFOUT_B41n	Y10		
3B	VREFB3BN0	IO			DIFFIO_RX_B42n	DIFFOUT_B42n	AA9	DQ6B	
3B	VREFB3BN0	IO			DIFFIO_TX_B41p	DIFFOUT_B41p	AA10	DQ6B	
3B	VREFB3BN0	IO			DIFFIO_RX_B42p	DIFFOUT_B42p	Y9	DQ6B	
3B	VREFB3BN0	IO			DIFFIO_RX_B43n	DIFFOUT_B43n	L9	DQSn6B	



Pin Information for the Cyclone® V 5CGXBC9 Device  
Version 1.2  
Note (1)

Bank Number	VREF	Pin Name/Function	Optional Function(s)	Configuration Function	Dedicated Tx/Rx Channel	Emulated LVDS Output Channel	U484	DQS for X8	DQS for X16
3B	VREFB3B0	IO			DIFFIO_TX_B44n	DIFFOUT_B44n	W11	DQ6B	
3B	VREFB3B0	IO			DIFFIO_RX_B43p	DIFFOUT_B43p	M10	DQS6B	
3B	VREFB3B0	IO			DIFFIO_TX_B44p	DIFFOUT_B44p	Y11		
3B	VREFB3B0	IO	FPLL_BL_CLKOUT1,FPLL_BL_CLKOUTn		DIFFIO_TX_B45n	DIFFOUT_B45n	AB10	DQ6B	
3B	VREFB3B0	IO			DIFFIO_RX_B46n	DIFFOUT_B46n	U10	DQ6B	
3B	VREFB3B0	IO	FPLL_BL_CLKOUT0,FPLL_BL_CLKOUTp,FPLL_BL_FB		DIFFIO_TX_B45p	DIFFOUT_B45p	AB11	DQ6B	
3B	VREFB3B0	IO			DIFFIO_RX_B46p	DIFFOUT_B46p	U11	DQ6B	
3B	VREFB3B0	IO	CLK1n		DIFFIO_RX_B47n	DIFFOUT_B47n	T10		
3B	VREFB3B0	IO			DIFFIO_TX_B48n	DIFFOUT_B48n	R11	DQ6B	
3B	VREFB3B0	IO	CLK1p		DIFFIO_RX_B47p	DIFFOUT_B47p	R10		
3B	VREFB3B0	IO			DIFFIO_TX_B48p	DIFFOUT_B48p	P12	DQ6B	
4A	VREFB4A0	IO	RZQ_0		DIFFIO_TX_B49n	DIFFOUT_B49n	AA13		
4A	VREFB4A0	IO			DIFFIO_RX_B50n	DIFFOUT_B50n	W12	DQ7B	
4A	VREFB4A0	IO			DIFFIO_TX_B49p	DIFFOUT_B49p	AB13	DQ7B	
4A	VREFB4A0	IO			DIFFIO_RX_B50p	DIFFOUT_B50p	Y12	DQ7B	
4A	VREFB4A0	IO			DIFFIO_RX_B51n	DIFFOUT_B51n	U12	DQS7B	
4A	VREFB4A0	IO			DIFFIO_TX_B52n	DIFFOUT_B52n	R12	DQ7B	
4A	VREFB4A0	IO			DIFFIO_RX_B51p	DIFFOUT_B51p	T12	DQS7B	
4A	VREFB4A0	IO			DIFFIO_TX_B52p	DIFFOUT_B52p	T13		
4A	VREFB4A0	IO			DIFFIO_TX_B53n	DIFFOUT_B53n	AB15	DQ7B	
4A	VREFB4A0	IO			DIFFIO_RX_B54n	DIFFOUT_B54n	W13	DQ7B	
4A	VREFB4A0	IO			DIFFIO_TX_B53p	DIFFOUT_B53p	AB16	DQ7B	
4A	VREFB4A0	IO			DIFFIO_RX_B54p	DIFFOUT_B54p	V13	DQ7B	
4A	VREFB4A0	IO	CLK2n		DIFFIO_RX_B55n	DIFFOUT_B55n	T14		
4A	VREFB4A0	IO			DIFFIO_TX_B56n	DIFFOUT_B56n	AB18	DQ7B	
4A	VREFB4A0	IO	CLK2p		DIFFIO_RX_B55p	DIFFOUT_B55p	U13		
4A	VREFB4A0	IO			DIFFIO_TX_B56p	DIFFOUT_B56p	AA18	DQ7B	
4A	VREFB4A0	IO			DIFFIO_TX_B57n	DIFFOUT_B57n	AA19		
4A	VREFB4A0	IO			DIFFIO_RX_B58n	DIFFOUT_B58n	Y14	DQ8B	DQ1B
4A	VREFB4A0	IO			DIFFIO_TX_B57p	DIFFOUT_B57p	Y19	DQ8B	DQ1B
4A	VREFB4A0	IO			DIFFIO_RX_B58p	DIFFOUT_B58p	W14	DQ8B	DQ1B
4A	VREFB4A0	IO			DIFFIO_RX_B59n	DIFFOUT_B59n	P14	DQS8B	DQ1B
4A	VREFB4A0	IO			DIFFIO_TX_B60n	DIFFOUT_B60n	AA20	DQ8B	DQ1B
4A	VREFB4A0	IO			DIFFIO_RX_B59p	DIFFOUT_B59p	R14	DQS8B	DQ1B
4A	VREFB4A0	IO			DIFFIO_TX_B60p	DIFFOUT_B60p	Y20		
4A	VREFB4A0	IO			DIFFIO_TX_B61n	DIFFOUT_B61n	AA15	DQ8B	DQ1B
4A	VREFB4A0	IO			DIFFIO_RX_B62n	DIFFOUT_B62n	U15	DQ8B	DQ1B
4A	VREFB4A0	IO			DIFFIO_TX_B61p	DIFFOUT_B61p	Y15	DQ8B	DQ1B
4A	VREFB4A0	IO			DIFFIO_RX_B62p	DIFFOUT_B62p	V15	DQ8B	DQ1B
4A	VREFB4A0	IO	CLK3n		DIFFIO_RX_B63n	DIFFOUT_B63n	R15		
4A	VREFB4A0	IO			DIFFIO_TX_B64n	DIFFOUT_B64n	AB20	DQ8B	DQ1B
4A	VREFB4A0	IO	CLK3p		DIFFIO_RX_B63p	DIFFOUT_B63p	T15		
4A	VREFB4A0	IO			DIFFIO_TX_B64p	DIFFOUT_B64p	AB21	DQ8B	DQ1B
4A	VREFB4A0	IO			DIFFIO_TX_B65n	DIFFOUT_B65n	AB22		
4A	VREFB4A0	IO			DIFFIO_RX_B66n	DIFFOUT_B66n	Y16	DQ9B	DQ1B
4A	VREFB4A0	IO			DIFFIO_TX_B65p	DIFFOUT_B65p	AA22	DQ9B	DQ1B
4A	VREFB4A0	IO			DIFFIO_RX_B66p	DIFFOUT_B66p	Y17	DQ9B	DQ1B
4A	VREFB4A0	IO			DIFFIO_RX_B67n	DIFFOUT_B67n	U16	DQS9B	DQS1B
4A	VREFB4A0	IO			DIFFIO_TX_B68n	DIFFOUT_B68n	AA17	DQ9B	DQ1B
4A	VREFB4A0	IO			DIFFIO_RX_B67p	DIFFOUT_B67p	U17	DQS9B	DQS1B
4A	VREFB4A0	IO			DIFFIO_TX_B68p	DIFFOUT_B68p	AB17		
4A	VREFB4A0	IO			DIFFIO_TX_B69n	DIFFOUT_B69n	Y22	DQ9B	DQ1B
4A	VREFB4A0	IO			DIFFIO_RX_B70n	DIFFOUT_B70n	V18	DQ9B	DQ1B
4A	VREFB4A0	IO			DIFFIO_TX_B69p	DIFFOUT_B69p	Y21	DQ9B	DQ1B
4A	VREFB4A0	IO			DIFFIO_RX_B70p	DIFFOUT_B70p	W18	DQ9B	DQ1B
4A	VREFB4A0	IO			DIFFIO_RX_B71n	DIFFOUT_B71n	W16		
4A	VREFB4A0	IO			DIFFIO_TX_B72n	DIFFOUT_B72n	W21	DQ9B	DQ1B
4A	VREFB4A0	IO			DIFFIO_RX_B71p	DIFFOUT_B71p	W17		
4A	VREFB4A0	IO			DIFFIO_TX_B72p	DIFFOUT_B72p	W22	DQ9B	DQ1B
5A	VREFB5A0	IO	RZQ_1		DIFFIO_TX_R1p	DIFFOUT_R1p	U22	DQ1R	
5A	VREFB5A0	IO		INIT_DONE	DIFFIO_RX_R2p	DIFFOUT_R2p	V20		
5A	VREFB5A0	IO		PR_REQUEST	DIFFIO_TX_R1n	DIFFOUT_R1n	U21	DQ1R	
5A	VREFB5A0	IO		CRC_ERROR	DIFFIO_RX_R2n	DIFFOUT_R2n	V19		
5A	VREFB5A0	IO		nCEO	DIFFIO_TX_R3p	DIFFOUT_R3p	T19	DQ1R	
5A	VREFB5A0	IO			DIFFIO_RX_R4p	DIFFOUT_R4p	T17	DQ1R	
5A	VREFB5A0	IO		CvP_CONFDONE	DIFFIO_TX_R3n	DIFFOUT_R3n	T20	DQ1R	
5A	VREFB5A0	IO			DIFFIO_RX_R4n	DIFFOUT_R4n	T18	DQ1R	
5A	VREFB5A0	IO		DEV_OE	DIFFIO_TX_R5p	DIFFOUT_R5p	T22		
5A	VREFB5A0	IO			DIFFIO_RX_R6p	DIFFOUT_R6p	R16	DQS1R	
5A	VREFB5A0	IO		DEV_CLRn	DIFFIO_TX_R5n	DIFFOUT_R5n	R22	DQ1R	
5A	VREFB5A0	IO			DIFFIO_RX_R6n	DIFFOUT_R6n	R17	DQS1R	



Pin Information for the Cyclone® V 5CGXBC9 Device  
Version 1.2  
Note (1)

Bank Number	VREF	Pin Name/Function	Optional Function(s)	Configuration Function	Dedicated Tx/Rx Channel	Emulated LVDS Output Channel	U484	DQS for X8	DQS for X16
5A	VREFB5A0	IO			DIFFIO_TX_R7p	DIFFOUT_R7p	R20	DQ1R	
5A	VREFB5A0	IO			DIFFIO_RX_R8p	DIFFOUT_R8p	R19	DQ1R	
5A	VREFB5A0	IO			DIFFIO_TX_R7n	DIFFOUT_R7n	R21		
5A	VREFB5A0	IO			DIFFIO_RX_R8n	DIFFOUT_R8n	P19	DQ1R	
5B	VREFB5B0	IO			DIFFIO_RX_R25p	DIFFOUT_R25p	P16		
5B	VREFB5B0	IO			DIFFIO_TX_R26p	DIFFOUT_R26p	P21	DQ4R	
5B	VREFB5B0	IO			DIFFIO_RX_R25n	DIFFOUT_R25n	N16		
5B	VREFB5B0	IO			DIFFIO_TX_R26n	DIFFOUT_R26n	P22	DQ4R	
5B	VREFB5B0	IO			DIFFIO_RX_R27p	DIFFOUT_R27p	N20	DQ4R	
5B	VREFB5B0	IO			DIFFIO_TX_R28p	DIFFOUT_R28p	M22	DQ4R	
5B	VREFB5B0	IO			DIFFIO_RX_R27n	DIFFOUT_R27n	N21	DQ4R	
5B	VREFB5B0	IO			DIFFIO_TX_R28n	DIFFOUT_R28n	L22	DQ4R	
5B	VREFB5B0	IO			DIFFIO_RX_R29p	DIFFOUT_R29p	P18	DQS4R	
5B	VREFB5B0	IO			DIFFIO_TX_R30p	DIFFOUT_R30p	K22		
5B	VREFB5B0	IO			DIFFIO_RX_R29n	DIFFOUT_R29n	N18	DQS4R	
5B	VREFB5B0	IO			DIFFIO_TX_R30n	DIFFOUT_R30n	J22	DQ4R	
5B	VREFB5B0	IO			DIFFIO_RX_R31p	DIFFOUT_R31p	M21	DQ4R	
5B	VREFB5B0	IO			DIFFIO_TX_R32p	DIFFOUT_R32p	F22	DQ4R	
5B	VREFB5B0	IO			DIFFIO_RX_R31n	DIFFOUT_R31n	M20	DQ4R	
5B	VREFB5B0	IO			DIFFIO_TX_R32n	DIFFOUT_R32n	E22		
5B	VREFB5B0	IO	CLK7p,FPLL_BR_FBp		DIFFIO_RX_R33p	DIFFOUT_R33p	M16		
5B	VREFB5B0	IO			DIFFIO_TX_R34p	DIFFOUT_R34p	E21	DQ5R	
5B	VREFB5B0	IO	CLK7n,FPLL_BR_FBn		DIFFIO_RX_R33n	DIFFOUT_R33n	M17		
5B	VREFB5B0	IO			DIFFIO_TX_R34n	DIFFOUT_R34n	D22	DQ5R	
5B	VREFB5B0	IO			DIFFIO_RX_R35p	DIFFOUT_R35p	L19	DQ5R	
5B	VREFB5B0	IO			DIFFIO_TX_R36p	DIFFOUT_R36p	K21	DQ5R	
5B	VREFB5B0	IO			DIFFIO_RX_R35n	DIFFOUT_R35n	L20	DQ5R	
5B	VREFB5B0	IO			DIFFIO_TX_R36n	DIFFOUT_R36n	J21	DQ5R	
5B	VREFB5B0	IO			DIFFIO_RX_R37p	DIFFOUT_R37p	L15	DQS5R	
5B	VREFB5B0	IO			DIFFIO_TX_R38p	DIFFOUT_R38p	G22		
5B	VREFB5B0	IO			DIFFIO_RX_R37n	DIFFOUT_R37n	K15	DQS5R	
5B	VREFB5B0	IO			DIFFIO_TX_R38n	DIFFOUT_R38n	G21	DQ5R	
5B	VREFB5B0	IO			DIFFIO_RX_R39p	DIFFOUT_R39p	L18	DQ5R	
5B	VREFB5B0	IO			DIFFIO_TX_R40p	DIFFOUT_R40p	G20	DQ5R	
5B	VREFB5B0	IO			DIFFIO_RX_R39n	DIFFOUT_R39n	K19	DQ5R	
5B	VREFB5B0	IO			DIFFIO_TX_R40n	DIFFOUT_R40n	H21		
5B	VREFB5B0	IO	CLK6p		DIFFIO_RX_R41p	DIFFOUT_R41p	L17		
5B	VREFB5B0	IO			DIFFIO_TX_R42p	DIFFOUT_R42p	E20	DQ6R	
5B	VREFB5B0	IO	CLK6n		DIFFIO_RX_R41n	DIFFOUT_R41n	K17		
5B	VREFB5B0	IO			DIFFIO_TX_R42n	DIFFOUT_R42n	F20	DQ6R	
5B	VREFB5B0	IO			DIFFIO_RX_R43p	DIFFOUT_R43p	H20	DQ6R	
5B	VREFB5B0	IO	FPLL_BR_CLKOUT0,FPLL_BR_CLKOUTp,FPLL_BR_FB		DIFFIO_TX_R44p	DIFFOUT_R44p	G18	DQ6R	
5B	VREFB5B0	IO			DIFFIO_RX_R43n	DIFFOUT_R43n	H19	DQ6R	
5B	VREFB5B0	IO	FPLL_BR_CLKOUT1,FPLL_BR_CLKOUTn		DIFFIO_TX_R44n	DIFFOUT_R44n	G17	DQ6R	
5B	VREFB5B0	IO			DIFFIO_RX_R45p	DIFFOUT_R45p	K16	DQS6R	
5B	VREFB5B0	IO			DIFFIO_TX_R46p	DIFFOUT_R46p	F19		
5B	VREFB5B0	IO			DIFFIO_RX_R45n	DIFFOUT_R45n	J16	DQS6R	
5B	VREFB5B0	IO			DIFFIO_TX_R46n	DIFFOUT_R46n	F18	DQ6R	
5B	VREFB5B0	IO			DIFFIO_RX_R47p	DIFFOUT_R47p	J17	DQ6R	
5B	VREFB5B0	IO			DIFFIO_TX_R48p	DIFFOUT_R48p	J19	DQ6R	
5B	VREFB5B0	IO			DIFFIO_RX_R47n	DIFFOUT_R47n	J18	DQ6R	
5B	VREFB5B0	IO			DIFFIO_TX_R48n	DIFFOUT_R48n	H18		
		GND					F17		
7A	VREFB7A0	IO			DIFFIO_RX_T25p	DIFFOUT_T25p	H16		
7A	VREFB7A0	IO			DIFFIO_TX_T26p	DIFFOUT_T26p	C21	DQ4T	DQ1T
7A	VREFB7A0	IO			DIFFIO_RX_T25n	DIFFOUT_T25n	G16		
7A	VREFB7A0	IO			DIFFIO_TX_T26n	DIFFOUT_T26n	C20	DQ4T	DQ1T
7A	VREFB7A0	IO			DIFFIO_RX_T27p	DIFFOUT_T27p	D18	DQ4T	DQ1T
7A	VREFB7A0	IO			DIFFIO_TX_T28p	DIFFOUT_T28p	B20	DQ4T	DQ1T
7A	VREFB7A0	IO			DIFFIO_RX_T27n	DIFFOUT_T27n	E17	DQ4T	DQ1T
7A	VREFB7A0	IO			DIFFIO_TX_T28n	DIFFOUT_T28n	B21	DQ4T	DQ1T
7A	VREFB7A0	IO			DIFFIO_RX_T29p	DIFFOUT_T29p	G15	DQS4T	DQS1T
7A	VREFB7A0	IO			DIFFIO_TX_T30p	DIFFOUT_T30p	B22		
7A	VREFB7A0	IO			DIFFIO_RX_T29n	DIFFOUT_T29n	G14	DQS4T	DQS1T
7A	VREFB7A0	IO			DIFFIO_TX_T30n	DIFFOUT_T30n	A22	DQ4T	DQ1T
7A	VREFB7A0	IO			DIFFIO_RX_T31p	DIFFOUT_T31p	E16	DQ4T	DQ1T
7A	VREFB7A0	IO			DIFFIO_TX_T32p	DIFFOUT_T32p	A20	DQ4T	DQ1T
7A	VREFB7A0	IO			DIFFIO_RX_T31n	DIFFOUT_T31n	D17	DQ4T	DQ1T
7A	VREFB7A0	IO			DIFFIO_TX_T32n	DIFFOUT_T32n	A19		
7A	VREFB7A0	IO	CLK11p		DIFFIO_RX_T33p	DIFFOUT_T33p	G13		
7A	VREFB7A0	IO			DIFFIO_TX_T34p	DIFFOUT_T34p	C19	DQ5T	DQ1T



Pin Information for the Cyclone® V 5CGXBC9 Device  
Version 1.2  
Note (1)

Bank Number	VREF	Pin Name/Function	Optional Function(s)	Configuration Function	Dedicated Tx/Rx Channel	Emulated LVDS Output Channel	U484	DQS for X8	DQS for X16
7A	VREFB7A0	IO	CLK11n		DIFFIO_RX_T33n	DIFFOUT_T33n	F14		
7A	VREFB7A0	IO			DIFFIO_TX_T34n	DIFFOUT_T34n	C18	DQ5T	DQ1T
7A	VREFB7A0	IO			DIFFIO_RX_T35p	DIFFOUT_T35p	C16	DQ5T	DQ1T
7A	VREFB7A0	IO			DIFFIO_TX_T36p	DIFFOUT_T36p	B16	DQ5T	DQ1T
7A	VREFB7A0	IO			DIFFIO_RX_T35n	DIFFOUT_T35n	C15	DQ5T	DQ1T
7A	VREFB7A0	IO			DIFFIO_TX_T36n	DIFFOUT_T36n	B15	DQ5T	DQ1T
7A	VREFB7A0	IO			DIFFIO_RX_T37p	DIFFOUT_T37p	G12	DQS5T	DQ1T
7A	VREFB7A0	IO			DIFFIO_TX_T38p	DIFFOUT_T38p	A18		
7A	VREFB7A0	IO			DIFFIO_RX_T37n	DIFFOUT_T37n	H12	DQSn5T	DQ1T
7A	VREFB7A0	IO			DIFFIO_TX_T38n	DIFFOUT_T38n	A17	DQ5T	DQ1T
7A	VREFB7A0	IO			DIFFIO_RX_T39p	DIFFOUT_T39p	F15	DQ5T	DQ1T
7A	VREFB7A0	IO			DIFFIO_TX_T40p	DIFFOUT_T40p	B18	DQ5T	DQ1T
7A	VREFB7A0	IO			DIFFIO_RX_T39n	DIFFOUT_T39n	E14	DQ5T	DQ1T
7A	VREFB7A0	IO			DIFFIO_TX_T40n	DIFFOUT_T40n	B17		
7A	VREFB7A0	IO	CLK10p		DIFFIO_RX_T41p	DIFFOUT_T41p	H10		
7A	VREFB7A0	IO			DIFFIO_TX_T42p	DIFFOUT_T42p	A15	DQ6T	
7A	VREFB7A0	IO	CLK10n		DIFFIO_RX_T41n	DIFFOUT_T41n	G11		
7A	VREFB7A0	IO			DIFFIO_TX_T42n	DIFFOUT_T42n	A14	DQ6T	
7A	VREFB7A0	IO			DIFFIO_RX_T43p	DIFFOUT_T43p	D13	DQ6T	
7A	VREFB7A0	IO			DIFFIO_TX_T44p	DIFFOUT_T44p	C14	DQ6T	
7A	VREFB7A0	IO			DIFFIO_RX_T43n	DIFFOUT_T43n	C13	DQ6T	
7A	VREFB7A0	IO			DIFFIO_TX_T44n	DIFFOUT_T44n	D14	DQ6T	
7A	VREFB7A0	IO			DIFFIO_RX_T45p	DIFFOUT_T45p	H9	DQS6T	
7A	VREFB7A0	IO			DIFFIO_TX_T46p	DIFFOUT_T46p	A13		
7A	VREFB7A0	IO			DIFFIO_RX_T45n	DIFFOUT_T45n	G8	DQSn6T	
7A	VREFB7A0	IO			DIFFIO_TX_T46n	DIFFOUT_T46n	B13	DQ6T	
7A	VREFB7A0	IO			DIFFIO_RX_T47p	DIFFOUT_T47p	E12	DQ6T	
7A	VREFB7A0	IO			DIFFIO_TX_T48p	DIFFOUT_T48p	B12	DQ6T	
7A	VREFB7A0	IO			DIFFIO_RX_T47n	DIFFOUT_T47n	F12	DQ6T	
7A	VREFB7A0	IO	RZQ_2		DIFFIO_TX_T48n	DIFFOUT_T48n	A12		
8A	VREFB8A0	IO	CLK9p		DIFFIO_RX_T49p	DIFFOUT_T49p	G10		
8A	VREFB8A0	IO			DIFFIO_TX_T50p	DIFFOUT_T50p	C11	DQ7T	
8A	VREFB8A0	IO	CLK9n		DIFFIO_RX_T49n	DIFFOUT_T49n	F10		
8A	VREFB8A0	IO			DIFFIO_TX_T50n	DIFFOUT_T50n	B11	DQ7T	
8A	VREFB8A0	IO			DIFFIO_RX_T51p	DIFFOUT_T51p	D11	DQ7T	
8A	VREFB8A0	IO	FPLL_TL_CLKOUT0,FPLL_TL_CLKOUTp,FPLL_TL_FB		DIFFIO_TX_T52p	DIFFOUT_T52p	A8	DQ7T	
8A	VREFB8A0	IO			DIFFIO_RX_T51n	DIFFOUT_T51n	E11	DQ7T	
8A	VREFB8A0	IO	FPLL_TL_CLKOUT1,FPLL_TL_CLKOUTn		DIFFIO_TX_T52n	DIFFOUT_T52n	A7	DQ7T	
8A	VREFB8A0	IO			DIFFIO_RX_T53p	DIFFOUT_T53p	J9	DQS7T	
8A	VREFB8A0	IO			DIFFIO_TX_T54p	DIFFOUT_T54p	F8		
8A	VREFB8A0	IO			DIFFIO_RX_T53n	DIFFOUT_T53n	J8	DQSn7T	
8A	VREFB8A0	IO			DIFFIO_TX_T54n	DIFFOUT_T54n	E7	DQ7T	
8A	VREFB8A0	IO			DIFFIO_RX_T55p	DIFFOUT_T55p	C10	DQ7T	
8A	VREFB8A0	IO			DIFFIO_TX_T56p	DIFFOUT_T56p	C6	DQ7T	
8A	VREFB8A0	IO			DIFFIO_RX_T55n	DIFFOUT_T55n	C9	DQ7T	
8A	VREFB8A0	IO			DIFFIO_TX_T56n	DIFFOUT_T56n	D7		
8A	VREFB8A0	IO	CLK8p,FPLL_TL_FBp		DIFFIO_RX_T57p	DIFFOUT_T57p	K7		
8A	VREFB8A0	IO			DIFFIO_TX_T58p	DIFFOUT_T58p	A10	DQ8T	
8A	VREFB8A0	IO	CLK8n,FPLL_TL_FBn		DIFFIO_RX_T57n	DIFFOUT_T57n	J7		
8A	VREFB8A0	IO			DIFFIO_TX_T58n	DIFFOUT_T58n	A9	DQ8T	
8A	VREFB8A0	IO			DIFFIO_RX_T59p	DIFFOUT_T59p	D9	DQ8T	
8A	VREFB8A0	IO			DIFFIO_TX_T60p	DIFFOUT_T60p	B6	DQ8T	
8A	VREFB8A0	IO			DIFFIO_RX_T59n	DIFFOUT_T59n	D8	DQ8T	
8A	VREFB8A0	IO			DIFFIO_TX_T60n	DIFFOUT_T60n	B5	DQ8T	
8A	VREFB8A0	IO			DIFFIO_RX_T61p	DIFFOUT_T61p	H8	DQS8T	
8A	VREFB8A0	IO			DIFFIO_TX_T62p	DIFFOUT_T62p	C8		
8A	VREFB8A0	IO			DIFFIO_RX_T61n	DIFFOUT_T61n	G7	DQSn8T	
8A	VREFB8A0	IO			DIFFIO_TX_T62n	DIFFOUT_T62n	B8	DQ8T	
8A	VREFB8A0	IO			DIFFIO_RX_T63p	DIFFOUT_T63p	H6	DQ8T	
8A	VREFB8A0	IO			DIFFIO_TX_T64p	DIFFOUT_T64p	E6	DQ8T	
8A	VREFB8A0	IO			DIFFIO_RX_T63n	DIFFOUT_T63n	G6	DQ8T	
8A	VREFB8A0	IO			DIFFIO_TX_T64n	DIFFOUT_T64n	F7		
9A		MSEL0		MSEL0			L6		
9A		CONF_DONE		CONF_DONE			J6		
9A		MSEL1		MSEL1			K6		
9A		nSTATUS		nSTATUS			G5		
9A		nCE		nCE			H5		
9A		MSEL2		MSEL2			A2		
9A		MSEL3		MSEL3			E5		
9A		nCONFIG		nCONFIG			A4		
9A		MSEL4		MSEL4			C5		



Pin Information for the Cyclone® V 5CGXBC9 Device  
Version 1.2  
Note (1)

Bank Number	VREF	Pin Name/Function	Optional Function(s)	Configuration Function	Dedicated Tx/Rx Channel	Emulated LVDS Output Channel	U484	DQS for X8	DQS for X16
		GND					F3		
		GND					M9		
		GND					V22		
		GND					L3		
		GND					N11		
		GND					W20		
		GND					F11		
		GND					C3		
		GND					Y8		
		GND					K14		
		GND					D1		
		GND					K8		
		GND					V2		
		GND					C7		
		GND					A5		
		GND					B2		
		GND					M14		
		GND					M4		
		GND					G9		
		GND					D2		
		GND					L5		
		GND					J5		
		GND					K1		
		GND					F1		
		GND					C22		
		GND					AB1		
		GND					L16		
		GND					C4		
		GND					H2		
		GND					H1		
		GND					J13		
		GND					AB2		
		GND					E4		
		GND					AB19		
		GND					D5		
		GND					J20		
		GND					V17		
		GND					A11		
		GND					U5		
		GND					G3		
		GND					H14		
		GND					T11		
		GND					M2		
		GND					J15		
		GND					D10		
		GND					J3		
		GND					L13		
		GND					F6		
		GND					H4		
		GND					U9		
		GND					N7		
		GND					U19		
		GND					N15		
		GND					K12		
		GND					AA11		
		GND					K2		
		GND					E3		
		GND					P10		
		GND					A21		
		GND					F2		
		GND					M1		
		GND					P1		
		GND					K10		
		GND					Y5		
		GND					D20		
		GND					B14		
		GND					Y2		
		GND					T2		
		GND					K4		
		GND					P4		
		GND					C17		



Pin Information for the Cyclone® V 5CGXBC9 Device  
Version 1.2  
Note (1)

Bank Number	VREF	Pin Name/Function	Optional Function(s)	Configuration Function	Dedicated Tx/Rx Channel	Emulated LVDS Output Channel	U484	DQS for X8	DQS for X16
		GND					M12		
		GND					N22		
		GND					Y1		
		GND					N13		
		GND					W4		
		GND					AA3		
		GND					B1		
		GND					B14		
		GND					U14		
		GND					R3		
		GND					AA16		
		GND					T1		
		GND					AA4		
		GND					H3		
		GND					V1		
		GND					F21		
		GND					N5		
		GND					M19		
		GND					U3		
		GND					J11		
		GND					Y13		
		GND					E13		
		GND					P2		
		GND					N3		
		GND					R13		
		GND					L11		
		GND					W3		
		GND					F16		
		VCC					M13		
		VCC					K13		
		VCC					J10		
		VCC					M11		
		VCC					P13		
		VCC					H15		
		VCC					M15		
		VCC					N14		
		VCC					L12		
		VCC					J12		
		VCC					H13		
		VCC					L10		
		VCC					K9		
		VCC					P11		
		VCC					P15		
		VCC					N12		
		VCC					H11		
		VCC					J14		
		VCC					L14		
		VCC					K11		
		DNU					B3		
		DNU					B4		
		DNU					AB3		
		DNU					V11		
		DNU					D21		
		DNU					E10		
		VCCPGM					Y6		
		VCCPGM					U20		
		VCCPGM					B7		
		VCCBAT					A3		
		VCCIO3A					AA6		
		VCCIO3A					T6		
		VCCIO3B					R8		
		VCCIO3B					AB9		
		VCCIO3B					W10		
		VCCIO3B					V7		
		VCCIO4A					Y18		
		VCCIO4A					W15		
		VCCIO4A					T16		
		VCCIO4A					V12		
		VCCIO4A					AB14		
		VCCIO4A					AA21		
		VCCIO5A					T21		
		VCCIO5A					R18		



Pin Information for the Cyclone® V 5CGXBC9 Device  
Version 1.2  
Note (1)

Bank Number	VREF	Pin Name/Function	Optional Function(s)	Configuration Function	Dedicated Tx/Rx Channel	Emulated LVDS Output Channel	U484	DQS for X8	DQS for X16
		VCCIO5B					G19		
		VCCIO5B					N17		
		VCCIO5B					P20		
		VCCIO5B					K18		
		VCCIO5B					L21		
		VCCIO5B					H22		
		VCCIO7A					H17		
		VCCIO7A					C12		
		VCCIO7A					D15		
		VCCIO7A					B19		
		VCCIO7A					A16		
		VCCIO7A					E18		
		VCCIO8A					E8		
		VCCIO8A					A6		
		VCCIO8A					H7		
		VCCIO8A					B9		
		VCCPD3A					V6		
		VCCPD3B4A					V14		
		VCCPD3B4A					V10		
		VCCPD3B4A					W9		
		VCCPD3B4A					V16		
		VCCPD5A					P17		
		VCCPD5B					N19		
		VCCPD5B					M18		
		VCCPD7A8A					E9		
		VCCPD7A8A					F13		
		VCCPD7A8A					F9		
		VCCPD7A8A					E15		
3A	VREFB3AN0	VREFB3AN0					W6		
3B	VREFB3BN0	VREFB3BN0					AB12		
4A	VREFB4AN0	VREFB4AN0					AA14		
5A	VREFB5AN0	VREFB5AN0					V21		
5B	VREFB5BN0	VREFB5BN0					K20		
7A	VREFB7AN0	VREFB7AN0					D16		
8A	VREFB8AN0	VREFB8AN0					B10		
		NC					C2		
		NC					C1		
		NC					D4		
		NC					D3		
		VCCH_GXBL					T3		
		VCCH_GXBL					M3		
		VCCL_GXBL					P3		
		VCCL_GXBL					K3		
		RREF_TL					A1		
		VCCA_FPLL					T4		
		VCCA_FPLL					F4		
		VCCA_FPLL					U18		
		VCCA_FPLL					E19		
		VCC_AUX					D19		
		VCC_AUX					AA12		
		VCC_AUX					W19		
		VCC_AUX					D6		
		VCC_AUX					D12		
		VCC_AUX					AB5		
		VCCE_GXBL					N4		
		VCCE_GXBL					L4		
		VCCE_GXBL					J4		
		VCCE_GXBL					K5		

Note:

(1) For more information about pin definition and pin connection guidelines, refer to the [Cyclone V Device Family Pin Connection Guidelines](#).



Pin Information for the Cyclone® V 5CGXBC9 Device  
Version 1.2  
Note (1)

Bank Number	VREF	Pin Name/Function	Optional Function(s)	Configuration Function	Dedicated Tx/Rx Channel	Emulated LVDS Output Channel	F484	DQS for X8	DQS for X16
GXB_L1		REFCLK1Ln					F5		
GXB_L1		REFCLK1Lp					G4		
GXB_L1		GXB_TX_L5n					D3		
GXB_L1		GXB_TX_L5p					D4		
GXB_L1		GXB_RX_L5p,GXB_REFCLK_L5p					C2		
GXB_L1		GXB_RX_L5n,GXB_REFCLK_L5n					C1		
GXB_L1		GXB_TX_L4n					E1		
GXB_L1		GXB_TX_L4p					E2		
GXB_L1		GXB_RX_L4p,GXB_REFCLK_L4p					G2		
GXB_L1		GXB_RX_L4n,GXB_REFCLK_L4n					G1		
GXB_L1		GXB_TX_L3n					J1		
GXB_L1		GXB_TX_L3p					J2		
GXB_L1		GXB_RX_L3p,GXB_REFCLK_L3p					L2		
GXB_L1		GXB_RX_L3n,GXB_REFCLK_L3n					L1		
GXB_L0		GXB_TX_L2n					N1		
GXB_L0		GXB_TX_L2p					N2		
GXB_L0		GXB_RX_L2p,GXB_REFCLK_L2p					R2		
GXB_L0		GXB_RX_L2n,GXB_REFCLK_L2n					R1		
GXB_L0		GXB_TX_L1n					U1		
GXB_L0		GXB_TX_L1p					U2		
GXB_L0		GXB_RX_L1p,GXB_REFCLK_L1p					W2		
GXB_L0		GXB_RX_L1n,GXB_REFCLK_L1n					W1		
GXB_L0		GXB_TX_L0n					Y3		
GXB_L0		GXB_TX_L0p					Y4		
GXB_L0		GXB_RX_L0p,GXB_REFCLK_L0p					AA2		
GXB_L0		GXB_RX_L0n,GXB_REFCLK_L0n					AA1		
GXB_L0		REFCLK0Lp					V4		
GXB_L0		REFCLK0Ln					U4		
3A		TDO		TDO			M5		
3A		nCS0		DATA4			R4		
3A		TMS		TMS			P5		
3A		AS_DATA3		DATA3			T4		
3A		TCK		TCK			V5		
3A		AS_DATA2		DATA2			AA5		
3A		TDI		TDI			W5		
3A		AS_DATA1		DATA1			AB3		
3A		DCLK		DCLK			V3		
3A		AS_DATA0,ASDO		DATA0			AB4		
3A	VREFB3AN0	IO		DATA6	DIFFIO_RX_B1n	DIFFOUT_B1n	R6	DQ1B	
3A	VREFB3AN0	IO		DATA5	DIFFIO_TX_B2n	DIFFOUT_B2n	U7		
3A	VREFB3AN0	IO		DATA8	DIFFIO_RX_B1p	DIFFOUT_B1p	R5	DQ1B	
3A	VREFB3AN0	IO		DATA7	DIFFIO_TX_B2p	DIFFOUT_B2p	U8	DQ1B	
3A	VREFB3AN0	IO		DATA10	DIFFIO_RX_B3n	DIFFOUT_B3n	P6	DQSn1B	
3A	VREFB3AN0	IO		DATA9	DIFFIO_TX_B4n	DIFFOUT_B4n	W8	DQ1B	
3A	VREFB3AN0	IO		DATA12	DIFFIO_RX_B3p	DIFFOUT_B3p	N6	DQS1B	
3A	VREFB3AN0	IO		DATA11	DIFFIO_TX_B4p	DIFFOUT_B4p	W9		
3A	VREFB3AN0	IO		DATA14	DIFFIO_RX_B5n	DIFFOUT_B5n	T7	DQ1B	
3A	VREFB3AN0	IO		DATA13	DIFFIO_TX_B6n	DIFFOUT_B6n	U6	DQ1B	
3A	VREFB3AN0	IO		CLKUSR	DIFFIO_RX_B5p	DIFFOUT_B5p	T8	DQ1B	
3A	VREFB3AN0	IO		DATA15	DIFFIO_TX_B6p	DIFFOUT_B6p	V6	DQ1B	
3A	VREFB3AN0	IO		PR_DONE	DIFFIO_RX_B7n	DIFFOUT_B7n	M6		
3A	VREFB3AN0	IO		PR_READY	DIFFIO_TX_B8n	DIFFOUT_B8n	R7	DQ1B	
3A	VREFB3AN0	IO		PR_ERROR	DIFFIO_RX_B7p	DIFFOUT_B7p	M7		
3A	VREFB3AN0	IO			DIFFIO_TX_B8p	DIFFOUT_B8p	P7	DQ1B	
3B	VREFB3BN0	IO			DIFFIO_TX_B33n	DIFFOUT_B33n	AB6		
3B	VREFB3BN0	IO			DIFFIO_RX_B34n	DIFFOUT_B34n	V9	DQ2B	
3B	VREFB3BN0	IO			DIFFIO_TX_B33p	DIFFOUT_B33p	AB5	DQ2B	
3B	VREFB3BN0	IO			DIFFIO_RX_B34p	DIFFOUT_B34p	V10	DQ2B	
3B	VREFB3BN0	IO			DIFFIO_RX_B35n	DIFFOUT_B35n	P8	DQSn2B	
3B	VREFB3BN0	IO			DIFFIO_TX_B36n	DIFFOUT_B36n	AA7	DQ2B	
3B	VREFB3BN0	IO			DIFFIO_RX_B35p	DIFFOUT_B35p	N8	DQS2B	
3B	VREFB3BN0	IO			DIFFIO_TX_B36p	DIFFOUT_B36p	AB7		
3B	VREFB3BN0	IO			DIFFIO_TX_B37n	DIFFOUT_B37n	AA8	DQ2B	
3B	VREFB3BN0	IO			DIFFIO_RX_B38n	DIFFOUT_B38n	T9	DQ2B	
3B	VREFB3BN0	IO			DIFFIO_TX_B37p	DIFFOUT_B37p	AB8	DQ2B	
3B	VREFB3BN0	IO			DIFFIO_RX_B38p	DIFFOUT_B38p	U10	DQ2B	
3B	VREFB3BN0	IO	CLK0n,FPLL_BL_FBn		DIFFIO_RX_B39n	DIFFOUT_B39n	M8		
3B	VREFB3BN0	IO			DIFFIO_TX_B40n	DIFFOUT_B40n	AA10	DQ2B	
3B	VREFB3BN0	IO	CLK0p,FPLL_BL_FBp		DIFFIO_RX_B39p	DIFFOUT_B39p	M9		
3B	VREFB3BN0	IO			DIFFIO_TX_B40p	DIFFOUT_B40p	AA9	DQ2B	
3B	VREFB3BN0	IO			DIFFIO_TX_B41n	DIFFOUT_B41n	Y10		





Pin Information for the Cyclone® V 5CGXBC9 Device  
Version 1.2  
Note (1)

Bank Number	VREF	Pin Name/Function	Optional Function(s)	Configuration Function	Dedicated Tx/Rx Channel	Emulated LVDS Output Channel	F484	DQS for X8	DQS for X16
3B	VREFB3BNO	IO			DIFFIO_RX_B42n	DIFFFOUT_B42n	T10	DQ3B	
3B	VREFB3BNO	IO			DIFFIO_TX_B41p	DIFFFOUT_B41p	Y9	DQ3B	
3B	VREFB3BNO	IO			DIFFIO_RX_B42p	DIFFFOUT_B42p	R9	DQ3B	
3B	VREFB3BNO	IO			DIFFIO_RX_B43n	DIFFFOUT_B43n	U11	DQS3B	
3B	VREFB3BNO	IO			DIFFIO_TX_B44n	DIFFFOUT_B44n	R12	DQ3B	
3B	VREFB3BNO	IO			DIFFIO_RX_B43p	DIFFFOUT_B43p	U12	DQS3B	
3B	VREFB3BNO	IO			DIFFIO_TX_B44p	DIFFFOUT_B44p	P12		
3B	VREFB3BNO	IO	FPLL_CLKOUT1,FPLL_CLKOUTn		DIFFIO_TX_B45n	DIFFFOUT_B45n	AB10	DQ3B	
3B	VREFB3BNO	IO			DIFFIO_RX_B46n	DIFFFOUT_B46n	R10	DQ3B	
3B	VREFB3BNO	IO	FPLL_CLKOUT0,FPLL_CLKOUTp,FPLL_CLK_FB		DIFFIO_TX_B45p	DIFFFOUT_B45p	AB11	DQ3B	
3B	VREFB3BNO	IO			DIFFIO_RX_B46p	DIFFFOUT_B46p	R11	DQ3B	
3B	VREFB3BNO	IO	CLK1n		DIFFIO_RX_B47n	DIFFFOUT_B47n	P9		
3B	VREFB3BNO	IO			DIFFIO_TX_B48n	DIFFFOUT_B48n	Y11	DQ3B	
3B	VREFB3BNO	IO	CLK1p		DIFFIO_RX_B47p	DIFFFOUT_B47p	N9		
3B	VREFB3BNO	IO			DIFFIO_TX_B48p	DIFFFOUT_B48p	AA12	DQ3B	
4A	VREFB4ANO	IO	RZQ_0		DIFFIO_TX_B49n	DIFFFOUT_B49n	AB13		
4A	VREFB4ANO	IO			DIFFIO_RX_B50n	DIFFFOUT_B50n	V13	DQ4B	
4A	VREFB4ANO	IO			DIFFIO_TX_B49p	DIFFFOUT_B49p	AB12	DQ4B	
4A	VREFB4ANO	IO			DIFFIO_RX_B50p	DIFFFOUT_B50p	U13	DQ4B	
4A	VREFB4ANO	IO			DIFFIO_RX_B51n	DIFFFOUT_B51n	T12	DQS4B	
4A	VREFB4ANO	IO			DIFFIO_TX_B52n	DIFFFOUT_B52n	AA14	DQ4B	
4A	VREFB4ANO	IO			DIFFIO_RX_B51p	DIFFFOUT_B51p	T13	DQS4B	
4A	VREFB4ANO	IO			DIFFIO_TX_B52p	DIFFFOUT_B52p	AA13		
4A	VREFB4ANO	IO			DIFFIO_TX_B53n	DIFFFOUT_B53n	AB15	DQ4B	
4A	VREFB4ANO	IO			DIFFIO_RX_B54n	DIFFFOUT_B54n	Y14	DQ4B	
4A	VREFB4ANO	IO			DIFFIO_TX_B53p	DIFFFOUT_B53p	AA15	DQ4B	
4A	VREFB4ANO	IO			DIFFIO_RX_B54p	DIFFFOUT_B54p	Y15	DQ4B	
4A	VREFB4ANO	IO	CLK2n		DIFFIO_RX_B55n	DIFFFOUT_B55n	V14		
4A	VREFB4ANO	IO			DIFFIO_TX_B56n	DIFFFOUT_B56n	AB17	DQ4B	
4A	VREFB4ANO	IO	CLK2p		DIFFIO_RX_B55p	DIFFFOUT_B55p	V15		
4A	VREFB4ANO	IO			DIFFIO_TX_B56p	DIFFFOUT_B56p	AB18	DQ4B	
4A	VREFB4ANO	IO			DIFFIO_TX_B57n	DIFFFOUT_B57n	AB20		
4A	VREFB4ANO	IO			DIFFIO_RX_B58n	DIFFFOUT_B58n	Y16	DQ5B	DQ1B
4A	VREFB4ANO	IO			DIFFIO_TX_B57p	DIFFFOUT_B57p	AB21	DQ5B	DQ1B
4A	VREFB4ANO	IO			DIFFIO_RX_B58p	DIFFFOUT_B58p	Y17	DQ5B	DQ1B
4A	VREFB4ANO	IO			DIFFIO_RX_B59n	DIFFFOUT_B59n	T14	DQS5B	DQ1B
4A	VREFB4ANO	IO			DIFFIO_TX_B60n	DIFFFOUT_B60n	AA17	DQ5B	DQ1B
4A	VREFB4ANO	IO			DIFFIO_RX_B59p	DIFFFOUT_B59p	U15	DQS5B	DQ1B
4A	VREFB4ANO	IO			DIFFIO_TX_B60p	DIFFFOUT_B60p	AA18		
4A	VREFB4ANO	IO			DIFFIO_TX_B61n	DIFFFOUT_B61n	AA19	DQ5B	DQ1B
4A	VREFB4ANO	IO			DIFFIO_RX_B62n	DIFFFOUT_B62n	V20	DQ5B	DQ1B
4A	VREFB4ANO	IO			DIFFIO_TX_B61p	DIFFFOUT_B61p	AA20	DQ5B	DQ1B
4A	VREFB4ANO	IO	CLK3n		DIFFIO_RX_B62p	DIFFFOUT_B62p	W19	DQ5B	DQ1B
4A	VREFB4ANO	IO			DIFFIO_RX_B63n	DIFFFOUT_B63n	V16		
4A	VREFB4ANO	IO			DIFFIO_TX_B64n	DIFFFOUT_B64n	AB22	DQ5B	DQ1B
4A	VREFB4ANO	IO	CLK3p		DIFFIO_RX_B63p	DIFFFOUT_B63p	W16		
4A	VREFB4ANO	IO			DIFFIO_TX_B64p	DIFFFOUT_B64p	AA22	DQ5B	DQ1B
4A	VREFB4ANO	IO			DIFFIO_TX_B65n	DIFFFOUT_B65n	Y22		
4A	VREFB4ANO	IO			DIFFIO_RX_B66n	DIFFFOUT_B66n	Y20	DQ6B	DQ1B
4A	VREFB4ANO	IO			DIFFIO_TX_B65p	DIFFFOUT_B65p	W22	DQ6B	DQ1B
4A	VREFB4ANO	IO			DIFFIO_RX_B66p	DIFFFOUT_B66p	Y19	DQ6B	DQ1B
4A	VREFB4ANO	IO			DIFFIO_RX_B67n	DIFFFOUT_B67n	P14	DQS6B	DQS1B
4A	VREFB4ANO	IO			DIFFIO_TX_B68n	DIFFFOUT_B68n	Y21	DQ6B	DQ1B
4A	VREFB4ANO	IO			DIFFIO_RX_B67p	DIFFFOUT_B67p	R14	DQS6B	DQS1B
4A	VREFB4ANO	IO			DIFFIO_TX_B68p	DIFFFOUT_B68p	W21		
4A	VREFB4ANO	IO			DIFFIO_TX_B69n	DIFFFOUT_B69n	U22	DQ6B	DQ1B
4A	VREFB4ANO	IO			DIFFIO_RX_B70n	DIFFFOUT_B70n	V19	DQ6B	DQ1B
4A	VREFB4ANO	IO			DIFFIO_TX_B69p	DIFFFOUT_B69p	V21	DQ6B	DQ1B
4A	VREFB4ANO	IO			DIFFIO_RX_B70p	DIFFFOUT_B70p	V18	DQ6B	DQ1B
4A	VREFB4ANO	IO			DIFFIO_RX_B71n	DIFFFOUT_B71n	U16		
4A	VREFB4ANO	IO			DIFFIO_TX_B72n	DIFFFOUT_B72n	U21	DQ6B	DQ1B
4A	VREFB4ANO	IO			DIFFIO_RX_B71p	DIFFFOUT_B71p	U17		
4A	VREFB4ANO	IO			DIFFIO_TX_B72p	DIFFFOUT_B72p	U20	DQ6B	DQ1B
5A	VREFB5ANO	IO	RZQ_1		DIFFIO_TX_R1p	DIFFFOUT_R1p	T19	DQ1R	
5A	VREFB5ANO	IO		INIT_DONE	DIFFIO_RX_R2p	DIFFFOUT_R2p	T18		
5A	VREFB5ANO	IO		PR_REQUEST	DIFFIO_TX_R1n	DIFFFOUT_R1n	T20	DQ1R	
5A	VREFB5ANO	IO		CRC_ERROR	DIFFIO_RX_R2n	DIFFFOUT_R2n	T17		
5A	VREFB5ANO	IO		nCEO	DIFFIO_TX_R3p	DIFFFOUT_R3p	T22	DQ1R	
5A	VREFB5ANO	IO			DIFFIO_RX_R4p	DIFFFOUT_R4p	T15	DQ1R	
5A	VREFB5ANO	IO		CvP_CONFDONE	DIFFIO_TX_R3n	DIFFFOUT_R3n	R22	DQ1R	
5A	VREFB5ANO	IO			DIFFIO_RX_R4n	DIFFFOUT_R4n	R15	DQ1R	



Pin Information for the Cyclone® V 5CGXBC9 Device  
Version 1.2  
Note (1)

Bank Number	VREF	Pin Name/Function	Optional Function(s)	Configuration Function	Dedicated Tx/Rx Channel	Emulated LVDS Output Channel	F484	DQS for X8	DQS for X16
5A	VREFB5A0	IO		DEV_OE	DIFFIO_TX_R5p	DIFFOUT_R5p	R21		
5A	VREFB5A0	IO			DIFFIO_RX_R6p	DIFFOUT_R6p	R16	DQS1R	
5A	VREFB5A0	IO		DEV_CLRn	DIFFIO_TX_R5n	DIFFOUT_R5n	P22	DQ1R	
5A	VREFB5A0	IO			DIFFIO_RX_R6n	DIFFOUT_R6n	R17	DQSn1R	
5A	VREFB5A0	IO			DIFFIO_TX_R7p	DIFFOUT_R7p	P19	DQ1R	
5A	VREFB5A0	IO			DIFFIO_RX_R8p	DIFFOUT_R8p	P16	DQ1R	
5A	VREFB5A0	IO			DIFFIO_TX_R7n	DIFFOUT_R7n	P18		
5A	VREFB5A0	IO			DIFFIO_RX_R8n	DIFFOUT_R8n	P17	DQ1R	
5B	VREFB5B0	IO	CLK6p		DIFFIO_RX_R41p	DIFFOUT_R41p	N16		
5B	VREFB5B0	IO			DIFFIO_TX_R42p	DIFFOUT_R42p	N20	DQ2R	
5B	VREFB5B0	IO	CLK6n		DIFFIO_RX_R41n	DIFFOUT_R41n	M16		
5B	VREFB5B0	IO			DIFFIO_TX_R42n	DIFFOUT_R42n	N21	DQ2R	
5B	VREFB5B0	IO			DIFFIO_RX_R43p	DIFFOUT_R43p	N19	DQ2R	
5B	VREFB5B0	IO	FPLL_BR_CLKOUT0,FPLL_BR_CLKOUTp,FPLL_BR_FB		DIFFIO_TX_R44p	DIFFOUT_R44p	M22	DQ2R	
5B	VREFB5B0	IO			DIFFIO_RX_R43n	DIFFOUT_R43n	M18	DQ2R	
5B	VREFB5B0	IO	FPLL_BR_CLKOUT1,FPLL_BR_CLKOUTn		DIFFIO_TX_R44n	DIFFOUT_R44n	L22	DQ2R	
5B	VREFB5B0	IO			DIFFIO_RX_R45p	DIFFOUT_R45p	K17	DQS2R	
5B	VREFB5B0	IO			DIFFIO_TX_R46p	DIFFOUT_R46p	M20		
5B	VREFB5B0	IO			DIFFIO_RX_R45n	DIFFOUT_R45n	L17	DQSn2R	
5B	VREFB5B0	IO			DIFFIO_TX_R46n	DIFFOUT_R46n	M21	DQ2R	
5B	VREFB5B0	IO			DIFFIO_RX_R47p	DIFFOUT_R47p	L19	DQ2R	
5B	VREFB5B0	IO			DIFFIO_TX_R48p	DIFFOUT_R48p	K21	DQ2R	
5B	VREFB5B0	IO			DIFFIO_RX_R47n	DIFFOUT_R47n	L18	DQ2R	
5B	VREFB5B0	IO			DIFFIO_TX_R48n	DIFFOUT_R48n	K22		
7A		GND					F17		
7A	VREFB7A0	IO			DIFFIO_RX_T9p	DIFFOUT_T9p	H21		
7A	VREFB7A0	IO			DIFFIO_TX_T10p	DIFFOUT_T10p	E21	DQ1T	
7A	VREFB7A0	IO			DIFFIO_RX_T9n	DIFFOUT_T9n	G21		
7A	VREFB7A0	IO			DIFFIO_TX_T10n	DIFFOUT_T10n	D21	DQ1T	
7A	VREFB7A0	IO			DIFFIO_RX_T11p	DIFFOUT_T11p	E19	DQ1T	
7A	VREFB7A0	IO			DIFFIO_TX_T12p	DIFFOUT_T12p	C20	DQ1T	
7A	VREFB7A0	IO			DIFFIO_RX_T11n	DIFFOUT_T11n	D19	DQ1T	
7A	VREFB7A0	IO			DIFFIO_TX_T12n	DIFFOUT_T12n	B20	DQ1T	
7A	VREFB7A0	IO			DIFFIO_RX_T13p	DIFFOUT_T13p	J21	DQS1T	
7A	VREFB7A0	IO			DIFFIO_TX_T14p	DIFFOUT_T14p	B18		
7A	VREFB7A0	IO			DIFFIO_RX_T13n	DIFFOUT_T13n	J22	DQSn1T	
7A	VREFB7A0	IO			DIFFIO_TX_T14n	DIFFOUT_T14n	B17	DQ1T	
7A	VREFB7A0	IO			DIFFIO_RX_T15p	DIFFOUT_T15p	C21	DQ1T	
7A	VREFB7A0	IO			DIFFIO_TX_T16p	DIFFOUT_T16p	G22	DQ1T	
7A	VREFB7A0	IO			DIFFIO_RX_T15n	DIFFOUT_T15n	B21	DQ1T	
7A	VREFB7A0	IO			DIFFIO_TX_T16n	DIFFOUT_T16n	F22		
7A	VREFB7A0	IO			DIFFIO_RX_T25p	DIFFOUT_T25p	K20		
7A	VREFB7A0	IO			DIFFIO_TX_T26p	DIFFOUT_T26p	B16	DQ2T	DQ1T
7A	VREFB7A0	IO			DIFFIO_RX_T25n	DIFFOUT_T25n	K19		
7A	VREFB7A0	IO			DIFFIO_TX_T26n	DIFFOUT_T26n	C16	DQ2T	DQ1T
7A	VREFB7A0	IO			DIFFIO_RX_T27p	DIFFOUT_T27p	D17	DQ2T	DQ1T
7A	VREFB7A0	IO			DIFFIO_TX_T28p	DIFFOUT_T28p	G17	DQ2T	DQ1T
7A	VREFB7A0	IO			DIFFIO_RX_T27n	DIFFOUT_T27n	E16	DQ2T	DQ1T
7A	VREFB7A0	IO			DIFFIO_TX_T28n	DIFFOUT_T28n	G16	DQ2T	DQ1T
7A	VREFB7A0	IO			DIFFIO_RX_T29p	DIFFOUT_T29p	G18	DQS2T	DQS1T
7A	VREFB7A0	IO			DIFFIO_TX_T30p	DIFFOUT_T30p	J19		
7A	VREFB7A0	IO			DIFFIO_RX_T29n	DIFFOUT_T29n	H18	DQSn2T	DQSn1T
7A	VREFB7A0	IO			DIFFIO_TX_T30n	DIFFOUT_T30n	J18	DQ2T	DQ1T
7A	VREFB7A0	IO			DIFFIO_RX_T31p	DIFFOUT_T31p	E15	DQ2T	DQ1T
7A	VREFB7A0	IO			DIFFIO_TX_T32p	DIFFOUT_T32p	A15	DQ2T	DQ1T
7A	VREFB7A0	IO			DIFFIO_RX_T31n	DIFFOUT_T31n	F15	DQ2T	DQ1T
7A	VREFB7A0	IO			DIFFIO_TX_T32n	DIFFOUT_T32n	A14		
7A	VREFB7A0	IO	CLK11p		DIFFIO_RX_T33p	DIFFOUT_T33p	H16		
7A	VREFB7A0	IO			DIFFIO_TX_T34p	DIFFOUT_T34p	J17	DQ3T	DQ1T
7A	VREFB7A0	IO	CLK11n		DIFFIO_RX_T33n	DIFFOUT_T33n	H15		
7A	VREFB7A0	IO			DIFFIO_TX_T34n	DIFFOUT_T34n	K16	DQ3T	DQ1T
7A	VREFB7A0	IO			DIFFIO_RX_T35p	DIFFOUT_T35p	C15	DQ3T	DQ1T
7A	VREFB7A0	IO			DIFFIO_TX_T36p	DIFFOUT_T36p	G15	DQ3T	DQ1T
7A	VREFB7A0	IO			DIFFIO_RX_T35n	DIFFOUT_T35n	B15	DQ3T	DQ1T
7A	VREFB7A0	IO			DIFFIO_TX_T36n	DIFFOUT_T36n	F14	DQ3T	DQ1T
7A	VREFB7A0	IO			DIFFIO_RX_T37p	DIFFOUT_T37p	H14	DQS3T	DQ1T
7A	VREFB7A0	IO			DIFFIO_TX_T38p	DIFFOUT_T38p	B13		
7A	VREFB7A0	IO			DIFFIO_RX_T37n	DIFFOUT_T37n	J13	DQSn3T	DQ1T
7A	VREFB7A0	IO			DIFFIO_TX_T38n	DIFFOUT_T38n	A13	DQ3T	DQ1T
7A	VREFB7A0	IO			DIFFIO_RX_T39p	DIFFOUT_T39p	E14	DQ3T	DQ1T
7A	VREFB7A0	IO			DIFFIO_TX_T40p	DIFFOUT_T40p	J11	DQ3T	DQ1T



Pin Information for the Cyclone® V 5CGXBC9 Device  
Version 1.2  
Note (1)

Bank Number	VREF	Pin Name/Function	Optional Function(s)	Configuration Function	Dedicated Tx/Rx Channel	Emulated LVDS Output Channel	F484	DQS for X8	DQS for X16
7A	VREFB7A0	IO			DIFFIO_RX_T39n	DIFFFOUT_T39n	F13	DQ3T	DQ1T
7A	VREFB7A0	IO			DIFFIO_TX_T40n	DIFFFOUT_T40n	H10		
7A	VREFB7A0	IO	CLK10p		DIFFIO_RX_T41p	DIFFFOUT_T41p	H13		
7A	VREFB7A0	IO			DIFFIO_TX_T42p	DIFFFOUT_T42p	G11	DQ4T	
7A	VREFB7A0	IO	CLK10n		DIFFIO_RX_T41n	DIFFFOUT_T41n	G13		
7A	VREFB7A0	IO			DIFFIO_TX_T42n	DIFFFOUT_T42n	F12	DQ4T	
7A	VREFB7A0	IO			DIFFIO_RX_T43p	DIFFFOUT_T43p	D13	DQ4T	
7A	VREFB7A0	IO			DIFFIO_TX_T44p	DIFFFOUT_T44p	B12	DQ4T	
7A	VREFB7A0	IO			DIFFIO_RX_T43n	DIFFFOUT_T43n	C13	DQ4T	
7A	VREFB7A0	IO			DIFFIO_TX_T44n	DIFFFOUT_T44n	A12	DQ4T	
7A	VREFB7A0	IO			DIFFIO_RX_T45p	DIFFFOUT_T45p	H11	DQS4T	
7A	VREFB7A0	IO			DIFFIO_TX_T46p	DIFFFOUT_T46p	L8		
7A	VREFB7A0	IO			DIFFIO_RX_T45n	DIFFFOUT_T45n	G12	DQS4T	
7A	VREFB7A0	IO			DIFFIO_TX_T46n	DIFFFOUT_T46n	K9	DQ4T	
7A	VREFB7A0	IO			DIFFIO_RX_T47p	DIFFFOUT_T47p	D12	DQ4T	
7A	VREFB7A0	IO			DIFFIO_TX_T48p	DIFFFOUT_T48p	C11	DQ4T	
7A	VREFB7A0	IO			DIFFIO_RX_T47n	DIFFFOUT_T47n	E12	DQ4T	
7A	VREFB7A0	IO	RZQ_2		DIFFIO_TX_T48n	DIFFFOUT_T48n	B11		
8A	VREFB8A0	IO	CLK9p		DIFFIO_RX_T49p	DIFFFOUT_T49p	G10		
8A	VREFB8A0	IO			DIFFIO_TX_T50p	DIFFFOUT_T50p	L7	DQ5T	
8A	VREFB8A0	IO	CLK9n		DIFFIO_RX_T49n	DIFFFOUT_T49n	F10		
8A	VREFB8A0	IO			DIFFIO_TX_T50n	DIFFFOUT_T50n	K7	DQ5T	
8A	VREFB8A0	IO			DIFFIO_RX_T51p	DIFFFOUT_T51p	J7	DQ5T	
8A	VREFB8A0	IO	FPLL_TL_CLKOUT0,FPLL_TL_CLKOUTp,FPLL_TL_FB		DIFFIO_TX_T52p	DIFFFOUT_T52p	H8	DQ5T	
8A	VREFB8A0	IO			DIFFIO_RX_T51n	DIFFFOUT_T51n	J8	DQ5T	
8A	VREFB8A0	IO	FPLL_TL_CLKOUT1,FPLL_TL_CLKOUTn		DIFFIO_TX_T52n	DIFFFOUT_T52n	G8	DQ5T	
8A	VREFB8A0	IO			DIFFIO_RX_T53p	DIFFFOUT_T53p	J9	DQS5T	
8A	VREFB8A0	IO			DIFFIO_TX_T54p	DIFFFOUT_T54p	A10		
8A	VREFB8A0	IO			DIFFIO_RX_T53n	DIFFFOUT_T53n	H9	DQS5T	
8A	VREFB8A0	IO			DIFFIO_TX_T54n	DIFFFOUT_T54n	A9	DQ5T	
8A	VREFB8A0	IO			DIFFIO_RX_T55p	DIFFFOUT_T55p	B10	DQ5T	
8A	VREFB8A0	IO			DIFFIO_TX_T56p	DIFFFOUT_T56p	A5	DQ5T	
8A	VREFB8A0	IO			DIFFIO_RX_T55n	DIFFFOUT_T55n	C9	DQ5T	
8A	VREFB8A0	IO			DIFFIO_TX_T56n	DIFFFOUT_T56n	B5		
8A	VREFB8A0	IO	CLK8p,FPLL_TL_FBp		DIFFIO_RX_T57p	DIFFFOUT_T57p	E10		
8A	VREFB8A0	IO			DIFFIO_TX_T58p	DIFFFOUT_T58p	B6	DQ6T	
8A	VREFB8A0	IO	CLK8n,FPLL_TL_FBn		DIFFIO_RX_T57n	DIFFFOUT_T57n	F9		
8A	VREFB8A0	IO			DIFFIO_TX_T58n	DIFFFOUT_T58n	B7	DQ6T	
8A	VREFB8A0	IO			DIFFIO_RX_T59p	DIFFFOUT_T59p	A8	DQ6T	
8A	VREFB8A0	IO			DIFFIO_TX_T60p	DIFFFOUT_T60p	C6	DQ6T	
8A	VREFB8A0	IO			DIFFIO_RX_T59n	DIFFFOUT_T59n	A7	DQ6T	
8A	VREFB8A0	IO			DIFFIO_TX_T60n	DIFFFOUT_T60n	D6	DQ6T	
8A	VREFB8A0	IO			DIFFIO_RX_T61p	DIFFFOUT_T61p	E9	DQS6T	
8A	VREFB8A0	IO			DIFFIO_TX_T62p	DIFFFOUT_T62p	D7		
8A	VREFB8A0	IO			DIFFIO_RX_T61n	DIFFFOUT_T61n	D9	DQS6T	
8A	VREFB8A0	IO			DIFFIO_TX_T62n	DIFFFOUT_T62n	C8	DQ6T	
8A	VREFB8A0	IO			DIFFIO_RX_T63p	DIFFFOUT_T63p	G6	DQ6T	
8A	VREFB8A0	IO			DIFFIO_TX_T64p	DIFFFOUT_T64p	F7	DQ6T	
8A	VREFB8A0	IO			DIFFIO_RX_T63n	DIFFFOUT_T63n	H6	DQ6T	
8A	VREFB8A0	IO			DIFFIO_TX_T64n	DIFFFOUT_T64n	E7		
9A		MSEL0		MSEL0			L6		
9A		CONF_DONE		CONF_DONE			K6		
9A		MSEL1		MSEL1			J6		
9A		nSTATUS		nSTATUS			H5		
9A		nCE		nCE			G5		
9A		MSEL2		MSEL2			A2		
9A		MSEL3		MSEL3			E5		
9A		nCONFIG		nCONFIG			A4		
9A		MSEL4		MSEL4			F3		
9A		GND					C5		
		GND					J20		
		GND					L21		
		GND					N22		
		GND					T21		
		GND					Y18		
		GND					AB14		
		GND					V12		
		GND					AA6		
		GND					V7		
		GND					U5		
		GND					AA4		



Pin Information for the Cyclone® V 5CGXBC9 Device  
Version 1.2  
Note (1)

Bank Number	VREF	Pin Name/Function	Optional Function(s)	Configuration Function	Dedicated Tx/Rx Channel	Emulated LVDS Output Channel	F484	DQS for X8	DQS for X16
		GND					Y5		
		GND					U3		
		GND					R3		
		GND					P4		
		GND					P2		
		GND					N5		
		GND					L3		
		GND					M4		
		GND					L5		
		GND					K2		
		GND					J3		
		GND					K4		
		GND					H2		
		GND					H3		
		GND					J5		
		GND					G3		
		GND					H4		
		GND					F2		
		GND					B1		
		GND					E3		
		GND					AB19		
		GND					AB9		
		GND					AB2		
		GND					AB1		
		GND					AA11		
		GND					AA3		
		GND					Y2		
		GND					Y1		
		GND					W4		
		GND					W3		
		GND					V22		
		GND					V17		
		GND					V2		
		GND					V1		
		GND					U9		
		GND					T16		
		GND					T2		
		GND					T1		
		GND					R13		
		GND					P10		
		GND					P1		
		GND					N17		
		GND					N15		
		GND					N13		
		GND					N11		
		GND					N7		
		GND					N3		
		GND					M14		
		GND					M12		
		GND					M10		
		GND					M2		
		GND					M1		
		GND					L15		
		GND					L13		
		GND					L11		
		GND					K14		
		GND					K12		
		GND					K10		
		GND					K8		
		GND					K1		
		GND					J15		
		GND					H22		
		GND					H12		
		GND					H7		
		GND					H1		
		GND					G19		
		GND					G9		
		GND					F16		
		GND					F6		
		GND					F1		
		GND					E13		



Pin Information for the Cyclone® V 5CGXBC9 Device  
Version 1.2  
Note (1)

Bank Number	VREF	Pin Name/Function	Optional Function(s)	Configuration Function	Dedicated Tx/Rx Channel	Emulated LVDS Output Channel	F484	DQS for X8	DQS for X16
		GND					E4		
		GND					D20		
		GND					D10		
		GND					D5		
		GND					D2		
		GND					D1		
		GND					C17		
		GND					C4		
		GND					C3		
		GND					B14		
		GND					B9		
		GND					B2		
		GND					A21		
		GND					A11		
		VCC					P15		
		VCC					P13		
		VCC					P11		
		VCC					N14		
		VCC					N12		
		VCC					N10		
		VCC					M15		
		VCC					M13		
		VCC					M11		
		VCC					L16		
		VCC					L14		
		VCC					L12		
		VCC					L10		
		VCC					K15		
		VCC					K13		
		VCC					K11		
		VCC					J16		
		VCC					J14		
		VCC					J12		
		VCC					J10		
		DNU					B3		
		DNU					B4		
		DNU					Y6		
		DNU					V11		
		DNU					E17		
		DNU					L9		
		VCCPGM					V8		
		VCCPGM					R19		
		VCCPGM					F8		
		VCCBAT					A3		
		VCCIO3A					T6		
		VCCIO3A					Y8		
		VCCIO3B					R8		
		VCCIO3B					Y13		
		VCCIO3B					W10		
		VCCIO3B					T11		
		VCCIO4A					U19		
		VCCIO4A					AA21		
		VCCIO4A					AA16		
		VCCIO4A					W20		
		VCCIO4A					W15		
		VCCIO4A					U14		
		VCCIO5A					P20		
		VCCIO5A					R18		
		VCCIO5B					M19		
		VCCIO5B					K18		
		VCCIO7A					B19		
		VCCIO7A					H17		
		VCCIO7A					G14		
		VCCIO7A					F21		
		VCCIO7A					F11		
		VCCIO7A					E18		
		VCCIO7A					D15		
		VCCIO7A					C22		
		VCCIO7A					C12		
		VCCIO7A					A16		
		VCCIO8A					A6		



Pin Information for the Cyclone® V 5CGXBC9 Device  
Version 1.2  
Note (1)

Bank Number	VREF	Pin Name/Function	Optional Function(s)	Configuration Function	Dedicated Tx/Rx Channel	Emulated LVDS Output Channel	F484	DQS for X8	DQS for X16
		VCCIO8A					G7		
		VCCIO8A					E8		
		VCCIO8A					C7		
		VCCPD3A					W6		
		VCCPD3B4A					W12		
		VCCPD3B4A					W17		
		VCCPD3B4A					W14		
		VCCPD3B4A					W11		
		VCCPD5A					P21		
		VCCPD5B					M17		
		VCCPD5B					N18		
		VCCPD7A8A					D8		
		VCCPD7A8A					E11		
		VCCPD7A8A					D16		
		VCCPD7A8A					D14		
		VCCPD7A8A					C10		
3A	VREFB3AN0	VREFB3AN0					Y7		
3B	VREFB3BN0	VREFB3BN0					Y12		
4A	VREFB4AN0	VREFB4AN0					AB16		
5A	VREFB5AN0	VREFB5AN0					R20		
5B	VREFB5BN0	VREFB5BN0					L20		
7A	VREFB7AN0	VREFB7AN0					C14		
8A	VREFB8AN0	VREFB8AN0					B8		
		NC					H20		
		NC					G20		
		NC					F20		
		NC					F19		
		NC					F18		
		NC					E22		
		NC					E20		
		NC					D22		
		NC					C19		
		NC					C18		
		NC					B22		
		NC					A22		
		NC					A20		
		NC					A19		
		NC					A18		
		NC					A17		
		VCCH_GXBL					M3		
		VCCH_GXBL					T3		
		VCCL_GXBL					K3		
		VCCL_GXBL					P3		
		RREF_TL					A1		
		VCCA_FPLL					T5		
		VCCA_FPLL					F4		
		VCCA_FPLL					U18		
		VCCA_FPLL					H19		
		VCC_AUX					E6		
		VCC_AUX					D11		
		VCC_AUX					W18		
		VCC_AUX					W13		
		VCC_AUX					W7		
		VCC_AUX					D18		
		VCCE_GXBL					J4		
		VCCE_GXBL					N4		
		VCCE_GXBL					L4		
		VCCE_GXBL					K5		

Note:  
(1) For more information about pin definition and pin connection guidelines, refer to the [Cyclone V Device Family Pin Connection Guidelines](#).



Pin Information for the Cyclone® V 5CGXBC9 Device  
Version 1.2  
Note (1)

Bank Number	VREF	Pin Name/Function	Optional Function(s)	Configuration Function	Dedicated Tx/Rx Channel	Emulated LVDS Output Channel	F672	DQS for X8	DQS for X16
GXB L2		GXB_TX_L8n					C3		
GXB L2		GXB_TX_L8p					C4		
GXB L2		GXB_RX_L8p,GXB_REFCLK_L8p					D2		
GXB L2		GXB_RX_L8n,GXB_REFCLK_L8n					D1		
GXB L2		GXB_TX_L7n					E3		
GXB L2		GXB_TX_L7p					E4		
GXB L2		GXB_RX_L7p,GXB_REFCLK_L7p					F2		
GXB L2		GXB_RX_L7n,GXB_REFCLK_L7n					F1		
GXB L2		GXB_TX_L6n					G3		
GXB L2		GXB_TX_L6p					G4		
GXB L2		GXB_RX_L6p,GXB_REFCLK_L6p					H2		
GXB L2		GXB_RX_L6n,GXB_REFCLK_L6n					H1		
GXB L2		REFCLK2Lp					M6		
GXB L2		REFCLK2Ln					L5		
GXB L1		REFCLK1Ln					P6		
GXB L1		REFCLK1Lp					N7		
GXB L1		GXB_TX_L5n					K1		
GXB L1		GXB_TX_L5p					K2		
GXB L1		GXB_RX_L5p,GXB_REFCLK_L5p					M2		
GXB L1		GXB_RX_L5n,GXB_REFCLK_L5n					M1		
GXB L1		GXB_TX_L4n					P1		
GXB L1		GXB_TX_L4p					P2		
GXB L1		GXB_RX_L4p,GXB_REFCLK_L4p					T2		
GXB L1		GXB_RX_L4n,GXB_REFCLK_L4n					T1		
GXB L1		GXB_TX_L3n					W3		
GXB L1		GXB_TX_L3p					W4		
GXB L1		GXB_RX_L3p,GXB_REFCLK_L3p					V2		
GXB L1		GXB_RX_L3n,GXB_REFCLK_L3n					V1		
GXB L0		GXB_TX_L2n					AA3		
GXB L0		GXB_TX_L2p					AA4		
GXB L0		GXB_RX_L2p,GXB_REFCLK_L2p					Y2		
GXB L0		GXB_RX_L2n,GXB_REFCLK_L2n					Y1		
GXB L0		GXB_TX_L1n					AC3		
GXB L0		GXB_TX_L1p					AC4		
GXB L0		GXB_RX_L1p,GXB_REFCLK_L1p					AB2		
GXB L0		GXB_RX_L1n,GXB_REFCLK_L1n					AB1		
GXB L0		GXB_TX_L0n					AE3		
GXB L0		GXB_TX_L0p					AE4		
GXB L0		GXB_RX_L0p,GXB_REFCLK_L0p					AD2		
GXB L0		GXB_RX_L0n,GXB_REFCLK_L0n					AD1		
GXB L0		REFCLK0Lp					V6		
GXB L0		REFCLK0Ln					W6		
3A		TDO		TDO			V7		
3A		nCS0		DATA4			Y6		
3A		TMS		TMS			R6		
3A		AS_DATA3		DATA3			U6		
3A		TCK		TCK			Y5		
3A		AS_DATA2		DATA2			AB5		
3A		TDI		TDI			T6		
3A		AS_DATA1		DATA1			AD5		
3A		DCLK		DCLK			N8		
3A		AS_DATA0,ASDO		DATA0			AF5		
3A	VREFB3AN0	IO		DATA6	DIFFIO_RX_B1n	DIFFOUT_B1n	T7	DQ1B	
3A	VREFB3AN0	IO		DATA5	DIFFIO_TX_B2n	DIFFOUT_B2n	U7		
3A	VREFB3AN0	IO		DATA8	DIFFIO_RX_B1p	DIFFOUT_B1p	T8	DQ1B	
3A	VREFB3AN0	IO		DATA7	DIFFIO_TX_B2p	DIFFOUT_B2p	V8	DQ1B	
3A	VREFB3AN0	IO		DATA10	DIFFIO_RX_B3n	DIFFOUT_B3n	W8	DQS1B	
3A	VREFB3AN0	IO		DATA9	DIFFIO_TX_B4n	DIFFOUT_B4n	AB6	DQ1B	
3A	VREFB3AN0	IO		DATA12	DIFFIO_RX_B3p	DIFFOUT_B3p	Y9	DQS1B	
3A	VREFB3AN0	IO		DATA11	DIFFIO_TX_B4p	DIFFOUT_B4p	AA6		
3A	VREFB3AN0	IO		DATA14	DIFFIO_RX_B5n	DIFFOUT_B5n	R10	DQ1B	
3A	VREFB3AN0	IO		DATA13	DIFFIO_TX_B6n	DIFFOUT_B6n	AA7	DQ1B	
3A	VREFB3AN0	IO		CLKUSR	DIFFIO_RX_B5p	DIFFOUT_B5p	R9	DQ1B	
3A	VREFB3AN0	IO		DATA15	DIFFIO_TX_B6p	DIFFOUT_B6p	Y8	DQ1B	
3A	VREFB3AN0	IO		PR_DONE	DIFFIO_RX_B7n	DIFFOUT_B7n	R8		
3A	VREFB3AN0	IO		PR_READY	DIFFIO_TX_B8n	DIFFOUT_B8n	AD6	DQ1B	
3A	VREFB3AN0	IO		PR_ERROR	DIFFIO_RX_B7p	DIFFOUT_B7p	P8		
3A	VREFB3AN0	IO			DIFFIO_TX_B8p	DIFFOUT_B8p	AD7	DQ1B	
3B	VREFB3BN0	IO			DIFFIO_TX_B33n	DIFFOUT_B33n	U9		
3B	VREFB3BN0	IO			DIFFIO_RX_B34n	DIFFOUT_B34n	Y11	DQ2B	
3B	VREFB3BN0	IO			DIFFIO_TX_B33p	DIFFOUT_B33p	T9	DQ2B	
3B	VREFB3BN0	IO			DIFFIO_RX_B34p	DIFFOUT_B34p	W11	DQ2B	
3B	VREFB3BN0	IO			DIFFIO_RX_B35n	DIFFOUT_B35n	T11	DQS2B	
3B	VREFB3BN0	IO			DIFFIO_TX_B36n	DIFFOUT_B36n	AC10	DQ2B	
3B	VREFB3BN0	IO			DIFFIO_RX_B35p	DIFFOUT_B35p	R11	DQS2B	
3B	VREFB3BN0	IO			DIFFIO_TX_B36p	DIFFOUT_B36p	AB10		
3B	VREFB3BN0	IO			DIFFIO_TX_B37n	DIFFOUT_B37n	AC8	DQ2B	
3B	VREFB3BN0	IO			DIFFIO_RX_B38n	DIFFOUT_B38n	AB11	DQ2B	



Pin Information for the Cyclone® V 5CGXBC9 Device

Version 1.2

Note (1)

Bank Number	VREF	Pin Name/Function	Optional Function(s)	Configuration Function	Dedicated Tx/Rx Channel	Emulated LVDS Output Channel	F672	DQS for X8	DQS for X16
3B	VREFB3BN0	IO			DIFFIO TX B37p	DIFFOUT B37p	AC9	DQ2B	
3B	VREFB3BN0	IO			DIFFIO RX B38p	DIFFOUT B38p	AB12	DQ2B	
3B	VREFB3BN0	IO	CLK0n,FPLL_BL_FBn		DIFFIO RX B39n	DIFFOUT B39n	T12		
3B	VREFB3BN0	IO			DIFFIO TX B40n	DIFFOUT B40n	Y10	DQ2B	
3B	VREFB3BN0	IO	CLK0p,FPLL_BL_FBp		DIFFIO RX B39p	DIFFOUT B39p	T13		
3B	VREFB3BN0	IO			DIFFIO TX B40p	DIFFOUT B40p	W10	DQ2B	
3B	VREFB3BN0	IO			DIFFIO TX B41n	DIFFOUT B41n	V9		
3B	VREFB3BN0	IO			DIFFIO RX B42n	DIFFOUT B42n	AE8	DQ3B	
3B	VREFB3BN0	IO			DIFFIO TX B41p	DIFFOUT B41p	V10	DQ3B	
3B	VREFB3BN0	IO			DIFFIO RX B42p	DIFFOUT B42p	AD8	DQ3B	
3B	VREFB3BN0	IO			DIFFIO RX B43n	DIFFOUT B43n	P10	DQS3B	
3B	VREFB3BN0	IO			DIFFIO TX B44n	DIFFOUT B44n	AF9	DQ3B	
3B	VREFB3BN0	IO			DIFFIO RX B43p	DIFFOUT B43p	N10	DQS3B	
3B	VREFB3BN0	IO			DIFFIO TX B44p	DIFFOUT B44p	AE9		
3B	VREFB3BN0	IO	FPLL_BL_CLKOUT1,FPLL_BL_CLKOUTn		DIFFIO TX B45n	DIFFOUT B45n	AF8	DQ3B	
3B	VREFB3BN0	IO			DIFFIO RX B46n	DIFFOUT B46n	U11	DQ3B	
3B	VREFB3BN0	IO	FPLL_BL_CLKOUT0,FPLL_BL_CLKOUTp,FPLL_BL_FB		DIFFIO TX B45p	DIFFOUT B45p	AF7	DQ3B	
3B	VREFB3BN0	IO			DIFFIO RX B46p	DIFFOUT B46p	U10	DQ3B	
3B	VREFB3BN0	IO	CLK1n		DIFFIO RX B47n	DIFFOUT B47n	P12		
3B	VREFB3BN0	IO			DIFFIO TX B48n	DIFFOUT B48n	AF6	DQ3B	
3B	VREFB3BN0	IO	CLK1p		DIFFIO RX B47p	DIFFOUT B47p	P11		
3B	VREFB3BN0	IO			DIFFIO TX B48p	DIFFOUT B48p	AE6	DQ3B	
4A	VREFB4AN0	IO	RZQ_0		DIFFIO TX B49n	DIFFOUT B49n	AE11		
4A	VREFB4AN0	IO			DIFFIO RX B50n	DIFFOUT B50n	AA14	DQ4B	
4A	VREFB4AN0	IO			DIFFIO TX B49p	DIFFOUT B49p	AD11	DQ4B	
4A	VREFB4AN0	IO			DIFFIO RX B50p	DIFFOUT B50p	Y14	DQ4B	
4A	VREFB4AN0	IO			DIFFIO RX B51n	DIFFOUT B51n	W13	DQS4B	
4A	VREFB4AN0	IO			DIFFIO TX B52n	DIFFOUT B52n	AD12	DQ4B	
4A	VREFB4AN0	IO			DIFFIO RX B51p	DIFFOUT B51p	V13	DQS4B	
4A	VREFB4AN0	IO			DIFFIO TX B52p	DIFFOUT B52p	AD13		
4A	VREFB4AN0	IO			DIFFIO TX B53n	DIFFOUT B53n	AE10	DQ4B	
4A	VREFB4AN0	IO			DIFFIO RX B54n	DIFFOUT B54n	Y13	DQ4B	
4A	VREFB4AN0	IO			DIFFIO TX B53p	DIFFOUT B53p	AD10	DQ4B	
4A	VREFB4AN0	IO			DIFFIO RX B54p	DIFFOUT B54p	W12	DQ4B	
4A	VREFB4AN0	IO	CLK2n		DIFFIO RX B55n	DIFFOUT B55n	Y12		
4A	VREFB4AN0	IO			DIFFIO TX B56n	DIFFOUT B56n	AF12	DQ4B	
4A	VREFB4AN0	IO	CLK2p		DIFFIO RX B55p	DIFFOUT B55p	U12		
4A	VREFB4AN0	IO			DIFFIO TX B56p	DIFFOUT B56p	AF11	DQ4B	
4A	VREFB4AN0	IO			DIFFIO TX B57n	DIFFOUT B57n	AC13		
4A	VREFB4AN0	IO			DIFFIO RX B58n	DIFFOUT B58n	AC15	DQ5B	DQ1B
4A	VREFB4AN0	IO			DIFFIO TX B57p	DIFFOUT B57p	AC14	DQ5B	DQ1B
4A	VREFB4AN0	IO			DIFFIO RX B58p	DIFFOUT B58p	AB15	DQ5B	DQ1B
4A	VREFB4AN0	IO			DIFFIO RX B59n	DIFFOUT B59n	V14	DQS5B	DQ1B
4A	VREFB4AN0	IO			DIFFIO TX B60n	DIFFOUT B60n	AF13	DQ5B	DQ1B
4A	VREFB4AN0	IO			DIFFIO RX B59p	DIFFOUT B59p	U14	DQS5B	DQ1B
4A	VREFB4AN0	IO			DIFFIO TX B60p	DIFFOUT B60p	AE13		
4A	VREFB4AN0	IO			DIFFIO TX B61n	DIFFOUT B61n	AF14	DQ5B	DQ1B
4A	VREFB4AN0	IO			DIFFIO RX B62n	DIFFOUT B62n	AB16	DQ5B	DQ1B
4A	VREFB4AN0	IO			DIFFIO TX B61p	DIFFOUT B61p	AE14	DQ5B	DQ1B
4A	VREFB4AN0	IO			DIFFIO RX B62p	DIFFOUT B62p	AA16	DQ5B	DQ1B
4A	VREFB4AN0	IO	CLK3n		DIFFIO RX B63n	DIFFOUT B63n	Y16		
4A	VREFB4AN0	IO			DIFFIO TX B64n	DIFFOUT B64n	AF18	DQ5B	DQ1B
4A	VREFB4AN0	IO	CLK3p		DIFFIO RX B63p	DIFFOUT B63p	Y15		
4A	VREFB4AN0	IO			DIFFIO TX B64p	DIFFOUT B64p	AE18	DQ5B	DQ1B
4A	VREFB4AN0	IO			DIFFIO TX B65n	DIFFOUT B65n	AD18		
4A	VREFB4AN0	IO			DIFFIO RX B66n	DIFFOUT B66n	AD16	DQ6B	DQ1B
4A	VREFB4AN0	IO			DIFFIO TX B65p	DIFFOUT B65p	AC18	DQ6B	DQ1B
4A	VREFB4AN0	IO			DIFFIO RX B66p	DIFFOUT B66p	AD17	DQ6B	DQ1B
4A	VREFB4AN0	IO			DIFFIO RX B67n	DIFFOUT B67n	W15	DQS6B	DQS1B
4A	VREFB4AN0	IO			DIFFIO TX B68n	DIFFOUT B68n	AF19	DQ6B	DQ1B
4A	VREFB4AN0	IO			DIFFIO RX B67p	DIFFOUT B67p	V15	DQS6B	DQS1B
4A	VREFB4AN0	IO			DIFFIO TX B68p	DIFFOUT B68p	AE19		
4A	VREFB4AN0	IO			DIFFIO TX B69n	DIFFOUT B69n	AF22	DQ6B	DQ1B
4A	VREFB4AN0	IO			DIFFIO RX B70n	DIFFOUT B70n	AC17	DQ6B	DQ1B
4A	VREFB4AN0	IO			DIFFIO TX B69p	DIFFOUT B69p	AF21	DQ6B	DQ1B
4A	VREFB4AN0	IO			DIFFIO RX B70p	DIFFOUT B70p	AB17	DQ6B	DQ1B
4A	VREFB4AN0	IO			DIFFIO RX B71n	DIFFOUT B71n	U17		
4A	VREFB4AN0	IO			DIFFIO TX B72n	DIFFOUT B72n	AE21	DQ6B	DQ1B
4A	VREFB4AN0	IO			DIFFIO RX B71p	DIFFOUT B71p	T17		
4A	VREFB4AN0	IO			DIFFIO TX B72p	DIFFOUT B72p	AE20	DQ6B	DQ1B
4A	VREFB4AN0	IO			DIFFIO TX B73n	DIFFOUT B73n	AD20		
4A	VREFB4AN0	IO			DIFFIO RX B74n	DIFFOUT B74n	AE15	DQ7B	DQ2B
4A	VREFB4AN0	IO			DIFFIO TX B73p	DIFFOUT B73p	AC20	DQ7B	DQ2B
4A	VREFB4AN0	IO			DIFFIO RX B74p	DIFFOUT B74p	AE16	DQ7B	DQ2B
4A	VREFB4AN0	IO			DIFFIO RX B75n	DIFFOUT B75n	W17	DQS7B	DQ2B
4A	VREFB4AN0	IO			DIFFIO TX B76n	DIFFOUT B76n	AD21	DQ7B	DQ2B
4A	VREFB4AN0	IO			DIFFIO RX B75p	DIFFOUT B75p	W16	DQS7B	DQ2B
4A	VREFB4AN0	IO			DIFFIO TX B76p	DIFFOUT B76p	AD22		





Pin Information for the Cyclone® V 5CGXBC9 Device  
Version 1.2  
Note (1)

Bank Number	VREF	Pin Name/Function	Optional Function(s)	Configuration Function	Dedicated Tx/Rx Channel	Emulated LVDS Output Channel	F672	DQS for X8	DQS for X16
4A	VREFB4AN0	IO			DIFFIO TX B77n	DIFFOUT B77n	AE23	DQ7B	DO2B
4A	VREFB4AN0	IO			DIFFIO RX B78n	DIFFOUT B78n	AF16	DQ7B	DO2B
4A	VREFB4AN0	IO			DIFFIO TX B77p	DIFFOUT B77p	AD23	DQ7B	DO2B
4A	VREFB4AN0	IO			DIFFIO RX B78p	DIFFOUT B78p	AF17	DQ7B	DO2B
4A	VREFB4AN0	IO			DIFFIO RX B79n	DIFFOUT B79n	U16		
4A	VREFB4AN0	IO			DIFFIO TX B80n	DIFFOUT B80n	AF23	DQ7B	DO2B
4A	VREFB4AN0	IO			DIFFIO RX B79p	DIFFOUT B79p	U15		
4A	VREFB4AN0	IO			DIFFIO TX B80p	DIFFOUT B80p	AE24	DQ7B	DO2B
4A	VREFB4AN0	IO			DIFFIO TX B81n	DIFFOUT B81n	AF24		
4A	VREFB4AN0	IO			DIFFIO RX B82n	DIFFOUT B82n	AA18	DQ8B	DO2B
4A	VREFB4AN0	IO			DIFFIO TX B81p	DIFFOUT B81p	AE25	DQ8B	DO2B
4A	VREFB4AN0	IO			DIFFIO RX B82p	DIFFOUT B82p	Y18	DQ8B	DO2B
4A	VREFB4AN0	IO			DIFFIO TX B83n	DIFFOUT B83n	V17	DQSn8B	DOsn2B
4A	VREFB4AN0	IO			DIFFIO TX B84n	DIFFOUT B84n	AE26	DQ8B	DO2B
4A	VREFB4AN0	IO			DIFFIO RX B83p	DIFFOUT B83p	V18	DQSn8B	DOsn2B
4A	VREFB4AN0	IO			DIFFIO TX B84p	DIFFOUT B84p	AD26		
4A	VREFB4AN0	IO			DIFFIO TX B85n	DIFFOUT B85n	AC19	DQ8B	DO2B
4A	VREFB4AN0	IO			DIFFIO RX B86n	DIFFOUT B86n	Y19	DQ8B	DO2B
4A	VREFB4AN0	IO			DIFFIO TX B85p	DIFFOUT B85p	AB19	DQ8B	DO2B
4A	VREFB4AN0	IO			DIFFIO RX B86p	DIFFOUT B86p	Y20	DQ8B	DO2B
4A	VREFB4AN0	IO			DIFFIO RX B87n	DIFFOUT B87n	W18		
4A	VREFB4AN0	IO			DIFFIO TX B88n	DIFFOUT B88n	AA21	DQ8B	DO2B
4A	VREFB4AN0	IO			DIFFIO RX B87p	DIFFOUT B87p	V19		
4A	VREFB4AN0	IO			DIFFIO TX B88p	DIFFOUT B88p	AB22	DQ8B	DO2B
5A	VREFB5AN0	IO	RZQ_1		DIFFIO TX R1p	DIFFOUT R1p	AC22	DQ1R	
5A	VREFB5AN0	IO		INIT_DONE	DIFFIO RX R2p	DIFFOUT R2p	U19		
5A	VREFB5AN0	IO		PR_REQUEST	DIFFIO TX R1n	DIFFOUT R1n	AC23	DQ1R	
5A	VREFB5AN0	IO		CRC_ERROR	DIFFIO RX R2n	DIFFOUT R2n	V20		
5A	VREFB5AN0	IO		nCEO	DIFFIO TX R3p	DIFFOUT R3p	AA22	DQ1R	
5A	VREFB5AN0	IO			DIFFIO RX R4p	DIFFOUT R4p	W20	DQ1R	
5A	VREFB5AN0	IO		CvP_CONFDONE	DIFFIO TX R3n	DIFFOUT R3n	AA23	DQ1R	
5A	VREFB5AN0	IO			DIFFIO RX R4n	DIFFOUT R4n	W21	DQ1R	
5A	VREFB5AN0	IO		DEV_OE	DIFFIO TX R5p	DIFFOUT R5p	AC24		
5A	VREFB5AN0	IO			DIFFIO RX R6p	DIFFOUT R6p	V22	DQS1R	
5A	VREFB5AN0	IO		DEV CLRn	DIFFIO TX R5n	DIFFOUT R5n	AB24	DQ1R	
5A	VREFB5AN0	IO			DIFFIO RX R6n	DIFFOUT R6n	U22	DQSn1R	
5A	VREFB5AN0	IO			DIFFIO TX R7p	DIFFOUT R7p	Y23	DQ1R	
5A	VREFB5AN0	IO			DIFFIO RX R8p	DIFFOUT R8p	T19	DQ1R	
5A	VREFB5AN0	IO			DIFFIO TX R7n	DIFFOUT R7n	Y24		
5A	VREFB5AN0	IO			DIFFIO RX R8n	DIFFOUT R8n	U20	DQ1R	
5B	VREFB5BN0	IO	CLK7p.FPLL_BR_FBp		DIFFIO RX R33p	DIFFOUT R33p	T21		
5B	VREFB5BN0	IO			DIFFIO TX R34p	DIFFOUT R34p	V23	DQ2R	
5B	VREFB5BN0	IO	CLK7n.FPLL_BR_FBn		DIFFIO RX R33n	DIFFOUT R33n	T22		
5B	VREFB5BN0	IO			DIFFIO TX R34n	DIFFOUT R34n	V24	DQ2R	
5B	VREFB5BN0	IO			DIFFIO RX R35p	DIFFOUT R35p	T23	DQ2R	
5B	VREFB5BN0	IO			DIFFIO TX R36p	DIFFOUT R36p	AA24	DQ2R	
5B	VREFB5BN0	IO			DIFFIO RX R35n	DIFFOUT R35n	T24	DQ2R	
5B	VREFB5BN0	IO			DIFFIO TX R36n	DIFFOUT R36n	AB25	DQ2R	
5B	VREFB5BN0	IO			DIFFIO RX R37p	DIFFOUT R37p	R23	DQS2R	
5B	VREFB5BN0	IO			DIFFIO TX R38p	DIFFOUT R37p	AD25		
5B	VREFB5BN0	IO			DIFFIO RX R37n	DIFFOUT R37n	P23	DQSn2R	
5B	VREFB5BN0	IO			DIFFIO TX R38n	DIFFOUT R37n	AC25	DQ2R	
5B	VREFB5BN0	IO			DIFFIO RX R39p	DIFFOUT R39p	R24	DQ2R	
5B	VREFB5BN0	IO			DIFFIO TX R40p	DIFFOUT R40p	U24	DQ2R	
5B	VREFB5BN0	IO			DIFFIO RX R39n	DIFFOUT R39n	R25	DQ2R	
5B	VREFB5BN0	IO			DIFFIO TX R40n	DIFFOUT R40n	V25		
5B	VREFB5BN0	IO	CLK6p		DIFFIO RX R41p	DIFFOUT R41p	R20		
5B	VREFB5BN0	IO			DIFFIO TX R42p	DIFFOUT R42p	AB26	DQ3R	
5B	VREFB5BN0	IO	CLK6n		DIFFIO RX R41n	DIFFOUT R41n	P20		
5B	VREFB5BN0	IO			DIFFIO TX R42n	DIFFOUT R42n	AA26	DQ3R	
5B	VREFB5BN0	IO			DIFFIO RX R43p	DIFFOUT R43p	T26	DQ3R	
5B	VREFB5BN0	IO	FPLL_BR_CLKOUT0,FPLL_BR_CLKOUTp,FPLL_BR_FB		DIFFIO TX R44p	DIFFOUT R44p	Y25	DQ3R	
5B	VREFB5BN0	IO			DIFFIO RX R43n	DIFFOUT R43n	R26	DQ3R	
5B	VREFB5BN0	IO	FPLL_BR_CLKOUT1,FPLL_BR_CLKOUTn		DIFFIO TX R44n	DIFFOUT R44n	Y26	DQ3R	
5B	VREFB5BN0	IO			DIFFIO RX R45p	DIFFOUT R45p	P21	DQS3R	
5B	VREFB5BN0	IO			DIFFIO TX R46p	DIFFOUT R46p	W25		
5B	VREFB5BN0	IO			DIFFIO RX R45n	DIFFOUT R45n	P22	DQSn3R	
5B	VREFB5BN0	IO			DIFFIO TX R46n	DIFFOUT R46n	W26	DQ3R	
5B	VREFB5BN0	IO			DIFFIO RX R47p	DIFFOUT R47p	N25	DQ3R	
5B	VREFB5BN0	IO			DIFFIO TX R48p	DIFFOUT R48p	U25	DQ3R	
5B	VREFB5BN0	IO			DIFFIO RX R47n	DIFFOUT R47n	P26	DQ3R	
5B	VREFB5BN0	IO			DIFFIO TX R48n	DIFFOUT R48n	U26		
6A	VREFB6AN0	IO	CLK5p		DIFFIO RX R49p	DIFFOUT R49p	N20		
6A	VREFB6AN0	IO			DIFFIO TX R50p	DIFFOUT R50p	J25	DQ4R	
6A	VREFB6AN0	IO	CLK5n		DIFFIO RX R49n	DIFFOUT R49n	M21		
6A	VREFB6AN0	IO			DIFFIO TX R50n	DIFFOUT R50n	J26	DQ4R	
6A	VREFB6AN0	IO			DIFFIO RX R51p	DIFFOUT R51p	N24	DQ4R	
6A	VREFB6AN0	IO	FPLL_TR_CLKOUT0,FPLL_TR_CLKOUTp,FPLL_TR_FB		DIFFIO TX R52p	DIFFOUT R52p	F26	DQ4R	



Pin Information for the Cyclone® V 5CGXBC9 Device  
Version 1.2  
Note (1)

Bank Number	VREF	Pin Name/Function	Optional Function(s)	Configuration Function	Dedicated Tx/Rx Channel	Emulated LVDS Output Channel	F672	DQS for X8	DQS for X16
6A	VREFB6AN0	IO			DIFFIO_RX_R51n	DIFFOUT_R51n	M24	DQ4R	
6A	VREFB6AN0	IO	FPLL_TR_CLKOUT1,FPLL_TR_CLKOUTn		DIFFIO_TX_R52n	DIFFOUT_R52n	G26	DQ4R	
6A	VREFB6AN0	IO			DIFFIO_RX_R53p	DIFFOUT_R53p	N23	DQS4R	
6A	VREFB6AN0	IO			DIFFIO_TX_R54p	DIFFOUT_R54p	G25		
6A	VREFB6AN0	IO			DIFFIO_RX_R53n	DIFFOUT_R53n	M22	DQSn4R	
6A	VREFB6AN0	IO			DIFFIO_TX_R54n	DIFFOUT_R54n	H25	DQ4R	
6A	VREFB6AN0	IO			DIFFIO_RX_R55p	DIFFOUT_R55p	M25	DQ4R	
6A	VREFB6AN0	IO			DIFFIO_TX_R56p	DIFFOUT_R56p	D26	DQ4R	
6A	VREFB6AN0	IO			DIFFIO_RX_R55n	DIFFOUT_R55n	M26	DQ4R	
6A	VREFB6AN0	IO			DIFFIO_TX_R56n	DIFFOUT_R56n	E26		
6A	VREFB6AN0	IO	CLK4p,FPLL_TR_FBp		DIFFIO_RX_R57p	DIFFOUT_R57p	K25		
6A	VREFB6AN0	IO			DIFFIO_TX_R58p	DIFFOUT_R58p	E24	DQS5R	
6A	VREFB6AN0	IO	CLK4n,FPLL_TR_FBn		DIFFIO_RX_R57n	DIFFOUT_R57n	K26		
6A	VREFB6AN0	IO			DIFFIO_TX_R58n	DIFFOUT_R58n	E25	DQS5R	
6A	VREFB6AN0	IO			DIFFIO_RX_R59p	DIFFOUT_R59p	K24	DQS5R	
6A	VREFB6AN0	IO			DIFFIO_TX_R60p	DIFFOUT_R60p	F24	DQS5R	
6A	VREFB6AN0	IO			DIFFIO_RX_R59n	DIFFOUT_R59n	K23	DQS5R	
6A	VREFB6AN0	IO			DIFFIO_TX_R60n	DIFFOUT_R60n	G24	DQS5R	
6A	VREFB6AN0	IO			DIFFIO_RX_R61p	DIFFOUT_R61p	L23	DQS5R	
6A	VREFB6AN0	IO			DIFFIO_TX_R62p	DIFFOUT_R62p	H23		
6A	VREFB6AN0	IO			DIFFIO_RX_R61n	DIFFOUT_R61n	L24	DQS5nR	
6A	VREFB6AN0	IO			DIFFIO_TX_R62n	DIFFOUT_R62n	H24	DQS5R	
6A	VREFB6AN0	IO			DIFFIO_RX_R63p	DIFFOUT_R63p	H22	DQS5R	
6A	VREFB6AN0	IO			DIFFIO_TX_R64p	DIFFOUT_R64p	F23	DQS5R	
6A	VREFB6AN0	IO			DIFFIO_RX_R63n	DIFFOUT_R63n	J23	DQS5R	
6A	VREFB6AN0	IO			DIFFIO_TX_R64n	DIFFOUT_R64n	G22		
6A	VREFB6AN0	IO			DIFFIO_RX_R73p	DIFFOUT_R73p	L22		
6A	VREFB6AN0	IO			DIFFIO_TX_R74p	DIFFOUT_R74p	B25	DQ6R	
6A	VREFB6AN0	IO			DIFFIO_RX_R73n	DIFFOUT_R73n	K21		
6A	VREFB6AN0	IO			DIFFIO_TX_R74n	DIFFOUT_R74n	B26	DQ6R	
6A	VREFB6AN0	IO			DIFFIO_RX_R75p	DIFFOUT_R75p	H19	DQ6R	
6A	VREFB6AN0	IO			DIFFIO_TX_R76p	DIFFOUT_R76p	D25	DQ6R	
6A	VREFB6AN0	IO			DIFFIO_RX_R75n	DIFFOUT_R75n	H20	DQ6R	
6A	VREFB6AN0	IO			DIFFIO_TX_R76n	DIFFOUT_R76n	C25	DQ6R	
6A	VREFB6AN0	IO			DIFFIO_RX_R77p	DIFFOUT_R77p	J20	DQS6R	
6A	VREFB6AN0	IO			DIFFIO_TX_R78p	DIFFOUT_R78p	D22		
6A	VREFB6AN0	IO			DIFFIO_RX_R77n	DIFFOUT_R77n	J21	DQS6nR	
6A	VREFB6AN0	IO			DIFFIO_TX_R78n	DIFFOUT_R78n	E23	DQ6R	
6A	VREFB6AN0	IO			DIFFIO_RX_R79p	DIFFOUT_R79p	G20	DQ6R	
6A	VREFB6AN0	IO			DIFFIO_TX_R80p	DIFFOUT_R80p	E21	DQ6R	
6A	VREFB6AN0	IO			DIFFIO_RX_R79n	DIFFOUT_R79n	F21	DQ6R	
6A	VREFB6AN0	IO			DIFFIO_TX_R80n	DIFFOUT_R80n	F22		
7A		GND					D23		
7A	VREFB7AN0	IO			DIFFIO_RX_T9p	DIFFOUT_T9p	H15		
7A	VREFB7AN0	IO			DIFFIO_TX_T10p	DIFFOUT_T10p	C23	DQ1T	DQ1T
7A	VREFB7AN0	IO			DIFFIO_RX_T9n	DIFFOUT_T9n	J16		
7A	VREFB7AN0	IO			DIFFIO_TX_T10n	DIFFOUT_T10n	C22	DQ1T	DQ1T
7A	VREFB7AN0	IO			DIFFIO_RX_T11p	DIFFOUT_T11p	B24	DQ1T	DQ1T
7A	VREFB7AN0	IO			DIFFIO_TX_T12p	DIFFOUT_T12p	A23	DQ1T	DQ1T
7A	VREFB7AN0	IO			DIFFIO_RX_T11n	DIFFOUT_T11n	A24	DQ1T	DQ1T
7A	VREFB7AN0	IO			DIFFIO_TX_T12n	DIFFOUT_T12n	A22	DQ1T	DQ1T
7A	VREFB7AN0	IO			DIFFIO_RX_T13p	DIFFOUT_T13p	H18	DQS1T	DQS1T
7A	VREFB7AN0	IO			DIFFIO_TX_T14p	DIFFOUT_T14p	B22		
7A	VREFB7AN0	IO			DIFFIO_RX_T13n	DIFFOUT_T13n	H17	DQS1nT	DQS1nT
7A	VREFB7AN0	IO			DIFFIO_TX_T14n	DIFFOUT_T14n	A21	DQ1T	DQ1T
7A	VREFB7AN0	IO			DIFFIO_RX_T15p	DIFFOUT_T15p	D21	DQ1T	DQ1T
7A	VREFB7AN0	IO			DIFFIO_TX_T16p	DIFFOUT_T16p	B21	DQ1T	DQ1T
7A	VREFB7AN0	IO			DIFFIO_RX_T15n	DIFFOUT_T15n	D20	DQ1T	DQ1T
7A	VREFB7AN0	IO			DIFFIO_TX_T16n	DIFFOUT_T16n	B20		
7A	VREFB7AN0	IO			DIFFIO_RX_T17p	DIFFOUT_T17p	G16		
7A	VREFB7AN0	IO			DIFFIO_TX_T18p	DIFFOUT_T18p	C20	DQ2T	DQ1T
7A	VREFB7AN0	IO			DIFFIO_RX_T17n	DIFFOUT_T17n	G17		
7A	VREFB7AN0	IO			DIFFIO_TX_T18n	DIFFOUT_T18n	B19	DQ2T	DQ1T
7A	VREFB7AN0	IO			DIFFIO_RX_T19p	DIFFOUT_T19p	E20	DQ2T	DQ1T
7A	VREFB7AN0	IO			DIFFIO_TX_T20p	DIFFOUT_T20p	C19	DQ2T	DQ1T
7A	VREFB7AN0	IO			DIFFIO_RX_T19n	DIFFOUT_T19n	E19	DQ2T	DQ1T
7A	VREFB7AN0	IO			DIFFIO_TX_T20n	DIFFOUT_T20n	C18	DQ2T	DQ1T
7A	VREFB7AN0	IO			DIFFIO_RX_T21p	DIFFOUT_T21p	J12	DQS2T	DQ1T
7A	VREFB7AN0	IO			DIFFIO_TX_T22p	DIFFOUT_T22p	A19		
7A	VREFB7AN0	IO			DIFFIO_RX_T21n	DIFFOUT_T21n	J11	DQS2nT	DQ1T
7A	VREFB7AN0	IO			DIFFIO_TX_T22n	DIFFOUT_T22n	A18	DQ2T	DQ1T
7A	VREFB7AN0	IO			DIFFIO_RX_T23p	DIFFOUT_T23p	D18	DQ2T	DQ1T
7A	VREFB7AN0	IO			DIFFIO_TX_T24p	DIFFOUT_T24p	A17	DQ2T	DQ1T
7A	VREFB7AN0	IO			DIFFIO_RX_T23n	DIFFOUT_T23n	D17	DQ2T	DQ1T
7A	VREFB7AN0	IO			DIFFIO_TX_T24n	DIFFOUT_T24n	A16		
7A	VREFB7AN0	IO			DIFFIO_RX_T25p	DIFFOUT_T25p	H14		
7A	VREFB7AN0	IO			DIFFIO_TX_T26p	DIFFOUT_T26p	C17	DQ3T	DQ2T
7A	VREFB7AN0	IO			DIFFIO_RX_T25n	DIFFOUT_T25n	H13		



Pin Information for the Cyclone® V 5CGXBC9 Device  
Version 1.2  
Note (1)

Bank Number	VREF	Pin Name/Function	Optional Function(s)	Configuration Function	Dedicated Tx/Rx Channel	Emulated LVDS Output Channel	F672	DQS for X8	DQS for X16
7A	VREFB7A0	IO			DIFFIO TX T26n	DIFFOUT T26n	B17	DQ3T	DO2T
7A	VREFB7A0	IO			DIFFIO RX T27p	DIFFOUT T27p	E18	DQ3T	DO2T
7A	VREFB7A0	IO			DIFFIO TX T28p	DIFFOUT T28p	A14	DQ3T	DO2T
7A	VREFB7A0	IO			DIFFIO RX T27n	DIFFOUT T27n	F18	DQ3T	DO2T
7A	VREFB7A0	IO			DIFFIO TX T28n	DIFFOUT T28n	B14	DQ3T	DO2T
7A	VREFB7A0	IO			DIFFIO RX T29p	DIFFOUT T29p	L12	DQS3T	DQS2T
7A	VREFB7A0	IO			DIFFIO TX T30p	DIFFOUT T30p	B15		
7A	VREFB7A0	IO			DIFFIO RX T29n	DIFFOUT T29n	K11	DQSn3T	DQSn2T
7A	VREFB7A0	IO			DIFFIO TX T30n	DIFFOUT T30n	C15	DQ3T	DO2T
7A	VREFB7A0	IO			DIFFIO RX T31p	DIFFOUT T31p	C14	DQ3T	DO2T
7A	VREFB7A0	IO			DIFFIO TX T32p	DIFFOUT T32p	A8	DQ3T	DO2T
7A	VREFB7A0	IO			DIFFIO RX T31n	DIFFOUT T31n	D15	DQ3T	DO2T
7A	VREFB7A0	IO			DIFFIO TX T32n	DIFFOUT T32n	A9		
7A	VREFB7A0	IO	CLK11p		DIFFIO RX T33p	DIFFOUT T33p	G15		
7A	VREFB7A0	IO			DIFFIO TX T34p	DIFFOUT T34p	C9	DQ4T	DO2T
7A	VREFB7A0	IO	CLK11n		DIFFIO RX T33n	DIFFOUT T33n	G14		
7A	VREFB7A0	IO			DIFFIO TX T34n	DIFFOUT T34n	B9	DQ4T	DO2T
7A	VREFB7A0	IO			DIFFIO RX T35p	DIFFOUT T35p	E16	DQ4T	DO2T
7A	VREFB7A0	IO			DIFFIO TX T36p	DIFFOUT T36p	D10	DQ4T	DO2T
7A	VREFB7A0	IO			DIFFIO RX T35n	DIFFOUT T35n	D16	DQ4T	DO2T
7A	VREFB7A0	IO			DIFFIO TX T36n	DIFFOUT T36n	C10	DQ4T	DO2T
7A	VREFB7A0	IO			DIFFIO RX T37p	DIFFOUT T37p	N12	DQS4T	DO2T
7A	VREFB7A0	IO			DIFFIO TX T38p	DIFFOUT T38p	B10		
7A	VREFB7A0	IO			DIFFIO RX T37n	DIFFOUT T37n	M12	DQSn4T	DO2T
7A	VREFB7A0	IO			DIFFIO TX T38n	DIFFOUT T38n	A11	DQ4T	DO2T
7A	VREFB7A0	IO			DIFFIO RX T39p	DIFFOUT T39p	F16	DQ4T	DO2T
7A	VREFB7A0	IO			DIFFIO TX T40p	DIFFOUT T40p	E10	DQ4T	DO2T
7A	VREFB7A0	IO			DIFFIO RX T39n	DIFFOUT T39n	E15	DQ4T	DO2T
7A	VREFB7A0	IO			DIFFIO TX T40n	DIFFOUT T40n	E11		
7A	VREFB7A0	IO	CLK10p		DIFFIO RX T41p	DIFFOUT T41p	H12		
7A	VREFB7A0	IO			DIFFIO TX T42p	DIFFOUT T42p	B12	DQ5T	
7A	VREFB7A0	IO	CLK10n		DIFFIO RX T41n	DIFFOUT T41n	G11		
7A	VREFB7A0	IO			DIFFIO TX T42n	DIFFOUT T42n	A13	DQ5T	
7A	VREFB7A0	IO			DIFFIO RX T43p	DIFFOUT T43p	G12	DQ5T	
7A	VREFB7A0	IO			DIFFIO TX T44p	DIFFOUT T44p	A12	DQ5T	
7A	VREFB7A0	IO			DIFFIO RX T43n	DIFFOUT T43n	F12	DQ5T	
7A	VREFB7A0	IO			DIFFIO TX T44n	DIFFOUT T44n	B11	DQ5T	
7A	VREFB7A0	IO			DIFFIO RX T45p	DIFFOUT T45p	M11	DQS5T	
7A	VREFB7A0	IO			DIFFIO TX T46p	DIFFOUT T46p	C13		
7A	VREFB7A0	IO			DIFFIO RX T45n	DIFFOUT T45n	L11	DQSn5T	
7A	VREFB7A0	IO			DIFFIO TX T46n	DIFFOUT T46n	C12	DQ5T	
7A	VREFB7A0	IO			DIFFIO RX T47p	DIFFOUT T47p	E13	DQ5T	
7A	VREFB7A0	IO			DIFFIO TX T48p	DIFFOUT T48p	D11	DQ5T	
7A	VREFB7A0	IO			DIFFIO RX T47n	DIFFOUT T47n	D13	DQ5T	
7A	VREFB7A0	IO	RZQ_2		DIFFIO TX T48n	DIFFOUT T48n	D12		
8A	VREFB8A0	IO	CLK9p		DIFFIO RX T49p	DIFFOUT T49p	N9		
8A	VREFB8A0	IO			DIFFIO TX T50p	DIFFOUT T50p	A5	DQ6T	
8A	VREFB8A0	IO	CLK9n		DIFFIO RX T49n	DIFFOUT T49n	M10		
8A	VREFB8A0	IO			DIFFIO TX T50n	DIFFOUT T50n	B6	DQ6T	
8A	VREFB8A0	IO			DIFFIO RX T51p	DIFFOUT T51p	H8	DQ6T	
8A	VREFB8A0	IO	FPLL_TL_CLKOUT0,FPLL_TL_CLKOUTp,FPLL_TL_FB		DIFFIO TX T52p	DIFFOUT T52p	A7	DQ6T	
8A	VREFB8A0	IO			DIFFIO RX T51n	DIFFOUT T51n	H9	DQ6T	
8A	VREFB8A0	IO	FPLL_TL_CLKOUT1,FPLL_TL_CLKOUTn		DIFFIO TX T52n	DIFFOUT T52n	B7	DQ6T	
8A	VREFB8A0	IO			DIFFIO RX T53p	DIFFOUT T53p	M9	DQS6T	
8A	VREFB8A0	IO			DIFFIO TX T54p	DIFFOUT T54p	D6		
8A	VREFB8A0	IO			DIFFIO RX T53n	DIFFOUT T53n	L9	DQSn6T	
8A	VREFB8A0	IO			DIFFIO TX T54n	DIFFOUT T54n	E6	DQ6T	
8A	VREFB8A0	IO			DIFFIO RX T55p	DIFFOUT T55p	H10	DQ6T	
8A	VREFB8A0	IO			DIFFIO TX T56p	DIFFOUT T56p	D7	DQ6T	
8A	VREFB8A0	IO			DIFFIO RX T55n	DIFFOUT T55n	G10	DQ6T	
8A	VREFB8A0	IO			DIFFIO TX T56n	DIFFOUT T56n	C7		
8A	VREFB8A0	IO	CLK9p,FPLL_TL_FBp		DIFFIO RX T57p	DIFFOUT T57p	L8		
8A	VREFB8A0	IO			DIFFIO TX T58p	DIFFOUT T58p	F6	DQ7T	
8A	VREFB8A0	IO	CLK9n,FPLL_TL_FBn		DIFFIO RX T57n	DIFFOUT T57n	K9		
8A	VREFB8A0	IO			DIFFIO TX T58n	DIFFOUT T58n	G6	DQ7T	
8A	VREFB8A0	IO			DIFFIO RX T59p	DIFFOUT T59p	K8	DQ7T	
8A	VREFB8A0	IO			DIFFIO TX T60p	DIFFOUT T60p	G7	DQ7T	
8A	VREFB8A0	IO			DIFFIO RX T59n	DIFFOUT T59n	J8	DQ7T	
8A	VREFB8A0	IO			DIFFIO TX T60n	DIFFOUT T60n	F7	DQ7T	
8A	VREFB8A0	IO			DIFFIO RX T61p	DIFFOUT T61p	K10	DQS7T	
8A	VREFB8A0	IO			DIFFIO TX T62p	DIFFOUT T62p	H7		
8A	VREFB8A0	IO			DIFFIO RX T61n	DIFFOUT T61n	J10	DQSn7T	
8A	VREFB8A0	IO			DIFFIO TX T62n	DIFFOUT T62n	J7	DQ7T	
8A	VREFB8A0	IO			DIFFIO RX T63p	DIFFOUT T63p	L7	DQ7T	
8A	VREFB8A0	IO			DIFFIO TX T64p	DIFFOUT T64p	D8	DQ7T	
8A	VREFB8A0	IO			DIFFIO RX T63n	DIFFOUT T63n	K6	DQ7T	
8A	VREFB8A0	IO			DIFFIO TX T64n	DIFFOUT T64n	E9		
9A		MSEL0		MSEL0			M7		



Pin Information for the Cyclone® V 5CGXBC9 Device  
Version 1.2  
Note (1)

Bank Number	VREF	Pin Name/Function	Optional Function(s)	Configuration Function	Dedicated Tx/Rx Channel	Emulated LVDS Output Channel	F672	DQS for X8	DQS for X16
9A		CONF_DONE		CONF_DONE			A6		
9A		MSEL1		MSEL1			L6		
9A		nSTATUS		nSTATUS			B5		
9A		nCE		nCE			D5		
9A		MSEL2		MSEL2			A2		
9A		MSEL3		MSEL3			K5		
9A		nCONFIG		nCONFIG			F5		
9A		MSEL4		MSEL4			J5		
9A		GND					H5		
		GND					E7		
		GND					G5		
		GND					C11		
		GND					D14		
		GND					E17		
		GND					F20		
		GND					G23		
		GND					L25		
		GND					N21		
		GND					P24		
		GND					P19		
		GND					T20		
		GND					U23		
		GND					Y22		
		GND					AA15		
		GND					AE17		
		GND					AD14		
		GND					M8		
		GND					A25		
		GND					D24		
		GND					H26		
		GND					Y26		
		GND					AA25		
		GND					AC26		
		GND					AF25		
		GND					K22		
		GND					AD24		
		GND					C21		
		GND					L20		
		GND					K19		
		GND					M19		
		GND					W19		
		GND					AC21		
		GND					AF20		
		GND					B18		
		GND					L18		
		GND					K17		
		GND					J18		
		GND					N18		
		GND					M17		
		GND					R18		
		GND					P17		
		GND					AB18		
		GND					A15		
		GND					H16		
		GND					L16		
		GND					L14		
		GND					K15		
		GND					J14		
		GND					N16		
		GND					N14		
		GND					M15		
		GND					T15		
		GND					R16		
		GND					R14		
		GND					P15		
		GND					V16		
		GND					G13		
		GND					K13		
		GND					K12		
		GND					M13		
		GND					R12		
		GND					P13		
		GND					U13		
		GND					Y12		
		GND					F10		
		GND					L10		
		GND					J9		
		GND					N11		



Pin Information for the Cyclone® V 5CGXBC9 Device  
Version 1.2  
Note (1)

Bank Number	VREF	Pin Name/Function	Optional Function(s)	Configuration Function	Dedicated Tx/Rx Channel	Emulated LVDS Output Channel	F672	DQS for X8	DQS for X16
		GND					T10		
		GND					P9		
		GND					W9		
		GND					AC11		
		GND					AF10		
		GND					B8		
		GND					H6		
		GND					N6		
		GND					R7		
		GND					P7		
		GND					AB8		
		GND					AE7		
		GND					C5		
		GND					B4		
		GND					F4		
		GND					E5		
		GND					D4		
		GND					H4		
		GND					L4		
		GND					J4		
		GND					N4		
		GND					M5		
		GND					T5		
		GND					R4		
		GND					P5		
		GND					V5		
		GND					V4		
		GND					U4		
		GND					AA5		
		GND					Y4		
		GND					W5		
		GND					AC5		
		GND					AB4		
		GND					AF4		
		GND					AE5		
		GND					AD4		
		GND					C2		
		GND					C1		
		GND					B3		
		GND					B2		
		GND					F3		
		GND					E2		
		GND					E1		
		GND					D3		
		GND					H3		
		GND					G2		
		GND					G1		
		GND					L2		
		GND					L1		
		GND					K3		
		GND					J2		
		GND					J1		
		GND					N2		
		GND					N1		
		GND					M3		
		GND					T3		
		GND					R2		
		GND					R1		
		GND					P3		
		GND					V3		
		GND					U2		
		GND					U1		
		GND					AA2		
		GND					AA1		
		GND					Y3		
		GND					W2		
		GND					W1		
		GND					AC2		
		GND					AC1		
		GND					AB3		
		GND					AF3		
		GND					AF2		
		GND					AE2		
		GND					AE1		
		GND					AD3		
		VCC					J19		
		VCC					L19		
		VCC					K20		



Pin Information for the Cyclone® V 5CGXBC9 Device  
Version 1.2  
Note (1)

Bank Number	VREF	Pin Name/Function	Optional Function(s)	Configuration Function	Dedicated Tx/Rx Channel	Emulated LVDS Output Channel	F672	DQS for X8	DQS for X16
		VCC					N19		
		VCC					M20		
		VCC					R19		
		VCC					L17		
		VCC					K18		
		VCC					J17		
		VCC					N17		
		VCC					M18		
		VCC					T18		
		VCC					R17		
		VCC					P18		
		VCC					L15		
		VCC					K16		
		VCC					K14		
		VCC					J15		
		VCC					N15		
		VCC					M16		
		VCC					M14		
		VCC					T16		
		VCC					T14		
		VCC					R15		
		VCC					P16		
		VCC					P14		
		VCC					L13		
		VCC					J13		
		VCC					N13		
		VCC					R13		
		DNU					A4		
		DNU					A3		
		DNU					AB7		
		DNU					AA12		
		DNU					C24		
		DNU					F14		
		VCCPGM					AA9		
		VCCPGM					W22		
		VCCPGM					F8		
		VCCBAT					E8		
		VCCIO3A					Y7		
		VCCIO3A					AC6		
		VCCIO3B					V11		
		VCCIO3B					AA10		
		VCCIO3B					AD9		
		VCCIO3B					U8		
		VCCIO4A					U18		
		VCCIO4A					AE22		
		VCCIO4A					AA20		
		VCCIO4A					AD19		
		VCCIO4A					Y17		
		VCCIO4A					W14		
		VCCIO4A					AC16		
		VCCIO4A					AF15		
		VCCIO4A					AB13		
		VCCIO4A					AE12		
		VCCIO5A					V21		
		VCCIO5A					AB23		
		VCCIO5B					N26		
		VCCIO5B					T25		
		VCCIO5B					W24		
		VCCIO5B					R22		
		VCCIO6A					C26		
		VCCIO6A					F25		
		VCCIO6A					J24		
		VCCIO6A					E22		
		VCCIO6A					M23		
		VCCIO6A					H21		
		VCCIO7A					B23		
		VCCIO7A					A20		
		VCCIO7A					D19		
		VCCIO7A					G18		
		VCCIO7A					C16		
		VCCIO7A					F15		
		VCCIO7A					B13		
		VCCIO7A					E12		
		VCCIO7A					A10		
		VCCIO7A					H11		
		VCCIO8A					C6		
		VCCIO8A					D9		
		VCCIO8A					G8		



Bank Number	VREF	Pin Name/Function	Optional Function(s)	Configuration Function	Dedicated Tx/Rx Channel	Emulated LVDS Output Channel	F672	DQS for X8	DQS for X16
		VCCIO8A					K7		
		VCCPD3A					AB9		
		VCCPD3B4A					AA17		
		VCCPD3B4A					AA11		
		VCCPD3B4A					AA19		
		VCCPD3B4A					AB21		
		VCCPD3B4A					AA13		
		VCCPD5A					U21		
		VCCPD5B					N22		
		VCCPD5B					R21		
		VCCPD6A					J22		
		VCCPD6A					L21		
		VCCPD7A8A					F19		
		VCCPD7A8A					F17		
		VCCPD7A8A					F13		
		VCCPD7A8A					F11		
		VCCPD7A8A					F9		
3A	VREFB3AN0	VREFB3AN0					AC7		
3B	VREFB3BN0	VREFB3BN0					AC12		
4A	VREFB4AN0	VREFB4AN0					AD15		
5A	VREFB5AN0	VREFB5AN0					W23		
5B	VREFB5BN0	VREFB5BN0					P25		
6A	VREFB6AN0	VREFB6AN0					L26		
7A	VREFB7AN0	VREFB7AN0					B16		
8A	VREFB8AN0	VREFB8AN0					C8		
		VCCH GXBL					R3		
		VCCH GXBL					T4		
		VCCH GXBL					L3		
		VCCL GXBL					J3		
		VCCL GXBL					N3		
		VCCL GXBL					U3		
		RREF TL					B1		
		VCCA FPLL					W7		
		VCCA FPLL					J6		
		VCCA FPLL					Y21		
		VCCA FPLL					G21		
		VCC AUX					G9		
		VCC AUX					E14		
		VCC AUX					G19		
		VCC AUX					AB20		
		VCC AUX					AB14		
		VCC AUX					AA8		
		VCCE GXBL					U5		
		VCCE GXBL					K4		
		VCCE GXBL					N5		
		VCCE GXBL					M4		
		VCCE GXBL					R5		
		VCCE GXBL					P4		

Note:

(1) For more information about pin definition and pin connection guidelines, refer to the [Cyclone V Device Family Pin Connection Guidelines](#).



Bank Number	VREF	Pin Name/Function	Optional Function(s)	Configuration Function	Dedicated Tx/Rx Channel	Emulated LVDS Output Channel	F896	DQS for X8	DQS for X16
GXB L3		REFCLK3Ln					L7		
GXB L3		REFCLK3Lp					K8		
GXB L3		GXB_TX_L11n					D3		
GXB L3		GXB_TX_L11p					D4		
GXB L3		GXB_RX_L11p,GXB_REFCLK_L11p					E2		
GXB L3		GXB_RX_L11n,GXB_REFCLK_L11n					E1		
GXB L3		GXB_TX_L10n					F3		
GXB L3		GXB_TX_L10p					F4		
GXB L3		GXB_RX_L10p,GXB_REFCLK_L10p					G2		
GXB L3		GXB_RX_L10n,GXB_REFCLK_L10n					G1		
GXB L3		GXB_TX_L9n					H3		
GXB L3		GXB_TX_L9p					H4		
GXB L3		GXB_RX_L9p,GXB_REFCLK_L9p					J2		
GXB L3		GXB_RX_L9n,GXB_REFCLK_L9n					J1		
GXB L2		GXB_TX_L8n					K3		
GXB L2		GXB_TX_L8p					K4		
GXB L2		GXB_RX_L8p,GXB_REFCLK_L8p					L2		
GXB L2		GXB_RX_L8n,GXB_REFCLK_L8n					L1		
GXB L2		GXB_TX_L7n					M3		
GXB L2		GXB_TX_L7p					M4		
GXB L2		GXB_RX_L7p,GXB_REFCLK_L7p					N2		
GXB L2		GXB_RX_L7n,GXB_REFCLK_L7n					N1		
GXB L2		GXB_TX_L6n					P3		
GXB L2		GXB_TX_L6p					P4		
GXB L2		GXB_RX_L6p,GXB_REFCLK_L6p					R2		
GXB L2		GXB_RX_L6n,GXB_REFCLK_L6n					R1		
GXB L2		REFCLK2Lp					P8		
GXB L2		REFCLK2Ln					N7		
GXB L1		REFCLK1Ln					R7		
GXB L1		REFCLK1Lp					R8		
GXB L1		GXB_TX_L5n					T3		
GXB L1		GXB_TX_L5p					T4		
GXB L1		GXB_RX_L5p,GXB_REFCLK_L5p					U2		
GXB L1		GXB_RX_L5n,GXB_REFCLK_L5n					U1		
GXB L1		GXB_TX_L4n					V3		
GXB L1		GXB_TX_L4p					V4		
GXB L1		GXB_RX_L4p,GXB_REFCLK_L4p					W2		
GXB L1		GXB_RX_L4n,GXB_REFCLK_L4n					W1		
GXB L1		GXB_TX_L3n					Y3		
GXB L1		GXB_TX_L3p					Y4		
GXB L1		GXB_RX_L3p,GXB_REFCLK_L3p					AA2		
GXB L1		GXB_RX_L3n,GXB_REFCLK_L3n					AA1		
GXB L0		GXB_TX_L2n					AB3		
GXB L0		GXB_TX_L2p					AB4		
GXB L0		GXB_RX_L2p,GXB_REFCLK_L2p					AC2		
GXB L0		GXB_RX_L2n,GXB_REFCLK_L2n					AC1		
GXB L0		GXB_TX_L1n					AD3		
GXB L0		GXB_TX_L1p					AD4		
GXB L0		GXB_RX_L1p,GXB_REFCLK_L1p					AE2		
GXB L0		GXB_RX_L1n,GXB_REFCLK_L1n					AE1		
GXB L0		GXB_TX_L0n					AF3		
GXB L0		GXB_TX_L0p					AF4		
GXB L0		GXB_RX_L0p,GXB_REFCLK_L0p					AG2		
GXB L0		GXB_RX_L0n,GXB_REFCLK_L0n					AG1		
GXB L0		REFCLK0Lp					W8		
GXB L0		REFCLK0Ln					W7		
3A		TDO		TDO			W9		
3A		nCSO		DATA4			AA7		
3A		TMS		TMS			V7		
3A		AS_DATA3		DATA3			AB7		
3A		TCK		TCK			AC7		
3A		AS_DATA2		DATA2			AE7		
3A		TDI		TDI			U7		
3A		AS_DATA1		DATA1			AE5		
3A		DCLK		DCLK			T7		
3A		AS_DATA0,ASDO		DATA0			AG5		
3A	VREFB3ANO	IO		DATA6	DIFFIO_RX_B1n	DIFFOUT_B1n	U12	DQ1B	
3A	VREFB3ANO	IO		DATA5	DIFFIO_TX_B2n	DIFFOUT_B2n	AA10		
3A	VREFB3ANO	IO		DATA8	DIFFIO_RX_B1p	DIFFOUT_B1p	U11	DQ1B	
3A	VREFB3ANO	IO		DATA7	DIFFIO_TX_B2p	DIFFOUT_B2p	Y10	DQ1B	
3A	VREFB3ANO	IO		DATA10	DIFFIO_RX_B3n	DIFFOUT_B3n	Y11	DQS1B	
3A	VREFB3ANO	IO		DATA9	DIFFIO_TX_B4n	DIFFOUT_B4n	AD9	DQ1B	
3A	VREFB3ANO	IO		DATA12	DIFFIO_RX_B3p	DIFFOUT_B3p	AA11	DQS1B	
3A	VREFB3ANO	IO		DATA11	DIFFIO_TX_B4p	DIFFOUT_B4p	AC9		
3A	VREFB3ANO	IO		DATA14	DIFFIO_RX_B5n	DIFFOUT_B5n	R10	DQ1B	
3A	VREFB3ANO	IO		DATA13	DIFFIO_TX_B6n	DIFFOUT_B6n	W10	DQ1B	
3A	VREFB3ANO	IO		CLKUSR	DIFFIO_RX_B5p	DIFFOUT_B5p	T11	DQ1B	
3A	VREFB3ANO	IO		DATA15	DIFFIO_TX_B6p	DIFFOUT_B6p	V9	DQ1B	





Pin Information for the Cyclone® V 5CGXBC9 Device  
Version 1.2  
Note (1)

Bank Number	VREF	Pin Name/Function	Optional Function(s)	Configuration Function	Dedicated Tx/Rx Channel	Emulated LVDS Output Channel	F896	DQS for X8	DQS for X16
3A	VREFB3AN0	IO		PR_DONE	DIFFIO_RX_B7n	DIFFOUT_B7n	V10		
3A	VREFB3AN0	IO		PR_READY	DIFFIO_TX_B8n	DIFFOUT_B8n	AF6	DQ1B	
3A	VREFB3AN0	IO		PR_ERROR	DIFFIO_RX_B7p	DIFFOUT_B7p	V11		
3A	VREFB3AN0	IO			DIFFIO_TX_B8p	DIFFOUT_B8p	AF7	DQ1B	
3A	VREFB3AN0	IO			DIFFIO_TX_B9n	DIFFOUT_B9n	AB9		
3A	VREFB3AN0	IO			DIFFIO_RX_B10n	DIFFOUT_B10n	AH6	DQ2B	
3A	VREFB3AN0	IO			DIFFIO_TX_B9p	DIFFOUT_B9p	AA9	DQ2B	
3A	VREFB3AN0	IO			DIFFIO_RX_B10p	DIFFOUT_B10p	AG6	DQ2B	
3A	VREFB3AN0	IO			DIFFIO_RX_B11n	DIFFOUT_B11n	U8	DQSn2B	
3A	VREFB3AN0	IO			DIFFIO_TX_B12n	DIFFOUT_B12n	AG8	DQ2B	
3A	VREFB3AN0	IO			DIFFIO_RX_B11p	DIFFOUT_B11p	T9	DQS2B	
3A	VREFB3AN0	IO			DIFFIO_TX_B12p	DIFFOUT_B12p	AF8		
3A	VREFB3AN0	IO			DIFFIO_TX_B13n	DIFFOUT_B13n	AB8	DQ2B	
3A	VREFB3AN0	IO			DIFFIO_RX_B14n	DIFFOUT_B14n	AH5	DQ2B	
3A	VREFB3AN0	IO			DIFFIO_TX_B13p	DIFFOUT_B13p	AA8	DQ2B	
3A	VREFB3AN0	IO			DIFFIO_RX_B14p	DIFFOUT_B14p	AH4	DQ2B	
3A	VREFB3AN0	IO			DIFFIO_RX_B15n	DIFFOUT_B15n	U9		
3A	VREFB3AN0	IO			DIFFIO_TX_B16n	DIFFOUT_B16n	AH7	DQ2B	
3A	VREFB3AN0	IO			DIFFIO_RX_B15p	DIFFOUT_B15p	T10		
3A	VREFB3AN0	IO			DIFFIO_TX_B16p	DIFFOUT_B16p	AG7	DQ2B	
3B	VREFB3BN0	IO			DIFFIO_TX_B25n	DIFFOUT_B25n	AF10		
3B	VREFB3BN0	IO			DIFFIO_RX_B26n	DIFFOUT_B26n	AD13	DQ3B	DQ1B
3B	VREFB3BN0	IO			DIFFIO_TX_B25p	DIFFOUT_B25p	AE10	DQ3B	DQ1B
3B	VREFB3BN0	IO			DIFFIO_RX_B26p	DIFFOUT_B26p	AD12	DQ3B	DQ1B
3B	VREFB3BN0	IO			DIFFIO_RX_B27n	DIFFOUT_B27n	W12	DQSn3B	DQ1B
3B	VREFB3BN0	IO			DIFFIO_TX_B28n	DIFFOUT_B28n	AJ2	DQ3B	DQ1B
3B	VREFB3BN0	IO			DIFFIO_RX_B27p	DIFFOUT_B27p	V12	DQS3B	DQ1B
3B	VREFB3BN0	IO			DIFFIO_TX_B28p	DIFFOUT_B28p	AJ1		
3B	VREFB3BN0	IO			DIFFIO_TX_B29n	DIFFOUT_B29n	AK3	DQ3B	DQ1B
3B	VREFB3BN0	IO			DIFFIO_RX_B30n	DIFFOUT_B30n	AE13	DQ3B	DQ1B
3B	VREFB3BN0	IO			DIFFIO_TX_B29p	DIFFOUT_B29p	AJ3	DQ3B	DQ1B
3B	VREFB3BN0	IO			DIFFIO_RX_B30p	DIFFOUT_B30p	AE12	DQ3B	DQ1B
3B	VREFB3BN0	IO			DIFFIO_RX_B31n	DIFFOUT_B31n	AB13		
3B	VREFB3BN0	IO			DIFFIO_TX_B32n	DIFFOUT_B32n	AJ5	DQ3B	DQ1B
3B	VREFB3BN0	IO			DIFFIO_RX_B31p	DIFFOUT_B31p	AB12		
3B	VREFB3BN0	IO			DIFFIO_TX_B32p	DIFFOUT_B32p	AJ4	DQ3B	DQ1B
3B	VREFB3BN0	IO			DIFFIO_TX_B33n	DIFFOUT_B33n	AK6		
3B	VREFB3BN0	IO			DIFFIO_RX_B34n	DIFFOUT_B34n	AG12	DQ4B	DQ1B
3B	VREFB3BN0	IO			DIFFIO_TX_B33p	DIFFOUT_B33p	AK5	DQ4B	DQ1B
3B	VREFB3BN0	IO			DIFFIO_RX_B34p	DIFFOUT_B34p	AF13	DQ4B	DQ1B
3B	VREFB3BN0	IO			DIFFIO_RX_B35n	DIFFOUT_B35n	AA13	DQSn4B	DQSn1B
3B	VREFB3BN0	IO			DIFFIO_TX_B36n	DIFFOUT_B36n	AK7	DQ4B	DQ1B
3B	VREFB3BN0	IO			DIFFIO_RX_B35p	DIFFOUT_B35p	Y12	DQS4B	DQS1B
3B	VREFB3BN0	IO			DIFFIO_TX_B36p	DIFFOUT_B36p	AJ7		
3B	VREFB3BN0	IO			DIFFIO_TX_B37n	DIFFOUT_B37n	AK8	DQ4B	DQ1B
3B	VREFB3BN0	IO			DIFFIO_RX_B38n	DIFFOUT_B38n	AG11	DQ4B	DQ1B
3B	VREFB3BN0	IO			DIFFIO_TX_B37p	DIFFOUT_B37p	AJ8	DQ4B	DQ1B
3B	VREFB3BN0	IO			DIFFIO_RX_B38p	DIFFOUT_B38p	AF11	DQ4B	DQ1B
3B	VREFB3BN0	IO			DIFFIO_RX_B39n	DIFFOUT_B39n	AC14		
3B	VREFB3BN0	IO	CLK0n,FPLL_BL_FBn		DIFFIO_TX_B40n	DIFFOUT_B40n	AG9	DQ4B	DQ1B
3B	VREFB3BN0	IO	CLK0p,FPLL_BL_FBp		DIFFIO_RX_B39p	DIFFOUT_B39p	AB14		
3B	VREFB3BN0	IO			DIFFIO_TX_B40p	DIFFOUT_B40p	AF9	DQ4B	DQ1B
3B	VREFB3BN0	IO			DIFFIO_TX_B41n	DIFFOUT_B41n	AJ9		
3B	VREFB3BN0	IO			DIFFIO_RX_B42n	DIFFOUT_B42n	AJ10	DQ5B	
3B	VREFB3BN0	IO			DIFFIO_TX_B41p	DIFFOUT_B41p	AH9	DQ5B	
3B	VREFB3BN0	IO			DIFFIO_RX_B42p	DIFFOUT_B42p	AH10	DQ5B	
3B	VREFB3BN0	IO			DIFFIO_RX_B43n	DIFFOUT_B43n	AA14	DQSn5B	
3B	VREFB3BN0	IO			DIFFIO_TX_B44n	DIFFOUT_B44n	AK11	DQ5B	
3B	VREFB3BN0	IO			DIFFIO_RX_B43p	DIFFOUT_B43p	Y13	DQS5B	
3B	VREFB3BN0	IO			DIFFIO_TX_B44p	DIFFOUT_B44p	AK10		
3B	VREFB3BN0	IO	FPLL_BL_CLKOUT1,FPLL_BL_CLKOUTn		DIFFIO_TX_B45n	DIFFOUT_B45n	AH12	DQ5B	
3B	VREFB3BN0	IO			DIFFIO_RX_B46n	DIFFOUT_B46n	AG14	DQ5B	
3B	VREFB3BN0	IO	FPLL_BL_CLKOUT0,FPLL_BL_CLKOUTp,FPLL_BL_FB		DIFFIO_TX_B45p	DIFFOUT_B45p	AH11	DQ5B	
3B	VREFB3BN0	IO			DIFFIO_RX_B46p	DIFFOUT_B46p	AG13	DQ5B	
3B	VREFB3BN0	IO	CLK1n		DIFFIO_RX_B47n	DIFFOUT_B47n	AA15		
3B	VREFB3BN0	IO			DIFFIO_TX_B48n	DIFFOUT_B48n	AK12	DQ5B	
3B	VREFB3BN0	IO	CLK1p		DIFFIO_RX_B47p	DIFFOUT_B47p	Y15		
3B	VREFB3BN0	IO			DIFFIO_TX_B48p	DIFFOUT_B48p	AJ12	DQ5B	
4A	VREFB4AN0	IO	RZQ_0		DIFFIO_TX_B49n	DIFFOUT_B49n	AK13		
4A	VREFB4AN0	IO			DIFFIO_RX_B50n	DIFFOUT_B50n	AF15	DQ6B	
4A	VREFB4AN0	IO			DIFFIO_TX_B49p	DIFFOUT_B49p	AJ14	DQ6B	
4A	VREFB4AN0	IO			DIFFIO_RX_B50p	DIFFOUT_B50p	AE16	DQ6B	
4A	VREFB4AN0	IO			DIFFIO_RX_B51n	DIFFOUT_B51n	AA16	DQSn6B	
4A	VREFB4AN0	IO			DIFFIO_TX_B52n	DIFFOUT_B52n	AH15	DQ6B	
4A	VREFB4AN0	IO			DIFFIO_RX_B51p	DIFFOUT_B51p	Y16	DQS6B	
4A	VREFB4AN0	IO			DIFFIO_TX_B52p	DIFFOUT_B52p	AH14		
4A	VREFB4AN0	IO			DIFFIO_TX_B53n	DIFFOUT_B53n	AK15	DQ6B	
4A	VREFB4AN0	IO			DIFFIO_RX_B54n	DIFFOUT_B54n	AE17	DQ6B	



Pin Information for the Cyclone® V 5CGXBC9 Device

Version 1.2

Note (1)

Bank Number	VREF	Pin Name/Function	Optional Function(s)	Configuration Function	Dedicated Tx/Rx Channel	Emulated LVDS Output Channel	F896	DQS for X8	DQS for X16
4A	VREFB4AN0	IO			DIFFIO TX B53p	DIFFOUT B53p	AJ15	DQ6B	
4A	VREFB4AN0	IO			DIFFIO RX B54p	DIFFOUT B54p	AD17	DQ6B	
4A	VREFB4AN0	IO	CLK2n		DIFFIO RX B55n	DIFFOUT B55n	AC15		
4A	VREFB4AN0	IO			DIFFIO TX B56n	DIFFOUT B56n	AF14	DQ6B	
4A	VREFB4AN0	IO	CLK2p		DIFFIO RX B55p	DIFFOUT B55p	AB16		
4A	VREFB4AN0	IO			DIFFIO TX B56p	DIFFOUT B56p	AE15	DQ6B	
4A	VREFB4AN0	IO			DIFFIO TX B57n	DIFFOUT B57n	AH17		
4A	VREFB4AN0	IO			DIFFIO RX B58n	DIFFOUT B58n	AK17	DQ7B	DO2B
4A	VREFB4AN0	IO			DIFFIO TX B57p	DIFFOUT B57p	AG17	DQ7B	DO2B
4A	VREFB4AN0	IO			DIFFIO RX B58p	DIFFOUT B58p	AK16	DQ7B	DO2B
4A	VREFB4AN0	IO			DIFFIO RX B59n	DIFFOUT B59n	Y18	DQS7B	DO2B
4A	VREFB4AN0	IO			DIFFIO TX B60n	DIFFOUT B60n	AJ18	DQ7B	DO2B
4A	VREFB4AN0	IO			DIFFIO RX B59p	DIFFOUT B59p	Y17	DQS7B	DO2B
4A	VREFB4AN0	IO			DIFFIO TX B60p	DIFFOUT B60p	AJ17		
4A	VREFB4AN0	IO			DIFFIO TX B61n	DIFFOUT B61n	AK18	DQ7B	DO2B
4A	VREFB4AN0	IO			DIFFIO RX B62n	DIFFOUT B62n	AG16	DQ7B	DO2B
4A	VREFB4AN0	IO			DIFFIO TX B61p	DIFFOUT B61p	AJ19	DQ7B	DO2B
4A	VREFB4AN0	IO			DIFFIO RX B62p	DIFFOUT B62p	AF16	DQ7B	DO2B
4A	VREFB4AN0	IO	CLK3n		DIFFIO RX B63n	DIFFOUT B63n	AB18		
4A	VREFB4AN0	IO			DIFFIO TX B64n	DIFFOUT B64n	AH20	DQ7B	DO2B
4A	VREFB4AN0	IO	CLK3p		DIFFIO TX B63p	DIFFOUT B63p	AB17		
4A	VREFB4AN0	IO			DIFFIO TX B64p	DIFFOUT B64p	AH19	DQ7B	DO2B
4A	VREFB4AN0	IO			DIFFIO TX B65n	DIFFOUT B65n	AK20		
4A	VREFB4AN0	IO			DIFFIO RX B66n	DIFFOUT B66n	AE18	DQ8B	DO2B
4A	VREFB4AN0	IO			DIFFIO TX B65p	DIFFOUT B65p	AJ20	DQ8B	DO2B
4A	VREFB4AN0	IO			DIFFIO RX B66p	DIFFOUT B66p	AD18	DQ8B	DO2B
4A	VREFB4AN0	IO			DIFFIO RX B67n	DIFFOUT B67n	AA20	DQS8B	DQS2B
4A	VREFB4AN0	IO			DIFFIO TX B68n	DIFFOUT B68n	AK22	DQ8B	DO2B
4A	VREFB4AN0	IO			DIFFIO RX B67p	DIFFOUT B67p	Y20	DQS8B	DQS2B
4A	VREFB4AN0	IO			DIFFIO TX B68p	DIFFOUT B68p	AK21		
4A	VREFB4AN0	IO			DIFFIO TX B69n	DIFFOUT B69n	AJ22	DQ8B	DO2B
4A	VREFB4AN0	IO			DIFFIO RX B70n	DIFFOUT B70n	AF19	DQ8B	DO2B
4A	VREFB4AN0	IO			DIFFIO TX B69p	DIFFOUT B69p	AH21	DQ8B	DO2B
4A	VREFB4AN0	IO			DIFFIO RX B70p	DIFFOUT B70p	AF18	DQ8B	DO2B
4A	VREFB4AN0	IO			DIFFIO RX B71n	DIFFOUT B71n	AA19		
4A	VREFB4AN0	IO			DIFFIO TX B72n	DIFFOUT B72n	AK23	DQ8B	DO2B
4A	VREFB4AN0	IO			DIFFIO RX B71p	DIFFOUT B71p	AA18		
4A	VREFB4AN0	IO			DIFFIO TX B72p	DIFFOUT B72p	AJ23	DQ8B	DO2B
4A	VREFB4AN0	IO			DIFFIO TX B73n	DIFFOUT B73n	AJ24		
4A	VREFB4AN0	IO			DIFFIO RX B74n	DIFFOUT B74n	AG19	DQ9B	DO3B
4A	VREFB4AN0	IO			DIFFIO TX B73p	DIFFOUT B73p	AH24	DQ9B	DO3B
4A	VREFB4AN0	IO			DIFFIO RX B74p	DIFFOUT B74p	AG18	DQ9B	DO3B
4A	VREFB4AN0	IO			DIFFIO RX B75n	DIFFOUT B75n	AC19	DQS9B	DO3B
4A	VREFB4AN0	IO			DIFFIO TX B76n	DIFFOUT B76n	AK25	DQ9B	DO3B
4A	VREFB4AN0	IO			DIFFIO RX B75p	DIFFOUT B75p	AB19	DQS9B	DO3B
4A	VREFB4AN0	IO			DIFFIO TX B76p	DIFFOUT B76p	AJ25		
4A	VREFB4AN0	IO			DIFFIO TX B77n	DIFFOUT B77n	AH25	DQ9B	DO3B
4A	VREFB4AN0	IO			DIFFIO RX B78n	DIFFOUT B78n	AE20	DQ9B	DO3B
4A	VREFB4AN0	IO			DIFFIO TX B77p	DIFFOUT B77p	AG24	DQ9B	DO3B
4A	VREFB4AN0	IO			DIFFIO RX B78p	DIFFOUT B78p	AD19	DQ9B	DO3B
4A	VREFB4AN0	IO			DIFFIO TX B79n	DIFFOUT B79n	AB21		
4A	VREFB4AN0	IO			DIFFIO TX B80n	DIFFOUT B80n	AK26	DQ9B	DO3B
4A	VREFB4AN0	IO			DIFFIO RX B79p	DIFFOUT B79p	AA21		
4A	VREFB4AN0	IO			DIFFIO TX B80p	DIFFOUT B80p	AJ27	DQ9B	DO3B
4A	VREFB4AN0	IO			DIFFIO TX B81n	DIFFOUT B81n	AK28		
4A	VREFB4AN0	IO			DIFFIO RX B82n	DIFFOUT B82n	AG21	DQ10B	DO3B
4A	VREFB4AN0	IO			DIFFIO TX B81p	DIFFOUT B81p	AK27	DQ10B	DO3B
4A	VREFB4AN0	IO			DIFFIO RX B82p	DIFFOUT B82p	AF20	DQ10B	DO3B
4A	VREFB4AN0	IO			DIFFIO RX B83n	DIFFOUT B83n	AD20	DQS10B	DQS3B
4A	VREFB4AN0	IO			DIFFIO TX B84n	DIFFOUT B84n	AH26	DQ10B	DO3B
4A	VREFB4AN0	IO			DIFFIO RX B83p	DIFFOUT B83p	AC21	DQS10B	DQS3B
4A	VREFB4AN0	IO			DIFFIO TX B84p	DIFFOUT B84p	AG26		
4A	VREFB4AN0	IO			DIFFIO TX B85n	DIFFOUT B85n	AF23	DQ10B	DO3B
4A	VREFB4AN0	IO			DIFFIO RX B86n	DIFFOUT B86n	AG22	DQ10B	DO3B
4A	VREFB4AN0	IO			DIFFIO TX B85p	DIFFOUT B85p	AE22	DQ10B	DO3B
4A	VREFB4AN0	IO			DIFFIO RX B86p	DIFFOUT B86p	AF21	DQ10B	DO3B
4A	VREFB4AN0	IO			DIFFIO RX B87n	DIFFOUT B87n	AC22		
4A	VREFB4AN0	IO			DIFFIO TX B88n	DIFFOUT B88n	AH22	DQ10B	DO3B
4A	VREFB4AN0	IO			DIFFIO RX B87p	DIFFOUT B87p	AB22		
4A	VREFB4AN0	IO			DIFFIO TX B88p	DIFFOUT B88p	AG23	DQ10B	DO3B
5A	VREFB5AN0	IO	RZQ 1		DIFFIO TX R1p	DIFFOUT R1p	AD23	DQ1R	
5A	VREFB5AN0	IO		INIT_DONE	DIFFIO RX R2p	DIFFOUT R2p	W22		
5A	VREFB5AN0	IO		PR_REQUEST	DIFFIO TX R1n	DIFFOUT R1n	AC24	DQ1R	
5A	VREFB5AN0	IO		CRC_ERROR	DIFFIO RX R2n	DIFFOUT R2n	Y21		
5A	VREFB5AN0	IO		nCEO	DIFFIO TX R3p	DIFFOUT R3p	AD24	DQ1R	
5A	VREFB5AN0	IO			DIFFIO RX R4p	DIFFOUT R4p	Y25	DQ1R	
5A	VREFB5AN0	IO		CvP_CONFDONE	DIFFIO TX R3n	DIFFOUT R3n	AD25	DQ1R	
5A	VREFB5AN0	IO			DIFFIO RX R4n	DIFFOUT R4n	Y26	DQ1R	



Pin Information for the Cyclone® V 5CGXBC9 Device  
Version 1.2  
Note (1)

Bank Number	VREF	Pin Name/Function	Optional Function(s)	Configuration Function	Dedicated Tx/Rx Channel	Emulated LVDS Output Channel	F896	DQS for X8	DQS for X16
5A	VREFB5A0	IO		DEV_OE	DIFFIO TX_R5p	DIFFOUT_R5p	AB26		
5A	VREFB5A0	IO			DIFFIO RX_R6p	DIFFOUT_R6p	Y23	DQS1R	
5A	VREFB5A0	IO		DEV_CLRn	DIFFIO TX_R5n	DIFFOUT_R5n	AA26	DQ1R	
5A	VREFB5A0	IO			DIFFIO RX_R6n	DIFFOUT_R6n	W24	DQSn1R	
5A	VREFB5A0	IO			DIFFIO TX_R7p	DIFFOUT_R7p	AC26	DQ1R	
5A	VREFB5A0	IO			DIFFIO RX_R8p	DIFFOUT_R8p	Y22	DQ1R	
5A	VREFB5A0	IO			DIFFIO TX_R7n	DIFFOUT_R7n	AC27		
5A	VREFB5A0	IO			DIFFIO RX_R8n	DIFFOUT_R8n	AA23	DQ1R	
5A	VREFB5A0	IO			DIFFIO RX_R17p	DIFFOUT_R17p	AA24		
5A	VREFB5A0	IO			DIFFIO TX_R18p	DIFFOUT_R18p	AE23	DQ2R	
5A	VREFB5A0	IO			DIFFIO RX_R17n	DIFFOUT_R17n	AA25		
5A	VREFB5A0	IO			DIFFIO TX_R18n	DIFFOUT_R18n	AF24	DQ2R	
5A	VREFB5A0	IO			DIFFIO RX_R19p	DIFFOUT_R19p	AE27	DQ2R	
5A	VREFB5A0	IO			DIFFIO TX_R20p	DIFFOUT_R20p	AE25	DQ2R	
5A	VREFB5A0	IO			DIFFIO RX_R19n	DIFFOUT_R19n	AD27	DQ2R	
5A	VREFB5A0	IO			DIFFIO TX_R20n	DIFFOUT_R20n	AE26	DQ2R	
5A	VREFB5A0	IO			DIFFIO RX_R21p	DIFFOUT_R21p	V21	DQS2R	
5A	VREFB5A0	IO			DIFFIO TX_R22p	DIFFOUT_R22p	AF25		
5A	VREFB5A0	IO			DIFFIO RX_R21n	DIFFOUT_R21n	V22	DQS2R	
5A	VREFB5A0	IO			DIFFIO TX_R22n	DIFFOUT_R22n	AF26	DQ2R	
5A	VREFB5A0	IO			DIFFIO RX_R23p	DIFFOUT_R23p	Y27	DQ2R	
5A	VREFB5A0	IO			DIFFIO TX_R24p	DIFFOUT_R24p	AH27	DQ2R	
5A	VREFB5A0	IO			DIFFIO RX_R23n	DIFFOUT_R23n	W27	DQ2R	
5A	VREFB5A0	IO			DIFFIO TX_R24n	DIFFOUT_R24n	AG27		
5B	VREFB5B0	IO			DIFFIO RX_R25p	DIFFOUT_R25p	V24		
5B	VREFB5B0	IO			DIFFIO TX_R26p	DIFFOUT_R26p	AJ28	DQ3R	DQ1R
5B	VREFB5B0	IO			DIFFIO RX_R25n	DIFFOUT_R25n	V25		
5B	VREFB5B0	IO			DIFFIO TX_R26n	DIFFOUT_R26n	AJ29	DQ3R	DQ1R
5B	VREFB5B0	IO			DIFFIO RX_R27p	DIFFOUT_R27p	AA28	DQ3R	DQ1R
5B	VREFB5B0	IO			DIFFIO TX_R28p	DIFFOUT_R28p	AH29	DQ3R	DQ1R
5B	VREFB5B0	IO			DIFFIO RX_R27n	DIFFOUT_R27n	Y28	DQ3R	DQ1R
5B	VREFB5B0	IO			DIFFIO TX_R28n	DIFFOUT_R28n	AG29	DQ3R	DQ1R
5B	VREFB5B0	IO			DIFFIO RX_R29p	DIFFOUT_R29p	V26	DQS3R	DQS1R
5B	VREFB5B0	IO			DIFFIO TX_R30p	DIFFOUT_R30p	AJ30		
5B	VREFB5B0	IO			DIFFIO RX_R29n	DIFFOUT_R29n	U26	DQS3R	DQS1R
5B	VREFB5B0	IO			DIFFIO TX_R30n	DIFFOUT_R30n	AH30	DQ3R	DQ1R
5B	VREFB5B0	IO			DIFFIO RX_R31p	DIFFOUT_R31p	AE30	DQ3R	DQ1R
5B	VREFB5B0	IO			DIFFIO TX_R32p	DIFFOUT_R32p	AG28	DQ3R	DQ1R
5B	VREFB5B0	IO			DIFFIO RX_R31n	DIFFOUT_R31n	AD30	DQ3R	DQ1R
5B	VREFB5B0	IO			DIFFIO TX_R32n	DIFFOUT_R32n	AF28		
5B	VREFB5B0	IO	CLK7p,FPLL_BR_FBp		DIFFIO RX_R33p	DIFFOUT_R33p	U21		
5B	VREFB5B0	IO			DIFFIO TX_R34p	DIFFOUT_R34p	AF29	DQ4R	DQ1R
5B	VREFB5B0	IO	CLK7n,FPLL_BR_FBn		DIFFIO RX_R33n	DIFFOUT_R33n	U22		
5B	VREFB5B0	IO			DIFFIO TX_R34n	DIFFOUT_R34n	AF30	DQ4R	DQ1R
5B	VREFB5B0	IO			DIFFIO RX_R35p	DIFFOUT_R35p	V27	DQ4R	DQ1R
5B	VREFB5B0	IO			DIFFIO TX_R36p	DIFFOUT_R36p	AE28	DQ4R	DQ1R
5B	VREFB5B0	IO			DIFFIO RX_R35n	DIFFOUT_R35n	W28	DQ4R	DQ1R
5B	VREFB5B0	IO			DIFFIO TX_R36n	DIFFOUT_R36n	AD28	DQ4R	DQ1R
5B	VREFB5B0	IO			DIFFIO RX_R37p	DIFFOUT_R37p	U27	DQS4R	DQ1R
5B	VREFB5B0	IO			DIFFIO TX_R38p	DIFFOUT_R38p	AD29		
5B	VREFB5B0	IO			DIFFIO RX_R37n	DIFFOUT_R37n	U28	DQS4R	DQ1R
5B	VREFB5B0	IO			DIFFIO TX_R38n	DIFFOUT_R38n	AC29	DQ4R	DQ1R
5B	VREFB5B0	IO			DIFFIO RX_R39p	DIFFOUT_R39p	AA29	DQ4R	DQ1R
5B	VREFB5B0	IO			DIFFIO TX_R40p	DIFFOUT_R40p	AB27	DQ4R	DQ1R
5B	VREFB5B0	IO			DIFFIO RX_R39n	DIFFOUT_R39n	AA30	DQ4R	DQ1R
5B	VREFB5B0	IO			DIFFIO TX_R40n	DIFFOUT_R40n	AB28		
5B	VREFB5B0	IO	CLK6p		DIFFIO RX_R41p	DIFFOUT_R41p	U23		
5B	VREFB5B0	IO			DIFFIO TX_R42p	DIFFOUT_R42p	AB29	DQ5R	
5B	VREFB5B0	IO	CLK6n		DIFFIO RX_R41n	DIFFOUT_R41n	T24		
5B	VREFB5B0	IO			DIFFIO TX_R42n	DIFFOUT_R42n	AC30	DQ5R	
5B	VREFB5B0	IO			DIFFIO RX_R43p	DIFFOUT_R43p	T28	DQ5R	
5B	VREFB5B0	IO	FPLL_BR_CLKOUT0,FPLL_BR_CLKOUTp,FPLL_BR_FB		DIFFIO TX_R44p	DIFFOUT_R44p	Y30	DQ5R	
5B	VREFB5B0	IO			DIFFIO RX_R43n	DIFFOUT_R43n	T29	DQ5R	
5B	VREFB5B0	IO	FPLL_BR_CLKOUT1,FPLL_BR_CLKOUTn		DIFFIO TX_R44n	DIFFOUT_R44n	W30	DQ5R	
5B	VREFB5B0	IO			DIFFIO RX_R45p	DIFFOUT_R45p	T25	DQS5R	
5B	VREFB5B0	IO			DIFFIO TX_R46p	DIFFOUT_R46p	V29		
5B	VREFB5B0	IO			DIFFIO RX_R45n	DIFFOUT_R45n	R26	DQS5R	
5B	VREFB5B0	IO			DIFFIO TX_R46n	DIFFOUT_R46n	W29	DQ5R	
5B	VREFB5B0	IO			DIFFIO RX_R47p	DIFFOUT_R47p	T30	DQ5R	
5B	VREFB5B0	IO			DIFFIO TX_R48p	DIFFOUT_R48p	U29	DQ5R	
5B	VREFB5B0	IO			DIFFIO RX_R47n	DIFFOUT_R47n	R30	DQ5R	
5B	VREFB5B0	IO			DIFFIO TX_R48n	DIFFOUT_R48n	V30		
6A	VREFB6A0	IO	CLK5p		DIFFIO RX_R49p	DIFFOUT_R49p	T23		
6A	VREFB6A0	IO			DIFFIO TX_R50p	DIFFOUT_R50p	P28	DQ6R	
6A	VREFB6A0	IO	CLK5n		DIFFIO RX_R49n	DIFFOUT_R49n	R23		
6A	VREFB6A0	IO			DIFFIO TX_R50n	DIFFOUT_R50n	N29	DQ6R	
6A	VREFB6A0	IO			DIFFIO RX_R51p	DIFFOUT_R51p	P29	DQ6R	
6A	VREFB6A0	IO	FPLL_TR_CLKOUT0,FPLL_TR_CLKOUTp,FPLL_TR_FB		DIFFIO TX_R52p	DIFFOUT_R52p	M29	DQ6R	



Pin Information for the Cyclone® V 5CGXBC9 Device

Version 1.2

Note (1)

Bank Number	VREF	Pin Name/Function	Optional Function(s)	Configuration Function	Dedicated Tx/Rx Channel	Emulated LVDS Output Channel	F896	DQS for X8	DQS for X16
6A	VREFB6AN0	IO			DIFFIO RX_R51n	DIFFOUT_R51n	P30	DQ6R	
6A	VREFB6AN0	IO	FPLL_TR_CLKOUT1,FPLL_TR_CLKOUTn		DIFFIO TX_R52n	DIFFOUT_R52n	N30	DQ6R	
6A	VREFB6AN0	IO			DIFFIO RX_R53p	DIFFOUT_R53p	P25	DQS6R	
6A	VREFB6AN0	IO			DIFFIO TX_R54p	DIFFOUT_R54p	L28		
6A	VREFB6AN0	IO			DIFFIO RX_R53n	DIFFOUT_R53n	R25	DQSn6R	
6A	VREFB6AN0	IO			DIFFIO TX_R54n	DIFFOUT_R54n	K28	DQ6R	
6A	VREFB6AN0	IO			DIFFIO RX_R55p	DIFFOUT_R55p	R27	DQ6R	
6A	VREFB6AN0	IO			DIFFIO TX_R56p	DIFFOUT_R56p	M27	DQ6R	
6A	VREFB6AN0	IO			DIFFIO RX_R55n	DIFFOUT_R55n	R28	DQ6R	
6A	VREFB6AN0	IO			DIFFIO TX_R56n	DIFFOUT_R56n	M28		
6A	VREFB6AN0	IO	CLK4p,FPLL_TR_FBp		DIFFIO RX_R57p	DIFFOUT_R57p	P22		
6A	VREFB6AN0	IO			DIFFIO TX_R58p	DIFFOUT_R58p	K25	DQ7R	DQ2R
6A	VREFB6AN0	IO	CLK4n,FPLL_TR_FBn		DIFFIO RX_R57n	DIFFOUT_R57n	P23		
6A	VREFB6AN0	IO			DIFFIO TX_R58n	DIFFOUT_R58n	K26	DQ7R	DQ2R
6A	VREFB6AN0	IO			DIFFIO RX_R59p	DIFFOUT_R59p	N26	DQ7R	DQ2R
6A	VREFB6AN0	IO			DIFFIO TX_R60p	DIFFOUT_R60p	L29	DQ7R	DQ2R
6A	VREFB6AN0	IO			DIFFIO RX_R59n	DIFFOUT_R59n	N27	DQ7R	DQ2R
6A	VREFB6AN0	IO			DIFFIO TX_R60n	DIFFOUT_R60n	L30	DQ7R	DQ2R
6A	VREFB6AN0	IO			DIFFIO RX_R61p	DIFFOUT_R61p	N24	DQS7R	DQS2R
6A	VREFB6AN0	IO			DIFFIO TX_R62p	DIFFOUT_R62p	K30		
6A	VREFB6AN0	IO			DIFFIO RX_R61n	DIFFOUT_R61n	N25	DQSn7R	DQSn2R
6A	VREFB6AN0	IO			DIFFIO TX_R62n	DIFFOUT_R62n	J30	DQ7R	DQ2R
6A	VREFB6AN0	IO			DIFFIO RX_R63p	DIFFOUT_R63p	L25	DQ7R	DQ2R
6A	VREFB6AN0	IO			DIFFIO TX_R64p	DIFFOUT_R64p	G27	DQ7R	DQ2R
6A	VREFB6AN0	IO			DIFFIO RX_R63n	DIFFOUT_R63n	L26	DQ7R	DQ2R
6A	VREFB6AN0	IO			DIFFIO TX_R64n	DIFFOUT_R64n	G28		
6A	VREFB6AN0	IO			DIFFIO RX_R65p	DIFFOUT_R65p	R21		
6A	VREFB6AN0	IO			DIFFIO TX_R66p	DIFFOUT_R66p	J28	DQ8R	DQ2R
6A	VREFB6AN0	IO			DIFFIO RX_R65n	DIFFOUT_R65n	R22		
6A	VREFB6AN0	IO			DIFFIO TX_R66n	DIFFOUT_R66n	J29	DQ8R	DQ2R
6A	VREFB6AN0	IO			DIFFIO RX_R67p	DIFFOUT_R67p	K27	DQ8R	DQ2R
6A	VREFB6AN0	IO			DIFFIO TX_R68p	DIFFOUT_R68p	H29	DQ8R	DQ2R
6A	VREFB6AN0	IO			DIFFIO RX_R67n	DIFFOUT_R67n	J27	DQ8R	DQ2R
6A	VREFB6AN0	IO			DIFFIO TX_R68n	DIFFOUT_R68n	H30	DQ8R	DQ2R
6A	VREFB6AN0	IO			DIFFIO RX_R69p	DIFFOUT_R69p	N22	DQS8R	DQ2R
6A	VREFB6AN0	IO			DIFFIO TX_R70p	DIFFOUT_R70p	H27		
6A	VREFB6AN0	IO			DIFFIO RX_R69n	DIFFOUT_R69n	M23	DQSn8R	DQ2R
6A	VREFB6AN0	IO			DIFFIO TX_R70n	DIFFOUT_R70n	G26	DQ8R	DQ2R
6A	VREFB6AN0	IO			DIFFIO RX_R71p	DIFFOUT_R71p	F25	DQ8R	DQ2R
6A	VREFB6AN0	IO			DIFFIO TX_R72p	DIFFOUT_R72p	F30	DQ8R	DQ2R
6A	VREFB6AN0	IO			DIFFIO RX_R71n	DIFFOUT_R71n	F26	DQ8R	DQ2R
6A	VREFB6AN0	IO			DIFFIO TX_R72n	DIFFOUT_R72n	E30		
6A	VREFB6AN0	IO			DIFFIO RX_R73p	DIFFOUT_R73p	R20		
6A	VREFB6AN0	IO			DIFFIO TX_R74p	DIFFOUT_R74p	G29	DQ9R	DQ3R
6A	VREFB6AN0	IO			DIFFIO RX_R73n	DIFFOUT_R73n	T21		
6A	VREFB6AN0	IO			DIFFIO TX_R74n	DIFFOUT_R74n	F29	DQ9R	DQ3R
6A	VREFB6AN0	IO			DIFFIO RX_R75p	DIFFOUT_R75p	L23	DQ9R	DQ3R
6A	VREFB6AN0	IO			DIFFIO TX_R76p	DIFFOUT_R76p	D30	DQ9R	DQ3R
6A	VREFB6AN0	IO			DIFFIO RX_R75n	DIFFOUT_R75n	L24	DQ9R	DQ3R
6A	VREFB6AN0	IO			DIFFIO TX_R76n	DIFFOUT_R76n	C30	DQ9R	DQ3R
6A	VREFB6AN0	IO			DIFFIO RX_R77p	DIFFOUT_R77p	N31	DQS9R	DQS3R
6A	VREFB6AN0	IO			DIFFIO TX_R78p	DIFFOUT_R78p	F28		
6A	VREFB6AN0	IO			DIFFIO RX_R77n	DIFFOUT_R77n	M22	DQSn9R	DQSn3R
6A	VREFB6AN0	IO			DIFFIO TX_R78n	DIFFOUT_R78n	E28	DQ9R	DQ3R
6A	VREFB6AN0	IO			DIFFIO RX_R79p	DIFFOUT_R79p	K21	DQ9R	DQ3R
6A	VREFB6AN0	IO			DIFFIO TX_R80p	DIFFOUT_R80p	C29	DQ9R	DQ3R
6A	VREFB6AN0	IO			DIFFIO RX_R79n	DIFFOUT_R79n	K22	DQ9R	DQ3R
6A	VREFB6AN0	IO			DIFFIO TX_R80n	DIFFOUT_R80n	B29		
6A	VREFB6AN0	IO			DIFFIO RX_R81p	DIFFOUT_R81p	M21		
6A	VREFB6AN0	IO			DIFFIO TX_R82p	DIFFOUT_R82p	B28	DQ10R	DQ3R
6A	VREFB6AN0	IO			DIFFIO RX_R81n	DIFFOUT_R81n	L21		
6A	VREFB6AN0	IO			DIFFIO TX_R82n	DIFFOUT_R82n	A29	DQ10R	DQ3R
6A	VREFB6AN0	IO			DIFFIO RX_R83p	DIFFOUT_R83p	H25	DQ10R	DQ3R
6A	VREFB6AN0	IO			DIFFIO TX_R84p	DIFFOUT_R84p	D28	DQ10R	DQ3R
6A	VREFB6AN0	IO			DIFFIO RX_R83n	DIFFOUT_R83n	H26	DQ10R	DQ3R
6A	VREFB6AN0	IO			DIFFIO TX_R84n	DIFFOUT_R84n	D29	DQ10R	DQ3R
6A	VREFB6AN0	IO			DIFFIO RX_R85p	DIFFOUT_R85p	P20	DQS10R	DQ3R
6A	VREFB6AN0	IO			DIFFIO TX_R86p	DIFFOUT_R86p	E27		
6A	VREFB6AN0	IO			DIFFIO RX_R85n	DIFFOUT_R85n	N20	DQSn10R	DQ3R
6A	VREFB6AN0	IO			DIFFIO TX_R86n	DIFFOUT_R86n	D27	DQ10R	DQ3R
6A	VREFB6AN0	IO			DIFFIO RX_R87p	DIFFOUT_R87p	J22	DQ10R	DQ3R
6A	VREFB6AN0	IO			DIFFIO TX_R88p	DIFFOUT_R88p	H24	DQ10R	DQ3R
6A	VREFB6AN0	IO			DIFFIO RX_R87n	DIFFOUT_R87n	J23	DQ10R	DQ3R
6A	VREFB6AN0	IO			DIFFIO TX_R88n	DIFFOUT_R88n	J25		
7A		GND					G24		
7A	VREFB7AN0	IO			DIFFIO RX_T9p	DIFFOUT_T9p	H21		
7A	VREFB7AN0	IO			DIFFIO TX_T10p	DIFFOUT_T10p	E26	DQ1T	DQ1T
7A	VREFB7AN0	IO			DIFFIO RX_T9n	DIFFOUT_T9n	G21		



Pin Information for the Cyclone® V 5CGXBC9 Device  
Version 1.2  
Note (1)

Bank Number	VREF	Pin Name/Function	Optional Function(s)	Configuration Function	Dedicated Tx/Rx Channel	Emulated LVDS Output Channel	F896	DQS for X8	DQS for X16
7A	VREFB7A0	IO			DIFFIO TX T10n	DIFFOUT T10n	E25	DQ1T	DQ1T
7A	VREFB7A0	IO			DIFFIO RX T11p	DIFFOUT T11p	G22	DQ1T	DQ1T
7A	VREFB7A0	IO			DIFFIO TX T12p	DIFFOUT T12p	C27	DQ1T	DQ1T
7A	VREFB7A0	IO			DIFFIO RX T11n	DIFFOUT T11n	G23	DQ1T	DQ1T
7A	VREFB7A0	IO			DIFFIO TX T12n	DIFFOUT T12n	C26	DQ1T	DQ1T
7A	VREFB7A0	IO			DIFFIO RX T13p	DIFFOUT T13p	L20	DQS1T	DQS1T
7A	VREFB7A0	IO			DIFFIO TX T14p	DIFFOUT T14p	B27		
7A	VREFB7A0	IO			DIFFIO RX T13n	DIFFOUT T13n	L19	DQSn1T	DQSn1T
7A	VREFB7A0	IO			DIFFIO TX T14n	DIFFOUT T14n	A28	DQ1T	DQ1T
7A	VREFB7A0	IO			DIFFIO RX T15p	DIFFOUT T15p	E22	DQ1T	DQ1T
7A	VREFB7A0	IO			DIFFIO TX T16p	DIFFOUT T16p	B26	DQ1T	DQ1T
7A	VREFB7A0	IO			DIFFIO RX T15n	DIFFOUT T15n	E21	DQ1T	DQ1T
7A	VREFB7A0	IO			DIFFIO TX T16n	DIFFOUT T16n	A26		
7A	VREFB7A0	IO			DIFFIO RX T17p	DIFFOUT T17p	J20		
7A	VREFB7A0	IO			DIFFIO TX T18p	DIFFOUT T18p	D25	DQ2T	DQ1T
7A	VREFB7A0	IO			DIFFIO RX T17n	DIFFOUT T17n	H20		
7A	VREFB7A0	IO			DIFFIO TX T18n	DIFFOUT T18n	C25	DQ2T	DQ1T
7A	VREFB7A0	IO			DIFFIO RX T19p	DIFFOUT T19p	C21	DQ2T	DQ1T
7A	VREFB7A0	IO			DIFFIO TX T20p	DIFFOUT T20p	D23	DQ2T	DQ1T
7A	VREFB7A0	IO			DIFFIO RX T19n	DIFFOUT T19n	C20	DQ2T	DQ1T
7A	VREFB7A0	IO			DIFFIO TX T20n	DIFFOUT T20n	C22	DQ2T	DQ1T
7A	VREFB7A0	IO			DIFFIO RX T21p	DIFFOUT T21p	K20	DQS2T	DQ1T
7A	VREFB7A0	IO			DIFFIO TX T22p	DIFFOUT T22p	E23		
7A	VREFB7A0	IO			DIFFIO RX T21n	DIFFOUT T21n	J19	DQSn2T	DQ1T
7A	VREFB7A0	IO			DIFFIO TX T22n	DIFFOUT T22n	D22	DQ2T	DQ1T
7A	VREFB7A0	IO			DIFFIO RX T23p	DIFFOUT T23p	D20	DQ2T	DQ1T
7A	VREFB7A0	IO			DIFFIO TX T24p	DIFFOUT T24p	A25	DQ2T	DQ1T
7A	VREFB7A0	IO			DIFFIO RX T23n	DIFFOUT T23n	C19	DQ2T	DQ1T
7A	VREFB7A0	IO			DIFFIO TX T24n	DIFFOUT T24n	A24		
7A	VREFB7A0	IO			DIFFIO RX T25p	DIFFOUT T25p	F20		
7A	VREFB7A0	IO			DIFFIO TX T26p	DIFFOUT T26p	C24	DQ3T	DQ2T
7A	VREFB7A0	IO			DIFFIO RX T25n	DIFFOUT T25n	E20		
7A	VREFB7A0	IO			DIFFIO TX T26n	DIFFOUT T26n	B24	DQ3T	DQ2T
7A	VREFB7A0	IO			DIFFIO RX T27p	DIFFOUT T27p	F19	DQ3T	DQ2T
7A	VREFB7A0	IO			DIFFIO TX T28p	DIFFOUT T28p	B23	DQ3T	DQ2T
7A	VREFB7A0	IO			DIFFIO RX T27n	DIFFOUT T27n	E18	DQ3T	DQ2T
7A	VREFB7A0	IO			DIFFIO TX T28n	DIFFOUT T28n	A23	DQ3T	DQ2T
7A	VREFB7A0	IO			DIFFIO RX T29p	DIFFOUT T29p	L18	DQS3T	DQS2T
7A	VREFB7A0	IO			DIFFIO TX T30p	DIFFOUT T30p	B22		
7A	VREFB7A0	IO			DIFFIO RX T29n	DIFFOUT T29n	K18	DQSn3T	DQSn2T
7A	VREFB7A0	IO			DIFFIO TX T30n	DIFFOUT T30n	B21	DQ3T	DQ2T
7A	VREFB7A0	IO			DIFFIO RX T31p	DIFFOUT T31p	D19	DQ3T	DQ2T
7A	VREFB7A0	IO			DIFFIO TX T32p	DIFFOUT T32p	A21	DQ3T	DQ2T
7A	VREFB7A0	IO			DIFFIO RX T31n	DIFFOUT T31n	D18	DQ3T	DQ2T
7A	VREFB7A0	IO			DIFFIO TX T32n	DIFFOUT T32n	A20		
7A	VREFB7A0	IO	CLK11p		DIFFIO RX T33p	DIFFOUT T33p	H19		
7A	VREFB7A0	IO			DIFFIO TX T34p	DIFFOUT T34p	B19	DQ4T	DQ2T
7A	VREFB7A0	IO	CLK11n		DIFFIO RX T33n	DIFFOUT T33n	J18		
7A	VREFB7A0	IO			DIFFIO TX T34n	DIFFOUT T34n	A19	DQ4T	DQ2T
7A	VREFB7A0	IO			DIFFIO RX T35p	DIFFOUT T35p	G18	DQ4T	DQ2T
7A	VREFB7A0	IO			DIFFIO TX T36p	DIFFOUT T36p	B18	DQ4T	DQ2T
7A	VREFB7A0	IO			DIFFIO RX T35n	DIFFOUT T35n	F18	DQ4T	DQ2T
7A	VREFB7A0	IO			DIFFIO TX T36n	DIFFOUT T36n	A18	DQ4T	DQ2T
7A	VREFB7A0	IO			DIFFIO RX T37p	DIFFOUT T37p	K16	DQS4T	DQ2T
7A	VREFB7A0	IO			DIFFIO TX T38p	DIFFOUT T38p	D14		
7A	VREFB7A0	IO			DIFFIO RX T37n	DIFFOUT T37n	L16	DQSn4T	DQ2T
7A	VREFB7A0	IO			DIFFIO TX T38n	DIFFOUT T38n	C14	DQ4T	DQ2T
7A	VREFB7A0	IO			DIFFIO RX T39p	DIFFOUT T39p	C17	DQ4T	DQ2T
7A	VREFB7A0	IO			DIFFIO TX T40p	DIFFOUT T40p	A16	DQ4T	DQ2T
7A	VREFB7A0	IO			DIFFIO RX T39n	DIFFOUT T39n	B17	DQ4T	DQ2T
7A	VREFB7A0	IO			DIFFIO TX T40n	DIFFOUT T40n	A15		
7A	VREFB7A0	IO	CLK10p		DIFFIO RX T41p	DIFFOUT T41p	H17		
7A	VREFB7A0	IO			DIFFIO TX T42p	DIFFOUT T42p	B14	DQ5T	
7A	VREFB7A0	IO	CLK10n		DIFFIO RX T41n	DIFFOUT T41n	G17		
7A	VREFB7A0	IO			DIFFIO TX T42n	DIFFOUT T42n	A14	DQ5T	
7A	VREFB7A0	IO			DIFFIO RX T43p	DIFFOUT T43p	E17	DQ5T	
7A	VREFB7A0	IO			DIFFIO TX T44p	DIFFOUT T44p	D12	DQ5T	
7A	VREFB7A0	IO			DIFFIO RX T43n	DIFFOUT T43n	D17	DQ5T	
7A	VREFB7A0	IO			DIFFIO TX T44n	DIFFOUT T44n	C12	DQ5T	
7A	VREFB7A0	IO			DIFFIO RX T45p	DIFFOUT T45p	K17	DQS5T	
7A	VREFB7A0	IO			DIFFIO TX T46p	DIFFOUT T46p	B13		
7A	VREFB7A0	IO			DIFFIO RX T45n	DIFFOUT T45n	J17	DQSn5T	
7A	VREFB7A0	IO			DIFFIO TX T46n	DIFFOUT T46n	A13	DQ5T	
7A	VREFB7A0	IO			DIFFIO RX T47p	DIFFOUT T47p	C16	DQ5T	
7A	VREFB7A0	IO			DIFFIO TX T48p	DIFFOUT T48p	C11	DQ5T	
7A	VREFB7A0	IO			DIFFIO RX T47n	DIFFOUT T47n	C15	DQ5T	
7A	VREFB7A0	IO	RZQ 2		DIFFIO TX T48n	DIFFOUT T48n	B12		
8A	VREFB8A0	IO	CLK9p		DIFFIO RX T49p	DIFFOUT T49p	L15		



Pin Information for the Cyclone® V 5CGXBC9 Device  
Version 1.2  
Note (1)

Bank Number	VREF	Pin Name/Function	Optional Function(s)	Configuration Function	Dedicated Tx/Rx Channel	Emulated LVDS Output Channel	F896	DQS for X8	DQS for X16
8A	VREFB8AN0	IO			DIFFIO TX_T50p	DIFFOUT_T50p	B11	DQ6T	
8A	VREFB8AN0	IO	CLK9n		DIFFIO RX_T49n	DIFFOUT_T49n	K15		
8A	VREFB8AN0	IO			DIFFIO TX_T50n	DIFFOUT_T50n	A11	DQ6T	
8A	VREFB8AN0	IO			DIFFIO RX_T51p	DIFFOUT_T51p	F16	DQ6T	
8A	VREFB8AN0	IO	FPLL_TL_CLKOUT0,FPLL_TL_CLKOUTp,FPLL_TL_FB		DIFFIO TX_T52p	DIFFOUT_T52p	F9	DQ6T	
8A	VREFB8AN0	IO			DIFFIO RX_T51n	DIFFOUT_T51n	E16	DQ6T	
8A	VREFB8AN0	IO	FPLL_TL_CLKOUT1,FPLL_TL_CLKOUTn		DIFFIO TX_T52n	DIFFOUT_T52n	E10	DQ6T	
8A	VREFB8AN0	IO			DIFFIO RX_T53p	DIFFOUT_T53p	M9	DQS6T	
8A	VREFB8AN0	IO			DIFFIO TX_T54p	DIFFOUT_T54p	D9		
8A	VREFB8AN0	IO			DIFFIO RX_T53n	DIFFOUT_T53n	M8	DQS6T	
8A	VREFB8AN0	IO			DIFFIO TX_T54n	DIFFOUT_T54n	C10	DQ6T	
8A	VREFB8AN0	IO			DIFFIO RX_T55p	DIFFOUT_T55p	F15	DQ6T	
8A	VREFB8AN0	IO			DIFFIO TX_T56p	DIFFOUT_T56p	A10	DQ6T	
8A	VREFB8AN0	IO			DIFFIO RX_T55n	DIFFOUT_T55n	E15	DQ6T	
8A	VREFB8AN0	IO			DIFFIO TX_T56n	DIFFOUT_T56n	A9		
8A	VREFB8AN0	IO	CLK8p,FPLL_TL_FBp		DIFFIO RX_T57p	DIFFOUT_T57p	L14		
8A	VREFB8AN0	IO			DIFFIO TX_T58p	DIFFOUT_T58p	C9	DQ7T	
8A	VREFB8AN0	IO	CLK8n,FPLL_TL_FBn		DIFFIO RX_T57n	DIFFOUT_T57n	L13		
8A	VREFB8AN0	IO			DIFFIO TX_T58n	DIFFOUT_T58n	B8	DQ7T	
8A	VREFB8AN0	IO			DIFFIO RX_T59p	DIFFOUT_T59p	E12	DQ7T	
8A	VREFB8AN0	IO			DIFFIO TX_T60p	DIFFOUT_T60p	B7	DQ7T	
8A	VREFB8AN0	IO			DIFFIO RX_T59n	DIFFOUT_T59n	D13	DQ7T	
8A	VREFB8AN0	IO			DIFFIO TX_T60n	DIFFOUT_T60n	A8	DQ7T	
8A	VREFB8AN0	IO			DIFFIO RX_T61p	DIFFOUT_T61p	J15	DQS7T	
8A	VREFB8AN0	IO			DIFFIO TX_T62p	DIFFOUT_T62p	B6		
8A	VREFB8AN0	IO			DIFFIO RX_T61n	DIFFOUT_T61n	H15	DQS7T	
8A	VREFB8AN0	IO			DIFFIO TX_T62n	DIFFOUT_T62n	A6	DQ7T	
8A	VREFB8AN0	IO			DIFFIO RX_T63p	DIFFOUT_T63p	E11	DQ7T	
8A	VREFB8AN0	IO			DIFFIO TX_T64p	DIFFOUT_T64p	C7	DQ7T	
8A	VREFB8AN0	IO			DIFFIO RX_T63n	DIFFOUT_T63n	D10	DQ7T	
8A	VREFB8AN0	IO			DIFFIO TX_T64n	DIFFOUT_T64n	C6		
8A	VREFB8AN0	IO			DIFFIO RX_T65p	DIFFOUT_T65p	L10		
8A	VREFB8AN0	IO			DIFFIO TX_T66p	DIFFOUT_T66p	F13	DQ8T	
8A	VREFB8AN0	IO			DIFFIO RX_T65n	DIFFOUT_T65n	L9		
8A	VREFB8AN0	IO			DIFFIO TX_T66n	DIFFOUT_T66n	E13	DQ8T	
8A	VREFB8AN0	IO			DIFFIO RX_T67p	DIFFOUT_T67p	G14	DQ8T	
8A	VREFB8AN0	IO			DIFFIO TX_T68p	DIFFOUT_T68p	A5	DQ8T	
8A	VREFB8AN0	IO			DIFFIO RX_T67n	DIFFOUT_T67n	F14	DQ8T	
8A	VREFB8AN0	IO			DIFFIO TX_T68n	DIFFOUT_T68n	A4	DQ8T	
8A	VREFB8AN0	IO			DIFFIO RX_T69p	DIFFOUT_T69p	J14	DQS8T	
8A	VREFB8AN0	IO			DIFFIO TX_T70p	DIFFOUT_T70p	J7		
8A	VREFB8AN0	IO			DIFFIO RX_T69n	DIFFOUT_T69n	H14	DQS8T	
8A	VREFB8AN0	IO			DIFFIO TX_T70n	DIFFOUT_T70n	H7	DQ8T	
8A	VREFB8AN0	IO			DIFFIO RX_T71p	DIFFOUT_T71p	L11	DQ8T	
8A	VREFB8AN0	IO			DIFFIO TX_T72p	DIFFOUT_T72p	J9	DQ8T	
8A	VREFB8AN0	IO			DIFFIO RX_T71n	DIFFOUT_T71n	K11	DQ8T	
8A	VREFB8AN0	IO			DIFFIO TX_T72n	DIFFOUT_T72n	H9		
8A	VREFB8AN0	IO			DIFFIO RX_T73p	DIFFOUT_T73p	P12		
8A	VREFB8AN0	IO			DIFFIO TX_T74p	DIFFOUT_T74p	G9	DQ9T	DQ3T
8A	VREFB8AN0	IO			DIFFIO RX_T73n	DIFFOUT_T73n	N12		
8A	VREFB8AN0	IO			DIFFIO TX_T74n	DIFFOUT_T74n	F8	DQ9T	DQ3T
8A	VREFB8AN0	IO			DIFFIO RX_T75p	DIFFOUT_T75p	H12	DQ9T	DQ3T
8A	VREFB8AN0	IO			DIFFIO TX_T76p	DIFFOUT_T76p	E8	DQ9T	DQ3T
8A	VREFB8AN0	IO			DIFFIO RX_T75n	DIFFOUT_T75n	G12	DQ9T	DQ3T
8A	VREFB8AN0	IO			DIFFIO TX_T76n	DIFFOUT_T76n	D8	DQ9T	DQ3T
8A	VREFB8AN0	IO			DIFFIO RX_T77p	DIFFOUT_T77p	K13	DQS9T	DQS3T
8A	VREFB8AN0	IO			DIFFIO TX_T78p	DIFFOUT_T78p	A3		
8A	VREFB8AN0	IO			DIFFIO RX_T77n	DIFFOUT_T77n	J13	DQS9T	DQS3T
8A	VREFB8AN0	IO			DIFFIO TX_T78n	DIFFOUT_T78n	A2	DQ9T	DQ3T
8A	VREFB8AN0	IO			DIFFIO RX_T79p	DIFFOUT_T79p	P10	DQ9T	DQ3T
8A	VREFB8AN0	IO			DIFFIO TX_T80p	DIFFOUT_T80p	D7	DQ9T	DQ3T
8A	VREFB8AN0	IO			DIFFIO RX_T79n	DIFFOUT_T79n	N11	DQ9T	DQ3T
8A	VREFB8AN0	IO			DIFFIO TX_T80n	DIFFOUT_T80n	D6		
8A	VREFB8AN0	IO			DIFFIO RX_T81p	DIFFOUT_T81p	R12		
8A	VREFB8AN0	IO			DIFFIO TX_T82p	DIFFOUT_T82p	E7	DQ10T	DQ3T
8A	VREFB8AN0	IO			DIFFIO RX_T81n	DIFFOUT_T81n	R11		
8A	VREFB8AN0	IO			DIFFIO TX_T82n	DIFFOUT_T82n	E6	DQ10T	DQ3T
8A	VREFB8AN0	IO			DIFFIO RX_T83p	DIFFOUT_T83p	K12	DQ10T	DQ3T
8A	VREFB8AN0	IO			DIFFIO TX_T84p	DIFFOUT_T84p	K10	DQ10T	DQ3T
8A	VREFB8AN0	IO			DIFFIO RX_T83n	DIFFOUT_T83n	J12	DQ10T	DQ3T
8A	VREFB8AN0	IO			DIFFIO TX_T84n	DIFFOUT_T84n	J10	DQ10T	DQ3T
8A	VREFB8AN0	IO			DIFFIO RX_T85p	DIFFOUT_T85p	N10	DQS10T	DQ3T
8A	VREFB8AN0	IO			DIFFIO TX_T86p	DIFFOUT_T86p	G6		
8A	VREFB8AN0	IO			DIFFIO RX_T85n	DIFFOUT_T85n	N9	DQS10T	DQ3T
8A	VREFB8AN0	IO			DIFFIO TX_T86n	DIFFOUT_T86n	F6	DQ10T	DQ3T
8A	VREFB8AN0	IO			DIFFIO RX_T87p	DIFFOUT_T87p	M12	DQ10T	DQ3T
8A	VREFB8AN0	IO			DIFFIO TX_T88p	DIFFOUT_T88p	G8	DQ10T	DQ3T
8A	VREFB8AN0	IO			DIFFIO RX_T87n	DIFFOUT_T87n	M11	DQ10T	DQ3T



Pin Information for the Cyclone® V 5CGXBC9 Device  
Version 1.2  
Note (1)

Bank Number	VREF	Pin Name/Function	Optional Function(s)	Configuration Function	Dedicated Tx/Rx Channel	Emulated LVDS Output Channel	F896	DQS for X8	DQS for X16
8A	VREFB8AN0	IO			DIFFIO_TX_T88n	DIFFOUT_T88n	G7		
9A		MSEL0		MSEL0			T8		
9A		CONF_DONE		CONF_DONE			L8		
9A		MSEL1		MSEL1			P9		
9A		nSTATUS		nSTATUS			K7		
9A		nCE		nCE			H6		
9A		MSEL2		MSEL2			G5		
9A		MSEL3		MSEL3			P7		
9A		nCONFIG		nCONFIG			C5		
9A		MSEL4		MSEL4			M7		
9A		GND					E5		
		GND					F22		
		GND					AK2		
		GND					AK14		
		GND					AK24		
		GND					AK29		
		GND					AJ6		
		GND					AJ11		
		GND					AJ21		
		GND					AH1		
		GND					AH2		
		GND					AH3		
		GND					AH8		
		GND					AH18		
		GND					AH28		
		GND					AG3		
		GND					AG4		
		GND					AG15		
		GND					AG25		
		GND					AF1		
		GND					AF2		
		GND					AF5		
		GND					AF12		
		GND					AF22		
		GND					AE3		
		GND					AE4		
		GND					AE6		
		GND					AE9		
		GND					AE19		
		GND					AE29		
		GND					AD1		
		GND					AD2		
		GND					AD5		
		GND					AD7		
		GND					AD16		
		GND					AD26		
		GND					AC3		
		GND					AC4		
		GND					AC6		
		GND					AC13		
		GND					AC23		
		GND					AB1		
		GND					AB2		
		GND					AB5		
		GND					AB10		
		GND					AB20		
		GND					AB30		
		GND					AA3		
		GND					AA4		
		GND					AA6		
		GND					AA17		
		GND					AA27		
		GND					Y1		
		GND					Y2		
		GND					Y5		
		GND					Y7		
		GND					Y14		
		GND					Y24		
		GND					W3		
		GND					W4		
		GND					W6		
		GND					W11		
		GND					W13		
		GND					W15		
		GND					W17		
		GND					W19		
		GND					W21		
		GND					V1		



Bank Number	VREF	Pin Name/Function	Optional Function(s)	Configuration Function	Dedicated Tx/Rx Channel	Emulated LVDS Output Channel	F896	DQS for X8	DQS for X16
		GND					V2		
		GND					V5		
		GND					V8		
		GND					V14		
		GND					V16		
		GND					V18		
		GND					V20		
		GND					V23		
		GND					V28		
		GND					U3		
		GND					U4		
		GND					U6		
		GND					U13		
		GND					U15		
		GND					U17		
		GND					U19		
		GND					U25		
		GND					T1		
		GND					T2		
		GND					T5		
		GND					T12		
		GND					T14		
		GND					T16		
		GND					T18		
		GND					T20		
		GND					T22		
		GND					R3		
		GND					R4		
		GND					R6		
		GND					R9		
		GND					R13		
		GND					R15		
		GND					R17		
		GND					R19		
		GND					R29		
		GND					P1		
		GND					P2		
		GND					P5		
		GND					P11		
		GND					P14		
		GND					P16		
		GND					P18		
		GND					P26		
		GND					N3		
		GND					N4		
		GND					N6		
		GND					N8		
		GND					N13		
		GND					N15		
		GND					N17		
		GND					N19		
		GND					N23		
		GND					M1		
		GND					M2		
		GND					M5		
		GND					M10		
		GND					M14		
		GND					M16		
		GND					M18		
		GND					M20		
		GND					M30		
		GND					L3		
		GND					L4		
		GND					L6		
		GND					L17		
		GND					L27		
		GND					K1		
		GND					K2		
		GND					K5		
		GND					K9		
		GND					K14		
		GND					K24		
		GND					J3		
		GND					J4		
		GND					J6		
		GND					J11		
		GND					J21		
		GND					H1		





Pin Information for the Cyclone® V 5CGXBC9 Device  
Version 1.2  
Note (1)

Bank Number	VREF	Pin Name/Function	Optional Function(s)	Configuration Function	Dedicated Tx/Rx Channel	Emulated LVDS Output Channel	F896	DQS for X8	DQS for X16
		GND					H2		
		GND					H5		
		GND					H8		
		GND					H11		
		GND					H18		
		GND					H28		
		GND					G3		
		GND					G4		
		GND					G15		
		GND					G25		
		GND					F1		
		GND					F2		
		GND					F5		
		GND					F12		
		GND					E3		
		GND					E4		
		GND					E9		
		GND					E19		
		GND					E29		
		GND					D1		
		GND					D2		
		GND					D5		
		GND					D16		
		GND					D26		
		GND					C2		
		GND					C3		
		GND					C4		
		GND					C13		
		GND					C23		
		GND					B1		
		GND					B2		
		GND					B10		
		GND					B20		
		GND					B30		
		GND					A12		
		GND					A17		
		GND					A27		
		VCC					M15		
		VCC					W14		
		VCC					W16		
		VCC					W18		
		VCC					W20		
		VCC					V13		
		VCC					V15		
		VCC					V17		
		VCC					V19		
		VCC					U14		
		VCC					U16		
		VCC					U18		
		VCC					U20		
		VCC					T13		
		VCC					T15		
		VCC					T17		
		VCC					T19		
		VCC					R14		
		VCC					R16		
		VCC					R18		
		VCC					P13		
		VCC					P15		
		VCC					P17		
		VCC					P19		
		VCC					N14		
		VCC					N16		
		VCC					N18		
		VCC					M13		
		VCC					M17		
		VCC					M19		
		DNU					B4		
		DNU					B3		
		DNU					AD8		
		DNU					AD14		
		DNU					F24		
		DNU					D15		
		VCCPGM					AC11		
		VCCPGM					AB24		
		VCCPGM					F10		
		VCCBAT					H10		
		VCCIO3A					U10		



Bank Number	VREF	Pin Name/Function	Optional Function(s)	Configuration Function	Dedicated Tx/Rx Channel	Emulated LVDS Output Channel	F896	DQS for X8	DQS for X16
		VCCIO3A					AD11		
		VCCIO3A					AC8		
		VCCIO3A					Y9		
		VCCIO3B					AA12		
		VCCIO3B					AK4		
		VCCIO3B					AK9		
		VCCIO3B					AH13		
		VCCIO3B					AG10		
		VCCIO3B					AE14		
		VCCIO4A					AK19		
		VCCIO4A					AJ16		
		VCCIO4A					AJ26		
		VCCIO4A					AH23		
		VCCIO4A					AG20		
		VCCIO4A					AF17		
		VCCIO4A					AD21		
		VCCIO4A					AC18		
		VCCIO4A					AB15		
		VCCIO4A					Y19		
		VCCIO5A					AF27		
		VCCIO5A					AE24		
		VCCIO5A					AB25		
		VCCIO5A					AA22		
		VCCIO5B					AG30		
		VCCIO5B					AC28		
		VCCIO5B					Y29		
		VCCIO5B					W26		
		VCCIO5B					U30		
		VCCIO5B					T27		
		VCCIO6A					R24		
		VCCIO6A					P21		
		VCCIO6A					N28		
		VCCIO6A					M25		
		VCCIO6A					L22		
		VCCIO6A					K29		
		VCCIO6A					J26		
		VCCIO6A					G30		
		VCCIO6A					F27		
		VCCIO6A					C28		
		VCCIO7A					K19		
		VCCIO7A					H23		
		VCCIO7A					G20		
		VCCIO7A					F17		
		VCCIO7A					E24		
		VCCIO7A					D21		
		VCCIO7A					C18		
		VCCIO7A					B15		
		VCCIO7A					B25		
		VCCIO7A					A22		
		VCCIO8A					A7		
		VCCIO8A					L12		
		VCCIO8A					J16		
		VCCIO8A					J16		
		VCCIO8A					H13		
		VCCIO8A					G10		
		VCCIO8A					F7		
		VCCIO8A					E14		
		VCCIO8A					D11		
		VCCIO8A					C8		
		VCCIO8A					B5		
		VCCPD3A					AD10		
		VCCPD3A					AB11		
		VCCPD3B4A					AC20		
		VCCPD3B4A					AE11		
		VCCPD3B4A					AE21		
		VCCPD3B4A					AD15		
		VCCPD3B4A					AC12		
		VCCPD3B4A					AC17		
		VCCPD5A					W23		
		VCCPD5A					W25		
		VCCPD5B					U24		
		VCCPD5B					T26		
		VCCPD6A					P24		
		VCCPD6A					M24		
		VCCPD6A					K23		
		VCCPD7A8A					D24		
		VCCPD7A8A					G13		
		VCCPD7A8A					G16		
		VCCPD7A8A					G19		



Bank Number	VREF	Pin Name/Function	Optional Function(s)	Configuration Function	Dedicated Tx/Rx Channel	Emulated LVDS Output Channel	F896	DQS for X8	DQS for X16
		VCCPD7A8A					F11		
		VCCPD7A8A					F21		
		VCCPD7A8A					F23		
3A	VREFB3AN0	VREFB3AN0					AE8		
3B	VREFB3BN0	VREFB3BN0					AJ13		
4A	VREFB4AN0	VREFB4AN0					AH16		
5A	VREFB5AN0	VREFB5AN0					AC25		
5B	VREFB5BN0	VREFB5BN0					P27		
6A	VREFB6AN0	VREFB6AN0					M26		
7A	VREFB7AN0	VREFB7AN0					B16		
8A	VREFB8AN0	VREFB8AN0					B9		
		VCCH GXBL					AB6		
		VCCH GXBL					V6		
		VCCH GXBL					P6		
		VCCH GXBL					K6		
		VCCL GXBL					AC5		
		VCCL GXBL					W5		
		VCCL GXBL					R5		
		VCCL GXBL					L5		
		RREF TL					C1		
		VCCA FPLL					Y8		
		VCCA FPLL					J8		
		VCCA FPLL					AB23		
		VCCA FPLL					J24		
		VCC AUX					G11		
		VCC AUX					AC10		
		VCC AUX					AD22		
		VCC AUX					AC16		
		VCC AUX					H16		
		VCC AUX					H22		
		VCCE GXBL					AD6		
		VCCE GXBL					AA5		
		VCCE GXBL					Y6		
		VCCE GXBL					U5		
		VCCE GXBL					T6		
		VCCE GXBL					N5		
		VCCE GXBL					M6		
		VCCE GXBL					J5		

Note:

(1) For more information about pin definition and pin connection guidelines, refer to the [Cyclone V Device Family Pin Connection Guidelines](#).



Bank Number	VREF	Pin Name/Function	Optional Function(s)	Configuration Function	Dedicated Tx/Rx Channel	Emulated LVDS Output Channel	F1152	DQS for X8	DQS for X16
GXB L3		REFCLK3Ln					P10		
GXB L3		REFCLK3Lp					R11		
GXB L3		GXB_TX_L11n					F3		
GXB L3		GXB_TX_L11p					F4		
GXB L3		GXB_RX_L11p,GXB_REFCLK_L11p					G2		
GXB L3		GXB_RX_L11n,GXB_REFCLK_L11n					G1		
GXB L3		GXB_TX_L10n					H3		
GXB L3		GXB_TX_L10p					H4		
GXB L3		GXB_RX_L10p,GXB_REFCLK_L10p					J2		
GXB L3		GXB_RX_L10n,GXB_REFCLK_L10n					J1		
GXB L3		GXB_TX_L9n					K3		
GXB L3		GXB_TX_L9p					K4		
GXB L3		GXB_RX_L9p,GXB_REFCLK_L9p					L2		
GXB L3		GXB_RX_L9n,GXB_REFCLK_L9n					L1		
GXB L2		GXB_TX_L8n					M3		
GXB L2		GXB_TX_L8p					M4		
GXB L2		GXB_RX_L8p,GXB_REFCLK_L8p					N2		
GXB L2		GXB_RX_L8n,GXB_REFCLK_L8n					N1		
GXB L2		GXB_TX_L7n					P3		
GXB L2		GXB_TX_L7p					P4		
GXB L2		GXB_RX_L7p,GXB_REFCLK_L7p					R2		
GXB L2		GXB_RX_L7n,GXB_REFCLK_L7n					R1		
GXB L2		GXB_TX_L6n					T3		
GXB L2		GXB_TX_L6p					T4		
GXB L2		GXB_RX_L6p,GXB_REFCLK_L6p					U2		
GXB L2		GXB_RX_L6n,GXB_REFCLK_L6n					U1		
GXB L2		REFCLK2Lp					U11		
GXB L2		REFCLK2Ln					T10		
GXB L1		REFCLK1Ln					V10		
GXB L1		REFCLK1Lp					W11		
GXB L1		GXB_TX_L5n					V3		
GXB L1		GXB_TX_L5p					V4		
GXB L1		GXB_RX_L5p,GXB_REFCLK_L5p					W2		
GXB L1		GXB_RX_L5n,GXB_REFCLK_L5n					W1		
GXB L1		GXB_TX_L4n					Y3		
GXB L1		GXB_TX_L4p					Y4		
GXB L1		GXB_RX_L4p,GXB_REFCLK_L4p					AA2		
GXB L1		GXB_RX_L4n,GXB_REFCLK_L4n					AA1		
GXB L1		GXB_TX_L3n					AB3		
GXB L1		GXB_TX_L3p					AB4		
GXB L1		GXB_RX_L3p,GXB_REFCLK_L3p					AC2		
GXB L1		GXB_RX_L3n,GXB_REFCLK_L3n					AC1		
GXB L0		GXB_TX_L2n					AD3		
GXB L0		GXB_TX_L2p					AD4		
GXB L0		GXB_RX_L2p,GXB_REFCLK_L2p					AE2		
GXB L0		GXB_RX_L2n,GXB_REFCLK_L2n					AE1		
GXB L0		GXB_TX_L1n					AF3		
GXB L0		GXB_TX_L1p					AF4		
GXB L0		GXB_RX_L1p,GXB_REFCLK_L1p					AG2		
GXB L0		GXB_RX_L1n,GXB_REFCLK_L1n					AG1		
GXB L0		GXB_TX_L0n					AH3		
GXB L0		GXB_TX_L0p					AH4		
GXB L0		GXB_RX_L0p,GXB_REFCLK_L0p					AJ2		
GXB L0		GXB_RX_L0n,GXB_REFCLK_L0n					AJ1		
GXB L0		REFCLK0Lp					AA11		
GXB L0		REFCLK0Ln					AB10		
3A		TDO		TDO			AF11		
3A		nCSO		DATA4			AG10		
3A		TMS		TMS			AG11		
3A		AS_DATA3		DATA3			AJ6		
3A		TCK		TCK			AK5		
3A		AS_DATA2		DATA2			AH8		
3A		TDI		TDI			AE10		
3A		AS_DATA1		DATA1			AJ7		
3A		DCLK		DCLK			AF10		
3A		AS_DATA0,ASDO		DATA0			AH9		
3A	VREFB3A0	IO		DATA6	DIFFIO RX B1n	DIFFOUT B1n	AD11	DQ1B	
3A	VREFB3A0	IO		DATA5	DIFFIO TX B2n	DIFFOUT B2n	AM4		
3A	VREFB3A0	IO		DATA8	DIFFIO RX B1p	DIFFOUT B1p	AD12	DQ1B	
3A	VREFB3A0	IO		DATA7	DIFFIO TX B2p	DIFFOUT B2p	AM5	DQ1B	
3A	VREFB3A0	IO		DATA10	DIFFIO RX B3n	DIFFOUT B3n	AJ11	DQS1B	
3A	VREFB3A0	IO		DATA9	DIFFIO TX B4n	DIFFOUT B4n	AL7	DQ1B	
3A	VREFB3A0	IO		DATA12	DIFFIO RX B3p	DIFFOUT B3p	AH12	DQS1B	
3A	VREFB3A0	IO		DATA11	DIFFIO TX B4p	DIFFOUT B4p	AK7		
3A	VREFB3A0	IO		DATA14	DIFFIO RX B5n	DIFFOUT B5n	AG13	DQ1B	
3A	VREFB3A0	IO		DATA13	DIFFIO TX B6n	DIFFOUT B6n	AL8	DQ1B	
3A	VREFB3A0	IO		CLKUSR	DIFFIO RX B5p	DIFFOUT B5p	AF13	DQ1B	
3A	VREFB3A0	IO		DATA15	DIFFIO TX B6p	DIFFOUT B6p	AK8	DQ1B	



Pin Information for the Cyclone® V 5CGXBC9 Device  
Version 1.2  
Note (1)

Bank Number	VREF	Pin Name/Function	Optional Function(s)	Configuration Function	Dedicated Tx/Rx Channel	Emulated LVDS Output Channel	F1152	DQS for X8	DQS for X16
3A	VREFB3A0	IO		PR_DONE	DIFFIO_RX_B7n	DIFFOUT_B7n	AC12		
3A	VREFB3A0	IO		PR_READY	DIFFIO_TX_B8n	DIFFOUT_B8n	AK9	DQ1B	
3A	VREFB3A0	IO		PR_ERROR	DIFFIO_RX_B7p	DIFFOUT_B7p	AC13		
3A	VREFB3A0	IO			DIFFIO_TX_B8p	DIFFOUT_B8p	AJ9	DQ1B	
3A	VREFB3A0	IO			DIFFIO_TX_B9n	DIFFOUT_B9n	AM6		
3A	VREFB3A0	IO			DIFFIO_RX_B10n	DIFFOUT_B10n	AK10	DQ2B	DO1B
3A	VREFB3A0	IO			DIFFIO_TX_B9p	DIFFOUT_B9p	AL6	DQ2B	DO1B
3A	VREFB3A0	IO			DIFFIO_RX_B10p	DIFFOUT_B10p	AJ10	DQ2B	DO1B
3A	VREFB3A0	IO			DIFFIO_RX_B11n	DIFFOUT_B11n	AB13	DQSn2B	DO1B
3A	VREFB3A0	IO			DIFFIO_TX_B12n	DIFFOUT_B12n	AN4	DQ2B	DO1B
3A	VREFB3A0	IO			DIFFIO_RX_B11p	DIFFOUT_B11p	AB14	DQS2B	DO1B
3A	VREFB3A0	IO			DIFFIO_TX_B12p	DIFFOUT_B12p	AN5		
3A	VREFB3A0	IO			DIFFIO_TX_B13n	DIFFOUT_B13n	AP5	DQ2B	DO1B
3A	VREFB3A0	IO			DIFFIO_RX_B14n	DIFFOUT_B14n	AJ12	DQ2B	DO1B
3A	VREFB3A0	IO			DIFFIO_TX_B13p	DIFFOUT_B13p	AP6	DQ2B	DO1B
3A	VREFB3A0	IO			DIFFIO_RX_B14p	DIFFOUT_B14p	AH13	DQ2B	DO1B
3A	VREFB3A0	IO			DIFFIO_RX_B15n	DIFFOUT_B15n	AE14		
3A	VREFB3A0	IO			DIFFIO_TX_B16n	DIFFOUT_B16n	AP7	DQ2B	DO1B
3A	VREFB3A0	IO			DIFFIO_RX_B15p	DIFFOUT_B15p	AD14		
3A	VREFB3A0	IO			DIFFIO_TX_B16p	DIFFOUT_B16p	AN7	DQ2B	DO1B
3A	VREFB3A0	IO			DIFFIO_TX_B17n	DIFFOUT_B17n	AN8		
3A	VREFB3A0	IO			DIFFIO_RX_B18n	DIFFOUT_B18n	AH14	DQ3B	DO1B
3A	VREFB3A0	IO			DIFFIO_TX_B17p	DIFFOUT_B17p	AM8	DQ3B	DO1B
3A	VREFB3A0	IO			DIFFIO_RX_B18p	DIFFOUT_B18p	AG14	DQ3B	DO1B
3A	VREFB3A0	IO			DIFFIO_RX_B19n	DIFFOUT_B19n	AC14	DQSn3B	DQSn1B
3A	VREFB3A0	IO			DIFFIO_TX_B20n	DIFFOUT_B20n	AN9	DQ3B	DO1B
3A	VREFB3A0	IO			DIFFIO_RX_B19p	DIFFOUT_B19p	AD15	DQS3B	DQS1B
3A	VREFB3A0	IO			DIFFIO_TX_B20p	DIFFOUT_B20p	AM9		
3A	VREFB3A0	IO			DIFFIO_TX_B21n	DIFFOUT_B21n	AM10	DQ3B	DO1B
3A	VREFB3A0	IO			DIFFIO_RX_B22n	DIFFOUT_B22n	AK14	DQ3B	DO1B
3A	VREFB3A0	IO			DIFFIO_TX_B21p	DIFFOUT_B21p	AL10	DQ3B	DO1B
3A	VREFB3A0	IO			DIFFIO_RX_B22p	DIFFOUT_B22p	AJ14	DQ3B	DO1B
3A	VREFB3A0	IO			DIFFIO_RX_B23n	DIFFOUT_B23n	AB15		
3A	VREFB3A0	IO			DIFFIO_TX_B24n	DIFFOUT_B24n	AK12	DQ3B	DO1B
3A	VREFB3A0	IO			DIFFIO_RX_B23p	DIFFOUT_B23p	AA15		
3A	VREFB3A0	IO			DIFFIO_TX_B24p	DIFFOUT_B24p	AK13	DQ3B	DO1B
3B	VREFB3B0	IO			DIFFIO_TX_B25n	DIFFOUT_B25n	AM11		
3B	VREFB3B0	IO			DIFFIO_RX_B26n	DIFFOUT_B26n	AM15	DQ4B	DO2B
3B	VREFB3B0	IO			DIFFIO_TX_B25p	DIFFOUT_B25p	AL11	DQ4B	DO2B
3B	VREFB3B0	IO			DIFFIO_RX_B26p	DIFFOUT_B26p	AL15	DQ4B	DO2B
3B	VREFB3B0	IO			DIFFIO_RX_B27n	DIFFOUT_B27n	AG15	DQSn4B	DO2B
3B	VREFB3B0	IO			DIFFIO_TX_B28n	DIFFOUT_B28n	AP9	DQ4B	DO2B
3B	VREFB3B0	IO			DIFFIO_RX_B27p	DIFFOUT_B27p	AG16	DQS4B	DO2B
3B	VREFB3B0	IO			DIFFIO_TX_B28p	DIFFOUT_B28p	AP10		
3B	VREFB3B0	IO			DIFFIO_TX_B29n	DIFFOUT_B29n	AP11	DQ4B	DO2B
3B	VREFB3B0	IO			DIFFIO_RX_B30n	DIFFOUT_B30n	AK15	DQ4B	DO2B
3B	VREFB3B0	IO			DIFFIO_TX_B29p	DIFFOUT_B29p	AN11	DQ4B	DO2B
3B	VREFB3B0	IO			DIFFIO_RX_B30p	DIFFOUT_B30p	AJ15	DQ4B	DO2B
3B	VREFB3B0	IO			DIFFIO_RX_B31n	DIFFOUT_B31n	AD16		
3B	VREFB3B0	IO			DIFFIO_TX_B32n	DIFFOUT_B32n	AL13	DQ4B	DO2B
3B	VREFB3B0	IO			DIFFIO_RX_B31p	DIFFOUT_B31p	AC16		
3B	VREFB3B0	IO			DIFFIO_TX_B32p	DIFFOUT_B32p	AL12	DQ4B	DO2B
3B	VREFB3B0	IO			DIFFIO_TX_B33n	DIFFOUT_B33n	AP12		
3B	VREFB3B0	IO			DIFFIO_RX_B34n	DIFFOUT_B34n	AN14	DQ5B	DO2B
3B	VREFB3B0	IO			DIFFIO_TX_B33p	DIFFOUT_B33p	AN12	DQ5B	DO2B
3B	VREFB3B0	IO			DIFFIO_RX_B34p	DIFFOUT_B34p	AM14	DQ5B	DO2B
3B	VREFB3B0	IO			DIFFIO_RX_B35n	DIFFOUT_B35n	AB16	DQSn5B	DQSn2B
3B	VREFB3B0	IO			DIFFIO_TX_B36n	DIFFOUT_B36n	AN13	DQ5B	DO2B
3B	VREFB3B0	IO			DIFFIO_RX_B35p	DIFFOUT_B35p	AA16	DQS5B	DQS2B
3B	VREFB3B0	IO			DIFFIO_TX_B36p	DIFFOUT_B36p	AM13		
3B	VREFB3B0	IO			DIFFIO_TX_B37n	DIFFOUT_B37n	AM16	DQ5B	DO2B
3B	VREFB3B0	IO			DIFFIO_RX_B38n	DIFFOUT_B38n	AJ16	DQ5B	DO2B
3B	VREFB3B0	IO			DIFFIO_TX_B37p	DIFFOUT_B37p	AL16	DQ5B	DO2B
3B	VREFB3B0	IO			DIFFIO_RX_B38p	DIFFOUT_B38p	AH16	DQ5B	DO2B
3B	VREFB3B0	IO	CLK0n,FPLL_BL_FBn		DIFFIO_RX_B39n	DIFFOUT_B39n	AC17		
3B	VREFB3B0	IO			DIFFIO_TX_B40n	DIFFOUT_B40n	AP14	DQ5B	DO2B
3B	VREFB3B0	IO	CLK0p,FPLL_BL_FBp		DIFFIO_RX_B39p	DIFFOUT_B39p	AD17		
3B	VREFB3B0	IO			DIFFIO_TX_B40p	DIFFOUT_B40p	AP15	DQ5B	DO2B
3B	VREFB3B0	IO			DIFFIO_TX_B41n	DIFFOUT_B41n	AP16		
3B	VREFB3B0	IO			DIFFIO_RX_B42n	DIFFOUT_B42n	AP17	DQ6B	
3B	VREFB3B0	IO			DIFFIO_TX_B41p	DIFFOUT_B41p	AN16	DQ6B	
3B	VREFB3B0	IO			DIFFIO_RX_B42p	DIFFOUT_B42p	AN17	DQ6B	
3B	VREFB3B0	IO			DIFFIO_RX_B43n	DIFFOUT_B43n	AA17	DQSn6B	
3B	VREFB3B0	IO			DIFFIO_TX_B44n	DIFFOUT_B44n	AL17	DQ6B	
3B	VREFB3B0	IO			DIFFIO_RX_B43p	DIFFOUT_B43p	AA18	DQS6B	
3B	VREFB3B0	IO			DIFFIO_TX_B44p	DIFFOUT_B44p	AK17		
3B	VREFB3B0	IO	FPLL_BL_CLKOUT1,FPLL_BL_CLKOUTn		DIFFIO_TX_B45n	DIFFOUT_B45n	AN18	DQ6B	
3B	VREFB3B0	IO			DIFFIO_RX_B46n	DIFFOUT_B46n	AJ17	DQ6B	



Pin Information for the Cyclone® V 5CGXBC9 Device  
Version 1.2  
Note (1)

Bank Number	VREF	Pin Name/Function	Optional Function(s)	Configuration Function	Dedicated Tx/Rx Channel	Emulated LVDS Output Channel	F1152	DQS for X8	DQS for X16
3B	VREFB3BN0	IO	FPLL_CLKOUT0,FPLL_CLKOUTp,FPLL_CLK_FB		DIFFIO TX B45p	DIFFOUT B45p	AM18	DQ6B	
3B	VREFB3BN0	IO			DIFFIO RX B46p	DIFFOUT B46p	AH17	DQ6B	
3B	VREFB3BN0	IO	CLK1n		DIFFIO RX B47n	DIFFOUT B47n	AB18		
3B	VREFB3BN0	IO			DIFFIO TX B48n	DIFFOUT B48n	AL18	DQ6B	
3B	VREFB3BN0	IO	CLK1p		DIFFIO RX B47p	DIFFOUT B47p	AC18		
3B	VREFB3BN0	IO			DIFFIO TX B48p	DIFFOUT B48p	AK18	DQ6B	
4A	VREFB4AN0	IO	RZQ_0		DIFFIO TX B49n	DIFFOUT B49n	AP19		
4A	VREFB4AN0	IO			DIFFIO RX B50n	DIFFOUT B50n	AN19	DQ7B	
4A	VREFB4AN0	IO			DIFFIO TX B49p	DIFFOUT B49p	AP20	DQ7B	
4A	VREFB4AN0	IO			DIFFIO RX B50p	DIFFOUT B50p	AM19	DQ7B	
4A	VREFB4AN0	IO			DIFFIO RX B51n	DIFFOUT B51n	AC19	DQS7B	
4A	VREFB4AN0	IO			DIFFIO TX B52n	DIFFOUT B52n	AP21	DQ7B	
4A	VREFB4AN0	IO			DIFFIO RX B51p	DIFFOUT B51p	AB19	DQS7B	
4A	VREFB4AN0	IO			DIFFIO TX B52p	DIFFOUT B52p	AN21		
4A	VREFB4AN0	IO			DIFFIO TX B53n	DIFFOUT B53n	AK19	DQ7B	
4A	VREFB4AN0	IO			DIFFIO RX B54n	DIFFOUT B54n	AH19	DQ7B	
4A	VREFB4AN0	IO			DIFFIO TX B53p	DIFFOUT B53p	AJ19	DQ7B	
4A	VREFB4AN0	IO			DIFFIO RX B54p	DIFFOUT B54p	AG19	DQ7B	
4A	VREFB4AN0	IO	CLK2n		DIFFIO RX B55n	DIFFOUT B55n	AG18		
4A	VREFB4AN0	IO			DIFFIO TX B56n	DIFFOUT B56n	AM21	DQ7B	
4A	VREFB4AN0	IO	CLK2p		DIFFIO RX B55p	DIFFOUT B55p	AF18		
4A	VREFB4AN0	IO			DIFFIO TX B56p	DIFFOUT B56p	AL21	DQ7B	
4A	VREFB4AN0	IO			DIFFIO TX B57n	DIFFOUT B57n	AP22		
4A	VREFB4AN0	IO			DIFFIO RX B58n	DIFFOUT B58n	AM20	DQ8B	DQ3B
4A	VREFB4AN0	IO			DIFFIO TX B57p	DIFFOUT B57p	AN22	DQ8B	DQ3B
4A	VREFB4AN0	IO			DIFFIO RX B58p	DIFFOUT B58p	AL20	DQ8B	DQ3B
4A	VREFB4AN0	IO			DIFFIO RX B59n	DIFFOUT B59n	AE19	DQS8B	DQ3B
4A	VREFB4AN0	IO			DIFFIO TX B60n	DIFFOUT B60n	AN23	DQ8B	DQ3B
4A	VREFB4AN0	IO			DIFFIO RX B59p	DIFFOUT B59p	AD19	DQS8B	DQ3B
4A	VREFB4AN0	IO			DIFFIO TX B60p	DIFFOUT B60p	AM23		
4A	VREFB4AN0	IO			DIFFIO TX B61n	DIFFOUT B61n	AP26	DQ8B	DQ3B
4A	VREFB4AN0	IO			DIFFIO RX B62n	DIFFOUT B62n	AP24	DQ8B	DQ3B
4A	VREFB4AN0	IO			DIFFIO TX B61p	DIFFOUT B61p	AN26	DQ8B	DQ3B
4A	VREFB4AN0	IO			DIFFIO RX B62p	DIFFOUT B62p	AP25	DQ8B	DQ3B
4A	VREFB4AN0	IO	CLK3n		DIFFIO RX B63n	DIFFOUT B63n	AE20		
4A	VREFB4AN0	IO			DIFFIO TX B64n	DIFFOUT B64n	AN24	DQ8B	DQ3B
4A	VREFB4AN0	IO	CLK3p		DIFFIO TX B63p	DIFFOUT B63p	AD20		
4A	VREFB4AN0	IO			DIFFIO TX B64p	DIFFOUT B64p	AM24	DQ8B	DQ3B
4A	VREFB4AN0	IO			DIFFIO TX B65n	DIFFOUT B65n	AL22		
4A	VREFB4AN0	IO			DIFFIO RX B66n	DIFFOUT B66n	AP27	DQ9B	DQ3B
4A	VREFB4AN0	IO			DIFFIO TX B65p	DIFFOUT B65p	AK22	DQ9B	DQ3B
4A	VREFB4AN0	IO			DIFFIO RX B66p	DIFFOUT B66p	AN27	DQ9B	DQ3B
4A	VREFB4AN0	IO			DIFFIO RX B67n	DIFFOUT B67n	AK20	DQS9B	DQS3B
4A	VREFB4AN0	IO			DIFFIO TX B68n	DIFFOUT B68n	AJ21	DQ9B	DQ3B
4A	VREFB4AN0	IO			DIFFIO RX B67p	DIFFOUT B67p	AJ20	DQS9B	DQS3B
4A	VREFB4AN0	IO			DIFFIO TX B68p	DIFFOUT B68p	AJ22		
4A	VREFB4AN0	IO			DIFFIO TX B69n	DIFFOUT B69n	AP29	DQ9B	DQ3B
4A	VREFB4AN0	IO			DIFFIO RX B70n	DIFFOUT B70n	AH21	DQ9B	DQ3B
4A	VREFB4AN0	IO			DIFFIO TX B69p	DIFFOUT B69p	AP30	DQ9B	DQ3B
4A	VREFB4AN0	IO			DIFFIO RX B70p	DIFFOUT B70p	AH22	DQ9B	DQ3B
4A	VREFB4AN0	IO			DIFFIO RX B71n	DIFFOUT B71n	AB20		
4A	VREFB4AN0	IO			DIFFIO TX B72n	DIFFOUT B72n	AN28	DQ9B	DQ3B
4A	VREFB4AN0	IO			DIFFIO RX B71p	DIFFOUT B71p	AB21		
4A	VREFB4AN0	IO			DIFFIO TX B72p	DIFFOUT B72p	AM28	DQ9B	DQ3B
4A	VREFB4AN0	IO			DIFFIO TX B73n	DIFFOUT B73n	AM25		
4A	VREFB4AN0	IO			DIFFIO RX B74n	DIFFOUT B74n	AL23	DQ10B	DQ4B
4A	VREFB4AN0	IO			DIFFIO TX B73p	DIFFOUT B73p	AL25	DQ10B	DQ4B
4A	VREFB4AN0	IO			DIFFIO RX B74p	DIFFOUT B74p	AK23	DQ10B	DQ4B
4A	VREFB4AN0	IO			DIFFIO RX B75n	DIFFOUT B75n	AA20	DQS10B	DQ4B
4A	VREFB4AN0	IO			DIFFIO TX B76n	DIFFOUT B76n	AM26	DQ10B	DQ4B
4A	VREFB4AN0	IO			DIFFIO RX B75p	DIFFOUT B75p	Y20	DQS10B	DQ4B
4A	VREFB4AN0	IO			DIFFIO TX B76p	DIFFOUT B76p	AL26		
4A	VREFB4AN0	IO			DIFFIO TX B77n	DIFFOUT B77n	AP31	DQ10B	DQ4B
4A	VREFB4AN0	IO			DIFFIO RX B78n	DIFFOUT B78n	AK24	DQ10B	DQ4B
4A	VREFB4AN0	IO			DIFFIO TX B77p	DIFFOUT B77p	AN31	DQ10B	DQ4B
4A	VREFB4AN0	IO			DIFFIO RX B78p	DIFFOUT B78p	AJ24	DQ10B	DQ4B
4A	VREFB4AN0	IO			DIFFIO RX B79n	DIFFOUT B79n	AG21		
4A	VREFB4AN0	IO			DIFFIO TX B80n	DIFFOUT B80n	AL28	DQ10B	DQ4B
4A	VREFB4AN0	IO			DIFFIO RX B79p	DIFFOUT B79p	AF22		
4A	VREFB4AN0	IO			DIFFIO TX B80p	DIFFOUT B80p	AL27	DQ10B	DQ4B
4A	VREFB4AN0	IO			DIFFIO TX B81n	DIFFOUT B81n	AP32		
4A	VREFB4AN0	IO			DIFFIO RX B82n	DIFFOUT B82n	AH23	DQ11B	DQ4B
4A	VREFB4AN0	IO			DIFFIO TX B81p	DIFFOUT B81p	AN32	DQ11B	DQ4B
4A	VREFB4AN0	IO			DIFFIO RX B82p	DIFFOUT B82p	AG23	DQ11B	DQ4B
4A	VREFB4AN0	IO			DIFFIO RX B83n	DIFFOUT B83n	AD21	DQS11B	DQS4B
4A	VREFB4AN0	IO			DIFFIO TX B84n	DIFFOUT B84n	AN29	DQ11B	DQ4B
4A	VREFB4AN0	IO			DIFFIO RX B83p	DIFFOUT B83p	AC21	DQS11B	DQS4B
4A	VREFB4AN0	IO			DIFFIO TX B84p	DIFFOUT B84p	AM29		



Pin Information for the Cyclone® V 5CGXBC9 Device  
Version 1.2  
Note (1)

Bank Number	VREF	Pin Name/Function	Optional Function(s)	Configuration Function	Dedicated Tx/Rx Channel	Emulated LVDS Output Channel	F1152	DQS for X8	DQS for X16
4A	VREFB4AN0	IO			DIFFIO TX_B85n	DIFFOUT_B85n	AK27	DQ11B	DQ4B
4A	VREFB4AN0	IO			DIFFIO RX_B86n	DIFFOUT_B86n	AK25	DQ11B	DQ4B
4A	VREFB4AN0	IO			DIFFIO TX_B85p	DIFFOUT_B85p	AK28	DQ11B	DQ4B
4A	VREFB4AN0	IO			DIFFIO RX_B86p	DIFFOUT_B86p	AJ25	DQ11B	DQ4B
4A	VREFB4AN0	IO			DIFFIO RX_B87n	DIFFOUT_B87n	AF23		
4A	VREFB4AN0	IO			DIFFIO TX_B88n	DIFFOUT_B88n	AM30	DQ11B	DQ4B
4A	VREFB4AN0	IO			DIFFIO RX_B87p	DIFFOUT_B87p	AE23		
4A	VREFB4AN0	IO			DIFFIO TX_B88p	DIFFOUT_B88p	AL30	DQ11B	DQ4B
4A	VREFB4AN0	IO			DIFFIO TX_B89n	DIFFOUT_B89n	AK29		
4A	VREFB4AN0	IO			DIFFIO RX_B90n	DIFFOUT_B90n	AH24	DQ12B	
4A	VREFB4AN0	IO			DIFFIO TX_B89p	DIFFOUT_B89p	AJ29	DQ12B	
4A	VREFB4AN0	IO			DIFFIO RX_B90p	DIFFOUT_B90p	AG24	DQ12B	
4A	VREFB4AN0	IO			DIFFIO RX_B91n	DIFFOUT_B91n	AD22	DQS12B	
4A	VREFB4AN0	IO			DIFFIO TX_B92n	DIFFOUT_B92n	AM31	DQ12B	
4A	VREFB4AN0	IO			DIFFIO RX_B91p	DIFFOUT_B91p	AC22	DQS12B	
4A	VREFB4AN0	IO			DIFFIO TX_B92p	DIFFOUT_B92p	AL31		
4A	VREFB4AN0	IO			DIFFIO TX_B93n	DIFFOUT_B93n	AJ26	DQ12B	
4A	VREFB4AN0	IO			DIFFIO RX_B94n	DIFFOUT_B94n	AG26	DQ12B	
4A	VREFB4AN0	IO			DIFFIO TX_B93p	DIFFOUT_B93p	AH26	DQ12B	
4A	VREFB4AN0	IO			DIFFIO RX_B94p	DIFFOUT_B94p	AG25	DQ12B	
4A	VREFB4AN0	IO			DIFFIO RX_B95n	DIFFOUT_B95n	AE25		
4A	VREFB4AN0	IO			DIFFIO TX_B96n	DIFFOUT_B96n	AJ27	DQ12B	
4A	VREFB4AN0	IO			DIFFIO RX_B95p	DIFFOUT_B95p	AF25		
4A	VREFB4AN0	IO			DIFFIO TX_B96p	DIFFOUT_B96p	AH27	DQ12B	
5A	VREFB5AN0	IO	RZQ_1		DIFFIO TX_R1p	DIFFOUT_R1p	AD24	DQ1R	
5A	VREFB5AN0	IO		INIT_DONE	DIFFIO RX_R2p	DIFFOUT_R2p	AC23		
5A	VREFB5AN0	IO		PR_REQUEST	DIFFIO TX_R1n	DIFFOUT_R1n	AD25	DQ1R	
5A	VREFB5AN0	IO		CRC_ERROR	DIFFIO RX_R2n	DIFFOUT_R2n	AC24		
5A	VREFB5AN0	IO		nCEO	DIFFIO TX_R3p	DIFFOUT_R3p	AC27	DQ1R	
5A	VREFB5AN0	IO			DIFFIO RX_R4p	DIFFOUT_R4p	AB24	DQ1R	
5A	VREFB5AN0	IO		CvP_CONFDONE	DIFFIO TX_R3n	DIFFOUT_R3n	AC26	DQ1R	
5A	VREFB5AN0	IO			DIFFIO RX_R4n	DIFFOUT_R4n	AB23	DQ1R	
5A	VREFB5AN0	IO		DEV_OE	DIFFIO TX_R5p	DIFFOUT_R5p	AE29		
5A	VREFB5AN0	IO			DIFFIO RX_R6p	DIFFOUT_R6p	AA21	DQS1R	
5A	VREFB5AN0	IO		DEV CLRn	DIFFIO TX_R5n	DIFFOUT_R5n	AD29	DQ1R	
5A	VREFB5AN0	IO			DIFFIO RX_R6n	DIFFOUT_R6n	AA22	DQS1R	
5A	VREFB5AN0	IO			DIFFIO TX_R7p	DIFFOUT_R7p	AC28	DQ1R	
5A	VREFB5AN0	IO			DIFFIO RX_R8p	DIFFOUT_R8p	Y24	DQ1R	
5A	VREFB5AN0	IO			DIFFIO TX_R7n	DIFFOUT_R7n	AC29		
5A	VREFB5AN0	IO			DIFFIO RX_R8n	DIFFOUT_R8n	Y25	DQ1R	
5A	VREFB5AN0	IO			DIFFIO RX_R9p	DIFFOUT_R9p	AB25		
5A	VREFB5AN0	IO			DIFFIO TX_R10p	DIFFOUT_R10p	AF27	DQ2R	DQ1R
5A	VREFB5AN0	IO			DIFFIO RX_R9n	DIFFOUT_R9n	AA25		
5A	VREFB5AN0	IO			DIFFIO TX_R10n	DIFFOUT_R10n	AF26	DQ2R	DQ1R
5A	VREFB5AN0	IO			DIFFIO RX_R11p	DIFFOUT_R11p	AB28	DQ2R	DQ1R
5A	VREFB5AN0	IO			DIFFIO TX_R12p	DIFFOUT_R12p	AE28	DQ2R	DQ1R
5A	VREFB5AN0	IO			DIFFIO RX_R11n	DIFFOUT_R11n	AB29	DQ2R	DQ1R
5A	VREFB5AN0	IO			DIFFIO TX_R12n	DIFFOUT_R12n	AF28	DQ2R	DQ1R
5A	VREFB5AN0	IO			DIFFIO RX_R13p	DIFFOUT_R13p	AA23	DQS2R	DQS1R
5A	VREFB5AN0	IO			DIFFIO TX_R14p	DIFFOUT_R14p	AG28		
5A	VREFB5AN0	IO			DIFFIO RX_R13n	DIFFOUT_R13n	Y22	DQS2R	DQS1R
5A	VREFB5AN0	IO			DIFFIO TX_R14n	DIFFOUT_R14n	AH28	DQ2R	DQ1R
5A	VREFB5AN0	IO			DIFFIO RX_R15p	DIFFOUT_R15p	AB30	DQ2R	DQ1R
5A	VREFB5AN0	IO			DIFFIO TX_R16p	DIFFOUT_R16p	AG29	DQ2R	DQ1R
5A	VREFB5AN0	IO			DIFFIO RX_R15n	DIFFOUT_R15n	AA30	DQ2R	DQ1R
5A	VREFB5AN0	IO			DIFFIO TX_R16n	DIFFOUT_R16n	AH29		
5A	VREFB5AN0	IO			DIFFIO RX_R17p	DIFFOUT_R17p	AA27		
5A	VREFB5AN0	IO			DIFFIO TX_R18p	DIFFOUT_R18p	AK30	DQ3R	DQ1R
5A	VREFB5AN0	IO			DIFFIO RX_R17n	DIFFOUT_R17n	AA28		
5A	VREFB5AN0	IO			DIFFIO TX_R18n	DIFFOUT_R18n	AJ30	DQ3R	DQ1R
5A	VREFB5AN0	IO			DIFFIO RX_R19p	DIFFOUT_R19p	AG30	DQ3R	DQ1R
5A	VREFB5AN0	IO			DIFFIO TX_R20p	DIFFOUT_R20p	AN33	DQ3R	DQ1R
5A	VREFB5AN0	IO			DIFFIO RX_R19n	DIFFOUT_R19n	AF30	DQ3R	DQ1R
5A	VREFB5AN0	IO			DIFFIO TX_R20n	DIFFOUT_R20n	AM33	DQ3R	DQ1R
5A	VREFB5AN0	IO			DIFFIO RX_R21p	DIFFOUT_R21p	Y23	DQS3R	DQ1R
5A	VREFB5AN0	IO			DIFFIO TX_R22p	DIFFOUT_R22p	AL32		
5A	VREFB5AN0	IO			DIFFIO RX_R21n	DIFFOUT_R21n	W24	DQS3R	DQ1R
5A	VREFB5AN0	IO			DIFFIO TX_R22n	DIFFOUT_R22n	AK32	DQ3R	DQ1R
5A	VREFB5AN0	IO			DIFFIO RX_R23p	DIFFOUT_R23p	AH31	DQ3R	DQ1R
5A	VREFB5AN0	IO			DIFFIO TX_R24p	DIFFOUT_R24p	AL33	DQ3R	DQ1R
5A	VREFB5AN0	IO			DIFFIO RX_R23n	DIFFOUT_R23n	AJ31	DQ3R	DQ1R
5A	VREFB5AN0	IO			DIFFIO TX_R24n	DIFFOUT_R24n	AK33		
5B	VREFB5BN0	IO			DIFFIO RX_R25p	DIFFOUT_R25p	AA32		
5B	VREFB5BN0	IO			DIFFIO TX_R26p	DIFFOUT_R26p	AE30	DQ4R	DQ2R
5B	VREFB5BN0	IO			DIFFIO RX_R25n	DIFFOUT_R25n	Y32		
5B	VREFB5BN0	IO			DIFFIO TX_R26n	DIFFOUT_R26n	AD30	DQ4R	DQ2R
5B	VREFB5BN0	IO			DIFFIO RX_R27p	DIFFOUT_R27p	Y28	DQ4R	DQ2R
5B	VREFB5BN0	IO			DIFFIO TX_R28p	DIFFOUT_R28p	AH32	DQ4R	DQ2R



Pin Information for the Cyclone® V 5CGXBC9 Device  
Version 1.2  
Note (1)

Bank Number	VREF	Pin Name/Function	Optional Function(s)	Configuration Function	Dedicated Tx/Rx Channel	Emulated LVDS Output Channel	F1152	DQS for X8	DQS for X16
5B	VREFB5B0	IO			DIFFIO RX_R27n	DIFFOUT_R27n	Y27	DQ4R	DO2R
5B	VREFB5B0	IO			DIFFIO TX_R28n	DIFFOUT_R28n	AJ32	DQ4R	DO2R
5B	VREFB5B0	IO			DIFFIO RX_R29p	DIFFOUT_R29p	Y29	DQS4R	DO2SR
5B	VREFB5B0	IO			DIFFIO TX_R30p	DIFFOUT_R30p	AG31		
5B	VREFB5B0	IO			DIFFIO RX_R29n	DIFFOUT_R29n	Y30	DQS4R	DO2SR
5B	VREFB5B0	IO			DIFFIO TX_R30n	DIFFOUT_R30n	AF31	DQ4R	DO2R
5B	VREFB5B0	IO			DIFFIO RX_R31p	DIFFOUT_R31p	AC31	DQ4R	DO2R
5B	VREFB5B0	IO			DIFFIO TX_R32p	DIFFOUT_R32p	AN34	DQ4R	DO2R
5B	VREFB5B0	IO			DIFFIO RX_R31n	DIFFOUT_R31n	AC32	DQ4R	DO2R
5B	VREFB5B0	IO			DIFFIO TX_R32n	DIFFOUT_R32n	AM34		
5B	VREFB5B0	IO	CLK7p,FPLL_BR_FBp		DIFFIO RX_R33p	DIFFOUT_R33p	W26		
5B	VREFB5B0	IO			DIFFIO TX_R34p	DIFFOUT_R34p	AA31	DQ5R	DO2R
5B	VREFB5B0	IO	CLK7n,FPLL_BR_FBn		DIFFIO RX_R33n	DIFFOUT_R33n	W27		
5B	VREFB5B0	IO			DIFFIO TX_R34n	DIFFOUT_R34n	AB31	DQ5R	DO2R
5B	VREFB5B0	IO			DIFFIO RX_R35p	DIFFOUT_R35p	AK34	DQ5R	DO2R
5B	VREFB5B0	IO			DIFFIO TX_R36p	DIFFOUT_R36p	AH33	DQ5R	DO2R
5B	VREFB5B0	IO			DIFFIO RX_R35n	DIFFOUT_R35n	AJ34	DQ5R	DO2R
5B	VREFB5B0	IO			DIFFIO TX_R36n	DIFFOUT_R36n	AG33	DQ5R	DO2R
5B	VREFB5B0	IO			DIFFIO RX_R37p	DIFFOUT_R37p	W29	DQS5R	DO2R
5B	VREFB5B0	IO			DIFFIO TX_R38p	DIFFOUT_R38p	AD31		
5B	VREFB5B0	IO			DIFFIO RX_R37n	DIFFOUT_R37n	W30	DQS5R	DO2R
5B	VREFB5B0	IO			DIFFIO TX_R38n	DIFFOUT_R38n	AD32	DQ5R	DO2R
5B	VREFB5B0	IO			DIFFIO RX_R39p	DIFFOUT_R39p	W31	DQ5R	DO2R
5B	VREFB5B0	IO			DIFFIO TX_R40p	DIFFOUT_R40p	AE32	DQ5R	DO2R
5B	VREFB5B0	IO			DIFFIO RX_R39n	DIFFOUT_R39n	V31	DQ5R	DO2R
5B	VREFB5B0	IO			DIFFIO TX_R40n	DIFFOUT_R40n	AF32		
5B	VREFB5B0	IO	CLK6p		DIFFIO RX_R41p	DIFFOUT_R41p	V28		
5B	VREFB5B0	IO			DIFFIO TX_R42p	DIFFOUT_R42p	AG34	DQ6R	
5B	VREFB5B0	IO	CLK6n		DIFFIO RX_R41n	DIFFOUT_R41n	V27		
5B	VREFB5B0	IO			DIFFIO TX_R42n	DIFFOUT_R42n	AH34	DQ6R	
5B	VREFB5B0	IO			DIFFIO RX_R43p	DIFFOUT_R43p	AC33	DQ6R	
5B	VREFB5B0	IO	FPLL_BR_CLKOUT0,FPLL_BR_CLKOUTp,FPLL_BR_FB		DIFFIO TX_R44p	DIFFOUT_R44p	AF33	DQ6R	
5B	VREFB5B0	IO			DIFFIO RX_R43n	DIFFOUT_R43n	AC34	DQ6R	
5B	VREFB5B0	IO	FPLL_BR_CLKOUT1,FPLL_BR_CLKOUTn		DIFFIO TX_R44n	DIFFOUT_R44n	AE33	DQ6R	
5B	VREFB5B0	IO			DIFFIO RX_R45p	DIFFOUT_R45p	V24	DQS6R	
5B	VREFB5B0	IO			DIFFIO TX_R46p	DIFFOUT_R46p	AE34		
5B	VREFB5B0	IO			DIFFIO RX_R45n	DIFFOUT_R45n	V23	DQS6R	
5B	VREFB5B0	IO			DIFFIO TX_R46n	DIFFOUT_R46n	AD34	DQ6R	
5B	VREFB5B0	IO			DIFFIO RX_R47p	DIFFOUT_R47p	W32	DQ6R	
5B	VREFB5B0	IO			DIFFIO TX_R48p	DIFFOUT_R48p	AB33	DQ6R	
5B	VREFB5B0	IO			DIFFIO RX_R47n	DIFFOUT_R47n	V32	DQ6R	
5B	VREFB5B0	IO			DIFFIO TX_R48n	DIFFOUT_R48n	AB34		
6A	VREFB6A0	IO	CLK5p		DIFFIO RX_R49p	DIFFOUT_R49p	U31		
6A	VREFB6A0	IO			DIFFIO TX_R50p	DIFFOUT_R50p	Y33	DQ7R	
6A	VREFB6A0	IO	CLK5n		DIFFIO RX_R49n	DIFFOUT_R49n	U30		
6A	VREFB6A0	IO			DIFFIO TX_R50n	DIFFOUT_R50n	AA33	DQ7R	
6A	VREFB6A0	IO			DIFFIO RX_R51p	DIFFOUT_R51p	U28	DQ7R	
6A	VREFB6A0	IO	FPLL_TR_CLKOUT0,FPLL_TR_CLKOUTp,FPLL_TR_FB		DIFFIO TX_R52p	DIFFOUT_R52p	Y34	DQ7R	
6A	VREFB6A0	IO			DIFFIO RX_R51n	DIFFOUT_R51n	U29	DQ7R	
6A	VREFB6A0	IO	FPLL_TR_CLKOUT1,FPLL_TR_CLKOUTn		DIFFIO TX_R52n	DIFFOUT_R52n	W34	DQ7R	
6A	VREFB6A0	IO			DIFFIO RX_R53p	DIFFOUT_R53p	U24	DQS7R	
6A	VREFB6A0	IO			DIFFIO TX_R54p	DIFFOUT_R54p	V33		
6A	VREFB6A0	IO			DIFFIO RX_R53n	DIFFOUT_R53n	U25	DQS7R	
6A	VREFB6A0	IO			DIFFIO TX_R54n	DIFFOUT_R54n	V34	DQ7R	
6A	VREFB6A0	IO			DIFFIO RX_R55p	DIFFOUT_R55p	R34	DQ7R	
6A	VREFB6A0	IO			DIFFIO TX_R56p	DIFFOUT_R56p	U34	DQ7R	
6A	VREFB6A0	IO			DIFFIO RX_R55n	DIFFOUT_R55n	P34	DQ7R	
6A	VREFB6A0	IO			DIFFIO TX_R56n	DIFFOUT_R56n	U33		
6A	VREFB6A0	IO	CLK4p,FPLL_TR_FBp		DIFFIO RX_R57p	DIFFOUT_R57p	T31		
6A	VREFB6A0	IO			DIFFIO TX_R58p	DIFFOUT_R58p	T33	DQ8R	DQ3R
6A	VREFB6A0	IO	CLK4n,FPLL_TR_FBn		DIFFIO RX_R57n	DIFFOUT_R57n	T30		
6A	VREFB6A0	IO			DIFFIO TX_R58n	DIFFOUT_R58n	T32	DQ8R	DQ3R
6A	VREFB6A0	IO			DIFFIO RX_R59p	DIFFOUT_R59p	T27	DQ8R	DQ3R
6A	VREFB6A0	IO			DIFFIO TX_R60p	DIFFOUT_R60p	M34	DQ8R	DQ3R
6A	VREFB6A0	IO			DIFFIO RX_R59n	DIFFOUT_R59n	T28	DQ8R	DQ3R
6A	VREFB6A0	IO			DIFFIO TX_R60n	DIFFOUT_R60n	M33	DQ8R	DQ3R
6A	VREFB6A0	IO			DIFFIO RX_R61p	DIFFOUT_R61p	U23	DQS8R	DQS3R
6A	VREFB6A0	IO			DIFFIO TX_R62p	DIFFOUT_R62p	K34		
6A	VREFB6A0	IO			DIFFIO RX_R61n	DIFFOUT_R61n	T23	DQS8R	DQS3R
6A	VREFB6A0	IO			DIFFIO TX_R62n	DIFFOUT_R62n	J34	DQ8R	DQ3R
6A	VREFB6A0	IO			DIFFIO RX_R63p	DIFFOUT_R63p	N33	DQ8R	DQ3R
6A	VREFB6A0	IO			DIFFIO TX_R64p	DIFFOUT_R64p	L33	DQ8R	DQ3R
6A	VREFB6A0	IO			DIFFIO RX_R63n	DIFFOUT_R63n	N34	DQ8R	DQ3R
6A	VREFB6A0	IO			DIFFIO TX_R64n	DIFFOUT_R64n	L32		
6A	VREFB6A0	IO			DIFFIO RX_R65p	DIFFOUT_R65p	R32		
6A	VREFB6A0	IO			DIFFIO TX_R66p	DIFFOUT_R66p	K33	DQ9R	DQ3R
6A	VREFB6A0	IO			DIFFIO RX_R65n	DIFFOUT_R65n	R33		
6A	VREFB6A0	IO			DIFFIO TX_R66n	DIFFOUT_R66n	K32	DQ9R	DQ3R





Pin Information for the Cyclone® V 5CGXBC9 Device  
Version 1.2  
Note (1)

Bank Number	VREF	Pin Name/Function	Optional Function(s)	Configuration Function	Dedicated Tx/Rx Channel	Emulated LVDS Output Channel	F1152	DQS for X8	DQS for X16
6A	VREFB6A0	IO			DIFFIO_RX_R67p	DIFFOUT_R67p	R27	DQ9R	DQ3R
6A	VREFB6A0	IO			DIFFIO_TX_R68p	DIFFOUT_R68p	H34	DQ9R	DQ3R
6A	VREFB6A0	IO			DIFFIO_RX_R67n	DIFFOUT_R67n	R28	DQ9R	DQ3R
6A	VREFB6A0	IO			DIFFIO_TX_R68n	DIFFOUT_R68n	H33	DQ9R	DQ3R
6A	VREFB6A0	IO			DIFFIO_RX_R69p	DIFFOUT_R69p	T25	DQS9R	DQ3R
6A	VREFB6A0	IO			DIFFIO_TX_R70p	DIFFOUT_R70p	N32		
6A	VREFB6A0	IO			DIFFIO_RX_R69n	DIFFOUT_R69n	R25	DQSn9R	DQ3R
6A	VREFB6A0	IO			DIFFIO_TX_R70n	DIFFOUT_R70n	N31	DQ9R	DQ3R
6A	VREFB6A0	IO			DIFFIO_RX_R71p	DIFFOUT_R71p	P32	DQ9R	DQ3R
6A	VREFB6A0	IO			DIFFIO_TX_R72p	DIFFOUT_R72p	G34	DQ9R	DQ3R
6A	VREFB6A0	IO			DIFFIO_RX_R71n	DIFFOUT_R71n	P31	DQ9R	DQ3R
6A	VREFB6A0	IO			DIFFIO_TX_R72n	DIFFOUT_R72n	G33		
6A	VREFB6A0	IO			DIFFIO_RX_R73p	DIFFOUT_R73p	R30		
6A	VREFB6A0	IO			DIFFIO_TX_R74p	DIFFOUT_R74p	M31	DQ10R	DQ4R
6A	VREFB6A0	IO			DIFFIO_RX_R73n	DIFFOUT_R73n	R29		
6A	VREFB6A0	IO			DIFFIO_TX_R74n	DIFFOUT_R74n	L31	DQ10R	DQ4R
6A	VREFB6A0	IO			DIFFIO_RX_R75p	DIFFOUT_R75p	L30	DQ10R	DQ4R
6A	VREFB6A0	IO			DIFFIO_TX_R76p	DIFFOUT_R76p	J32	DQ10R	DQ4R
6A	VREFB6A0	IO			DIFFIO_RX_R75n	DIFFOUT_R75n	K30	DQ10R	DQ4R
6A	VREFB6A0	IO			DIFFIO_TX_R76n	DIFFOUT_R76n	H32	DQ10R	DQ4R
6A	VREFB6A0	IO			DIFFIO_RX_R77p	DIFFOUT_R77p	R23	DQS10R	DQS4R
6A	VREFB6A0	IO			DIFFIO_TX_R78p	DIFFOUT_R78p	J31		
6A	VREFB6A0	IO			DIFFIO_RX_R77n	DIFFOUT_R77n	R24	DQSn10R	DQSn4R
6A	VREFB6A0	IO			DIFFIO_TX_R78n	DIFFOUT_R78n	H31	DQ10R	DQ4R
6A	VREFB6A0	IO			DIFFIO_RX_R79p	DIFFOUT_R79p	N28	DQ10R	DQ4R
6A	VREFB6A0	IO			DIFFIO_TX_R80p	DIFFOUT_R80p	P30	DQ10R	DQ4R
6A	VREFB6A0	IO			DIFFIO_RX_R79n	DIFFOUT_R79n	M28	DQ10R	DQ4R
6A	VREFB6A0	IO			DIFFIO_TX_R80n	DIFFOUT_R80n	N29		
6A	VREFB6A0	IO			DIFFIO_RX_R81p	DIFFOUT_R81p	P27		
6A	VREFB6A0	IO			DIFFIO_TX_R82p	DIFFOUT_R82p	G31	DQ11R	DQ4R
6A	VREFB6A0	IO			DIFFIO_RX_R81n	DIFFOUT_R81n	N27		
6A	VREFB6A0	IO			DIFFIO_TX_R82n	DIFFOUT_R82n	G30	DQ11R	DQ4R
6A	VREFB6A0	IO			DIFFIO_RX_R83p	DIFFOUT_R83p	M29	DQ11R	DQ4R
6A	VREFB6A0	IO			DIFFIO_TX_R84p	DIFFOUT_R84p	J30	DQ11R	DQ4R
6A	VREFB6A0	IO			DIFFIO_RX_R83n	DIFFOUT_R83n	M30	DQ11R	DQ4R
6A	VREFB6A0	IO			DIFFIO_TX_R84n	DIFFOUT_R84n	J29	DQ11R	DQ4R
6A	VREFB6A0	IO			DIFFIO_RX_R85p	DIFFOUT_R85p	P24	DQS11R	DQ4R
6A	VREFB6A0	IO			DIFFIO_TX_R86p	DIFFOUT_R86p	H29		
6A	VREFB6A0	IO			DIFFIO_RX_R85n	DIFFOUT_R85n	P25	DQSn11R	DQ4R
6A	VREFB6A0	IO			DIFFIO_TX_R86n	DIFFOUT_R86n	H28	DQ11R	DQ4R
6A	VREFB6A0	IO			DIFFIO_RX_R87p	DIFFOUT_R87p	L28	DQ11R	DQ4R
6A	VREFB6A0	IO			DIFFIO_TX_R88p	DIFFOUT_R88p	K29	DQ11R	DQ4R
6A	VREFB6A0	IO			DIFFIO_RX_R87n	DIFFOUT_R87n	L27	DQ11R	DQ4R
6A	VREFB6A0	IO			DIFFIO_TX_R88n	DIFFOUT_R88n	K28		
7A		GND					J26		
7A	VREFB7A0	IO			DIFFIO_RX_T1p	DIFFOUT_T1p	K25		
7A	VREFB7A0	IO			DIFFIO_TX_T2p	DIFFOUT_T2p	H27	DQ1T	
7A	VREFB7A0	IO			DIFFIO_RX_T1n	DIFFOUT_T1n	J25		
7A	VREFB7A0	IO			DIFFIO_TX_T2n	DIFFOUT_T2n	H26	DQ1T	
7A	VREFB7A0	IO			DIFFIO_RX_T3p	DIFFOUT_T3p	G25	DQ1T	
7A	VREFB7A0	IO			DIFFIO_TX_T3p	DIFFOUT_T3p	G28	DQ1T	
7A	VREFB7A0	IO			DIFFIO_RX_T3n	DIFFOUT_T3n	F25	DQ1T	
7A	VREFB7A0	IO			DIFFIO_TX_T4n	DIFFOUT_T4n	G29	DQ1T	
7A	VREFB7A0	IO			DIFFIO_RX_T5p	DIFFOUT_T5p	M24	DQS1T	
7A	VREFB7A0	IO			DIFFIO_TX_T6p	DIFFOUT_T6p	F26		
7A	VREFB7A0	IO			DIFFIO_RX_T5n	DIFFOUT_T5n	N24	DQSn1T	
7A	VREFB7A0	IO			DIFFIO_TX_T6n	DIFFOUT_T6n	G26	DQ1T	
7A	VREFB7A0	IO			DIFFIO_RX_T7p	DIFFOUT_T7p	G24	DQ1T	
7A	VREFB7A0	IO			DIFFIO_TX_T8p	DIFFOUT_T8p	F30	DQ1T	
7A	VREFB7A0	IO			DIFFIO_RX_T7n	DIFFOUT_T7n	H24	DQ1T	
7A	VREFB7A0	IO			DIFFIO_TX_T8n	DIFFOUT_T8n	E30		
7A	VREFB7A0	IO			DIFFIO_RX_T9p	DIFFOUT_T9p	M25		
7A	VREFB7A0	IO			DIFFIO_TX_T10p	DIFFOUT_T10p	F27	DQ2T	DQ1T
7A	VREFB7A0	IO			DIFFIO_RX_T9n	DIFFOUT_T9n	L25		
7A	VREFB7A0	IO			DIFFIO_TX_T10n	DIFFOUT_T10n	F28	DQ2T	DQ1T
7A	VREFB7A0	IO			DIFFIO_RX_T11p	DIFFOUT_T11p	D30	DQ2T	DQ1T
7A	VREFB7A0	IO			DIFFIO_TX_T12p	DIFFOUT_T12p	C32	DQ2T	DQ1T
7A	VREFB7A0	IO			DIFFIO_RX_T11n	DIFFOUT_T11n	D29	DQ2T	DQ1T
7A	VREFB7A0	IO			DIFFIO_TX_T12n	DIFFOUT_T12n	C31	DQ2T	DQ1T
7A	VREFB7A0	IO			DIFFIO_RX_T13p	DIFFOUT_T13p	L23	DQS2T	DQS1T
7A	VREFB7A0	IO			DIFFIO_TX_T14p	DIFFOUT_T14p	E29		
7A	VREFB7A0	IO			DIFFIO_RX_T13n	DIFFOUT_T13n	K23	DQSn2T	DQSn1T
7A	VREFB7A0	IO			DIFFIO_TX_T14n	DIFFOUT_T14n	E28	DQ2T	DQ1T
7A	VREFB7A0	IO			DIFFIO_RX_T15p	DIFFOUT_T15p	H23	DQ2T	DQ1T
7A	VREFB7A0	IO			DIFFIO_TX_T16p	DIFFOUT_T16p	B31	DQ2T	DQ1T
7A	VREFB7A0	IO			DIFFIO_RX_T15n	DIFFOUT_T15n	G23	DQ2T	DQ1T
7A	VREFB7A0	IO			DIFFIO_TX_T16n	DIFFOUT_T16n	B30		
7A	VREFB7A0	IO			DIFFIO_RX_T17p	DIFFOUT_T17p	L22		



Pin Information for the Cyclone® V 5CGXBC9 Device

Version 1.2

Note (1)

Bank Number	VREF	Pin Name/Function	Optional Function(s)	Configuration Function	Dedicated Tx/Rx Channel	Emulated LVDS Output Channel	F1152	DQS for X8	DQS for X16
7A	VREFB7A0	IO			DIFFIO TX T18p	DIFFOUT T18p	E24	DQ3T	DO1T
7A	VREFB7A0	IO			DIFFIO RX T17n	DIFFOUT T17n	K22		
7A	VREFB7A0	IO			DIFFIO TX T18n	DIFFOUT T18n	E25	DQ3T	DO1T
7A	VREFB7A0	IO			DIFFIO RX T19p	DIFFOUT T19p	F23	DQ3T	DO1T
7A	VREFB7A0	IO			DIFFIO TX T20p	DIFFOUT T20p	C29	DQ3T	DO1T
7A	VREFB7A0	IO			DIFFIO RX T19n	DIFFOUT T19n	F22	DQ3T	DO1T
7A	VREFB7A0	IO			DIFFIO TX T20n	DIFFOUT T20n	C28	DQ3T	DO1T
7A	VREFB7A0	IO			DIFFIO RX T21p	DIFFOUT T21p	M23	DQS3T	DO1T
7A	VREFB7A0	IO			DIFFIO TX T22p	DIFFOUT T22p	E27		
7A	VREFB7A0	IO			DIFFIO RX T21n	DIFFOUT T21n	N23	DQSn3T	DO1T
7A	VREFB7A0	IO			DIFFIO TX T22n	DIFFOUT T22n	D26	DQ3T	DO1T
7A	VREFB7A0	IO			DIFFIO RX T23p	DIFFOUT T23p	H22	DQ3T	DO1T
7A	VREFB7A0	IO			DIFFIO TX T24p	DIFFOUT T24p	B28	DQ3T	DO1T
7A	VREFB7A0	IO			DIFFIO RX T23n	DIFFOUT T23n	H21	DQ3T	DO1T
7A	VREFB7A0	IO			DIFFIO TX T24n	DIFFOUT T24n	B29		
7A	VREFB7A0	IO			DIFFIO RX T25p	DIFFOUT T25p	L21		
7A	VREFB7A0	IO			DIFFIO TX T26p	DIFFOUT T26p	E22	DQ4T	DO2T
7A	VREFB7A0	IO			DIFFIO RX T25n	DIFFOUT T25n	L20		
7A	VREFB7A0	IO			DIFFIO TX T26n	DIFFOUT T26n	E23	DQ4T	DO2T
7A	VREFB7A0	IO			DIFFIO RX T27p	DIFFOUT T27p	F21	DQ4T	DO2T
7A	VREFB7A0	IO			DIFFIO TX T28p	DIFFOUT T28p	D27	DQ4T	DO2T
7A	VREFB7A0	IO			DIFFIO RX T27n	DIFFOUT T27n	G21	DQ4T	DO2T
7A	VREFB7A0	IO			DIFFIO TX T28n	DIFFOUT T28n	C27	DQ4T	DO2T
7A	VREFB7A0	IO			DIFFIO RX T29p	DIFFOUT T29p	N22	DQS4T	DQS2T
7A	VREFB7A0	IO			DIFFIO TX T30p	DIFFOUT T30p	D25		
7A	VREFB7A0	IO			DIFFIO RX T29n	DIFFOUT T29n	M21	DQSn4T	DQSn2T
7A	VREFB7A0	IO			DIFFIO TX T30n	DIFFOUT T30n	C26	DQ4T	DO2T
7A	VREFB7A0	IO			DIFFIO RX T31p	DIFFOUT T31p	F20	DQ4T	DO2T
7A	VREFB7A0	IO			DIFFIO TX T32p	DIFFOUT T32p	D24	DQ4T	DO2T
7A	VREFB7A0	IO			DIFFIO RX T31n	DIFFOUT T31n	G20	DQ4T	DO2T
7A	VREFB7A0	IO			DIFFIO TX T32n	DIFFOUT T32n	C24		
7A	VREFB7A0	IO	CLK11p		DIFFIO RX T33p	DIFFOUT T33p	J20		
7A	VREFB7A0	IO			DIFFIO TX T34p	DIFFOUT T34p	A28	DQ5T	DO2T
7A	VREFB7A0	IO	CLK11n		DIFFIO RX T33n	DIFFOUT T33n	K19		
7A	VREFB7A0	IO			DIFFIO TX T34n	DIFFOUT T34n	A27	DQ5T	DO2T
7A	VREFB7A0	IO			DIFFIO RX T35p	DIFFOUT T35p	D22	DQ5T	DO2T
7A	VREFB7A0	IO			DIFFIO TX T36p	DIFFOUT T36p	B26	DQ5T	DO2T
7A	VREFB7A0	IO			DIFFIO RX T35n	DIFFOUT T35n	C23	DQ5T	DO2T
7A	VREFB7A0	IO			DIFFIO TX T36n	DIFFOUT T36n	B25	DQ5T	DO2T
7A	VREFB7A0	IO			DIFFIO RX T37p	DIFFOUT T37p	M20	DQS5T	DO2T
7A	VREFB7A0	IO			DIFFIO TX T38p	DIFFOUT T38p	C22		
7A	VREFB7A0	IO			DIFFIO RX T37n	DIFFOUT T37n	M19	DQSn5T	DO2T
7A	VREFB7A0	IO			DIFFIO TX T38n	DIFFOUT T38n	D21	DQ5T	DO2T
7A	VREFB7A0	IO			DIFFIO RX T39p	DIFFOUT T39p	E20	DQ5T	DO2T
7A	VREFB7A0	IO			DIFFIO TX T40p	DIFFOUT T40p	A26	DQ5T	DO2T
7A	VREFB7A0	IO			DIFFIO RX T39n	DIFFOUT T39n	D20	DQ5T	DO2T
7A	VREFB7A0	IO			DIFFIO TX T40n	DIFFOUT T40n	A25		
7A	VREFB7A0	IO	CLK10p		DIFFIO RX T41p	DIFFOUT T41p	H19		
7A	VREFB7A0	IO			DIFFIO TX T42p	DIFFOUT T42p	B23	DQ6T	
7A	VREFB7A0	IO	CLK10n		DIFFIO RX T41n	DIFFOUT T41n	H18		
7A	VREFB7A0	IO			DIFFIO TX T42n	DIFFOUT T42n	B24	DQ6T	
7A	VREFB7A0	IO			DIFFIO RX T43p	DIFFOUT T43p	C21	DQ6T	
7A	VREFB7A0	IO			DIFFIO TX T44p	DIFFOUT T44p	A23	DQ6T	
7A	VREFB7A0	IO			DIFFIO RX T43n	DIFFOUT T43n	B21	DQ6T	
7A	VREFB7A0	IO			DIFFIO TX T44n	DIFFOUT T44n	A22	DQ6T	
7A	VREFB7A0	IO			DIFFIO RX T45p	DIFFOUT T45p	M18	DQS6T	
7A	VREFB7A0	IO			DIFFIO TX T46p	DIFFOUT T46p	E19		
7A	VREFB7A0	IO			DIFFIO RX T45n	DIFFOUT T45n	L18	DQSn6T	
7A	VREFB7A0	IO			DIFFIO TX T46n	DIFFOUT T46n	D19	DQ6T	
7A	VREFB7A0	IO			DIFFIO RX T47p	DIFFOUT T47p	B20	DQ6T	
7A	VREFB7A0	IO			DIFFIO TX T48p	DIFFOUT T48p	A21	DQ6T	
7A	VREFB7A0	IO			DIFFIO RX T47n	DIFFOUT T47n	B19	DQ6T	
7A	VREFB7A0	IO	RZQ_2		DIFFIO TX T48n	DIFFOUT T48n	A20		
8A	VREFB8A0	IO	CLK9p		DIFFIO RX T49p	DIFFOUT T49p	G18		
8A	VREFB8A0	IO			DIFFIO TX T50p	DIFFOUT T50p	C18	DQ7T	
8A	VREFB8A0	IO	CLK9n		DIFFIO RX T49n	DIFFOUT T49n	F18		
8A	VREFB8A0	IO			DIFFIO TX T50n	DIFFOUT T50n	C17	DQ7T	
8A	VREFB8A0	IO			DIFFIO RX T51p	DIFFOUT T51p	E18	DQ7T	
8A	VREFB8A0	IO	FPLL_TL_CLKOUT0,FPLL_TL_CLKOUTp,FPLL_TL_FB		DIFFIO TX T52p	DIFFOUT T52p	B18	DQ7T	
8A	VREFB8A0	IO			DIFFIO RX T51n	DIFFOUT T51n	E17	DQ7T	
8A	VREFB8A0	IO	FPLL_TL_CLKOUT1,FPLL_TL_CLKOUTn		DIFFIO TX T52n	DIFFOUT T52n	A18	DQ7T	
8A	VREFB8A0	IO			DIFFIO RX T53p	DIFFOUT T53p	M16	DQS7T	
8A	VREFB8A0	IO			DIFFIO TX T54p	DIFFOUT T54p	A17		
8A	VREFB8A0	IO			DIFFIO RX T53n	DIFFOUT T53n	L17	DQSn7T	
8A	VREFB8A0	IO			DIFFIO TX T54n	DIFFOUT T54n	A16	DQ7T	
8A	VREFB8A0	IO			DIFFIO RX T55p	DIFFOUT T55p	C16	DQ7T	
8A	VREFB8A0	IO			DIFFIO TX T56p	DIFFOUT T56p	B15	DQ7T	
8A	VREFB8A0	IO			DIFFIO RX T55n	DIFFOUT T55n	B16	DQ7T	



Pin Information for the Cyclone® V 5CGXBC9 Device

Version 1.2

Note (1)

Bank Number	VREF	Pin Name/Function	Optional Function(s)	Configuration Function	Dedicated Tx/Rx Channel	Emulated LVDS Output Channel	F1152	DQS for X8	DQS for X16
8A	VREFB8A0	IO			DIFFIO TX T56n	DIFFOUT T56n	A15		
8A	VREFB8A0	IO	CLK8p,FPLL_TL_FBp		DIFFIO RX T57p	DIFFOUT T57p	H17		
8A	VREFB8A0	IO			DIFFIO TX T58p	DIFFOUT T58p	A12	DQ8T	DQ3T
8A	VREFB8A0	IO	CLK8n,FPLL_TL_FBn		DIFFIO RX T57n	DIFFOUT T57n	H16		
8A	VREFB8A0	IO			DIFFIO TX T58n	DIFFOUT T58n	A11	DQ8T	DQ3T
8A	VREFB8A0	IO			DIFFIO RX T59p	DIFFOUT T59p	F17	DQ8T	DQ3T
8A	VREFB8A0	IO			DIFFIO TX T60p	DIFFOUT T60p	B13	DQ8T	DQ3T
8A	VREFB8A0	IO			DIFFIO RX T59n	DIFFOUT T59n	F16	DQ8T	DQ3T
8A	VREFB8A0	IO			DIFFIO TX T60n	DIFFOUT T60n	A13	DQ8T	DQ3T
8A	VREFB8A0	IO			DIFFIO RX T61p	DIFFOUT T61p	M15	DQS8T	DQS3T
8A	VREFB8A0	IO			DIFFIO TX T62p	DIFFOUT T62p	C14		
8A	VREFB8A0	IO			DIFFIO RX T61n	DIFFOUT T61n	M14	DQS8T	DQS3T
8A	VREFB8A0	IO			DIFFIO TX T62n	DIFFOUT T62n	B14	DQ8T	DQ3T
8A	VREFB8A0	IO			DIFFIO RX T63p	DIFFOUT T63p	D17	DQ8T	DQ3T
8A	VREFB8A0	IO			DIFFIO TX T64p	DIFFOUT T64p	B10	DQ8T	DQ3T
8A	VREFB8A0	IO			DIFFIO RX T63n	DIFFOUT T63n	D16	DQ8T	DQ3T
8A	VREFB8A0	IO			DIFFIO TX T64n	DIFFOUT T64n	A10		
8A	VREFB8A0	IO			DIFFIO RX T65p	DIFFOUT T65p	F15		
8A	VREFB8A0	IO			DIFFIO TX T66p	DIFFOUT T66p	A7	DQ9T	DQ3T
8A	VREFB8A0	IO			DIFFIO RX T65n	DIFFOUT T65n	G15		
8A	VREFB8A0	IO			DIFFIO TX T66n	DIFFOUT T66n	A6	DQ9T	DQ3T
8A	VREFB8A0	IO			DIFFIO RX T67p	DIFFOUT T67p	B8	DQ9T	DQ3T
8A	VREFB8A0	IO			DIFFIO TX T68p	DIFFOUT T68p	C11	DQ9T	DQ3T
8A	VREFB8A0	IO			DIFFIO RX T67n	DIFFOUT T67n	A8	DQ9T	DQ3T
8A	VREFB8A0	IO			DIFFIO TX T68n	DIFFOUT T68n	B11	DQ9T	DQ3T
8A	VREFB8A0	IO			DIFFIO RX T69p	DIFFOUT T69p	L16	DQS9T	DQ3T
8A	VREFB8A0	IO			DIFFIO TX T70p	DIFFOUT T70p	C9		
8A	VREFB8A0	IO			DIFFIO RX T69n	DIFFOUT T69n	L15	DQS9T	DQ3T
8A	VREFB8A0	IO			DIFFIO TX T70n	DIFFOUT T70n	B9	DQ9T	DQ3T
8A	VREFB8A0	IO			DIFFIO RX T71p	DIFFOUT T71p	E15	DQ9T	DQ3T
8A	VREFB8A0	IO			DIFFIO TX T72p	DIFFOUT T72p	C13	DQ9T	DQ3T
8A	VREFB8A0	IO			DIFFIO RX T71n	DIFFOUT T71n	D15	DQ9T	DQ3T
8A	VREFB8A0	IO			DIFFIO TX T72n	DIFFOUT T72n	C12		
8A	VREFB8A0	IO			DIFFIO RX T73p	DIFFOUT T73p	J15		
8A	VREFB8A0	IO			DIFFIO TX T74p	DIFFOUT T74p	B5	DQ10T	DQ4T
8A	VREFB8A0	IO			DIFFIO RX T73n	DIFFOUT T73n	K14		
8A	VREFB8A0	IO			DIFFIO TX T74n	DIFFOUT T74n	A5	DQ10T	DQ4T
8A	VREFB8A0	IO			DIFFIO RX T75p	DIFFOUT T75p	E14	DQ10T	DQ4T
8A	VREFB8A0	IO			DIFFIO TX T76p	DIFFOUT T76p	C6	DQ10T	DQ4T
8A	VREFB8A0	IO			DIFFIO RX T75n	DIFFOUT T75n	D14	DQ10T	DQ4T
8A	VREFB8A0	IO			DIFFIO TX T76n	DIFFOUT T76n	B6	DQ10T	DQ4T
8A	VREFB8A0	IO			DIFFIO RX T77p	DIFFOUT T77p	P14	DQS10T	DQS4T
8A	VREFB8A0	IO			DIFFIO TX T78p	DIFFOUT T78p	F13		
8A	VREFB8A0	IO			DIFFIO RX T77n	DIFFOUT T77n	N14	DQS10T	DQS4T
8A	VREFB8A0	IO			DIFFIO TX T78n	DIFFOUT T78n	E13	DQ10T	DQ4T
8A	VREFB8A0	IO			DIFFIO RX T79p	DIFFOUT T79p	H14	DQ10T	DQ4T
8A	VREFB8A0	IO			DIFFIO TX T80p	DIFFOUT T80p	B4	DQ10T	DQ4T
8A	VREFB8A0	IO			DIFFIO RX T79n	DIFFOUT T79n	G14	DQ10T	DQ4T
8A	VREFB8A0	IO			DIFFIO TX T80n	DIFFOUT T80n	A3		
8A	VREFB8A0	IO			DIFFIO RX T81p	DIFFOUT T81p	M13		
8A	VREFB8A0	IO			DIFFIO TX T82p	DIFFOUT T82p	D11	DQ11T	DQ4T
8A	VREFB8A0	IO			DIFFIO RX T81n	DIFFOUT T81n	L13		
8A	VREFB8A0	IO			DIFFIO TX T82n	DIFFOUT T82n	D10	DQ11T	DQ4T
8A	VREFB8A0	IO			DIFFIO RX T83p	DIFFOUT T83p	G13	DQ11T	DQ4T
8A	VREFB8A0	IO			DIFFIO TX T84p	DIFFOUT T84p	C8	DQ11T	DQ4T
8A	VREFB8A0	IO			DIFFIO RX T83n	DIFFOUT T83n	H13	DQ11T	DQ4T
8A	VREFB8A0	IO			DIFFIO TX T84n	DIFFOUT T84n	C7	DQ11T	DQ4T
8A	VREFB8A0	IO			DIFFIO RX T85p	DIFFOUT T85p	N13	DQS11T	DQ4T
8A	VREFB8A0	IO			DIFFIO TX T86p	DIFFOUT T86p	A2		
8A	VREFB8A0	IO			DIFFIO RX T85n	DIFFOUT T85n	N12	DQS11T	DQ4T
8A	VREFB8A0	IO			DIFFIO TX T86n	DIFFOUT T86n	B3	DQ11T	DQ4T
8A	VREFB8A0	IO			DIFFIO RX T87p	DIFFOUT T87p	E12	DQ11T	DQ4T
8A	VREFB8A0	IO			DIFFIO TX T88p	DIFFOUT T88p	C1	DQ11T	DQ4T
8A	VREFB8A0	IO			DIFFIO RX T87n	DIFFOUT T87n	D12	DQ11T	DQ4T
8A	VREFB8A0	IO			DIFFIO TX T88n	DIFFOUT T88n	B1		
8A	VREFB8A0	IO			DIFFIO RX T89p	DIFFOUT T89p	L12		
8A	VREFB8A0	IO			DIFFIO TX T90p	DIFFOUT T90p	F10	DQ12T	
8A	VREFB8A0	IO			DIFFIO RX T89n	DIFFOUT T89n	K13		
8A	VREFB8A0	IO			DIFFIO TX T90n	DIFFOUT T90n	E10	DQ12T	
8A	VREFB8A0	IO			DIFFIO RX T91p	DIFFOUT T91p	F12	DQ12T	
8A	VREFB8A0	IO			DIFFIO TX T92p	DIFFOUT T92p	E9	DQ12T	
8A	VREFB8A0	IO			DIFFIO RX T91n	DIFFOUT T91n	F11	DQ12T	
8A	VREFB8A0	IO			DIFFIO TX T92n	DIFFOUT T92n	D9	DQ12T	
8A	VREFB8A0	IO			DIFFIO RX T93p	DIFFOUT T93p	L11	DQS12T	
8A	VREFB8A0	IO			DIFFIO TX T94p	DIFFOUT T94p	E7		
8A	VREFB8A0	IO			DIFFIO RX T93n	DIFFOUT T93n	K12	DQS12T	
8A	VREFB8A0	IO			DIFFIO TX T94n	DIFFOUT T94n	D7	DQ12T	
8A	VREFB8A0	IO			DIFFIO RX T95p	DIFFOUT T95p	H12	DQ12T	



Pin Information for the Cyclone® V 5CGXBC9 Device  
Version 1.2  
Note (1)

Bank Number	VREF	Pin Name/Function	Optional Function(s)	Configuration Function	Dedicated Tx/Rx Channel	Emulated LVDS Output Channel	F1152	DQS for X8	DQS for X16
8A	VREFB8AN0	IO			DIFFIO_TX_T96p	DIFFOUT_T96p	F8	DQ12T	
8A	VREFB8AN0	IO			DIFFIO_RX_T95n	DIFFOUT_T95n	G11	DQ12T	
8A	VREFB8AN0	IO			DIFFIO_TX_T96n	DIFFOUT_T96n	E8		
9A		MSEL0		MSEL0			J12		
9A		CONF_DONE		CONF_DONE			G10		
9A		MSEL1		MSEL1			J11		
9A		nSTATUS		nSTATUS			G9		
9A		nCE		nCE			F7		
9A		MSEL2		MSEL2			F6		
9A		MSEL3		MSEL3			K10		
9A		nCONFIG		nCONFIG			G8		
9A		MSEL4		MSEL4			H7		
9A		GND					H8		
		GND					L24		
		GND					AP2		
		GND					AP4		
		GND					AP8		
		GND					AP13		
		GND					AP18		
		GND					AP23		
		GND					AP28		
		GND					AP33		
		GND					AN6		
		GND					AN15		
		GND					AN25		
		GND					AM3		
		GND					AM12		
		GND					AM22		
		GND					AM32		
		GND					AL5		
		GND					AL9		
		GND					AL19		
		GND					AL29		
		GND					AL34		
		GND					AK1		
		GND					AK2		
		GND					AK3		
		GND					AK6		
		GND					AK16		
		GND					AK26		
		GND					AJ3		
		GND					AJ4		
		GND					AJ5		
		GND					AJ13		
		GND					AJ23		
		GND					AJ33		
		GND					AH1		
		GND					AH2		
		GND					AH5		
		GND					AH10		
		GND					AH20		
		GND					AH30		
		GND					AG3		
		GND					AG4		
		GND					AG5		
		GND					AG6		
		GND					AG7		
		GND					AG17		
		GND					AG27		
		GND					AF1		
		GND					AF2		
		GND					AF5		
		GND					AF6		
		GND					AF7		
		GND					AF14		
		GND					AF24		
		GND					AF34		
		GND					AE3		
		GND					AE4		
		GND					AE5		
		GND					AE6		
		GND					AE7		
		GND					AE8		
		GND					AE9		
		GND					AE11		
		GND					AE21		
		GND					AE31		
		GND					AD1		



Pin Information for the Cyclone® V 5CGXBC9 Device  
Version 1.2  
Note (1)

Bank Number	VREF	Pin Name/Function	Optional Function(s)	Configuration Function	Dedicated Tx/Rx Channel	Emulated LVDS Output Channel	F1152	DQS for X8	DQS for X16
		GND					AD2		
		GND					AD5		
		GND					AD6		
		GND					AD7		
		GND					AD9		
		GND					AD10		
		GND					AD18		
		GND					AD28		
		GND					AC3		
		GND					AC4		
		GND					AC5		
		GND					AC6		
		GND					AC8		
		GND					AC10		
		GND					AC15		
		GND					AC25		
		GND					AB1		
		GND					AB2		
		GND					AB5		
		GND					AB6		
		GND					AB7		
		GND					AB9		
		GND					AB11		
		GND					AB12		
		GND					AB22		
		GND					AB32		
		GND					AA3		
		GND					AA4		
		GND					AA5		
		GND					AA6		
		GND					AA8		
		GND					AA10		
		GND					AA12		
		GND					AA14		
		GND					AA19		
		GND					AA29		
		GND					AA34		
		GND					Y1		
		GND					Y2		
		GND					Y5		
		GND					Y6		
		GND					Y7		
		GND					Y9		
		GND					Y10		
		GND					Y11		
		GND					Y13		
		GND					Y15		
		GND					Y17		
		GND					Y19		
		GND					Y21		
		GND					W3		
		GND					W4		
		GND					W5		
		GND					W6		
		GND					W8		
		GND					W10		
		GND					W12		
		GND					W14		
		GND					W16		
		GND					W18		
		GND					W20		
		GND					W22		
		GND					W23		
		GND					W33		
		GND					V1		
		GND					V2		
		GND					V5		
		GND					V6		
		GND					V7		
		GND					V9		
		GND					V11		
		GND					V13		
		GND					V15		
		GND					V17		
		GND					V19		
		GND					V21		
		GND					V30		
		GND					U3		



Bank Number	VREF	Pin Name/Function	Optional Function(s)	Configuration Function	Dedicated Tx/Rx Channel	Emulated LVDS Output Channel	F1152	DQS for X8	DQS for X16
		GND					U4		
		GND					U5		
		GND					U6		
		GND					U8		
		GND					U10		
		GND					U12		
		GND					U14		
		GND					U16		
		GND					U18		
		GND					U20		
		GND					U22		
		GND					U27		
		GND					T1		
		GND					T2		
		GND					T5		
		GND					T6		
		GND					T7		
		GND					T9		
		GND					T11		
		GND					T13		
		GND					T15		
		GND					T17		
		GND					T19		
		GND					T21		
		GND					T24		
		GND					T34		
		GND					R3		
		GND					R4		
		GND					R5		
		GND					R6		
		GND					R8		
		GND					R10		
		GND					R12		
		GND					R14		
		GND					R16		
		GND					R18		
		GND					R20		
		GND					R22		
		GND					R31		
		GND					P1		
		GND					P2		
		GND					P5		
		GND					P6		
		GND					P7		
		GND					P9		
		GND					P11		
		GND					P13		
		GND					P15		
		GND					P17		
		GND					P19		
		GND					P21		
		GND					P28		
		GND					N3		
		GND					N4		
		GND					N5		
		GND					N6		
		GND					N8		
		GND					N10		
		GND					N11		
		GND					N16		
		GND					N18		
		GND					N20		
		GND					N25		
		GND					M1		
		GND					M2		
		GND					M5		
		GND					M6		
		GND					M7		
		GND					M9		
		GND					M10		
		GND					M12		
		GND					M17		
		GND					M22		
		GND					M32		
		GND					L3		
		GND					L4		
		GND					L5		
		GND					L6		



Pin Information for the Cyclone® V 5CGXBC9 Device  
Version 1.2  
Note (1)

Bank Number	VREF	Pin Name/Function	Optional Function(s)	Configuration Function	Dedicated Tx/Rx Channel	Emulated LVDS Output Channel	F1152	DQS for X8	DQS for X16
		GND					L7		
		GND					L8		
		GND					L9		
		GND					L14		
		GND					L19		
		GND					L29		
		GND					L34		
		GND					K1		
		GND					K2		
		GND					K5		
		GND					K6		
		GND					K7		
		GND					K8		
		GND					K16		
		GND					K26		
		GND					J3		
		GND					J4		
		GND					J5		
		GND					J13		
		GND					J23		
		GND					J33		
		GND					H1		
		GND					H2		
		GND					H5		
		GND					H10		
		GND					H20		
		GND					H30		
		GND					G3		
		GND					G4		
		GND					G5		
		GND					G7		
		GND					G17		
		GND					G27		
		GND					F1		
		GND					F2		
		GND					F5		
		GND					F14		
		GND					F24		
		GND					F34		
		GND					E2		
		GND					E3		
		GND					E4		
		GND					E5		
		GND					E11		
		GND					E21		
		GND					E31		
		GND					D1		
		GND					D2		
		GND					D5		
		GND					D8		
		GND					D18		
		GND					D28		
		GND					D33		
		GND					C3		
		GND					C4		
		GND					C5		
		GND					C15		
		GND					C25		
		GND					B2		
		GND					B22		
		GND					B32		
		GND					B34		
		GND					A4		
		GND					A9		
		GND					A19		
		GND					A29		
		VCC					N21		
		VCC					AA13		
		VCC					Y12		
		VCC					Y14		
		VCC					Y16		
		VCC					Y18		
		VCC					W13		
		VCC					W15		
		VCC					W17		
		VCC					W19		
		VCC					W21		
		VCC					V12		



Bank Number	VREF	Pin Name/Function	Optional Function(s)	Configuration Function	Dedicated Tx/Rx Channel	Emulated LVDS Output Channel	F1152	DQS for X8	DQS for X16
		VCC					V14		
		VCC					V16		
		VCC					V18		
		VCC					V20		
		VCC					V22		
		VCC					U13		
		VCC					U15		
		VCC					U17		
		VCC					U19		
		VCC					U21		
		VCC					T12		
		VCC					T14		
		VCC					T16		
		VCC					T18		
		VCC					T20		
		VCC					T22		
		VCC					R13		
		VCC					R15		
		VCC					R17		
		VCC					R19		
		VCC					R21		
		VCC					P12		
		VCC					P16		
		VCC					P18		
		VCC					P20		
		VCC					P22		
		VCC					N15		
		VCC					N17		
		VCC					N19		
		DNU					D4		
		DNU					D3		
		DNU					AG9		
		DNU					AF17		
		DNU					J24		
		DNU					J17		
		VCCPGM					AF12		
		VCCPGM					AD27		
		VCCPGM					H11		
		VCCBAT					H9		
		VCCIO3A					AD13		
		VCCIO3A					AM7		
		VCCIO3A					AK11		
		VCCIO3A					AJ8		
		VCCIO3A					AG12		
		VCCIO3A					AF9		
		VCCIO3B					AB17		
		VCCIO3B					AN10		
		VCCIO3B					AM17		
		VCCIO3B					AL14		
		VCCIO3B					AH15		
		VCCIO3B					AE16		
		VCCIO4A					AD23		
		VCCIO4A					AN20		
		VCCIO4A					AN30		
		VCCIO4A					AM27		
		VCCIO4A					AL24		
		VCCIO4A					AK21		
		VCCIO4A					AJ18		
		VCCIO4A					AJ26		
		VCCIO4A					AH25		
		VCCIO4A					AG22		
		VCCIO4A					AF19		
		VCCIO4A					AC20		
		VCCIO5A					AA24		
		VCCIO5A					AK31		
		VCCIO5A					AF29		
		VCCIO5A					AE26		
		VCCIO5A					AB27		
		VCCIO5A					Y26		
		VCCIO5B					V25		
		VCCIO5B					AG32		
		VCCIO5B					AD33		
		VCCIO5B					AC30		
		VCCIO5B					Y31		
		VCCIO5B					W28		
		VCCIO6A					G32		
		VCCIO6A					U32		
		VCCIO6A					T29		





Pin Information for the Cyclone® V 5CGXBC9 Device  
Version 1.2  
Note (1)

Bank Number	VREF	Pin Name/Function	Optional Function(s)	Configuration Function	Dedicated Tx/Rx Channel	Emulated LVDS Output Channel	F1152	DQS for X8	DQS for X16
		VCCIO6A					R26		
		VCCIO6A					P23		
		VCCIO6A					P33		
		VCCIO6A					N30		
		VCCIO6A					M27		
		VCCIO6A					K31		
		VCCIO6A					J28		
		VCCIO7A					A24		
		VCCIO7A					K21		
		VCCIO7A					J18		
		VCCIO7A					H25		
		VCCIO7A					G22		
		VCCIO7A					F19		
		VCCIO7A					F29		
		VCCIO7A					E26		
		VCCIO7A					D23		
		VCCIO7A					C20		
		VCCIO7A					C30		
		VCCIO7A					B27		
		VCCIO8A					B17		
		VCCIO8A					K11		
		VCCIO8A					H15		
		VCCIO8A					G12		
		VCCIO8A					F9		
		VCCIO8A					E6		
		VCCIO8A					E16		
		VCCIO8A					D13		
		VCCIO8A					C10		
		VCCIO8A					B7		
		VCCIO8A					B12		
		VCCIO8A					A14		
		VCCPD3A					AE15		
		VCCPD3A					AE13		
		VCCPD3B4A					AE17		
		VCCPD3B4A					AF15		
		VCCPD3B4A					AF16		
		VCCPD3B4A					AF20		
		VCCPD3B4A					AF21		
		VCCPD3B4A					AE22		
		VCCPD5A					AA26		
		VCCPD5A					AB26		
		VCCPD5B					W25		
		VCCPD5B					V26		
		VCCPD6A					P26		
		VCCPD6A					U26		
		VCCPD6A					T26		
		VCCPD6A					N26		
		VCCPD7A8A					J22		
		VCCPD7A8A					K15		
		VCCPD7A8A					K17		
		VCCPD7A8A					K20		
		VCCPD7A8A					J14		
		VCCPD7A8A					J16		
		VCCPD7A8A					J19		
		VCCPD7A8A					J21		
3A	VREFB3AN0	VREFB3AN0					AH11		
3B	VREFB3BN0	VREFB3BN0					AH18		
4A	VREFB4AN0	VREFB4AN0					AG20		
5A	VREFB5AN0	VREFB5AN0					AE27		
5B	VREFB5BN0	VREFB5BN0					V29		
6A	VREFB6AN0	VREFB6AN0					P29		
7A	VREFB7AN0	VREFB7AN0					G19		
8A	VREFB8AN0	VREFB8AN0					G16		
		NC					AP3		
		NC					AN1		
		NC					AN2		
		NC					AN3		
		NC					AM1		
		NC					AM2		
		NC					AL1		
		NC					AL2		
		NC					AL3		
		NC					AL4		
		NC					AK4		
		NC					AH6		
		NC					AH7		
		NC					AG8		
		NC					AF8		



Pin Information for the Cyclone® V 5CGXBC9 Device  
Version 1.2  
Note (1)

Bank Number	VREF	Pin Name/Function	Optional Function(s)	Configuration Function	Dedicated Tx/Rx Channel	Emulated LVDS Output Channel	F1152	DQS for X8	DQS for X16
		NC					L10		
		NC					L26		
		NC					K9		
		NC					K27		
		NC					J6		
		NC					J7		
		NC					J8		
		NC					J9		
		NC					J27		
		NC					H6		
		NC					G6		
		NC					F31		
		NC					F32		
		NC					F33		
		NC					E32		
		NC					E33		
		NC					E34		
		NC					D6		
		NC					D31		
		NC					D32		
		NC					D34		
		NC					C2		
		NC					C19		
		NC					C33		
		NC					C34		
		NC					B33		
		NC					A30		
		NC					A31		
		NC					A32		
		NC					A33		
		NC					N9		
		VCCH GXBL					AB8		
		VCCH GXBL					W9		
		VCCH GXBL					T8		
		VCCL GXBL					N7		
		VCCL GXBL					AC7		
		VCCL GXBL					AA7		
		VCCL GXBL					W7		
		VCCL GXBL					U7		
		VCCL GXBL					R7		
		RREF TL					E1		
		VCCA FPLL					AC11		
		VCCA FPLL					M11		
		VCCA FPLL					AD26		
		VCCA FPLL					M26		
		VCC AUX					J10		
		VCC AUX					K18		
		VCC AUX					K24		
		VCC AUX					AE24		
		VCC AUX					AE18		
		VCC AUX					AE12		
		VCC AUX					P8		
		VCCE GXBL					AD8		
		VCCE GXBL					AC9		
		VCCE GXBL					AA9		
		VCCE GXBL					Y8		
		VCCE GXBL					V8		
		VCCE GXBL					U9		
		VCCE GXBL					R9		
		VCCE GXBL					M8		

Note:  
(1) For more information about pin definition and pin connection guidelines, refer to the [Cyclone V Device Family Pin Connection Guidelines](#).



Pin Information for the Cyclone® V 5CGXBC9 Device  
Version 1.2

Version Number	Date	Changes Made
1.0	7/3/2012	Initial release.
1.1	5/22/2013	Added U484 package.
1.2	10/11/2013	Removed nPERST* pins because this device does not support PCIe interface.